

Konfiguracja klienta VPN PPTP – TP-Link

W pierwszym kroku zaloguj się do swojego routera, uruchom przeglądarkę i wpisz domyślny adres routera: <http://192.168.1.1>

Przejdź do zakładki „**Network**” (1) i wybierz „**WAN**” (2)

Z zakładki „**WAN Connection Type**” wybierz „**PPTP**” (3)

W polu „**User Name**” (4) wpisz swój login

W polu „**Password**” (5) wpisz swoje hasło

W polu „**Server IP Address/Name**” (6) wpisz nazwę jednego z naszych serwerów VPN

Listę dostępnych serwerów VPN znajdziesz w panelu klienta: www.portal.vpnonline.pl

W polu „**MTU Size**” (7) wpisz wartość „**1400**”

W sekcji „**Connection Mode**” wybierz „**Connect Automatically**” (8)

Po wypełnieniu wszystkich wymaganych pozycji, kliknij „**Save**” (9)

Aby zestawić połączenie VPN kliknij „**Connect**” (10)

TP-LINK® 3G/4G Wireless N Router
Model No. TL-MR3020

WAN

WAN Connection Type: (3) PPTP/Russia PPTP

User Name: (4) Twój login

Password: (5) Twoje hasło

(10) Connect Disconnect **Disconnected!**

Dynamic IP Static IP

Server IP Address/Name: (6) Nazwa serwera VPN

IP Address: 0.0.0.0

Subnet Mask: 0.0.0.0

Gateway: 0.0.0.0

DNS: 0.0.0.0, 0.0.0.0

Internet IP Address: 0.0.0.0

Internet DNS: 0.0.0.0, 0.0.0.0

MTU Size (in bytes): (7) 1400 (The default is 1420, do not change unless necessary.)

Connection Mode: (8) Connect on Demand Connect Automatically Connect Manually

Max Idle Time: 15 minutes (0 means remain active at all times.)

(9) Save