Literature Review: Step and Orientation Detection with IMU-Based Sensors

Your Name
Dept. of Electrical, Computer and Software Engineering
The University of Auckland
Auckland, New Zealand · UPI / ID

***Abstract*—This review compares approaches to step detection and heading estimation for a body-worn pedestrian tracker built on an accelerometer and a magnetometer. Peak, threshold and frequency-domain step detectors are compared, as are gyroscope-based and magnetometer-based heading methods. Windowed peak detection and tilt-compensated magnetometer heading best suit this sensor set, provided the magnetometer is calibrated.**

***Keywords*—pedestrian dead reckoning, step detection, heading estimation, magnetometer, accelerometer**

I. Introduction

Step-based pedestrian dead reckoning (PDR) updates position once per step from a step length and a heading, which avoids the fast error growth of double-integrating acceleration [1]. Accuracy then rests on two separate estimates: whether a step occurred, and which way it went. This review compares approaches to each. My reading of the project brief and lab sheet is that the device is meant to use the accelerometer and magnetometer of the LSM303AGR, so I focus on methods that work with those two sensors and treat gyroscope-based work as a point of contrast.

II. Step Detection

II.A. Peak and Threshold Methods

Most systems detect steps as peaks in low-pass-filtered acceleration. Jin et al. project acceleration onto the vertical and accept a peak and valley only if they are at least 150 ms apart and differ from the previous extremum by a threshold [1]. Tian et al. use a 5 Hz low-pass filter, a minimum step interval of 0.2 s and a false-peak rejection window, and choose the acceleration axis from the way the phone is carried [2]. Brajdic and Harle compare many detectors on 130 walks from 27 people in six phone placements. Windowed peak detection reached a median step-count error of 1.3%, the same as HMM and wavelet methods at far lower cost, and only the back trouser pocket degraded counts noticeably [3]. They also find that no detector is fully reliable, and that standard-deviation thresholding is a cheap walk detector but gives false positives.

II.B. Frequency-Domain Methods

Kang et al. take the FFT of the gyroscope's angular-velocity magnitude, decide that the user is walking from the energy at 0.6–2 Hz, and count steps as step frequency multiplied by duration. They report 93.76% precision for walking detection and 95.74% step-counting accuracy over eight subjects at 20 Hz [4]. This avoids placement-specific thresholds, but it needs a gyroscope and a sliding window of several seconds. Step length is a separate problem: Jin et al. scale $(a_{\max} - a_{\min})^{\frac{1}{4}}$ and Tian et al. use height and step frequency [1], [2]. Neither is needed to count steps.

III. Heading Estimation

III.A. Gyroscope-Based Methods

Tian et al. average the gyroscope yaw over each step and identify gyroscope drift as a main source of position error [2]. Manos et al. show the same effect: plain integration of the vertical angular rate drifts quickly, and bias compensation during straight walking keeps the error under 15° after 85 s [5]. Both give heading that must be corrected or re-anchored over time.

III.B. Magnetometer-Based Methods

Manos et al. also compute heading from the magnetometer, using the accelerometer's gravity direction for tilt, and obtain about 5–6° average error over the last 20 s, comparable to the bias-compensated gyroscope but without drift [5]. Isaia et al. give a complete accelerometer-and-magnetometer pipeline: low-pass filter to isolate gravity, remap axes to the dominant gravity axis, compute pitch and roll, rotate the magnetometer readings into the horizontal plane and take the arctangent. RMSE ranged from 1.75° to 14.67° across ten placements, but only one pedestrian was tested against a compass reference of ±10° [6]. Jin et al. instead take orientation from the compass to project acceleration into world coordinates and integrate horizontal acceleration over about 1.4 s for heading, because PCA performed poorly at low sample rates [1].

All of these depend on the magnetic field. Jin et al. note orientation errors from field distortion by metal [1], and Isaia et al. list indoor interference as an open limitation [6]. The LSM303AGR provides hard-iron offset registers for correcting a fixed bias [7].

IV. Comparison and Chosen Approach

For step detection I will use windowed peak detection on low-pass-filtered acceleration with a minimum interval between steps. It needs only the accelerometer, is cheap enough for the microcontroller, and was among the most accurate methods in the largest comparison [3]. For heading I will use a tilt-compensated magnetometer with gravity from the accelerometer after hard-iron calibration [5], [6], because it does not drift and uses only the two sensors provided. The main risks are magnetic disturbance near metal, and the sampling rate: the template samples every 100 ms, which leaves few samples per step, so the timer period may need to be shortened.

Bibliography

[1] Y. Jin, H.-S. Toh, W.-S. Soh, and W.-C. Wong, "A Robust Dead-Reckoning Pedestrian Tracking System with Low Cost Sensors," in *Proc. IEEE Int. Conf. Pervasive Computing and Communications (PerCom)*, Seattle, WA, USA, Mar. 2011, pp. 222–230.

[2] Q. Tian, Z. Salcic, K. I.-K. Wang, and Y. Pan, "A Multi-Mode Dead Reckoning System for Pedestrian Tracking Using Smartphones," *IEEE Sensors Journal*, vol. 16, no. 7, pp. 2079–2093, Apr. 2016, doi: 10.1109/JSEN.2015.2510364.

[3] A. Brajdic and R. Harle, "Walk Detection and Step Counting on Unconstrained Smartphones," in *Proc. ACM Int. Joint Conf. Pervasive and Ubiquitous Computing (UbiComp)*, 2013, pp. 225–234.

Table I
Comparison of approaches

Work	Sensors	Step detection	Heading	Result / limitation
[1]	Acc, compass	Relative-threshold peak and valley	Compass-projected acceleration, integrated over 1.4 s	Metal distorts the field; phones sampled below 25 Hz
[2]	Acc, gyro	Peak detection with mode-specific axis and false-peak rejection	Gyro yaw averaged per step	98.91% position accuracy; gyro drift dominates error
[3]	Acc	Compares thresholds, peaks, frequency and HMM methods	None	Peak detection 1.3% median error; no method fully reliable
[4]	Gyro	FFT of angular-rate magnitude	None	95.74% counting accuracy; needs gyro and window
[5]	Acc, gyro, mag	None	Gyro with bias compensation vs. magnetometer with gravity	Magnetic about 5–6°; gyro under 15° after 85 s; pocket only
[6]	Acc, mag	None	Tilt-compensated magnetometer with axis remapping	1.75–14.67° RMSE; one subject; indoor interference

[4] X. Kang, B. Huang, and G. Qi, "A Novel Walking Detection and Step Counting Algorithm Using Unconstrained Smartphones," *Sensors*, vol. 18, no. 1, p. 297, 2018, doi: 10.3390/s18010297.

[5] A. Manos, I. Klein, and T. Hazan, "Gravity-Based Methods for Heading Computation in Pedestrian Dead Reckoning," *Sensors*, vol. 19, no. 5, p. 1170, 2019, doi: 10.3390/s19051170.

[6] C. Isaia, L. Yu, W. Cai, and M. P. Michaelides, "Axes Mapping and Sensor Fusion for Attitude-Unconstrained Pedestrian Dead Reckoning," *Sensors*, vol. 26, no. 6, p. 1968, 2026, doi: 10.3390/s26061968.

[7] STMicroelectronics, "Ultracompact high-performance eCompass module based on the LSM303AGR," technical report AN4825, 2017.