ЛМТК.467444.002-0433

DD1 CAT6219 (*STU): Vin, EN, Vout, BYP, GND; VD1, VD2; C1 2.2 мк, C2 2.2 мк, C3 0.01 мк; VUSB, +5V, +3.3V, GND

(2) +5VSNS — R8 30 к — +5V; R5 39 к — GND

(2) VUSBSNS — R9 30 к — VUSB; R6 39 к — GND

+3.3V — R11 3 к — R12 330 — (2) nBTN; C7 0.1 мк — GND; SB1, SH

XS1 DS1104-01

USB	⟩—
VBUS	1
D-	2
D+	3
ID	4
GND	5
КОРПУС	

DD2 USBLC6-2SC6 (*D): USB_D_N, USB_D_P, USBD_N, USBD_P; R1 33 USB_N, R2 33 USB_P; C4 2.2 мк; (2) USB

Z1 330Ω, 1200.0mA; VUSB; R3 3 к; VT1 BC817-40; +3.3V; R7 39 к; R10 3 к

R16 1 к — +3.3V; R13 330 — VD6 "РАБОТА" — GND; GLC

R14 330 — VD7 "РЕЖИМ"; YARC; YCRA

(2) CTLS

XP1 YPROG

Цепь	⟵
RST#	8
DCS#	5
DCK	1
DDD	9
DDQ	3
DRX	6
DTX	7
VDD	4
GND	2
GND	10

DR3.1 22 nRSTI; DR2.4 22 TMS; DR2.1 22 TCK; DR3.2 22 TDI; DR2.3 22 TDO; DR3.4 22 USART1/6_RX; DR3.3 22 USART1/6_TX/VBUS; DR2.2 22

+3.3V; GND; VD3 ESDA6V1SC6; VD5 ESDA6V1SC6

(2) DBG

DS1: SDI/IO0, SDO/IO1, SCK, nCS, nWP/IO2, nHLD/IO3, VCC, GND

R17 10 к, R19 10 к — nCSDF; R18 10 к — nCSSD; nRSTO

C6 0.1 мк

XS2 SD

DR4.1 47 к; DR4.2 47 к; DR4.3 47 к; DR4.4 47 к

SDnCS; SDDI; +3.3V; SDSCK; GND; SDDO

DR1.1 22; DR1.2 22; DR1.3 22; DR1.4 22

VD4 ESDA6V1SC6

DD3 SN74LVC1G125DBVR: EZ1, 1Z, VCC, GND; R4 3 к, C5 0.1 мк; SPI2_MOSI; SPI2_SCK; SPI2_MISO

(2) SPI2

R15 330 — nSDCD; C8 0.1 мк

XP2 "Плата ввода-вывода"

⟶	Цепь
1	+5 В
2	GND
3	VDDIO
4	GND
5	SYNC_S
6	DATA_S
7	IRQ_S
8	IO_S
9	SYNC_A
10	DATA_A
11	IRQ_A
12	IO_A
13	SYNC_B
14	DATA_B
15	IRQ_B
16	IO_B
17	VDDIO
18	GND
19	SYNC_C
20	DATA_C
21	IRQ_C
22	IO_C
23	SYNC_D
24	DATA_D
25	IRQ_D
26	IO_D
27	SYNC_E
28	DATA_E
29	IRQ_E
30	IO_E
31	VDDIO
32	GND
33	RXN
34	LDLA
35	RXP
36	LDSPD
37	TXN
38	EGND
39	TXP
40	КОРПУС

(2) ECON — +3.3V — R20 3 к, R21 3 к, R22 3 к, R23 3 к

I2C1_SCL; I2C1_SDA; I2C1_SMBA; I2C1_nRST; USART2/CAN1_TX; USART2/CAN1_RX; USART2_RTS; USART2_CTS; USART1_TX; USART1_RX; USART1_RTS_SW; USART1_CTS_SW; +3.3V; GND; U3_TX/SPI3_MOSI; U3_RX/SPI3_MISO; U3_RTS/SPI3_SCK; U3_CTS/SPI3_nCS; TIM1_CH1N; TIM1_CH2N; TIM1_CH3N; TIM1_BKIN; T1_CH1/A5; T1_CH2/A6; T1_CH3/A8; T1_CH4/A9; +3.3V; GND; RX_N; LDLA; RX_P; LDSPD; TX_N; GND; TX_P; SH

Подп. дата (23) | Инв. № дубл. (22) | Взам. инв. № (21) | Подп. и дата (20) | Инв. № подл. (19)

					ЛМТК.467444.002-0433	
(14)	(15)	(16)	(17)	(18)		
Изм.	Лист	№ докум.	Подп.	Дата		
Разраб.		Милин			SOVA R1.1 04	Лит. / Масса / Масштаб
Пров.					Схема электрическая принципиальная	
Т. контр.						Лист 1 / Листов 2
(10)		(11)	(12)	(13)		
Н. контр.						
Утв.						

Копировал (31) Формат А2

ЛМТК.467444.002-04З3

DD4

STM32F105VC76

MPU

PORT A
PA0/WKUP
PA1
PA2
PA3
PA4
PA5
PA6
PA7
PA8
PA9
PA10
PA11
PA12
PA13/JTMS/SWDIO
PA14/JTCK/SWCLK
PA15/JTDI

PORT B
PB0
PB1
PB2/BOOT1
PB3/JTDO/SWO
PB4/NJTRST
PB5
PB6
PB7
PB8
PB9
PB10
PB11
PB12
PB13
PB14
PB15

PORT C
PC0
PC1
PC2
PC3
PC4
PC5
PC6
PC7
PC8
PC9
PC10
PC11
PC12
PC13/TAMPER_RTC
PC14/OSC_32IN
PC15/OSC32OUT

PORT H
PH0/OSC_IN
PH1/OSC_OUT

PORT D
PD0 81 USART2/CAN1_RX
PD1 82 USART2/CAN1_TX
PD2 83
PD3 84 USART2_CTS
PD4 85 USART2_RTS
PD5 86 USART2/CAN1_TX
PD6 87 USART2/CAN1_RX
PD7 88 I2C1_nRST
PD8 55 U3_TX/SPI3_MOSI
PD9 56 U3_RX/SPI3_MISO
PD10 57
PD11 58 U3_CTS/SPI3_nCS
PD12 59 U3_RTS/SPI3_SCK
PD13 60 GLC
PD14 61 YARC
PD15 62 YCRA

PORT E
PE0 97 nRSTO
PE1 98 ETH_nINT
PE2 1 nSDCD
PE3 2 USART1_RTS_SW
PE4 3 USART1_CTS_SW
PE5 4 nCSDF
PE6 5 nCSSD
PE7 38 ETH_nRST
PE8 39 TIM1_CH1N
PE9 40 T1_CH1/A5
PE10 41 TIM1_CH2N
PE11 42 T1_CH2/A6
PE12 43 TIM1_CH3N
PE13 44 T1_CH3/A8
PE14 45 T1_CH4/A9
PE15 46 TIM1_BKIN

BOOT0 94 BOOT0
NRST 14 nRSTI

VDDA 22
VREF+ 21
VREF- 20
VSSA 19
VBAT 6 +3.3V
VDD 11
VDD 28
VDD 50
VDD 75
VDD 100
VSS 99
VSS 74
VSS 27
VSS 10
VSS 49
VCAP2 73

AIN0 23 (1) VUSBSNS
ETH_REF_CLK 24
ETH_MDIO 25
AIN3 26 (1) +5VSNS
U3_CTS/SPI3_nCS 29
T1_CH1/A5 30
T1_CH2/A6 31
ETH_CRS_DV 32
RCC_MCO 67
USART1/6_TX/VBUS 68
USART1/6_RX 69
USB_N 70
USB_P 71
TMS 72
TCK 76
TDI 77

T1_CH3/A8 35
T1_CH4/A9 36
BOOT1 37
TDO 89
90
I2C1_SMBA 91
USART1_TX 92
USART1_RX 93
I2C1_SCL 95
I2C1_SDA 96
SPI2_SCK 47
ETH_TX_EN 48
ETH_TXD0 51
ETH_TXD1 52
SPI2_MISO 53
SPI2_MOSI 54

15
ETH_MDC 16
17
18
ETH_RXD0 33
ETH_RXD1 34
USART1/6_TX/VBUS 63
USART1/6_RX 64
LDLA 65
LDSPD 66
U3_RTS/SPI3_SCK 78
U3_RX/SPI3_MISO 79
U3_TX/SPI3_MOSI 80
7
8
9

12
13

(1) DBG
(1) USB
(1) SPI2
(1) ECON
(1) nBTN
(1) CTLS

R24 3 к
GND

BQ1 25MHZ
C9 22
C10 22
R25 330

R28 33
R29 33
XP3.1
XP3.2

R27 3 к

R26 33
C11 0.01 мк
C23 2.2 мк
C24 0.1 мк
Z2
R32
R31

C20
C21
C19
0.1 мк
10 мк
C14
C17
C12
C13
C16

C18 2.2 мк
C22 2.2 мк
R30

R37 10 к
C26 0.1 мк

DD5

RCC_MCO
R34 10 к
+3.3V

CONFIG[0] 28
CONFIG[1] 29
ETH_REF_CLK 19 RXC/{B-CAST_OFF}
ETH_RXD0 16 RXD[0]/{DUPLEX}
ETH_RXD1 15 RXD[1]/{PHYAD[2]}
14 PHYAD[1]
13 PHYAD[0]
ETH_CRS_DV 18 CRS_DV/{CONFIG[2]}
20 RXER/{ISO}
22 NC
ETH_TXD0 24 TXD[0]
ETH_TXD1 25 TXD[1]
26 NC
27 NC
ETH_TX_EN 23 TXEN
R33 1 к
ETH_MDIO 11 MDIO
ETH_MDC 12 MDC
R35 10 к
ETH_nINT 21 INT/{NAND_Tree}
ETH_nRST 32 nRST
R36 10 к
C25 0.1 мк

R38
BQ2
C27 22
C29 22
25MHZ
XI/REFCLK 9
XO 8
RXP 5 RX_P
RXM 4 RX_N
TXP 7 TX_P
TXM 6 TX_N
LED[0]/{NWAYEN} 30 LDLA
LED[1]/{SPEED} 31 LDSPD
VDDIO 17
VDDA_3.3 3
VDD_1.2 2
REXT 10
GND 1
GND 33

R39 6.8 к
C28 2.2 мк
C30 10 мк
C31 0.1 мк
C32 0.1 мк
C33 10 мк
Z3
X1
"GND"

Подп. и дата	(20)				
Инв. № подл.	(19)				
Взам. инв. №	(21)				
Инв. № дубл.	(22)				
Подп. дата	(23)				
(14) Изм.	(15) Лист	(16) № докум.	(17) Подп.	(18) Дата	ЛМТК.467444.002-0433

Лист 2

Копировал (31) Формат А2

Order Code	Part Number	Comment	Package	Quantity	Description	Designator	Manufacturer
KX-7T 25.0 MHz	KX-7T 25.0 MHz	25MHZ	SMD3225	1	SMD Quartz Crystal	BQ1	Geyer
CC0603KRX5R6BB225	CC0603KRX5R6BB22	2.2 мк	0603	4	2.2uFx10 V, ±10%, X5R, Case 06	C1, C2, C4, C23	Yageo
CC0402KRX7R8BB103	CC0402KRX7R8BB10	0.01 мк	0402	2	10nFx25 V, ±10%, X7R, Case 04	C3, C11	Yageo
CC0402KRX7R6BB104	CC0402KRX7R6BB10	0.1 мк	0402	10	0.1uFx10 V, ±10%, X7R, Case 04	C6, C7, C12, C13, C	Yageo
CC0402JRNPO9BN220	CC0402JRNPO9BN22	22	0402	2	22pFx50 V, ±5%, NP0, Case 040	C9, C10	Yageo
CC0805KKX5R6BB106	CC0805KKX5R6BB10	10 мк	0805	3	10uFx10 V, ±10%, X5R, Case 08	C19, C20, C21	Yageo
CAT6219-330TDGT3	CAT6219-330TDGT3	CAT6219	SOT23-5	1	500 mA CMOS LDO Regulator	DD1	ON Semiconductor
USBLC6-2SC6	USBLC6-2SC6	USBLC6-2SC6	SOT23-6	1	Very low capacitance ESD protecti	DD2	STMicroelectronics
STM32F105VCT6	STM32F105VCT6	STM32F105VCT6	LQFP100	1	Connectivity line, ARM®-based	DD4	STMicroelectronics
YC164-JR-0722RL	YC164-JR-0722RL	22	0603x4	2	22Ohm R-Array /R-Network (con	DR2, DR3	Yageo
RC0402JR-0733RL	RC0402JR-0733RL	33	0402	5	33Ohm General Purpose Chip Re	R1, R2, R26, R28, R2	Yageo
RC0402JR-073KL	RC0402JR-073KL	3 к	0402	9	3kOhm General Purpose Chip Re	R3, R10, R11, R20, R	Yageo
RC0402JR-0739KL	RC0402JR-0739KL	39 к	0402	3	39kOhm General Purpose Chip R	R5, R6, R7	Yageo
RC0402JR-0730KL	RC0402JR-0730KL	30 к	0402	2	30kOhm General Purpose Chip R	R8, R9	Yageo
RC0402JR-07330RL	RC0402JR-07330RL	330	0402	4	330Ohm General Purpose Chip R	R12, R13, R14, R25	Yageo
RC0402JR-071KL	RC0402JR-071KL	1 к	0402	1	1kOhm General Purpose Chip Re	R16	Yageo
RC0402JR-070RL	RC0402JR-070RL	0	0402	2	0Ohm General Purpose Chip Resi	R30, R31	Yageo
RC0402JR-0710KL	RC0402JR-0710KL	10 к	0402	1	10kOhm General Purpose Chip R	R37	Yageo
IT-1188-160G-G	IT-1188-160G-G	SB-SSCNor		1	Side pushing SMT Type tact switch	SB1	Switronic
MBR0540T1G	MBR0540	MBR0540	SOD123	2	Surface Mount Schottky Power Re	VD1, VD2	ON Semiconductor
ESDA6V1SC6	ESDA6V1SC6	ESDA6V1SC6	SOT23-6	2	Quad Transil array for ESD protecti	VD3, VD5	STMicroelectronics
КИПД66Л8-Л	КИПД66Л8-Л	"РАБОТА"		1	Светодиод 3 мм	VD6	Планета СИД
КИПД45В8-М	КИПД45В8-М	"РЕЖИМ"	3 мм	1	Светодиод 3 мм двухцветный к	VD7	Планета СИД
BC817-40	BC817-40	BC817-40	SOT23	1	NPN general-purpose transistors	VT1	NXP
	TPR300_200i20	"GND"		1	Печатный контакт 3х2 мм	X1	
DS1014-10SF1B	YPROG_2mm_DCH_	YPROG		1	YPROG Connector (PLD2-10)	XP1	Connfly
DS1025-05-2*20P8BV	B2BMCU_8_6x4_E_T	"Плата ввода-вывода"		1	Соединитель для подключения	XP2	Connfly
DS1025-01-1*2P8BV1	PLS2-2	PLS2-2		1	DS1025-01 Series 2mm PIN HEAD	XP3	Connfly
DS1104-01-BN0R-ELC	DS1104-01-BN0R-EL	DS1104-01	USB micro B	1	Micro USB Female 5P	XS1	Connfly
BLM18PG331SN1#	BLM18PG331SN1#	330Ω, 1200.0mA	0603	2	330Ω@100MHz 1200.0mA 1608	Z1, Z2	Murata


XS1
R6
C4
DD2
C2
DD1
C3
R7
R37
R9
Z1
C1
VD1
VD2
C20
R5
R8
R2
R1
R10
C19
C21
G5


BQ1
C10
R25
C24
C9
Z2
C23
C11
SB1
R29
R3
R26
R31
C26
C16
C7
R12
C14
R11
R14
R13
R16
R28
VT1
C13
DD4
C17
DR3
VD5
R27
VD3
R24
DR2
R30
C15
R20
R21
R23
R22
C12


XP1
XP2


VD7
VD6
XP3


XS2
XS1
SOVA
1904R1.1
XP1
XP2
DD1
DD3
DD4
DD5
VD1
VD2
DS1
C6
C18
C20
C21
C25
C28
C31
C32
C33
R4
R5
R8
R17
R19
R33
R34
R36
R39


BQ1
R3
VT1
C13
Z2
R24
C22
C27
C29
C30
R30
C15
BQ2
R38
Z3
DD4
C12
R20
R21
R23
R22
X1
R27
C17
DR3
VD3
DR2
XP3