

PROJECT: AESOP infrastructure lane (T3 bring-up). Owner: c10vis-poem.
Context repos: c10vis-poem/aesop (protocol spec — read README.md, ARCHITECTURE.md, RESUME.md, profiles/nav.yaml first), c10vis-poem/Novus-Agenti (device/agent layer — read CLAUDE.md SOTU only, don't touch its code).
Another session is handling the Omni Claw UI build — do NOT touch Novus-Agenti code or branches. This lane is infrastructure only.

GOAL: stand up tier T3 (home node) per profiles/nav.yaml —
Jetson Orin Nano Super 8GB = hub (memory backends, gateway, librarian, small executive), Rubik Pi (Dragonwing) = desktop-OS + audio/TTS node, phone joins over Tailscale.

ORDER OF WORK:

1. TAILSCALE ON PHONE (do first, 10 min):

- Install the Tailscale Android APK (Play Store or F-Droid) — NOT the Termux pip/pkg route; the Android app gives the VPN tunnel that Termux traffic rides automatically.
- Log in, note the phone's 100.x.y.z tailnet IP.
- In Termux: `tailscale status` isn't available (app owns it) — verify instead with `curl http://<any-tailnet-ip>` once a second node exists.
- Enable MagicDNS in the admin console so nodes resolve by name.

2. JETSON ORIN NANO 8GB — PROCURE + FLASH:

Shopping/prep list:

- microSD: 128GB+ A2 U3 (256GB preferred — JetPack + models eat space).
- The Orin Nano Super Dev Kit needs a ONE-TIME firmware update to boot JetPack 6.x: if the board is new/older firmware, first boot JetPack 5.1.3 SD image to update QSPI firmware, OR use a Ubuntu 22.04 x86 host with NVIDIA SDK Manager over USB-C recovery mode. Check firmware version on first boot before assuming.
- Flash target: JetPack 6.x "SD Card Image" from developer.nvidia.com (Balena Etcher). No x86 host needed if firmware is already 36.x.
- First boot: ubuntu user setup, then:
`sudo apt update && sudo apt install -y curl git`
`curl -fsSL https://tailscale.com/install.sh | sh && sudo tailscale up`
- Install Docker (comes with JetPack) + docker compose.
- T3 services to stand up (containers preferred, 8GB RAM budget — this is a HUB not a big-model box):
 - a. Postgres + pgvector (OB1/Open Brain recall memory)
 - b. Vault sync target: bare git repo or Syncthing for ~/vault (canonical markdown; phone's ~/vault syncs here)
 - c. OmniRoute (Node >=20; c10vis-poem/OmniRoute) as the gateway
 - d. LATER, not first pass: onnxruntime + gemma-4-E2B ONNX (executive-small), reasoning-bank

- Success criteria: phone can `git push` vault to Jetson over tailnet; Postgres reachable at jetson:5432 from phone; OmniRoute dashboard loads at http://jetson:20128 from phone browser.

3. RUBIK PI (Qualcomm Dragonwing) — AFTER Jetson is stable:

- Flash per Qualcomm's Rubik Pi docs (Qualcomm Linux / Debian-based image; needs its flashing host tool — follow thundercomm/Qualcomm official docs for the exact image, don't guess).
- Join tailnet same as Jetson.
- Role per nav.yaml: desktop-os + TTS endpoint (kokoro/sherpa-onnx). sherpa-onnx has aarch64 glibc wheels — plain `pip install sherpa-onnx` should work here (unlike Termux/bionic). Model files: reuse the kokoro-multi-lang-v1.x bundle + Moonshine-base-int8 from the owner's HF mirrors — ONE shared ~/models folder, ABI-agnostic per aesop RESUME.md's shared-model/per-ABI-runtime decision.

CONSTRAINTS:

- Do not push to any Novus-Agenti branch. aesop repo: main only, docs only.
- No tokens/secrets in any commit. HF auth comes from environment/HF CLI login.
- If a step's docs conflict with reality (firmware, image names), verify against the official source before flashing — report, don't improvise.
- Log outcomes back into aesop/RESUME.md (append a dated section) so the next session inherits state.