Johnson's noise in the moving bar problem

1 The equations of motion

Let x be the position of the sliding, conducting bar that closes a U-shaped circuit with respect to the left end of said circuit. Let $v = \dot{x}$ be the velocity of the conducting bar. Let I be the electrical current that flows along the bar. Finally, let

$$\Gamma(t) = \lim_{dt \to 0} N(0, 1/dt), \tag{1}$$

where $N(\mu, \sigma^2)$ is the normal distribution with mean μ and variance σ^2, be a Gaussian white noise process. By *Langevin's hypothesis* we assume that the resistance in an electric circuit, produced by the collisions of the charge carriers as the traverse the conductor atomic network under the efect of a force, and the random thermal fluctuations of the charge carriers due to the vibration of the same network, are independent processes (though they are trully not). Also, following Gillespie [1], we assume that when x is fixed, the electric current $I(t)$ in the circuit is an Orstein-Uhlembeck (O-U) process, that is, it follows Langevin's equation with constant drift and diffusion coefficients. In this case, the equations of motion of the system are

$$\frac{dx}{dt} = v(t), \tag{2}$$

$$\frac{dv}{dt} = -\frac{lB_0}{M} I(t) + \frac{1}{2M} L' I(t)^2, \tag{3}$$

$$\frac{dI}{dt} = \frac{lB_0}{L(x)} v(t) - \frac{1}{L(x)} \left(R(x) + \frac{dL}{dx} v(t) \right) I(t) + \frac{g}{L(x)} \Gamma(t), \tag{4}$$

where M is the mass of the bar, $L(x)$ is the position-dependent self inductance of the circuit, $L' = dL/dx$, and $R(x)$ is the resistance of the circuit. g is a factor to be determined in what follows.

In absence of dissipation ($R = 0$) and thermal noise $g = 0$, the kinetic energy of the bar plus the energy stored in the induced magnetic field in the circuit is a conserved quantity

$$H = \frac{p^2}{2M} + \frac{\Phi^2}{2L(x)}, \tag{5}$$

where $p = Mv$ is the momentum of the bar and $\Phi = L(x)I(t)$ is the magnetic flux through the circuit. In terms of these momenta, and using the derivatives

$$\frac{\partial H}{\partial p} = \frac{p}{M} = v, \qquad \frac{\partial H}{\partial \Phi} = \frac{\Phi}{L} = I, \qquad \frac{\partial H}{\partial x} = -\frac{L'\Phi^2}{2L^2} = -\frac{L'I^2}{2}, \tag{6}$$

the equations of motion take the form

$$\begin{aligned}\dot{x} &= \frac{\partial H}{\partial p},\\ \dot{p} &= -\frac{\partial H}{\partial x} - lB_0\frac{\partial H}{\partial \Phi},\\ \dot{\Phi} &= lB_0\frac{\partial H}{\partial p} - R\frac{\partial H}{\partial \Phi} + g\Gamma(t).\end{aligned} \tag{7}$$

1.1 Fix the value of g

The *equipartition theorem* for the enregy tells us that, in equilibrium, the average energy contributed by each degree of freedom of a system is $k_BT/2$, where k_B is the Boltzmann constant and T is the absolute temperature of the reservoir in contact with system. Therefore, at equilibrium

$$\left\langle \frac{\Phi^{*2}}{2L^*} \right\rangle = \frac{1}{2}k_BT, \tag{8}$$

where the asterisk means the quantity is at thermal equilibrium, and the average is taken over the sample space of the random variable of interest, which in this case is $I(t)$. As L^* is not a functon of I, we obtain

$$\left\langle \Phi^{*2} \right\rangle = k_BTL^*. \tag{9}$$

On the other hand, when x is fixed equation (7) becomes

$$\frac{d\Phi^*}{dt} = -\frac{R^*}{L^*}\Phi^* + g\Gamma(t), \tag{10}$$

which is the Langevin equation of an O-U process with drift constant R^*/L^* and diffusion constant g, and its variance satisfies (see Gillespie [1])

$$\left\langle \Phi^{*2} \right\rangle = \frac{g^2L^*}{2R^*}. \tag{11}$$

By equating (9) and (11) we get

$$g = \sqrt{2k_BTR^*}. \tag{12}$$

We see that g does not depend on $L(x)$, and it is a function only of the temperature and resistance of the circuit.

The form of g can also be verified following a different route. The equations of motion (7) have the form (92) with a single white noise, $m = 1$. The drift is

$$b = (A - K)\nabla H, \qquad A = \begin{pmatrix} 0 & 1 & 0 \\ -1 & 0 & -lB_0 \\ 0 & lB_0 & 0 \end{pmatrix}, \qquad K = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & R \end{pmatrix}, \tag{13}$$

where A is a constant antisymmetric matrix that contains the conservative terms, and K is a symmetric matrix that contains the dissipation. The noise enters only in Φ and with a constant amplitude, so

$$\sigma = \begin{pmatrix} 0 \\ 0 \\ g \end{pmatrix}, \qquad D = \sigma\sigma^T = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & g^2 \end{pmatrix}. \tag{14}$$

The noise is additive, and there is no difference between the Itô and Stratonovich interpretations. Since D is constant, the probability current (103) splits as

$$\begin{aligned} J &= J^c + J^d, \\ J^c_i &= A_{ij}\partial_j H\,\rho, \\ J^d_i &= -K_{ij}\partial_j H\,\rho - \frac{1}{2}D_{ij}\partial_j\rho, \end{aligned} \tag{15}$$

the conservative part, and the dissipative plus noise part.

Conservative part: Let the density be any function of the energy, $\rho = F(H)$. Then

$$\begin{aligned} \partial_i J^c_i &= A_{ij}\partial_i\partial_j H\,F(H) + A_{ij}\partial_i H\partial_j H\,F'(H) \\ &= 0, \end{aligned} \tag{16}$$

since each term is the contraction of the antisymmetric A_{ij} with a symmetric quantity. The conservative part of the dynamics moves the probability along the surfaces of constant energy, with a current J^c that is not zero but has zero divergence, and leaves any function of H stationary.

Dissipative and noise part: K and D have only a $\Phi\Phi$ component, so J^d has only a Φ component

$$J_\Phi = -R\frac{\Phi}{L}\rho - \frac{g^2}{2}\frac{\partial\rho}{\partial\Phi}. \tag{17}$$

The first term is the drift of the flux towards zero due to the resistance, and the second term is the diffusion of the flux due to the Johnson emf. For the Gibbs density

$$\rho = \frac{1}{Z}e^{-H/kT}, \qquad \frac{\partial\rho}{\partial\Phi} = -\frac{1}{kT}\frac{\partial H}{\partial\Phi}\rho = -\frac{\Phi}{LkT}\rho, \tag{18}$$

the two terms are proportional to each other

$$J_\Phi = \frac{\Phi}{L}\rho\left(\frac{g^2}{2kT} - R\right). \tag{19}$$

Since the conservative part does not contribute, the Gibbs density is stationary if and only if $\partial J_\Phi/\partial\Phi = 0$. From

$$\frac{\partial J_\Phi}{\partial\Phi} = \frac{1}{L}\left(1 - \frac{\Phi^2}{LkT}\right)\rho\left(\frac{g^2}{2kT} - R\right), \tag{20}$$

which is not identically zero unless the last factor vanishes, the Gibbs density is stationary if and only if

$$g^2 = 2kTR, \tag{21}$$

in which case the current J_Φ itself vanishes for every x: the drift caused by the resistance and the diffusion caused by the noise balance each other at every point. This is the fluctuation-dissipation relation, written in general as $D = 2kTK$. With this value of g,

$$\rho \propto \exp\left(-\frac{p^2}{2MkT} - \frac{\Phi^2}{2L(x)kT}\right), \tag{22}$$

which is Gaussian in p and, for each x, in Φ, with $\langle p^2\rangle = MkT$ and $\langle\Phi^2|x\rangle = L(x)kT$, that is, $\langle Mv^2\rangle = \langle LI^2\rangle = kT$. Integrating over p and Φ leaves a density in x proportional to $\sqrt{L(x)}$, so the Gibbs density can be normalized only if x is confined to a bounded range.

Equation for the current: Itô's formula gives the equation for $I = \Phi/L(x)$ from (7). The only non-zero component of the diffusion matrix is $D_{\Phi\Phi} = g^2$ and $\partial^2 I/\partial\Phi^2 = 0$, so the second order term in (97) vanishes and the ordinary chain rule applies

$$\begin{aligned} dI &= \frac{\partial I}{\partial x}dx + \frac{\partial I}{\partial \Phi}d\Phi \\ &= -\frac{L'I}{L}v\,dt + \frac{1}{L}\left[(lB_0 v - RI)dt + g\,dW\right] \\ &= \left[\frac{lB_0 v}{L} - \frac{1}{L}(R + L'v)I\right]dt + \frac{g}{L}dW, \end{aligned} \tag{23}$$

which is the circuit equation with the noise amplitude $c(t) = g/L(x(t)) = \sqrt{2kTR}/L(x(t))$.

1.2 Units

We define an energy constant equal to the energy of the applied magnetic field contained in a volume d^3, of the order of the volume of the bar,

$$E_0 = \frac{B_0^2 d^3}{2\mu_0}, \tag{24}$$

where d is the radius of the wire, μ_0 the magnetic permeability of free space, and $B_0^2/2\mu_0$ is the energy density of the applied field. We also define a time constant related to the decay time of the induced current in the circuit when the position of the bar $x \to \infty$

$$\tau = \frac{\mu_0 d^2}{\rho_{Cu}}, \tag{25}$$

where ρ_{Cu} is the resistivity of copper. When L is constant, eliminating I from the equations of motion gives the equation of a damped oscillator for the velocity of the bar

$$\ddot{v} + 2\gamma\dot{v} + \omega^2 v = 0, \qquad \gamma = \frac{R}{2L}, \qquad \omega^2 = \frac{l^2 B_0^2}{ML}. \tag{26}$$

For two long parallel rails of radius d separated by a distance l, neglecting the internal inductance of the wires, $L \simeq (\mu_0 x/\pi)\ln(l/d)$ and $R \simeq 2\rho_{Cu}x/(\pi d^2)$, so that for $x \to \infty$

$$\frac{1}{\gamma} = \frac{2L}{R} \simeq \tau \ln\frac{l}{d}. \tag{27}$$

That is, τ is the inverse of the decay parameter γ up to the logarithmic factor that depends on the geometry of the circuit. τ is also the magnetic diffusion time across the radius of the wire, i.e., the time a change of the magnetic field takes to penetrate a conductor of radius d. Finally, we define a current constant

$$I_0 = \frac{2\pi B_0 d}{\mu_0}. \tag{28}$$

By Ampère's law, a wire of radius d carrying a current I produces at its surface the field $\mu_0 I/2\pi d$, so I_0 is the current whose own field at the surface of the wire equals the applied field.

Based on these characteristic constants of the system, we propose the following dimensionless quantities. Those not given directly by E_0, τ, I_0, d and B_0 are derived from them, so that the energy of the circuit and its dissipation keep their form.

- Time

$$t^* = \frac{t}{\tau}. \tag{29}$$

- Lengths

$$x^* = \frac{x}{d}, \qquad l^* = \frac{l}{d}. \tag{30}$$

- Velocity

$$v^* = \frac{\tau}{d} v. \tag{31}$$

- Mass

$$M^* = \frac{d^2}{E_0 \tau^2} M. \tag{32}$$

- Magnetic field

$$B^* = \frac{B}{B_0}, \tag{33}$$

so that the applied field is $B_0^* = 1$.

- Temperature

$$T^* = \frac{k_B}{E_0} T, \tag{34}$$

where k_B is Boltzmann's constant.

- Electric current

$$I^* = \frac{I}{I_0}. \tag{35}$$

I^* measures the self-field of the circuit relative to the applied field.

- Inductance and its gradient

$$L^* = \frac{I_0^2}{E_0} L = \frac{8\pi^2}{\mu_0 d} L, \qquad L'^* = \frac{dL^*}{dx^*} = \frac{8\pi^2}{\mu_0} L', \tag{36}$$

so that $L^* I^{*2} = L I^2 / E_0$.

- Magnetic flux

$$\Phi^* = \frac{I_0}{E_0} \Phi = \frac{4\pi}{B_0 d^2} \Phi. \tag{37}$$

- Electric resistance

$$R^* = \frac{\tau I_0^2}{E_0} R = \frac{8\pi^2 d}{\rho_{Cu}} R, \tag{38}$$

so that $R^*/L^* = \tau R/L$.

- White noise and its amplitude. Since $\langle \Gamma(t)\Gamma(t')\rangle = \delta(t-t')$, Γ has units of time$^{-1/2}$, and

$$\Gamma^* = \sqrt{\tau}\,\Gamma, \qquad g^* = \frac{\sqrt{\tau} I_0}{E_0} g, \tag{39}$$

  so that $\langle \Gamma^*(t^*)\Gamma^*(t'^*)\rangle = \delta(t^*-t'^*)$ and $g^* = \sqrt{2T^*R^*}$.

With these quantities the energy keeps its form, $H^* = H/E_0 = p^{*2}/2M^* + \Phi^{*2}/2L^*$, and the equations of motion become

$$\begin{aligned}
\frac{dx^*}{dt^*} &= v^*, \\
\frac{dv^*}{dt^*} &= -\frac{4\pi l^* B_0^*}{M^*} I^* + \frac{1}{2M^*} L'^* I^{*2}, \\
\frac{dI^*}{dt^*} &= \frac{4\pi l^* B_0^*}{L^*} v^* - \frac{1}{L^*}\left(R^* + L'^* v^*\right) I^* + \frac{g^*}{L^*}\Gamma^*(t^*).
\end{aligned} \tag{40}$$

The only numerical factor left is the $4\pi = B_0 I_0 d^2/E_0$ in the coupling between the bar and the circuit. It appears because E_0, I_0 and B_0 are three independent choices for the scales of only two independent dimensions, mass and current, once d and τ are fixed.

From here on we drop the asterisks for brevity, and all quantities are dimensionless unless stated otherwise. Using $B_0^* = 1$, the equations of motion read

$$\begin{aligned}
\frac{dx}{dt} &= v, \\
\frac{dv}{dt} &= -\frac{4\pi l}{M} I + \frac{1}{2M} L' I^2, \\
\frac{dI}{dt} &= \frac{4\pi l}{L} v - \frac{1}{L}\left(R + L' v\right) I + \frac{g}{L}\Gamma(t),
\end{aligned} \tag{41}$$

with $H = p^2/2M + \Phi^2/2L$ and $g = \sqrt{2TR}$.

1.3 Equilibrium with a moving bar

In the first derivation of g in Sec. 1.1 the position x is frozen, and L and R take fixed equilibrium values. In the simulation, however, x changes in time, and the noise amplitude $g/L(x(t))$ of the circuit equation (23) changes with it. Here we argue that this dependence does not prevent the system from reaching equilibrium, and we point out what can.

The x-dependence is harmless: The first derivation is a heuristic, valid only for fixed x, but the second derivation does not freeze x. With $g^2 = 2kTR(x)$, Eq. (21), the dissipative plus noise current (17) vanishes at every point (x, p, Φ) of phase space, and not only on average, whatever the functions $L(x)$ and $R(x)$ are. The conservative part leaves any function of $H = p^2/2M + \Phi^2/2L(x)$ stationary. Therefore the Gibbs density (22) is an exact stationary solution of the full dynamics, with the bar free to move.

In Sec. 1.1 the noise amplitude was treated as a constant, but $g = \sqrt{2kTR(x)}$ depends on x. This does not change the argument. The diffusion term of the Fokker-Planck equation is $\frac{1}{2}\partial_\Phi^2(D_{\Phi\Phi}\rho)$, and since $D_{\Phi\Phi} = g(x)^2$ does not depend on Φ it can be taken out of the derivative, so the current keeps the form (17). Moreover, x carries no noise of its own: it is a differentiable function of time, $\dot{x} = v$, so the dependence of g on x produces no Itô-Stratonovich correction to the drift.

The factor $1/L(x)$ in the noise amplitude of (23) is only the result of the change of variables from Φ to $I = \Phi/L(x)$. The same change of variables produces the term $-L'vI/L$ in the drift, and the two together keep the equation for I equivalent to the equation for Φ. A simulation that integrates (23), with g/L evaluated at the current position of the bar, samples the same Gibbs density, and conditional on x it must give $\langle Mv^2 \rangle = \langle L(x)I^2 \rangle = kT$.

What can prevent equilibrium:

- *The position cannot be normalized.* Integrating (22) over p and Φ leaves a marginal density in x proportional to $\sqrt{L(x)}$. For the rails $L \propto x$, which grows without bound, so the density in x cannot be normalized. In the dynamics this appears as a mean force on the bar,

$$\left\langle \frac{1}{2} L' I^2 \middle| x \right\rangle = \frac{1}{2} L' \frac{kT}{L} = kT \frac{d}{dx} \ln \sqrt{L(x)}, \tag{42}$$

  a thermal pressure that pushes the bar slowly towards larger x. The velocity and the current thermalize at every x, that is, they reach a local equilibrium, but x does not settle. A global equilibrium requires confining the bar, e.g., with a wall or a potential.

- *Discretization.* The Euler-Maruyama scheme equilibrates to a slightly wrong temperature, with an error of order dt relative to the fastest time scales, L/R and $1/\omega$ in (26). For the rails L/R is approximately independent of x, which helps, but as $x \to 0$ we have $L(x) \to 0$ and g/L diverges, so a small dt or a lower bound on x is needed there.

- *Ergodicity.* The noise acts only on Φ, and it reaches p only through the coupling lB_0. For $B_0 \neq 0$ this is enough for the system to thermalize, but for $B_0 = 0$ the velocity of the bar never thermalizes.

Check in the simulation: Bin the samples by x and verify that $\langle Mv^2 \rangle \simeq kT$ and $\langle L(x)I^2 \rangle \simeq kT$ in each bin. A slow outward drift of the histogram of x is the effect of the $\sqrt{L(x)}$ marginal density, not a failure of the noise amplitude $g/L(x)$.

A Brownian motion

The definitions and results of the appendices can be found in the book of Pavliotis [2].

Definition A.1. *A one-dimensional standard Brownian motion $W(t) : \mathbb{R}^+ \to \mathbb{R}$ is a real-valued stochastic process with almost surely (a.s.) continuous paths such that $W(0) = 0$, it has independent increments ΔW, and for every $t > s \geq 0$, the increment $\Delta W(t, s) = W(t) - W(s)$ has a Gaussian distribution with mean 0 and variance $t - s$*

$$g(x; t, s) = (2\pi(t-s))^{-\frac{1}{2}} e^{-\frac{x^2}{2(t-s)}}. \tag{43}$$

B Filtration

σ-algebra: A σ-algebra on a set X is a non-empty collection Σ of subsets of X closed under *complement*, countable *unions*, and countable *intersections*. The pair (X, Σ) is called a *measurable space*.

Let the measure space be the probability space $(\Omega, \mathcal{F}, \mathbb{P})$, where Ω is the *sample space*, i.e., the collection of the possible outcomes of the random variable. $\mathcal{F}$ is the *event space*, i.e., a σ-algebra formed by a collection of subsets of the sample space to which a probability measure can be applied. $\mathbb{P}$ is a map from $\mathcal{F}$ to $[0, 1]$, that is, a probability measure. Additionally, let the *state space* be the measurable set of possible d-dimensional outcomes of an experiment $(\mathbb{R}^d, \mathcal{B})$, where the Borel σ-algebra $\mathcal{B}$ is there to give the mathematical structure

that makes the state space measurable, i.e., probabilities can be asigned to states. A state can correspond to one or even a subset of elements of the sample space.

Let X_t be a stochastic process. Define $\sigma(X_t, t \in \mathbb{R}_+)$ as the smallest σ-algebra generated by the family of mappings $\{X_t; \mathbb{R}_+\}$ (a random variable for each t) such that this family is a stochastic process with sample space Ω and state space $(\mathbb{R}^d, \mathcal{B})$. That is, each X_t is a measurable function (random variable) with respect to the σ-algebra generated by the process.

Define a *filtration* on $(\Omega, \mathcal{F})$ as a non-decreasing family $\{\mathcal{F}_t; t \in \mathbb{R}_+\}$ of sub-σ-algebras of $\mathcal{F}$

$$\mathcal{F}_s \subseteq \mathcal{F}_t \subseteq \mathcal{F}, \quad \text{for } s \leq t.$$

Example: Let $\Omega = \{HH, HT, TH, TT\}$ be the space of outcomes of two coin flips. Let $\mathcal{F}$ be the power set of Ω, which is the largest σ-algebra on Ω

$$\Omega^* = \underbrace{\{\emptyset, \{HH\}, \{HT\}, \ldots, \{HH, HT\}, \ldots, \{HH, HT, TH, TT\}\}}_{2^4 = 16 \text{ subsets}}$$

Let the coins be flipped one at a time, the first at $t = 1$ and the second at $t = 2$. Before any flip nothing is known about the outcome, so the only events whose occurrence can be decided are the trivial ones

$$\mathcal{F}_0 = \{\emptyset, \Omega\}.$$

After the first flip we know whether the first coin landed heads or tails, but nothing about the second. The outcomes HH and HT cannot yet be told apart, and neither can TH and TT, so

$$\mathcal{F}_1 = \{\emptyset, \{HH, HT\}, \{TH, TT\}, \Omega\}.$$

This is a σ-algebra: $\{HH, HT\}^c = \{TH, TT\}$, and the unions and intersections of its elements are again elements of $\mathcal{F}_1$. After the second flip the outcome is completely known, every subset of Ω can be decided, and

$$\mathcal{F}_2 = \Omega^* = \mathcal{F}.$$

Therefore

$$\mathcal{F}_0 \subseteq \mathcal{F}_1 \subseteq \mathcal{F}_2 = \mathcal{F},$$

and $\{\mathcal{F}_0, \mathcal{F}_1, \mathcal{F}_2\}$ is a filtration on $(\Omega, \mathcal{F})$. To index it by $t \in \mathbb{R}_+$ as in the definition, set $\mathcal{F}_t = \mathcal{F}_0$ for $0 \leq t < 1$, $\mathcal{F}_t = \mathcal{F}_1$ for $1 \leq t < 2$, and $\mathcal{F}_t = \mathcal{F}_2$ for $t \geq 2$.

The filtration encodes the information available at each time: $\mathcal{F}_t$ contains exactly the events for which, at time t, one can say whether they happened or not. For instance, the event "the first flip is heads", $\{HH, HT\}$, belongs to $\mathcal{F}_1$, while the event "both flips give the same result", $\{HH, TT\}$, belongs to $\mathcal{F}_2$ but not to $\mathcal{F}_1$, since it cannot be decided until the second coin is flipped.

This is the filtration generated by the process itself. Let X_t be the result of the t-th flip, with $X_t = 1$ for heads and $X_t = 0$ for tails. Then $X_1^{-1}(\{1\}) = \{HH, HT\}$ and $X_1^{-1}(\{0\}) = \{TH, TT\}$, so that $\mathcal{F}_1 = \sigma(X_1)$, and similarly $\mathcal{F}_2 = \sigma(X_1, X_2)$. In general $\mathcal{F}_t = \sigma(X_s, s \leq t)$ is the smallest σ-algebra for which all the X_s with $s \leq t$ are measurable. Note that X_2 is not measurable with respect to $\mathcal{F}_1$, since $X_2^{-1}(\{1\}) = \{HH, TH\} \notin \mathcal{F}_1$: the second flip is not known at $t = 1$.

C Expected values

Every expected value in these notes is, by definition, an integral over the sample space Ω with respect to the probability measure $\mathbb{P}$. A random variable is a measurable function $X_t : \Omega \to \mathbb{R}^d$, and for a function f of the state

$$\mathbb{E}[f(X_t)] = \int_\Omega f(X_t(\omega)) d\mathbb{P}(\omega). \tag{44}$$

Each ω is one complete realization of the experiment, e.g., one whole history of the noise, so (44) is an average over the ensemble of realizations at a fixed time t.

In practice the expected value is computed as an integral over the state space. The random variable X_t carries $\mathbb{P}$ over to a probability measure on the state space $(\mathbb{R}^d, \mathcal{B})$, the *distribution* of X_t,

$$\mathbb{P}_{X_t}(\Gamma) = \mathbb{P}(X_t \in \Gamma) = \mathbb{P}(\{\omega | X_t(\omega) \in \Gamma\}), \qquad \Gamma \in \mathcal{B}, \tag{45}$$

and a change of variables gives

$$\begin{aligned} \mathbb{E}[f(X_t)] &= \int_{\mathbb{R}^d} f(x) \mathbb{P}_{X_t}(dx) \\ &= \int_{\mathbb{R}^d} f(x) \rho_t(x) dx, \end{aligned} \tag{46}$$

where the last equality holds when the distribution has a density ρ_t with respect to the Lebesgue measure. The density contains all that is needed to compute expected values at time t, and Ω never has to be known explicitly.

Some remarks on the notation:

- The angle brackets $\langle \cdot \rangle$ used in physics are the same expected value, $\langle f(X_t) \rangle = \mathbb{E}[f(X_t)]$. For example, $\langle Mv^2 \rangle$ in the stationary state is (46) with ρ_t the stationary density.
- The pairing $\langle f, \rho \rangle = \int f(x)\rho(x)dx$ used for the adjoint semigroup is not by itself an expected value. It is an integral over the state space, and it is equal to $\mathbb{E}[f(X_t)]$ only when ρ is the density of X_t.
- A conditional expected value is not a number. $\mathbb{E}[f(X_t)|\mathcal{F}_s]$ is a random variable, i.e., a function of ω, measurable with respect to $\mathcal{F}_s$, that averages only over what is not yet known at time s. $\mathbb{E}[f(X_t)|X_s = x]$ is the corresponding function of the state x.
- None of these are time averages along a single trajectory $t \mapsto X_t(\omega)$. A time average is equal to the ensemble average only for an ergodic process in its stationary state, which is an additional property and not part of the definition.

D Markov process

Let $\{X_t, t \in \mathbb{R}_+\}$ be a stochastic process, i.e., a family of random variables indexed by $t \in \mathbb{R}_+$, and let $\mathcal{F}_t = \sigma(X_s, s \le t)$ be the filtration generated by it.

Set $\mathcal{F}_\infty = \sigma(\cup_{t \in \mathbb{R}_+} \mathcal{F}_t)$. $\mathcal{F}_\infty$ is the smallest σ-algebra containing every $\mathcal{F}_t$, i.e., all the information that the filtration ever reveals. It should not be confused with $\mathcal{F}$, the σ-algebra of all the events on which $\mathbb{P}$ is defined. $\mathcal{F}$ is fixed beforehand as part of the probability space and the filtration only has to live inside it, so in general

$$\mathcal{F}_t \subseteq \mathcal{F}_\infty \subseteq \mathcal{F}, \quad \text{for all } t,$$

and the last inclusion can be strict: if $\mathcal{F}$ contains randomness that the process never observes, those events are in $\mathcal{F}$ but not in $\mathcal{F}_\infty$. For example, take three coin flips with $\mathcal{F}$ the power set of the eight outcomes, and a process that only records the first two flips. The event "the third flip is heads" is in $\mathcal{F}$ but not in $\mathcal{F}_\infty$. In the two-coin example of the appendix, on the other hand, $\mathcal{F}_\infty = \mathcal{F}_2 = \mathcal{F}$. Since the events outside $\mathcal{F}_\infty$ are irrelevant to the process, it is common to simply assume $\mathcal{F} = \mathcal{F}_\infty$.

The $\sigma(\cdot)$ in the definition is needed because the union of the $\mathcal{F}_t$ is in general not a σ-algebra. For a non-decreasing family the union is closed under complements and finite unions, but not under countable unions. For example, take an infinite sequence of coin flips with $\mathcal{F}_n = \sigma(X_1, \ldots, X_n)$. The union $\cup_n \mathcal{F}_n$ contains only the events that are decided by a finite number of flips. The event "heads occurs infinitely often" depends on the whole sequence, so it is not in $\cup_n \mathcal{F}_n$, but it is in $\mathcal{F}_\infty$, since it can be written as

$$\bigcap_{n\geq 1} \bigcup_{m\geq n} \{X_m = 1\},$$

a countable intersection of countable unions of events of the $\mathcal{F}_m$.

Definition D.1. *Let X_t be a stochastic process defined on a probability space $(\Omega, \mathcal{F}, \mathbb{P})$ with values in $\mathbb{R}^d$, and let $\mathcal{F}_t^X$ be the filtration generated by $\{X_t; t \in \mathbb{R}_+\}$. Then $\{X_t; t \in \mathbb{R}_+\}$ is a* **Markov process** *if*

$$\mathbb{P}(X_t \in \Gamma | \mathcal{F}_s^X) = \mathbb{P}(X_t \in \Gamma | X_s) \tag{47}$$

for all $t, s \in \mathbb{R}_+$ with $t \geq s$, and $\Gamma \in \mathcal{B}(\mathbb{R}^d)$. $\mathcal{F}_t^X$ is generated by events of the form $\{\omega | X_{t_1} \in \Gamma_1, X_{t_2} \in \Gamma_2, \ldots, X_{t_n} \in \Gamma_n\}$, with $0 \leq t_1 < t_2 < \cdots < t_n \leq t$ and $\Gamma_i \in \mathcal{B}(\mathbb{R}^d)$. The definition of a Markov process is equivalent to the hierarchy of equations

$$\mathbb{P}(X_t \in \Gamma | X_{t_1}, X_{t_2}, \ldots, X_{t_n}) = \mathbb{P}(X_t \in \Gamma | X_{t_n}),$$

for $n \geq 1$ and $0 \leq t_1 < t_2 < \cdots < t_n \leq t$ with $\Gamma \in \mathcal{B}(\mathbb{R}^d)$.

E Chapman-Kolmogorov equation

E.1 Discrete states

Consider first a Markov process in continuous time whose state space is a finite set $\{1, 2, \ldots, N\}$ instead of $\mathbb{R}^d$. The transition function is then the $N \times N$ *transition matrix* $P(s, t)$ with elements

$$P_{ij}(s, t) = \mathbb{P}(X_t = j | X_s = i), \qquad t \geq s, \tag{48}$$

the probability of being in the state j at time t given that the process was in the state i at time s. Its elements are non-negative and each of its rows adds up to one, $\sum_j P_{ij}(s, t) = 1$, since the process has to be in some state at time t.

Let $s \leq u \leq t$. To go from i at time s to j at time t the process has to pass through some state k at the intermediate time u. Adding the probabilities of these mutually exclusive alternatives, and using the Markov property to drop the condition on X_s once X_u is known,

$$\begin{aligned} \mathbb{P}(X_t = j | X_s = i) &= \sum_k \mathbb{P}(X_t = j | X_u = k, X_s = i) \mathbb{P}(X_u = k | X_s = i) \\ &= \sum_k \mathbb{P}(X_t = j | X_u = k) \mathbb{P}(X_u = k | X_s = i), \end{aligned} \tag{49}$$

that is,

$$P_{ij}(s,t) = \sum_k P_{ik}(s,u)P_{kj}(u,t). \tag{50}$$

This is the Chapman-Kolmogorov equation, and it is just a matrix product

$$P(s,t) = P(s,u)P(u,t). \tag{51}$$

In the same way, if π_i is the probability of the initial state i, the probability of a whole path is

$$\mathbb{P}(X_{t_0} = i_0, X_{t_1} = i_1, \ldots, X_{t_n} = i_n) = \pi_{i_0} \prod_{j=1}^{n} P_{i_{j-1}i_j}(t_{j-1}, t_j). \tag{52}$$

The continuous case below has the same structure. The matrix element $P_{ij}(s,t)$ becomes the transition probability density $p(y,t|x,s)$, with x in the place of the initial state i and y in the place of the final state j, and the sum over the intermediate state k becomes an integral over the intermediate point z. The matrix product becomes a composition of integral kernels, which is a convolution when the density depends only on the difference $y - x$, as it does for Brownian motion.

E.2 Continuous states

With every continuous time Markov process X_t defined in a probability space $(\Omega, \mathcal{F}, \mathbb{P})$ and a state space $(\mathbb{R}^d, \mathcal{B})$, we can associate the *transition function* [2]

$$P(\Gamma, t|X_s, s) := \mathbb{P}[X_t \in \Gamma|\mathcal{F}_s^X] \tag{53}$$

for all $t, s \in \mathbb{R}_+$, with $t \geq s$ and $\Gamma \in \mathcal{B}(\mathbb{R}^d)$. The transition function satisfies the *Chapman-Kolmogorov* equation

$$P(\Gamma, t|x, s) = \int_{\mathbb{R}^d} P(\Gamma, t|y, u)P(dy, u|x, s), \tag{54}$$

where $s \leq u \leq t$. Here $\int P(dy, u|x, s)$ is an integral against the transition probability measure itself. If this measure has a density $p(y, u|x, s)$ with respect to the Lebesgue measure, then $P(dy, u|x, s) = p(y, u|x, s)dy$ and the integral becomes an integral of the density with respect to the Lebesgue measure, $\int p(y, u|x, s)dy$. Such a density does not always exist. In what follows we consider Markov processes whose transition function has a density with respect to the Lebesgue measure:

$$P(\Gamma, t|x, s) = \int_\Gamma p(y, t|x, s)dy, \tag{55}$$

and refer to $p(y, t|x, s)$ as the *transition probability density*. From (54) and (55) we obtain

$$\int_\Gamma p(y, t|x, s)dy = \int_{\mathbb{R}^d} \int_\Gamma p(y, t|z, u)p(z, u|x, s)dydz. \tag{56}$$

Since Γ is arbitrary, the transition probability density itself satisfies the Chapman-Kolmogorov equation

$$p(y, t|x, s) = \int_{\mathbb{R}^d} p(y, t|z, u)p(z, u|x, s)dz, \tag{57}$$

for almost every y.

Assuming that the initial distribution has a density ρ, we can write

$$p(x_0, t_0, \ldots, x_n, t_n) = \rho(x_0) \prod_{j=1}^{n} p(x_j, t_j|x_{j-1}, t_{j-1}). \tag{58}$$

F Forward and backwards Kolmogorov equations

F.1 Discrete states

Let the state space be the finite set $\{1, 2, \ldots, N\}$ and let the process be time-homogeneous, so that the transition matrix depends only on the elapsed time. Write P_t for the matrix with elements

$$(P_t)_{ij} = \mathbb{P}(X_{s+t} = j | X_s = i). \tag{59}$$

The Chapman-Kolmogorov equation becomes

$$P_{t+h} = P_t P_h, \qquad P_0 = I, \tag{60}$$

where the product is a matrix product and I is the identity matrix. Then

$$\frac{dP_t}{dt} = \lim_{h\to 0^+} \frac{P_t P_h - P_t}{h} = P_t G, \qquad G = \lim_{h\to 0^+} \frac{P_h - I}{h}, \tag{61}$$

and, since $P_{t+h} = P_h P_t$ as well, also $dP_t/dt = GP_t$. The *generator* G is now an $N \times N$ matrix. For a short time h

$$(P_h)_{ij} = \delta_{ij} + G_{ij} h + o(h), \tag{62}$$

so for $i \neq j$ the element $G_{ij} \geq 0$ is the *transition rate* from i to j, the probability per unit time of jumping from i to j. Since each row of P_h adds up to one, each row of G adds up to zero

$$G_{ii} = -\sum_{j\neq i} G_{ij}, \tag{63}$$

which is minus the total rate of leaving the state i. The solution is the matrix exponential

$$P_t = e^{tG} = \sum_{n=0}^{\infty} \frac{t^n}{n!} G^n. \tag{64}$$

The matrix P_t can act on two different objects. A function of the state is a column vector $f = (f_1, \ldots, f_N)^T$, and P_t acts on it from the left

$$u_i(t) = (P_t f)_i = \sum_j (P_t)_{ij} f_j = \mathbb{E}[f(X_t) | X_0 = i]. \tag{65}$$

From $dP_t/dt = GP_t$ we obtain the *backward Kolmogorov equation*

$$\frac{du}{dt} = Gu, \qquad u(0) = f. \tag{66}$$

The probabilities of the states form a row vector $\pi(t) = (\pi_1(t), \ldots, \pi_N(t))$, with $\pi_j(t) = \mathbb{P}(X_t = j)$, and P_t acts on it from the right

$$\pi_j(t) = \sum_i \pi_i(0)(P_t)_{ij}, \qquad \pi(t) = \pi(0)P_t. \tag{67}$$

From $dP_t/dt = P_t G$ we obtain the *forward Kolmogorov equation*

$$\frac{d\pi}{dt} = \pi G, \qquad \text{or} \qquad \frac{d\pi^T}{dt} = G^T \pi^T. \tag{68}$$

Acting from the right on a row vector is the same as acting with the transpose on a column vector, so the probabilities evolve with P_t^T and G^T: for matrices the adjoint is the transpose. Using that the rows of G add up to zero, the forward equation reads in components

$$\frac{d\pi_j}{dt} = \sum_{i \neq j} \Big(\pi_i G_{ij} - \pi_j G_{ji} \Big), \tag{69}$$

which is called the *master equation*: the probability of the state j increases by the jumps into j and decreases by the jumps out of j. Both equations are contained in the expected value

$$\mathbb{E}[f(X_t)] = \sum_{i,j} \pi_i(0)(P_t)_{ij} f_j = \pi(0) P_t f, \tag{70}$$

where one can either evolve f and average over the initial probabilities, or evolve the probabilities and average f over them.

Example: For two states with transition rates α from 1 to 2 and β from 2 to 1,

$$G = \begin{pmatrix} -\alpha & \alpha \\ \beta & -\beta \end{pmatrix}, \qquad P_t = \Pi + e^{-(\alpha+\beta)t}(I - \Pi), \qquad \Pi = \frac{1}{\alpha+\beta} \begin{pmatrix} \beta & \alpha \\ \beta & \alpha \end{pmatrix}. \tag{71}$$

For $t \to \infty$ every row of P_t tends to the stationary probabilities $\pi = (\beta, \alpha)/(\alpha + \beta)$, which satisfy $\pi G = 0$, whatever the initial state.

The continuous case below has the same structure. The column vector f becomes a function $f(x)$, the row vector π becomes a probability density $\rho(x)$, the sums become integrals, and the matrix product becomes a composition of operators. The matrix G becomes a differential operator, its transpose becomes the adjoint G^*, and the master equation becomes the Fokker-Planck equation.

F.2 Continuous states

Let the process be *time-homogeneous*, i.e., let the transition function depend only on the elapsed time

$$P(\Gamma, t|x, s) = P(\Gamma, t - s|x, 0). \tag{72}$$

Introduce the notation

$$\begin{aligned} P_h(x, \Gamma) &= \mathbb{P}(X_{t+h} \in \Gamma | X_t = x) \\ &= \int_\Gamma p(y, t + h|x, t) dy, \end{aligned} \tag{73}$$

which does not depend on t, and where the last equality holds when a density exists. Let P_t also denote the operator that acts on a bounded measurable function f as

$$\begin{aligned} (P_t f)(x) &= \int_{\mathbb{R}^d} f(y) P_t(x, dy) \\ &= \mathbb{E}[f(X_t)|X_0 = x]. \end{aligned} \tag{74}$$

In this notation the Chapman-Kolmogorov equation with $s = 0$, $u = t$, and final time $t + h$ reads

$$P_{t+h}(x, \Gamma) = \int_{\mathbb{R}^d} P_h(y, \Gamma) P_t(x, dy), \tag{75}$$

that is, the operators form a semigroup

$$P_{t+h} = P_t \circ P_h, \qquad P_0 = I. \tag{76}$$

The differential form of the Chapman-Kolmogorov equation is

$$\begin{aligned} \frac{dP_t}{dt} &= \lim_{h\to 0^+} \frac{P_{t+h} - P_t}{h} \\ &= \lim_{h\to 0^+} \frac{P_t \circ P_h - P_t \circ I}{h} \\ &= P_t \circ \left(\lim_{h\to 0^+} \frac{P_h - I}{h} \right) \\ &= P_t \circ G, \end{aligned} \tag{77}$$

where

$$G = \lim_{h\to 0^+} \frac{P_h - I}{h} \tag{78}$$

is called the *generator* of the Markov process. The limit is understood as acting on the functions f for which it exists, which form the domain of G. For a finite state space G is a matrix and the limit exists for every f, but on $\mathbb{R}^d$ the generator is in general an unbounded differential operator, e.g., $G = \frac{1}{2}\Delta$ for Brownian motion. The definition of G allows us to write formally the P_t operator as

$$P_t = e^{tG}. \tag{79}$$

Since $t + h = h + t$, the semigroup property also gives $P_{t+h} = P_h \circ P_t$, so P_t and P_h always commute for a time-homogeneous process, and the same argument gives

$$\frac{dP_t}{dt} = G \circ P_t. \tag{80}$$

Both forms hold at once, $\frac{d}{dt}P_t f = P_t G f = G P_t f$ for f in the domain of G. They differ in where the small time step h is taken: at the end of the time interval in $P_t \circ P_h$, and at the beginning in $P_h \circ P_t$. Each of them leads to a different evolution equation.

Backward equation: Let

$$u(x,t) = (P_t f)(x) = \mathbb{E}[f(X_t)|X_0 = x]. \tag{81}$$

Applying $dP_t/dt = G \circ P_t$ to f gives the *backward Kolmogorov equation*

$$\begin{aligned} \frac{\partial u}{\partial t} &= \frac{\partial}{\partial t}\left(P_t f\right) \\ &= \frac{\partial}{\partial t}\left(e^{tG} f\right) \\ &= G\left(e^{tG} f\right) \\ &= G\left(P_t f\right) \\ &= Gu, \qquad u(x,0) = f(x), \end{aligned} \tag{82}$$

where G acts on the initial point x of the process.

Forward equation: The semigroup P_t evolves functions of the state. The evolution of the probability density of the state is given instead by the *adjoint semigroup*. Define the pairing

$$\langle f, \rho \rangle = \int_{\mathbb{R}^d} f(x)\rho(x)dx, \tag{83}$$

and the adjoint P_t^* of P_t by $\langle P_t f, \rho \rangle = \langle f, P_t^* \rho \rangle$ for all f and ρ. If X_0 has the density ρ_0, then

$$\begin{aligned} \mathbb{E}[f(X_t)] &= \int_{\mathbb{R}^d} \mathbb{E}[f(X_t)|X_0 = x]\rho_0(x)dx \\ &= \langle P_t f, \rho_0 \rangle \\ &= \langle f, P_t^* \rho_0 \rangle, \end{aligned} \tag{84}$$

so that

$$\rho_t = P_t^* \rho_0 \tag{85}$$

is the density of X_t. In terms of the transition probability density

$$\begin{aligned} (P_t f)(x) &= \int_{\mathbb{R}^d} p(y, t|x, 0) f(y) dy, \\ (P_t^* \rho)(y) &= \int_{\mathbb{R}^d} p(y, t|x, 0)\rho(x)dx, \end{aligned} \tag{86}$$

that is, P_t integrates over the final point and P_t^* over the initial point. Taking the adjoint reverses the order of a composition, $(P_t \circ P_h)^* = P_h^* \circ P_t^*$, so the P_t^* also form a semigroup, and its generator is the adjoint G^* of G, defined by $\langle Gf, \rho \rangle = \langle f, G^* \rho \rangle$. Using $dP_t/dt = P_t \circ G$,

$$\begin{aligned} \frac{d}{dt}\langle f, \rho_t \rangle &= \frac{d}{dt}\langle P_t f, \rho_0 \rangle \\ &= \langle P_t G f, \rho_0 \rangle \\ &= \langle Gf, \rho_t \rangle \\ &= \langle f, G^* \rho_t \rangle. \end{aligned} \tag{87}$$

Since this holds for every f in the domain of G, we obtain the *forward Kolmogorov equation*, or *Fokker-Planck equation*,

$$\frac{\partial \rho_t}{\partial t} = G^* \rho_t, \qquad \rho_{t=0} = \rho_0. \tag{88}$$

Since f and ρ_0 are arbitrary, the transition probability density satisfies both equations

$$\begin{aligned} \frac{\partial}{\partial t} p(y, t|x, 0) &= G_x p(y, t|x, 0) \\ &= G_y^* p(y, t|x, 0), \end{aligned} \tag{89}$$

where the subscript indicates the variable on which the operator acts: the backward equation is an equation in the initial point x, and the forward equation is an equation in the final point y. The two operators are different in general. For example, for

$$\begin{aligned} Gf &= b(x) \cdot \nabla f + \frac{1}{2}\Delta f, \\ G^* \rho &= -\nabla \cdot (b(x)\rho) + \frac{1}{2}\Delta \rho, \end{aligned} \tag{90}$$

and they coincide only if G is self-adjoint, as for Brownian motion, $b = 0$.

Remark: If the process is not time-homogeneous, the transition operators depend on two times, $(P_{s,t}f)(x) = \mathbb{E}[f(X_t)|X_s = x]$, the Chapman-Kolmogorov equation reads $P_{s,t} = P_{s,u} \circ P_{u,t}$ for $s \le u \le t$, and the generator G_t depends on time. The operators at different times do not commute in general, and the two differential forms are no longer the same identity,

$$\begin{aligned} \frac{\partial}{\partial t} P_{s,t} &= P_{s,t} \circ G_t, \\ -\frac{\partial}{\partial s} P_{s,t} &= G_s \circ P_{s,t}. \end{aligned} \tag{91}$$

The first one is an equation in the final time t and, through the adjoint, gives the forward equation $\partial \rho_t / \partial t = G_t^* \rho_t$. The second one is an equation in the initial time s and gives the backward equation for $u(x, s) = (P_{s,t}f)(x)$, $-\partial u / \partial s = G_s u$, with the final condition $u(x, t) = f(x)$.

G Fokker-Planck equation

This section writes the generator G and its adjoint G^* explicitly for a process defined by a stochastic differential equation, which turns the forward Kolmogorov equation into a partial differential equation for the probability density, the Fokker-Planck equation. It is then applied to the sliding-bar circuit, to obtain the conservative and the dissipative plus noise parts of the probability current used in Sec. 4 of `noise_derivation.pdf`, starting from the Hamiltonian and the equations of motion. Repeated indices are summed, and $\partial_i = \partial / \partial x_i$.

G.1 Stochastic differential equations and Itô's formula

The mathematical theory of stochastic differential equations and of the Fokker-Planck equation is given in [2], and a presentation in terms of the Langevin equation and the white noise $\Gamma(t)$, with the application to Johnson noise, in [1]. Let the state $X_t \in \mathbb{R}^d$ obey the Langevin equation

$$\frac{dX_i}{dt} = b_i(X) + \sigma_{ik}(X)\Gamma_k(t), \tag{92}$$

where b_i is the *drift*, σ_{ik} is a $d \times m$ matrix, and the $\Gamma_k(t)$ are m independent Gaussian white noises

$$\langle \Gamma_k(t) \rangle = 0, \qquad \langle \Gamma_k(t)\Gamma_l(t') \rangle = \delta_{kl}\delta(t - t'). \tag{93}$$

$\Gamma_k(t)$ is not an ordinary function of time. Its integral, however, is the Brownian motion $W_k(t) = \int_0^t \Gamma_k(s)ds$, so that $\Gamma_k(t)dt = dW_k(t)$, and (92) is given a meaning as the *stochastic differential equation*

$$dX_i = b_i(X)dt + \sigma_{ik}(X)dW_k. \tag{94}$$

In the *Itô* interpretation σ_{ik} is evaluated at the beginning of the time step. The increment $dW_k(t) = W_k(t + dt) - W_k(t)$ is independent of $\mathcal{F}_t$, while $\sigma_{ik}(X_t)$ is $\mathcal{F}_t$-measurable, and therefore

$$\mathbb{E}[\sigma_{ik}(X_t)dW_k(t)|\mathcal{F}_t] = \sigma_{ik}(X_t)\mathbb{E}[dW_k(t)] = 0. \tag{95}$$

The increments of the Brownian motion have variance $\mathbb{E}[dW_k dW_l] = \delta_{kl}dt$, so dW is of order $\sqrt{dt}$, and the terms of second order in dW contribute to first order in dt. In the limit $dt \to 0$ the terms of higher order than dt are negligible, which is summarized in the rules

$$dW_k dW_l = \delta_{kl}dt, \qquad dW_k dt = 0, \qquad dt^2 = 0. \tag{96}$$

Let $f(x)$ be a smooth function. Expanding $f(X_t)$ to second order in dX and using (94) and the rules above gives *Itô's formula*

$$\begin{aligned} df &= \partial_i f \, dX_i + \frac{1}{2}\partial_i\partial_j f \, dX_i dX_j \\ &= \left(b_i \partial_i f + \frac{1}{2} D_{ij} \partial_i \partial_j f \right) dt + \sigma_{ik} \partial_i f \, dW_k, \end{aligned} \tag{97}$$

where

$$D_{ij} = \sigma_{ik}\sigma_{jk} \tag{98}$$

is the *diffusion matrix*. The term with D_{ij} is the difference with the ordinary chain rule.

In the *Stratonovich* interpretation σ_{ik} is evaluated at the midpoint of the time step instead. The two interpretations differ by a drift term that contains the derivatives of σ_{ik}, so they are the same equation when σ_{ik} does not depend on the state, which is called *additive noise*.

G.2 Generator and probability current

Taking the expectation of (97) conditional on $X_t = x$, the last term vanishes because of (95). The expectation is an integral over the final state y with the transition probability density, in which $f(y)$ is expanded around x,

$$\begin{aligned} \mathbb{E}[f(X_{t+h})|X_t = x] &= \int_{\mathbb{R}^d} f(y) p(y, t+h|x,t) dy \\ &= f(x) + \partial_i f(x) \int_{\mathbb{R}^d} (y_i - x_i) p(y, t+h|x,t) dy \\ &\quad + \frac{1}{2}\partial_i\partial_j f(x) \int_{\mathbb{R}^d} (y_i - x_i)(y_j - x_j) p(y, t+h|x,t) dy + \ldots \\ &= f(x) + h\left(b_i \partial_i f + \frac{1}{2} D_{ij} \partial_i \partial_j f \right)(x) + o(h), \end{aligned} \tag{99}$$

where the two integrals are the first and second moments of the increment $X_{t+h} - x$, equal to $b_i(x)h + o(h)$ and $D_{ij}(x)h + o(h)$ according to (94) and the rules above. The left hand side is $(P_h f)(x)$, so the generator $G = \lim_{h\to 0^+}(P_h - I)/h$ of the process (94) is

$$Gf = b_i \partial_i f + \frac{1}{2} D_{ij} \partial_i \partial_j f. \tag{100}$$

Its adjoint is obtained by integrating by parts, for a density ρ that vanishes at infinity,

$$\begin{aligned} \langle Gf, \rho \rangle &= \int_{\mathbb{R}^d} \left(b_i \partial_i f + \frac{1}{2} D_{ij} \partial_i \partial_j f \right) \rho \, dx \\ &= \int_{\mathbb{R}^d} f \left(-\partial_i (b_i \rho) + \frac{1}{2} \partial_i \partial_j (D_{ij} \rho) \right) dx \\ &= \langle f, G^* \rho \rangle. \end{aligned} \tag{101}$$

The forward Kolmogorov equation $\partial\rho/\partial t = G^*\rho$ becomes the *Fokker-Planck equation*

$$\frac{\partial \rho}{\partial t} = -\partial_i (b_i \rho) + \frac{1}{2} \partial_i \partial_j (D_{ij} \rho). \tag{102}$$

It has the form of a continuity equation

$$\frac{\partial \rho}{\partial t} + \partial_i J_i = 0, \qquad J_i = b_i \rho - \frac{1}{2} \partial_j (D_{ij} \rho), \tag{103}$$

where J is the *probability current*: probability is conserved, and it changes in a region only by flowing through its boundary. The first term of J_i is the transport of probability by the drift, and the second term is the diffusion caused by the noise. A density is *stationary* if

$$\partial_i J_i = 0. \tag{104}$$

Note that this does not require $J = 0$. A current that circulates without accumulating probability anywhere is compatible with a stationary density.

References

[1] D. T. Gillespie, The mathematics of Brownian motion and Johnson noise, Am. J. Phys. **64**, 225–240 (1996).

[2] G. A. Pavliotis, *Stochastic Processes and Applications: Diffusion Processes, the Fokker-Planck and Langevin Equations*, Texts in Applied Mathematics, Vol. 60 (Springer, New York, 2014).