Micphone Array API

modifies history

Version	Contributor	Date	Change Log
v1.0	bob.xu	18/09/01	init

Summary

Wukong Robot has four micphone on the head, which support DOA(direction-of-arrival), EC (Echo cancellation) and BeamForming.
With the api we provide, you can get 16K HZ 16bit audio pcm data.

> Note：using AudioRecord could not access micphone array，but can access a single micphone on chest,which use for phone calling.

SDK

- MicRecordApi API

```java
public class MicRecordApi {
    /**
     * init
     * @param initCallback callback when init succ or fail
     */
    public void init(InitCallback initCallback);

    /**
     * startRecord
     * @param callback : {@link AudioDataCallback} callback when read new audio data
     */
    public void startRecord(AudioDataCallback callback) {
        weiNaAudioOptimize.startRecord();
        weiNaAudioOptimize.setAudioDataCallback(callback);
    }

    /**
     * stopRecord
     */
    public void stopRecord() {
        weiNaAudioOptimize.stopRecord();
    }

    /**
     *
     * @param errorCallback
     */
    public void setErrorCallback(ErrorCallback errorCallback) {
        weiNaAudioOptimize.setErrorCallback(errorCallback);
    }

    /**
     * direction-of-arrival (DOA) estimation and beamforming
     */
    public void startDOABeamForming() {
        weiNaAudioOptimize.setWakeupState(1);
    }

    /**
     * setDoaAngleCallback, when startDOABeamForming() be called,
     * DoaAngleCallback.onDoaAngle()will be call
     * @param doaCallback: {@link DoaAngleCallback}
     */
    public void setDoaAngleCallback(DoaAngleCallback doaCallback) {
        weiNaAudioOptimize.setWakeupAngleCallback(doaCallback);
    }
```