

```

#include <LedControl.h>

#include <TM1637Display.h>

LedControl lc(11,13,10,3);

TM1637Display display(6,2);

#define BUTTON1 4

#define BUTTON2 5

int score=0;

bool randomSmile,gameOver=false;

unsigned long startTime;

byte smile[8]={

B00111100,B01000010,B10100101,B10000001,

B10100101,B10011001,B01000010,B00111100};

byte sad[8]={

B00111100,B01000010,B10100101,B10000001,

B10011001,B10100101,B01000010,B00111100};

byte E[8]={

B11111111,B10000000,B10000000,B11111110,

B10000000,B10000000,B10000000,B11111111};

byte N[8]={

B10000001,B11000001,B10100001,B10010001,

B10001001,B10000101,B10000011,B10000001};

byte D[8]={

B11111100,B10000010,B10000001,B10000001,

B10000001,B10000001,B10000010,B11111100};

void drawPattern(int d,byte p[]){

```

```

    for(int r=0;r<8;r++)
        for(int c=0;c<8;c++)
            lc.setLed(d,r,c,bitRead(p[r],7-c));
    }

void showFaces(){
    drawPattern(0,smile);
    drawPattern(1,sad);
    if(randomSmile) drawPattern(2,smile);
    else drawPattern(2,sad);
}

void showEND(){
    drawPattern(0,E);
    drawPattern(1,N);
    drawPattern(2,D);
}

void newRound(){
    randomSmile=random(2);
    showFaces();
}

void setup(){
    pinMode(BUTTON1,INPUT_PULLUP);
    pinMode(BUTTON2,INPUT_PULLUP);
    display.setBrightness(7);
    display.showNumberDec(0);
    for(int i=0;i<3;i++){

```

```
lc.shutdown(i,false);

lc.setIntensity(i,8);

lc.clearDisplay(i);
}

randomSeed(analogRead(A0));

startTime=millis();

newRound();
}

void loop(){

if(!gameOver && millis()-startTime>=30000){

    gameOver=true;

    showEND();

    return;

}

if(gameOver) return;

if(digitalRead(BUTTON1)==LOW){

    if(randomSmile){

        score++;

        display.showNumberDec(score);

        while(digitalRead(BUTTON1)==LOW);

        delay(100);

        newRound();

    }

}

if(digitalRead(BUTTON2)==LOW){
```

```
if(!randomSmile){  
    score++;  
    display.showNumberDec(score);  
    while(digitalRead(BUTTON2)==LOW);  
    delay(100);  
    newRound();  
}  
}  
}
```