

PRM: Open API

PRM Open API Guide

[PRM Open API Guide](#)

[Overview](#)

[Getting API Key](#)

[Base URL](#)

[Authentication](#)

[1. User APIs](#)

[Query User](#)

[2. Product APIs](#)

[List Products](#)

[3. Version APIs](#)

[List Versions](#)

[Get Version Detail](#)

[Get Release History](#)

[4. Ticket APIs](#)

[List Version Tickets](#)

[5. Critical Issue APIs](#)

[List Critical Issues](#)

[Get Critical Issue Detail](#)

[Create Critical Issue](#)

[Update Critical Issue](#)

[Delete Critical Issue](#)

[Critical Issue Status Values](#)

[Linked Cases URL Whitelist](#)

[6. Metrics APIs](#)

[Get Product Metrics](#)

[Error Responses](#)

[401 Unauthorized](#)

[404 Not Found](#)

[400 Bad Request](#)

[500 Internal Error](#)

[Contact](#)

Overview

The PRM (Product Release Management) Open API provides external systems access to PRM data. It uses API Key authentication without requiring JWT tokens or RBAC permissions.

Getting API Key

Please contact **Neil.Wei** or **Dada.Chan** to obtain an API Key.

Base URL

```
1 https://core-api-gw.uid.alpha.ui.com
```

Authentication

All requests require the API Key in the Authorization header:

```
1 Authorization: <your-api-key>
```

1. User APIs

Query User

Query user information. Currently supports email lookup, more query options will be added in the future.

Endpoint: `POST /api/v1/public/openapi/users/query`

Request Body:

Field	Type	Required	Description
email	string	Yes*	User email address

*Note: Currently only email query is supported. More query options will be added in the future.

Curl Example:

```
1 curl -X POST "https://prm.ui.com/api/v1/public/openapi/users/query" \  
2   -H "Authorization: your-api-key" \  
3   -H "Content-Type: application/json" \  
4   -d '{  
5     "email": "john.doe@ui.com"  
6   }'
```

Response Example:

```
1 {  
2   "code": "SUCCESS",  
3   "msg": "success",  
4   "data": {  
5     "unique_id": "user-12345678-abcd-1234-efgh-123456789012",  
6     "email": "john.doe@ui.com",  
7     "first_name": "John",  
8     "last_name": "Doe",  
9     "avatar": "https://avatar.example.com/john.jpg",  
10    "status": "active",  
11    "created_at": 1706601600,  
12    "updated_at": 1706688000  
13  }  
14 }
```

2. Product APIs

List Products

Get a list of all products.

Endpoint: `GET /api/v1/public/openapi/products`

Query Parameters:

Parameter	Type	Required	Description
page_size	int	No	Number of items per page (default 10)

page_num	int	No	Page number (default 1)
search	string	No	Search keyword
type_id	string	No	Product type ID
product_line_id	string	No	Product line ID

Curl Example:

```
1 curl -X GET "https://prm.ui.com/api/v1/public/openapi/products?
  page_size=10&page_num=1" \
2   -H "Authorization: your-api-key"
```

Response Example:

```
1 {
2   "code": "SUCCESS",
3   "msg": "success",
4   "data": [
5     {
6       "unique_id": "unifi-access",
7       "name": "UniFi Access",
8       "description": "UniFi Access product line",
9       "product_type": {
10        "unique_id": "access",
11        "name": "Access"
12      },
13      "product_line": {
14        "unique_id": "unifi",
15        "name": "UniFi"
16      }
17    }
18  ],
19  "page_size": 10,
20  "page_num": 1,
21  "total": 50
22 }
```

3. Version APIs

List Versions

Get all versions for a specific product.

Endpoint: GET /api/v1/public/openapi/product/{product_id}/versions

Path Parameters:

Parameter	Type	Required	Description
product_id	string	Yes	Product unique_id

Curl Example:

```
1 curl -X GET "https://prm.ui.com/api/v1/public/openapi/product/unifi-
  access/versions" \
2   -H "Authorization: your-api-key"
```

Response Example:

```

1  {
2    "code": "SUCCESS",
3    "msg": "success",
4    "data": [
5      {
6        "unique_id": "version-001",
7        "version": "3.5.1",
8        "status": "RELEASED",
9        "release_date": "2026-01-15"
10     },
11     {
12       "unique_id": "version-002",
13       "version": "3.5.0",
14       "status": "RELEASED",
15       "release_date": "2026-01-01"
16     }
17   ]
18 }

```

Get Version Detail

Get detailed information about a specific version.

Endpoint: GET

/api/v1/public/openapi/product/{product_id}/versions/{version_id}

Path Parameters:

Parameter	Type	Required	Description
product_id	string	Yes	Product unique_id
version_id	string	Yes	Version unique_id

Curl Example:

```

1  curl -X GET "https://prm.ui.com/api/v1/public/openapi/product/unifi-
2    access/versions/version-001" \
    -H "Authorization: your-api-key"

```

Response Example:

```

1  {
2    "code": "SUCCESS",
3    "msg": "success",
4    "data": {
5      "unique_id": "version-001",
6      "version": "3.5.1",
7      "status": "RELEASED",
8      "release_date": "2026-01-15",
9      "release_notes": "Bug fixes and performance improvements",
10     "channels": ["GA", "EA"]
11   }
12 }

```

Get Release History

Get release history for a specific version.

Endpoint: GET

/api/v1/public/openapi/product/{product_id}/versions/{version_id}/release

Path Parameters:

Parameter	Type	Required	Description
product_id	string	Yes	Product unique_id
version_id	string	Yes	Version unique_id

Curl Example:

```
1 curl -X GET "https://prm.ui.com/api/v1/public/openapi/product/unifi-
  access/versions/version-001/release" \
2   -H "Authorization: your-api-key"
```

4. Ticket APIs

List Version Tickets

List tickets (features or bugfixes) for a specific version.

Endpoint: GET

/api/v1/public/openapi/product/{product_id}/versions/{version_id}/tickets

Path Parameters:

Parameter	Type	Required	Description
product_id	string	Yes	Product unique_id
version_id	string	Yes	Version unique_id

Query Parameters:

Parameter	Type	Required	Description
type	string	Yes	Type: FEATURE or BUGFIX
page_size	int	No	Number of items per page
page_num	int	No	Page number

Curl Example:

```
1 curl -X GET "https://prm.ui.com/api/v1/public/openapi/product/unifi-
  access/versions/version-001/tickets?type=FEATURE" \
2   -H "Authorization: your-api-key"
```

Response Example:

```
1 {
2   "code": "SUCCESS",
3   "msg": "success",
4   "data": [
5     {
6       "unique_id": "ticket-001",
7       "type": "FEATURE",
8       "title": "New dashboard widget",
9       "description": "Added new monitoring dashboard widget",
10      "jira_key": "AC-12345"
11    }
12  ],
13  "page_size": 10,
14  "page_num": 1,
15  "total": 5
16 }
```

5. Critical Issue APIs

List Critical Issues

Get all Critical Issues for a specific product with analytics data.

Endpoint: GET /api/v1/public/openapi/product/{product_id}/critical_issues

Path Parameters:

Parameter	Type	Required	Description
product_id	string	Yes	Product unique_id

Query Parameters:

Parameter	Type	Required	Description
time_range	string	No	Time range (e.g., 1w, 2w, 1m, 3m, 1y)
start	string	No	Start date (YYYY-MM-DD), must be used with end
end	string	No	End date (YYYY-MM-DD), must be used with start
status	string	No	Status filter (comma-separated, e.g., OPEN,IN_PROGRESS)
search	string	No	Search keyword

Curl Example:

```
1 curl -X GET "https://prm.ui.com/api/v1/public/openapi/product/unifi-
  access/critical_issues?time_range=1m&status=OPEN,IN_PROGRESS" \
2 -H "Authorization: your-api-key"
```

Response Example:

```
1 {
2   "code": "SUCCESS",
3   "msg": "success",
4   "data": {
5     "critical_issues": {
6       "total": 15,
7       "tickets": [
8         {
9           "unique_id": "ci-12345678-abcd-1234-efgh-123456789012",
10          "display_id": "AC-21567",
11          "product_id": "unifi-access",
12          "status": "IN_PROGRESS",
13          "issue_type": "SOFTWARE",
14          "description": "Device loses connection after firmware
15          update",
16          "jira_link": "https://ubiquiti.atlassian.net/browse/AC-
17          21567",
18          "event_at": "2026-01-15",
19          "created_at": "2026-01-15T08:30:00Z",
20          "updated_at": "2026-01-28T14:20:00Z"
21        }
22      ],
23      "counts": {
24        "OPEN": 5,
25        "IN_PROGRESS": 8,
26        "RESOLVED": 2
27      }
28    }
29  }
```

Get Critical Issue Detail

Get the complete details of a specific Critical Issue.

Endpoint: GET

/api/v1/public/openapi/product/{product_id}/critical_issues/{critical_issue_id}

Path Parameters:

Parameter	Type	Required	Description
product_id	string	Yes	Product unique_id
critical_issue_id	string	Yes	Critical Issue unique_id

Curl Example:

```
1 curl -X GET "https://prm.ui.com/api/v1/public/openapi/product/unifi-
  access/critical_issues/ci-12345678" \
2 -H "Authorization: your-api-key"
```

Response Example:

```
1  {
2    "code": "SUCCESS",
3    "data": {
4      "unique_id": "ci-12345678-abcd-1234-efgh-123456789012",
5      "display_id": "AC-21567",
6      "product_id": "unifi-access",
7      "status": "IN_PROGRESS",
8      "issue_type": "SOFTWARE",
9      "description": "<p>Device loses connection after firmware
10 update</p>",
11      "root_cause": {
12        "content": "<p>Memory leak in network module</p>",
13        "user": {
14          "unique_id": "user-456",
15          "name": "Jane Smith"
16        }
17      },
18      "solution": {
19        "content": "<p>Patch released in v3.5.1</p>",
20        "user": {
21          "unique_id": "user-456",
22          "name": "Jane Smith"
23        }
24      },
25      "jira_link": "https://ubiquiti.atlassian.net/browse/AC-21567",
26      "slack_link": "https://ui.slack.com/archives/C123/p456",
27      "linked_cases": [
28        {
29          "unique_id": "link-001",
30          "source_type": "feedback",
31          "link_url": "https://help.ui.com/hc/requests/5042017"
32        }
33      ],
34      "action_items": [
35        {
36          "unique_id": "action-001",
37          "description": "Code review for memory management",
38          "jira_url": "https://ubiquiti.atlassian.net/browse/AC-21568",
39          "status": "COMPLETED"
40        }
41      ]
42    }
43  }
```

Create Critical Issue

Create a new Critical Issue.

Endpoint: POST /api/v1/public/openapi/product/{product_id}/critical_issues

Path Parameters:

Parameter	Type	Required	Description
product_id	string	Yes	Product unique_id

Request Body:

Field	Type	Required	Description
description	string	Yes	Issue description (supports HTML)
status	string	No	Status (default OPEN)

scope	string	No	Scope category (e.g., Hardware, Software)
issue_type	string	No	Issue type (e.g., HARDWARE, SOFTWARE, FIRMWARE)
root_cause	string	No	Root cause analysis
solution	string	No	Solution description
lesson_learned	string	No	Lessons learned
fix_teams	array	No	List of team IDs
tech_owners	array	No	List of tech owner user IDs
jira_link	string	No	Jira link (can provide just issue key, e.g., "AC-123")
slack_link	string	No	Slack link
zendesk_link	string	No	Zendesk link
event_at	string	No	Event date (YYYY-MM-DD)
linked_cases	array	No	List of linked case URLs
action_items	array	No	List of action items

Curl Example:

```

1 curl -X POST "https://prm.ui.com/api/v1/public/openapi/product/unifi-
  access/critical_issues" \
2   -H "Authorization: your-api-key" \
3   -H "Content-Type: application/json" \
4   -d '{
5     "description": "<p>Device loses WiFi connection
intermittently</p>",
6     "status": "INVESTIGATING",
7     "issue_type": "FIRMWARE",
8     "jira_link": "AC-22000",
9     "tech_owners": ["user-id-001"],
10    "event_at": "2026-01-30"
11  }'
```

Response Example:

```

1 {
2   "code": "SUCCESS",
3   "msg": "Critical issue created successfully",
4   "data": {
5     "unique_id": "ci-new-12345678",
6     "display_id": "AC-22000",
7     "status": "INVESTIGATING",
8     "created_at": "2026-01-30T10:00:00Z"
9   }
10 }

```

Update Critical Issue

Update an existing Critical Issue. Only send fields that need to be updated.

Endpoint: PUT

/api/v1/public/openapi/product/{product_id}/critical_issues/{critical_issue_id}

Path Parameters:

Parameter	Type	Required	Description
product_id	string	Yes	Product unique_id
critical_issue_id	string	Yes	Critical Issue unique_id

Request Body: (All fields are optional)

Field	Type	Description
status	string	Update status
description	string	Update description
root_cause	string	Update root cause
solution	string	Update solution
lesson_learned	string	Update lessons learned
progress_comment	string	Update progress comment
tech_owners	array	Update tech owners
linked_cases	array	Update linked cases (replaces existing)

Curl Example:

```

1 curl -X PUT "https://prm.ui.com/api/v1/public/openapi/product/unifi-
2   access/critical_issues/ci-12345678" \
3   -H "Authorization: your-api-key" \
4   -H "Content-Type: application/json" \
5   -d '{
6     "status": "IN_PROGRESS",
7     "root_cause": "<p>Race condition in connection handler</p>",

```

```
7   "progress_comment": "Fix identified, implementing patch"
8   }'
```

Response Example:

```
1 {
2   "code": "SUCCESS",
3   "msg": "Critical issue updated successfully",
4   "data": {
5     "unique_id": "ci-12345678",
6     "status": "IN_PROGRESS",
7     "updated_at": "2026-01-30T12:30:00Z"
8   }
9 }
```

Delete Critical Issue

Soft delete a Critical Issue.

Endpoint: DELETE

/api/v1/public/openapi/product/{product_id}/critical_issues/{critical_issue_id}

Path Parameters:

Parameter	Type	Required	Description
product_id	string	Yes	Product unique_id
critical_issue_id	string	Yes	Critical Issue unique_id

Curl Example:

```
1 curl -X DELETE "https://prm.ui.com/api/v1/public/openapi/product/unifi-
2   access/critical_issues/ci-12345678" \
3   -H "Authorization: your-api-key"
```

Response Example:

```
1 {
2   "code": "SUCCESS",
3   "msg": "Critical issue deleted successfully"
4 }
```

Critical Issue Status Values

Status	Description
INVESTIGATING	Under investigation
MONITORING	Being monitored
IN_PROGRESS	Work in progress
QA_TESTING	In QA testing
RESOLVED	Resolved

OPEN	Open
CLOSED	Closed

Linked Cases URL Whitelist

The `linked_cases` field only accepts URLs from these domains:

- `<https://ubiquiti.atlassian.net/ >` (Jira)
- `<https://ui.slack.com/ >` (Slack)
- `<https://ubnt.zendesk.com/ >` (Zendesk)
- `<https://community.ui.com/ >` (Community)

6. Metrics APIs

Get Product Metrics

Get comprehensive product metrics including installations, crash rate, offline rate, etc.

Endpoint: `GET /api/v1/public/openapi/product/{product_id}/metrics`

Path Parameters:

Parameter	Type	Required	Description
product_id	string	Yes	Product unique_id

Query Parameters:

Parameter	Type	Required	Description
time_range	string	No	Time range (e.g., 1w, 2w, 1m, 3m, 1y). Either time_range or start+end must be provided.
start	string	No	Start date (YYYY-MM-DD), must be used with end
end	string	No	End date (YYYY-MM-DD), must be used with start

Curl Example:

```
1 curl -X GET "https://prm.ui.com/api/v1/public/openapi/product/unifi-  
access/metrics?time_range=1m" \  
2 -H "Authorization: your-api-key"
```

Response Example:

```
1 {  
2   "code": "SUCCESS",  
3   "msg": "success",  
4   "data": {  
5     "summary": {  
6       "installations": 150000,  
7       "crash_rate": 0.02,  
8       "offline_rate": 0.05,  
9       "update_success_rate": 0.98  
10    },  
11    "installations": {  
12      "stats": [  
13        {  
14          "date": "2026-01-28",  
15          "total": 150000,  
16          "new": 500  
17        }  
18      ],  
19      "version_list": [  
20        {  
21          "version": "3.5.1",  
22          "count": 80000  
23        }  
24      ]  
25    },  
26    "crash_rate": {  
27      "stats": [  
28        {  
29          "date": "2026-01-28",  
30          "rate": 0.02  
31        }  
32      ]  
33    },  
34    "offline_rate": {  
35      "stats": [  
36        {  
37          "date": "2026-01-28",  
38          "rate": 0.05  
39        }  
40      ]  
41    }  
42  }  
43 }
```

Error Responses

401 Unauthorized

```
1 {  
2   "code": "UNAUTHORIZED",  
3   "msg": "Invalid or missing API key"  
4 }
```

404 Not Found

```
1 {  
2   "code": "NOT_FOUND",  
3   "msg": "Resource not found"  
4 }
```

400 Bad Request

```
1 {  
2   "code": "INVALID_INPUT",  
3   "msg": "description is required"  
4 }
```

500 Internal Error

```
1 {  
2   "code": "INTERNAL_ERROR",  
3   "msg": "Failed to process request"  
4 }
```

Contact

For any questions, please contact **Neil.Wei**.

 [oidc-api.md](#)