

The University of Lahore
Department of Computer Science & IT
Mid Term Examination



Summer-2023

Course Title:	Programming Fundamentals	Course Code:	CS02115	Credit Hours:	4
Course Instructors:	Dr Nadeem Iqbal, Mr. Waqar, Mr Awais, Mr Majid, Mr Ahemd	Program Name:	BSCS		
Time Allowed:	60 Minutes	Maximum Marks:	25		
Date:	31-10-2023	Course Mentor:	Dr. Nadeem Iqbal		
Student's Name:		Signature:			
Reg. No:		Section:			

Question # 1: Write the Dry run and output or mention error if any. (4*4)=16

Question	Dry Run	Output or Error
<pre>#include <iostream> using namespace std; int main() { long long int _CPU_Register = (10 10) && (20 10); cout<<_CPU_Register; return 0; }</pre>		
<pre>#include <iostream> using namespace std; int main() { unsigned long int _ALU_MUX = 1+2/3-1; if(!_ALU_MUX) _ALU_MUX++; for(_ALU_MUX; _ALU_MUX<=1; cout<<_ALU_MUX++, (--++_ALU_MUX)); return 0; }</pre>		
<pre>#include <iostream> using namespace std; int main(){ for(0;0<=1;1) {cout<<"CPU Dead";} return 0; }</pre>		
<pre>#include <iostream> using namespace std; int main(){ int _RAM_BANK = (true)*(false); for(int i=1;i<=4;++_RAM_BANK,i*=2) for(int k=i;k<=4;++_RAM_BANK,k++); cout<<_RAM_BANK; return 0; }</pre>		

Write a program to draw the following Pattern

```
+/\//\//\//\//\+
|                   |
+/\//\//\//\//\+
```

```
+/\//\//\//\//\+
|                   |
|                   |
|                   |
|                   |
|                   |
+/\//\//\//\//\+
```

Write a program to get the interger no from the user, and check weather the number is prime or not, if the no is prime then Turn ON the LED, and if the No is not prime then Turn OFF the LED, use SWITCH Statement to handle the both cases.

Example Output:

Enter any interger no : 4

Turning OFF the LED.....

Example Output:

Enter any interger no : 11

Turning ON the LED.....