

Parameter	Description	Type	Size	Default						
power-level	Power level.	integer	Minimum value: 0 Maximum value: 17	17						
rogue-scan	Enable/disable rogue scan.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable rogue scan.</td></tr><tr><td><i>disable</i></td><td>Disable rogue scan.</td></tr></table>				Option	Description	<i>enable</i>	Enable rogue scan.	<i>disable</i>	Disable rogue scan.
	Option	Description								
	<i>enable</i>	Enable rogue scan.								
<i>disable</i>	Disable rogue scan.									
rogue-scan-mac-adjacency	MAC adjacency.	integer	Minimum value: 0 Maximum value: 31	7						
short-guard-interval	Enable/disable short guard interval.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>400 ns long guard interval.</td></tr><tr><td><i>disable</i></td><td>800 ns short guard interval.</td></tr></table>				Option	Description	<i>enable</i>	400 ns long guard interval.	<i>disable</i>	800 ns short guard interval.
	Option	Description								
	<i>enable</i>	400 ns long guard interval.								
<i>disable</i>	800 ns short guard interval.									

config system zone

Configure zones to group two or more interfaces. When a zone is created you can configure policies for the zone instead of individual interfaces in the zone.

```

config system zone
    Description: Configure zones to group two or more interfaces. When a zone is created you
    can configure policies for the zone instead of individual interfaces in the zone.
    edit <name>
        set description {string}
        set interface <interface-name1>, <interface-name2>, ...
        set intrazone [allow|deny]
        config tagging
            Description: Config object tagging.
            edit <name>
                set category {string}
                set tags <name1>, <name2>, ...
            next
        end
    next
end

```

config system zone

Parameter	Description	Type	Size	Default						
description	Description.	string	Maximum length: 127							
interface <interface-name>	Add interfaces to this zone. Interfaces must not be assigned to another zone or have firewall policies defined. Select interfaces to add to the zone.	string	Maximum length: 79							
intrazone	Allow or deny traffic routing between different interfaces in the same zone.	option	-	deny						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow traffic between interfaces in the zone.</td></tr><tr><td><i>deny</i></td><td>Deny traffic between interfaces in the zone.</td></tr></table>				Option	Description	<i>allow</i>	Allow traffic between interfaces in the zone.	<i>deny</i>	Deny traffic between interfaces in the zone.
Option	Description									
<i>allow</i>	Allow traffic between interfaces in the zone.									
<i>deny</i>	Deny traffic between interfaces in the zone.									
name	Zone name.	string	Maximum length: 35							

config tagging

Parameter	Description	Type	Size	Default
category	Tag category.	string	Maximum length: 63	
name	Tagging entry name.	string	Maximum length: 63	
tags <name>	Tags. Tag name.	string	Maximum length: 79	