I'm ready to connect to Q-Link.

CONNECT WITH A REAL 64/128:

PC SIDE SOFTWARE:
Software required: TCPSER4j-rc6.0
Requires JAVA
Use the config file from
www.quantum-link.org.
(Unzip and copy file to TCPSER4J folder)

ALTERNATIVE PC SOFTWARE:
You can also use: TCPSER
Use the follow line to start the PC side.
tcpser -d /dev/ttyS0 -s 1200 -i"e0&k0&c0"
-n"5551212=server:port -tsS

COMMODORE SIDE SOFTWARE:
Software required: Quantumlink.d64
Convert this .d64 to a real disk,
and use the following settings:
Modem:Hayes or Hayes-compatible
Speed:1200 Baud
Dial: Automatic
Phone: Tone
Number: +5551212

CONNECT WITH VICE 1.15:

PC SIDE SOFTWARE:
Software required: TCPSER4j-rc6.0   Requires JAVA
Download the config.xml file from
www.quantum-link.org and
place in the TCPSER4j folder.

Use WinVICE-1.15 (version 1.16 will not work)
Use the following line to start VICE after
TCPSER4j is started:
x64 -rsdev1 127.0.0.1:232 -rsuser 1200 -rsuserdev 0

VICE SIDE SOFTWARE:
Software required: Quantumlink.d64
Load this disk into VICE, and use the following settings:
Modem:Other command driven modems
Speed:1200 Baud
Dial: Automatic
Phone: Tone
Number: +5551212 Note: - & + are switched in vice.

HOW TO CONNECT:
Qlink software will display:
Type commands to modem, then
press F1 when connection is made.
Type ATDT1 and press ENTER
When you see a CONNECT 38400 message, press F1

CONNECT WITH VICE 1.16:

PC SIDE SOFTWARE:
Software required: WinVICE 1.16
Download the custom x64.exe file from
www.quantum-link.org and replace the
x64.exe file in the folder WinVICE was extracted.
Make the following configuration entries:
Settings --> RS232 Settings   Change RS232 Device 1 to:
66.135.38.238:5190

Settings --> Cart I/O Settings --> RS232 Userport settings
Enable RS232 Userport, Userport Device RS232 Device 1
Userport baud rate 1200

VICE SIDE SOFTWARE:
Software required: Quantumlink.d64
Load this disk into VICE, and use the following settings:
Modem:Other command driven modems
Speed:1200 Baud, Dial: Automatic, Phone: Tone
Number: +5551212 Note: - & + are switched in vice.

HOW TO CONNECT:
Qlink software will display:
Type commands to modem, then
press F1 when connection is made. Press F1 and enjoy!

For faster service, visit
www.quantum-link.org
info@quantum-link.org