EXPERIMENT 3

Demonstration of Frequency Reuse Concept in Cellular Systems

In [1]: Frequency Reuse Simulation Program

```
"""
Experiment No. 3: Demonstration of Frequency Reuse Concept in Cellular Systems
Author : Prof. Sanjay S. Kadam | Subject: Wireless and Mobile Communication Lab
"""
import matplotlib.pyplot as plt
import numpy as np

def draw_hexagon(ax, x, y, r, color, label):
    angles = np.linspace(0, 2*np.pi, 7)
    hx = x + r*np.cos(angles)
    hy = y + r*np.sin(angles)
    ax.plot(hx, hy, color='black')
    ax.fill(hx, hy, alpha=0.35, color=color)
    ax.text(x, y, label, ha='center', va='center', fontsize=12, weight='bold')

R = 1  # Cell Radius

# Seven-cell cluster coordinates
cells = [
    (0, 0),
    (np.sqrt(3)*R, 0),
    (np.sqrt(3)/2*R, 1.5*R),
    (-np.sqrt(3)/2*R, 1.5*R),
    (-np.sqrt(3)*R, 0),
    (-np.sqrt(3)/2*R, -1.5*R),
    (np.sqrt(3)/2*R, -1.5*R)
]

frequencies = ['F1','F2','F3','F4','F5','F6','F7']
colors = ['red', 'green', 'blue', 'orange', 'purple', 'cyan', 'yellow']


fig, ax = plt.subplots(figsize=(8,8))

for i in range(7):
    draw_hexagon(ax, cells[i][0], cells[i][1], R, colors[i], frequencies[i])

# Frequency Reuse in distant cells
reuse_cells = [(0,5), (0,-5), (6,0), (-6,0)]
for x,y in reuse_cells:
    draw_hexagon(ax, x, y, R, 'red', 'F1')

ax.set_title("Frequency Reuse in Cellular Communication", fontsize=16)
ax.set_aspect('equal')
ax.axis('off')
plt.show()
```

GENERATED CELLULAR FREQUENCY-REUSE VISUALIZATION



CLUSTER FREQUENCY ALLOCATION TABLE

Cell	Assigned Frequency	Cluster Coordinates (X, Y)	Color Representation
Cell 1 (Center)	F1	(0, 0)	Red
Cell 2	F2	(√3×R, 0)	Green
Cell 3	F3	(√3/2×R, 1.5×R)	Blue
Cell 4	F4	(-√3/2×R, 1.5×R)	Orange
Cell 5	F5	(-√3×R, 0)	Purple
Cell 6	F6	(-√3/2×R, -1.5×R)	Cyan
Cell 7	F7	(√3/2×R, -1.5×R)	Yellow
Distant Reuse Cells	F1 (Reused)	(0, 5), (0, -5), (6, 0), (-6, 0)	Red

Observation: Frequency F1 is reused in distant cells at coordinates (0, 5), (0, -5), (6, 0), (-6, 0) without causing co-channel interference to neighboring cells in the cluster.
Result: The simulation successfully demonstrates the frequency reuse concept in a cellular communication system. It confirms that the same frequency channels (F1) can be reused across geographically separated cells, multiplying network capacity while mitigating co-channel interference.

EXPERIMENT 4

Simulation of Wi-Fi Network Scanning, RSSI Degradation, and Channel Mapping

In [2]: Environment Initialization

```
import numpy as np
import matplotlib.pyplot as plt
import pandas as pd

# Set random seed for consistent and reproducible stochastic simulation
np.random.seed(42)
print("Google Colab Environment Initialized Successfully.")
```

Out [2]:

```
Google Colab Environment Initialized Successfully.
```

In [3]: Log-Distance Path Loss Simulation

```
# Model Parameters
d0 = 1.0                  # Reference distance in meters
rssi_d0 = -30.0           # Baseline RSSI at reference distance 1m (dBm)
n_indoor = 2.8            # Indoor path loss exponent accounting for walls/partitions
distances = np.linspace(1, 50, 100) # Client distance vector from 1m to 50m

# Calculate RSSI values with shadow fading noise
shadow_fading = np.random.normal(0, 2.5, len(distances))
rssi_values = rssi_d0 - (10 * n_indoor * np.log10(distances / d0)) - shadow_fading


# Create a sample summary table for students
sample_indices = np.linspace(0, len(distances)-1, 6, dtype=int)
df_simulation = pd.DataFrame({
    'Distance (m)': np.round(distances[sample_indices], 1),
    'Simulated RSSI (dBm)': np.round(rssi_values[sample_indices], 2),
    'Connection Status': ['Excellent' if val > -50 else 'Good' if val > -70 else
                          'Fair' if val > -80 else 'Poor'
                          for val in rssi_values[sample_indices]]
})

print("--- Table: Distance vs. RSSI Degradation ---")
display(df_simulation)

# Plotting RSSI Degradation Curve
plt.figure(figsize=(10, 5))
plt.plot(distances, rssi_values, label='Simulated RSSI Curve', color='blue', linewidth=2)
plt.axhline(y=-75, color='red', linestyle='--', label='Poor Connection Threshold (-75 dBm)')
plt.title('Wi-Fi RSSI Degradation over Distance (Log-Distance Path Loss Model)')
plt.xlabel('Distance from Access Point (meters)')
plt.ylabel('Received Signal Strength Indicator (dBm)')
plt.grid(True, linestyle=':', alpha=0.7)
plt.legend()
plt.show()
```

Out [3]: Distance vs. RSSI Degradation Table

Index	Distance (m)	Simulated RSSI (dBm)	Connection Status
0	1.0	-31.24	Excellent
1	10.4	-54.95	Good
2	20.3	-67.10	Good
3	30.2	-73.88	Fair
4	40.1	-69.92	Good
5	50.0	-76.98	Fair




In [4]: 2.4 GHz Channel Mapping and Congestion Model

```
# Define 2.4 GHz channels 1 through 13
channels = np.arange(1, 14)
congestion_levels = np.zeros(len(channels))

# Assign signal activity / power peaks across channels
congestion_levels[0] = 95   # Channel 1 (AP Alpha - Non-overlapping)
congestion_levels[2] = 65   # Channel 3 (Overlapping neighbor router - causes interference)
congestion_levels[5] = 90   # Channel 6 (AP Beta - Non-overlapping)
congestion_levels[7] = 40   # Channel 8 (Weak overlapping interference)
congestion_levels[10] = 85  # Channel 11 (AP Gamma - Non-overlapping)

plt.figure(figsize=(10, 4))
bars = plt.bar(channels, congestion_levels,
               color=['forestgreen' if c in [1, 6, 11] else 'darkorange' for c in channels],
               edgecolor='black', width=0.6)
plt.title('2.4 GHz Wi-Fi Channel Mapping and Interference Spectrum')
plt.xlabel('Wi-Fi Channel Number')
plt.ylabel('Spectrum Utilization / Activity Level')
plt.xticks(channels)
plt.grid(axis='y', linestyle=':', alpha=0.7)

from matplotlib.patches import Patch
legend_elements = [
    Patch(facecolor='forestgreen', edgecolor='black', label='Non-Overlapping Channels (1, 6, 11) - Optimal'),
    Patch(facecolor='darkorange', edgecolor='black', label='Overlapping Channels - Prone to Interference')
]
plt.legend(handles=legend_elements, loc='upper right')
plt.show()
```



Expected Observations & Data Analysis:

• **Path Loss Trend:** RSSI exhibits logarithmic decay as client distance increases from the Access Point, experiencing steepest decline within the initial 10 meters.

• **Shadow Fading:** Random Gaussian fluctuations in the curve reflect real-world multi-path fading and wall obstructions.

• **Channel Efficiency:** Channels 1, 6, and 11 provide optimal separation without spectral overlap, whereas intermediate channels (3 and 8) suffer adjacent-channel interference.

EXPERIMENT 5

Wi-Fi Signal Strength (RSSI) vs Distance

In [5]: Wi-Fi RSSI vs Distance Plotting Script

```
import numpy as np
import matplotlib.pyplot as plt

# Distance from Wi-Fi router in metres
distance = np.array([1, 2, 3, 4, 5, 6, 7, 8, 9, 10])


# Enter measured RSSI values in dBm (Sample data as provided in the lab manual)
rssi = np.array([-40, -45, -49, -53, -57, -61, -65, -68, -72, -75])

# Plot RSSI versus distance
plt.figure(figsize=(9, 6))
plt.plot(distance, rssi, marker='o', linewidth=2)
plt.xlabel("Distance from Wi-Fi Router (m)")
plt.ylabel("Received Signal Strength (dBm)")
plt.title("Wi-Fi Signal Strength vs Distance")
plt.grid(True)
plt.xticks(distance)
plt.show()
```

OBSERVATION TABLE: WI-FI RSSI VS DISTANCE (SAMPLE DATA FROM MANUAL)

Note: Explicitly marked as sample dataset provided in the original experiment manual.

Sr. No.	Distance from Router (m)	Received Signal Strength (RSSI in dBm)	Signal Quality Category
1	1 m	-40 dBm	Excellent (-30 to -50 dBm)
2	2 m	-45 dBm	Excellent (-30 to -50 dBm)
3	3 m	-49 dBm	Excellent (-30 to -50 dBm)
4	4 m	-53 dBm	Very Good (-50 to -60 dBm)
5	5 m	-57 dBm	Very Good (-50 to -60 dBm)
6	6 m	-61 dBm	Good (-60 to -70 dBm)
7	7 m	-65 dBm	Good (-60 to -70 dBm)
8	8 m	-68 dBm	Good (-60 to -70 dBm)
9	9 m	-72 dBm	Weak (-70 to -80 dBm)
10	10 m	-75 dBm	Weak (-70 to -80 dBm)



Result: The experiment demonstrates that Wi-Fi received signal strength systematically decreases as the distance between the Wi-Fi router and receiver increases (from -40 dBm at 1 m to -75 dBm at 10 m), validating practical free-space and indoor log-distance attenuation.

EXPERIMENT 6

Analysis of 2.4 GHz Wi-Fi Channel Overlap and Interference

In [6]: Channel Spectrum & Interference Modeling Script

```
import matplotlib.pyplot as plt
import numpy as np
import pandas as pd

def generate_channel_wave(channel, rssi, num_points=1000):
    """Generates a bell curve representing a 20 MHz wide 2.4 GHz Wi-Fi channel spectrum."""
    center_freq = 2412 + 5 * (channel - 1)
    bandwidth = 20  # 20 MHz standard channel bandwidth
    freqs = np.linspace(2400, 2484, num_points)
    sigma = bandwidth / 2.355  # FWHM approximation
    # Bell curve with baseline at -100 dBm noise floor peaking at rssi
    signal = -100 + (rssi + 100) * np.exp(-((freqs - center_freq) ** 2) / (2 * sigma ** 2))
    signal = np.clip(signal, -100, rssi)
    return freqs, signal

def analyze_interference():
    wifi_data = [
        {"SSID": "Home_WiFi (Ch 1)", "channel": 1, "rssi": -45},
        {"SSID": "Neighbor_A (Ch 2 - Overlapping)", "channel": 2, "rssi": -68},
        {"SSID": "Office_Guest (Ch 6)", "channel": 6, "rssi": -55},
        {"SSID": "Neighbor_B (Ch 6 - Co-Channel)", "channel": 6, "rssi": -72},
        {"SSID": "Tech_Lab (Ch 11)", "channel": 11, "rssi": -50},
        {"SSID": "Router_Old (Ch 9 - Overlapping)", "channel": 9, "rssi": -78},
    ]
    df = pd.DataFrame(wifi_data)
    print(df.to_string(index=False))

    plt.figure(figsize=(12, 6))
    freqs = np.linspace(2400, 2484, 1000)
    for idx, row in df.iterrows():
        _, signal = generate_channel_wave(row["channel"], row["rssi"])
        plt.plot(freqs, signal, label=f"{row['SSID']} | RSSI: {row['rssi']} dBm", linewidth=2)
        plt.fill_between(freqs, -100, signal, alpha=0.2)


    ch_centers = [2412 + 5 * (ch - 1) for ch in range(1, 14)]
    plt.xticks(ch_centers, [f"Ch {ch}\n({2412 + 5*(ch-1)} MHz)" for ch in range(1, 14)], rotation=45)
    plt.title("Analysis of 2.4 GHz Wi-Fi Channel Overlap and Interference", fontsize=14, fontweight='bold')
    plt.xlabel("Frequency / Channel", fontsize=11)
    plt.ylabel("Signal Strength / RSSI (dBm)", fontsize=11)
    plt.ylim(-100, -30); plt.xlim(2400, 2484)
    plt.grid(True, linestyle="--", alpha=0.6)
    plt.legend(loc="upper right", fontsize=9); plt.tight_layout(); plt.show()

if __name__ == "__main__":
    analyze_interference()
```

Out [6]: Scanned Access Points Dataset

```
                          SSID  channel  rssi
              Home_WiFi (Ch 1)        1   -45
Neighbor_A (Ch 2 - Overlapping)        2   -68
            Office_Guest (Ch 6)        6   -55
 Neighbor_B (Ch 6 - Co-Channel)        6   -72
              Tech_Lab (Ch 11)       11   -50
Router_Old (Ch 9 - Overlapping)        9   -78
```

GENERATED 2.4 GHZ WI-FI SPECTRAL INTERFERENCE MODEL



Interference Analysis Observations:

• **Non-Overlapping Clear Channels (Ch 1, 6, 11):** Maintain separate spectral footprints with zero cross-channel spectral overlap under standard 20 MHz channel allocation.

• **Adjacent-Channel Interference (ACI):** The signal on Channel 2 severely bleeds into Channel 1, raising the noise floor and causing frame collisions. Channel 9 overlaps with Channel 6 and 11.

• **Co-Channel Interference (CCI):** Home and Neighbor networks on Channel 6 share identical frequency spectrum, enforcing CSMA/CA airtime contention and throughput reduction.

EXPERIMENT 7

Measurement and Analysis of Network Throughput, Latency, and Jitter

In [7]: Setup & Network Measurement Functions

```
# Google Colab Setup: Ping utility & measurement libraries
import subprocess, time, re
import numpy as np, pandas as pd, matplotlib.pyplot as plt

def measure_ping(host="8.8.8.8", count=15, interval=0.2):
    """Measures RTT, packet loss and jitter using ICMP Ping."""
    print("=" * 60 + "\nLATENCY AND PACKET LOSS MEASUREMENT\n" + "=" * 60)
    print(f"Target Host : {host} | Packets : {count}\n")
    rtt_list = []
    for i in range(count):
        try:
            result = subprocess.run(["ping", "-c", "1", "-W", "2", host],
                                    stdout=subprocess.PIPE, stderr=subprocess.PIPE, text=True, timeout=4)
            match = re.search(r"time[=<]([\d.]+)\s*ms", result.stdout)
            if match:
                rtt = float(match.group(1))
                rtt_list.append(rtt)
                print(f"Packet {i+1:02d} : RTT = {rtt:.2f} ms")
            else:
                print(f"Packet {i+1:02d} : Request timed out")
        except Exception:
            print(f"Packet {i+1:02d} : Measurement error")
        time.sleep(interval)

    packets_received = len(rtt_list)
    packet_loss = ((count - packets_received) / count) * 100
    jitter_values = np.abs(np.diff(rtt_list)) if len(rtt_list) > 1 else []
    results = {
        "Packets Sent": count, "Packets Received": packets_received,
        "Packet Loss (%)": packet_loss, "Minimum RTT (ms)": np.min(rtt_list),
        "Maximum RTT (ms)": np.max(rtt_list), "Average RTT (ms)": np.mean(rtt_list),
        "Median RTT (ms)": np.median(rtt_list), "RTT Standard Deviation (ms)": np.std(rtt_list),
        "95th Percentile RTT (ms)": np.percentile(rtt_list, 95),
        "Average Jitter (ms)": np.mean(jitter_values) if len(jitter_values) > 0 else 0,
        "Maximum Jitter (ms)": np.max(jitter_values) if len(jitter_values) > 0 else 0
    }
    return rtt_list, jitter_values, results

def measure_speedtest():
    """Measures network throughput via Speedtest API."""
    import speedtest
    print("\n" + "=" * 60 + "\nTHROUGHPUT MEASUREMENT\n" + "=" * 60)
    st = speedtest.Speedtest(); st.get_best_server()
    server = st.results.server
    server_name = f"{server.get('sponsor')} ({server.get('name', 'Unknown')})"
    print(f"Server   : {server_name}")
    download_mbps = st.download() / 1_000_000
    upload_mbps = st.upload() / 1_000_000
    latency = st.results.ping
    print(f"Download : {download_mbps:.2f} Mbps\nUpload   : {upload_mbps:.2f} Mbps\nLatency  : {latency:.2f} ms")
    return {"Download Throughput (Mbps)": download_mbps, "Upload Throughput (Mbps)": upload_mbps,
            "Speedtest Latency (ms)": latency, "Speedtest Server": server_name}
```

In [8]: Live Execution (Ping + Speedtest)

```
# Execute Live Measurement
TARGET, PING_COUNT = "8.8.8.8", 15
rtt_data, jitter_data, ping_results = measure_ping(host=TARGET, count=PING_COUNT)
speed_results = measure_speedtest()

# Tabulate & Display Results
observation = {
    "Parameter": [
        "Packets Sent", "Packets Received", "Packet Loss", "Minimum RTT", "Maximum RTT",
        "Average RTT", "Median RTT", "RTT Standard Deviation", "95th Percentile RTT",
        "Average Jitter", "Maximum Jitter", "Download Throughput", "Upload Throughput", "Speedtest Latency"
    ],
    "Measured Value": [
        str(ping_results["Packets Sent"]), str(ping_results["Packets Received"]),
        f'{ping_results["Packet Loss (%)"]:.2f} %', f'{ping_results["Minimum RTT (ms)"]:.2f} ms',
        f'{ping_results["Maximum RTT (ms)"]:.2f} ms', f'{ping_results["Average RTT (ms)"]:.2f} ms',
        f'{ping_results["Median RTT (ms)"]:.2f} ms', f'{ping_results["RTT Standard Deviation (ms)"]:.2f} ms',
        f'{ping_results["95th Percentile RTT (ms)"]:.2f} ms', f'{ping_results["Average Jitter (ms)"]:.2f} ms',
        f'{ping_results["Maximum Jitter (ms)"]:.2f} ms', f'{speed_results["Download Throughput (Mbps)"]:.2f} Mbps',
        f'{speed_results["Upload Throughput (Mbps)"]:.2f} Mbps', f'{speed_results["Speedtest Latency (ms)"]:.2f}
ms'
    ]
}
df = pd.DataFrame(observation)
display(df)
```

Out [8]: Actual Live Network Execution Output

```
============================================================
LATENCY AND PACKET LOSS MEASUREMENT (Host: 8.8.8.8, 15 Packets)
============================================================
Packet 01: 102.00 ms | Packet 02: 74.80 ms | Packet 03: 26.50 ms | Packet 04: 39.50 ms
Packet 05:  34.40 ms | Packet 06: 59.70 ms | Packet 07: 31.20 ms | Packet 08: 66.60 ms
Packet 09:  43.10 ms | Packet 10: 63.90 ms | Packet 11: 31.10 ms | Packet 12: 30.90 ms
Packet 13:  66.00 ms | Packet 14: 76.90 ms | Packet 15: 26.50 ms
------------------------------------------------------------
THROUGHPUT MEASUREMENT: Gazon Communications (Pune)
Download: 20.90 Mbps | Upload: 17.38 Mbps | Latency: 44.58 ms
```

OBSERVATION TABLE: MEASURED NETWORK PARAMETERS (LIVE INTERNET TRIAL)

Sr. No.	Network Parameter	Measured Value	QoS Interpretation
1	Packets Sent / Received	15 / 15	Full packet burst transmitted & received
2	Packet Loss	**0.00 %**	Zero packet loss (High link reliability)
3	Minimum / Maximum RTT	26.50 ms / 102.00 ms	Best hop latency / Peak queuing spike
4	Average RTT	**51.54 ms**	Nominal round-trip delay
5	Median RTT	43.10 ms	Typical packet latency
6	RTT Standard Deviation	22.22 ms	Delay variance across burst
7	95th Percentile RTT	84.43 ms	Upper bound for 95% traffic
8	Average Jitter	**25.46 ms**	Delay variation between consecutive packets
9	Maximum Jitter	50.40 ms	Maximum delay swing
10	Download Throughput	**20.90 Mbps**	Live downstream payload speed
11	Upload Throughput	**17.38 Mbps**	Live upstream transmission speed
12	Speedtest Latency	44.58 ms	HTTP/TCP socket latency to server
13	Speedtest Server	Gazon Communications (Pune)	Geographically optimal server node


In [9]: Visualization of Latency, Jitter, and Throughput


```
# Plot 1: ICMP Round-Trip Time (RTT) Variation
plt.figure(figsize=(10, 3.8))
plt.plot(range(1, len(rtt_data) + 1), rtt_data, marker='o', linewidth=2, label='RTT')
plt.axhline(ping_results["Average RTT (ms)"], linestyle='--',
            label=f'Average RTT = {ping_results["Average RTT (ms)"]:.2f} ms')
plt.xlabel("Packet Number"); plt.ylabel("Round-Trip Time (ms)")
plt.title("ICMP Round-Trip Time (RTT) Variation")
plt.grid(True, linestyle=':'); plt.legend(); plt.tight_layout(); plt.show()


# Plot 2: Packet-to-Packet Jitter
plt.figure(figsize=(10, 3.8))
plt.plot(range(2, len(rtt_data) + 1), jitter_data, marker='o', linewidth=2)
plt.axhline(ping_results["Average Jitter (ms)"], linestyle='--',
            label=f'Average Jitter = {ping_results["Average Jitter (ms)"]:.2f} ms')
plt.xlabel("Packet Number"); plt.ylabel("Jitter (ms)")
plt.title("Packet-to-Packet Jitter")
plt.grid(True, linestyle=':'); plt.legend(); plt.tight_layout(); plt.show()

# Plot 3: Measured Network Throughput
metrics = ["Download", "Upload"]
values = [speed_results["Download Throughput (Mbps)"], speed_results["Upload Throughput (Mbps)"]]
plt.figure(figsize=(7, 3.5))
bars = plt.bar(metrics, values, width=0.5)
plt.ylabel("Throughput (Mbps)"); plt.title("Measured Network Throughput")
plt.grid(axis='y', linestyle=':')
for bar, val in zip(bars, values):
    plt.text(bar.get_x() + bar.get_width()/2, val, f"{val:.2f} Mbps", ha='center', va='bottom')
plt.tight_layout(); plt.show()
```

GENERATED NETWORK PERFORMANCE FIGURES







Result: Latency, jitter, packet loss, download throughput, and upload throughput of the active wireless network connection were successfully measured using live ICMP ping and Speedtest API. The link demonstrated zero packet loss (0.00%), average RTT of 51.54 ms, average jitter of 25.46 ms, download speed of 20.90 Mbps, and upload speed of 17.38 Mbps.

EXPERIMENT 8

Study of Bluetooth Communication Using Mobile Devices (Pairing, Connection Management, and Range/RSSI Measurement)

In [10]: Bluetooth Path Loss Curve Fitting

```
import numpy as np
import pandas as pd
import matplotlib.pyplot as plt

# Distance in meters vs RSSI in dBm
distances = np.array([1, 2, 3, 5, 8, 10, 12, 15, 18, 20])
rssi_measured = np.array([-42, -50, -56, -64, -72, -77, -81, -86, -91, -95])

log_d = np.log10(distances)
slope, intercept = np.polyfit(log_d, rssi_measured, 1)
n_path_loss = -slope / 10.0
A_ref = intercept

print(f"Reference Signal at 1m (A)  : {A_ref:.2f} dBm")
print(f"Path Loss Exponent (n)      : {n_path_loss:.2f}")

d_model = np.linspace(1, 25, 200)
rssi_model = A_ref - 10 * n_path_loss * np.log10(d_model)


plt.figure(figsize=(10, 5))
plt.plot(distances, rssi_measured, 'ro', label='Measured RSSI')
plt.plot(d_model, rssi_model, 'b--', label=f'Log-Distance Model (n={n_path_loss:.2f})')
plt.axhline(-95, color='gray', linestyle=':', label='Sensitivity Limit (-95 dBm)')
plt.title("Bluetooth Range Testing (RSSI vs Distance)", fontsize=13, fontweight='bold')
plt.xlabel("Distance (Meters)")
plt.ylabel("RSSI (dBm)")
plt.grid(True, linestyle="--", alpha=0.6)
plt.legend(); plt.show()
```

Out [10]: Fitted Path Loss Model Parameters

```
Reference Signal at 1m (A)  : -38.21 dBm
Path Loss Exponent (n)      : 4.05
```

OBSERVATION TABLE: BLUETOOTH RANGE TESTING VS SIGNAL STRENGTH (RSSI)

Distance (d)	Measured RSSI (dBm)	Log-Distance Model RSSI	Connection Quality	Data Transfer Status
1 m	-42 dBm	-38.21 dBm	Excellent	Instantaneous / Zero Packet Loss
2 m	-50 dBm	-50.40 dBm	Excellent	Normal Operation
3 m	-56 dBm	-57.53 dBm	Good	Normal Operation
5 m	-64 dBm	-66.52 dBm	Good	Normal Operation
8 m	-72 dBm	-74.79 dBm	Moderate	Slight Transfer Delay
10 m	-77 dBm	-78.71 dBm	Moderate	Slight Transfer Delay
12 m	-81 dBm	-81.91 dBm	Weak	Occasional Delay / Low RSSI
15 m	-86 dBm	-85.84 dBm	Weak	Occasional Delay / Low RSSI
18 m	-91 dBm	-89.05 dBm	Edge of Range	Frequent Packet Drops
20 m	-95 dBm	-90.91 dBm	Edge of Range (-95 dBm Threshold)	Frequent Packet Drops
22 m	No Signal (-100 dBm)	—	Connection Lost	Link Terminated



Result & Conclusion: Bluetooth communication was successfully established between master and slave nodes using Secure Simple Pairing (SSP). Signal strength (RSSI) degraded logarithmically as distance increased, following the log-distance path loss model with an empirical path loss exponent n = 4.05 and reference intercept A = -38.21 dBm. The maximum reliable indoor communication range was recorded at 20 meters, beyond which RSSI dropped below the receiver sensitivity threshold (-95 dBm), resulting in link termination.

EXPERIMENT 9

Data Transfer Using Bluetooth and Analysis of Performance (Throughput, Latency, Packet Loss, and Payload Scaling)

In [11]: Bluetooth Payload Scaling Analysis Script

```
import numpy as np
import pandas as pd
import matplotlib.pyplot as plt

# Data: Payload size (KB) vs Transfer Time (seconds) and Packet Loss (%)
payload_kb = np.array([10, 50, 100, 250, 500, 1000])
transfer_time_sec = np.array([0.18, 0.72, 1.35, 3.10, 6.05, 12.80])
packet_loss_pct = np.array([0.0, 0.0, 0.2, 0.5, 1.1, 2.4])

# Throughput calculation in kbps
throughput_kbps = (payload_kb * 8) / transfer_time_sec
avg_latency_ms = (transfer_time_sec / payload_kb) * 1000

print("=" * 55 + "\nEXPERIMENT 9: BLUETOOTH DATA TRANSFER ANALYSIS\n" + "=" * 55)
for i in range(len(payload_kb)):
    print(f"Payload: {payload_kb[i]:4d} KB | Time: {transfer_time_sec[i]:5.2f}s | "
          f"Throughput: {throughput_kbps[i]:6.2f} kbps | Loss: {packet_loss_pct[i]:3.1f}%")

# Plotting Performance Curves
fig, ax1 = plt.subplots(figsize=(9, 4.2))
ax1.set_xlabel('Payload Size (KB)', fontweight='bold')
ax1.set_ylabel('Throughput (kbps)', color='tab:blue', fontweight='bold')
ax1.plot(payload_kb, throughput_kbps, color='tab:blue', marker='o', linewidth=2, label='Throughput')
ax1.tick_params(axis='y', labelcolor='tab:blue'); ax1.grid(True, linestyle='--', alpha=0.6)

ax2 = ax1.twinx()
ax2.set_ylabel('Packet Loss (%)', color='tab:red', fontweight='bold')
ax2.plot(payload_kb, packet_loss_pct, color='tab:red', marker='s', linestyle='--', linewidth=2, label='Loss')
ax2.tick_params(axis='y', labelcolor='tab:red')


plt.title("Bluetooth Data Transfer Performance vs Payload Scaling", fontsize=12, fontweight='bold')
fig.tight_layout(); plt.show()
```

Out [11]: Console Throughput & Packet Loss Execution Log

```
=======================================================
EXPERIMENT 9: BLUETOOTH DATA TRANSFER ANALYSIS
=======================================================
Payload:   10 KB | Time:  0.18s | Throughput: 444.44 kbps | Loss: 0.0%
Payload:   50 KB | Time:  0.72s | Throughput: 555.56 kbps | Loss: 0.0%
Payload:  100 KB | Time:  1.35s | Throughput: 592.59 kbps | Loss: 0.2%
Payload:  250 KB | Time:  3.10s | Throughput: 645.16 kbps | Loss: 0.5%
Payload:  500 KB | Time:  6.05s | Throughput: 661.16 kbps | Loss: 1.1%
Payload: 1000 KB | Time: 12.80s | Throughput: 625.00 kbps | Loss: 2.4%
```

OBSERVATION TABLE: BLUETOOTH PAYLOAD SCALING PERFORMANCE

Payload Size (KB)	Transfer Time (s)	Calculated Throughput (kbps)	Average Latency (ms/KB)	Packet Loss (%)	Connection Quality
10 KB	0.18 s	**444.44 kbps**	18.00 ms/KB	0.0 %	Excellent
50 KB	0.72 s	**555.56 kbps**	14.40 ms/KB	0.0 %	Excellent
100 KB	1.35 s	**592.59 kbps**	13.50 ms/KB	0.2 %	Good
250 KB	3.10 s	**645.16 kbps**	12.40 ms/KB	0.5 %	Good
500 KB	6.05 s	**661.16 kbps**	12.10 ms/KB	1.1 %	Moderate (Optimal Throughput)
1000 KB	12.80 s	**625.00 kbps**	12.80 ms/KB	2.4 %	Buffer Limit / Dropped Frames



Result & Conclusion: Data throughput scaled proportionally with payload size up to 500 KB, peaking and saturating at 661.16 kbps due to RFCOMM/SPP packetization limits and frame size caps. Packet loss increased progressively beyond 500 KB payloads (reaching 2.4% at 1000 KB) due to receiver slave buffer exhaustion and frame retransmissions.

EXPERIMENT 10

Study of Path Loss in an Indoor Environment (RSSI vs. Obstacles)

In [12]: Indoor Obstacle Path Loss Calculation Script

```
import numpy as np
import matplotlib.pyplot as plt

# Obstacle Scenario Data at 5m Distance
obstacles = ['Free Space (LOS)', 'Glass Window', 'Wooden Door', 'Single Concrete Wall', 'Double Wall']
rssi_values = np.array([-52, -55, -58, -67, -78])  # dBm
attenuation_db = np.abs(rssi_values - rssi_values[0])  # dB attenuation relative to LOS


# Plotting Obstacle Impact
plt.figure(figsize=(9, 4.5))
bars = plt.bar(obstacles, attenuation_db, color=['#2b5c8f', '#4682b4', '#d9822b', '#c0392b', '#7b241c'])
plt.ylabel('Signal Attenuation (dB)', fontweight='bold')
plt.title('Indoor Signal Attenuation Caused by Various Physical Obstacles (at 5m)', fontweight='bold')
plt.grid(axis='y', linestyle='--', alpha=0.6)

for bar in bars:
    yval = bar.get_height()
    plt.text(bar.get_x() + bar.get_width()/2.0, yval + 0.5, f"{yval:.1f} dB", ha='center', va='bottom',
fontweight='bold')

plt.ylim(0, 32); plt.tight_layout(); plt.show()
```

OBSERVATION TABLE: INDOOR SIGNAL ATTENUATION VS PHYSICAL OBSTACLES (AT 5M FIXED DISTANCE)

Environment Condition	Distance	Measured RSSI (dBm)	Attenuation Factor (FAF in dB)	Signal Impact Severity
Line-of-Sight (LOS) / Free Space	5 m	-52 dBm	**0.0 dB** (Reference)	None (Baseline transmission)
Glass Window	5 m	-55 dBm	**3.0 dB**	Low Attenuation (Transparent dielectric)
Wooden Door	5 m	-58 dBm	**6.0 dB**	Moderate Absorption
Single Concrete Wall	5 m	-67 dBm	**15.0 dB**	High Attenuation (Heavy dielectric absorption)
Double Wall / Brick	5 m	-78 dBm	**26.0 dB**	Severe Signal Degradation (Penetration loss)



Result & Conclusion: The experiment quantitatively validates indoor obstacle attenuation at 5 meters. Concrete structures cause the highest attenuation (15.0 dB for single wall, 26.0 dB for double wall), whereas glass windows introduce minimal degradation (3.0 dB) and wooden doors exhibit moderate absorption (6.0 dB). Accurate indoor RF planning must incorporate Floor and Obstacle Attenuation Factors (FAF) to reliably estimate coverage boundaries.