Frozen SKY130 terminal map and geometry

Native device parameters from the frozen core. W and L are in micrometres. All nf values are 1.

Device	Type	SPICE D	Shown D	G	S	B	W	L	nf	m
MP	PFET	D_MP	O	G	VIN	VIN	5	0.15	1	1923
MF	PFET	D_MF	G	C	O	O	5	0.15	1	100
M1	NFET	D_M1	A	R	X	0	5	1.0	1	5
M2	NFET	D_M2	C	O	Y	0	5	1.0	1	5
L1	PFET	D_L1	Y	Y	R	R	5	0.15	1	10
L2	PFET	D_L2	X	X	O	O	5	0.15	1	10
P1	PFET	D_P1	A	A	VIN	VIN	5	0.15	1	5
P2	PFET	D_P2	C	A	VIN	VIN	5	0.15	1	3
B1	NFET	D_B1	X	BN1	0	0	5	0.3	1	5
B2	NFET	D_B2	Y	BN2	0	0	5	0.3	1	5
PH	PFET	D_PH	G	G	VIN	VIN	5	1.0	1	50
NB	NFET	D_NB	G	BB	0	0	5	0.3	1	4

VIN = 1.2 V, VREF = 0.8 V, ILOAD = 50 mA, nominal TT at 27 C.

BN1 = 0.659916053624 V, BN2 = 0.655649839629 V, BB = 0.6446128971 V.

VREF, BN1, BN2, and BB are ideal quiet voltage ports. COUT = 200 pF and CC = 100 pF.

Each SPICE drain connects to its shown node through an ideal zero volt current probe.

Models: sky130_fd_pr__pfet_01v8 and sky130_fd_pr__nfet_01v8.

This page records the frozen native core. It is not a process or corner qualification claim.