



Data Center and Physical Protection Guideline

Version: 2.0

Valid From Date: 19.08.2026

Last Review Date: 14.08.2026

Notes: This written rule uses gender-neutral and inclusive language. Whenever possible, the generic masculine is avoided and all employees of any gender identity (m/f/d) are addressed.

Content changes compared to the previous document version are highlighted in color.

Content

1. Purpose, Objectives and Basis	3
1.1. Purpose and Objectives	3
1.2. Basis of this Guideline	4
2. Functional Scope and Target Groups	5
2.1. Functional scope of applicability	5
2.2. Target groups	5
2.3. Transition period	6
3. Definitions	7
3.1. Requirements	7
3.2. Explanation of requirements and key definitions	8
4. Requirements	9
4.1. Requirements	9
4.1.1. Data Center	9
4.1.2. Physical Protection	33
5. Roles and Responsibilities	41
5.1. Creator	41
5.2. Guideline Owner	41
6. Appendix	42
6.1. Contact Information	42
6.2. Document History	42
6.3. Related Written Rules	42
6.4. Abbreviations	43

1. Purpose, Objectives and Basis

1.1. Purpose and Objectives

The Data Center and Physical Protection Guideline (hereinafter "Guideline") establishes control requirements for DBAG and/or adopting Legal Entities within DBG (refers only to Legal Entities that have ratified the Guideline at hand) and provides criteria for fulfilling the control requirements.

The purpose of the Guideline is to effectuate the below listed Minimum Requirements, stipulated in the ICT Risk Management Policy (structured into Core Functions), acting as objectives to the Guideline and the control requirements at hand:

Core Function	Minimum Requirement	ICT Risk Management Policy chapter
Govern	2. Allocate roles and responsibilities as detailed in chapter 5 in the ICT Risk Management Policy.	4.1
Govern	6. Have in place a mechanism to define and document responsibilities for implementing control requirements both within and outside IT and IS (e.g. HR). This can be documented e.g. as part of the ICT Control Framework (former Mandatory Control Framework (MCF)) .	4.1
Protect	1. Design and implement ICT risk management control requirements to achieve the protection goals and integrating them to the ICT Written Rules framework. These control requirements are including but not limited to ICT operations and physical and environmental security, network and infrastructure management, encryption and cryptographic controls, identity management and logical/physical access control, software development, change and project management, threat management, patch and vulnerability management, human resources, and third-party management, AI, IDP & NCLC¹, data management and other controls addressing poor administration and human error risks.	4.3

Table 1: Minimum Requirements

Note: The full list of Core Functions and Minimum Requirements is stipulated in the ICT Risk Management Policy.

¹ IDP refers to Individual Data Processing, and NCLC refers to No-Code/Low-Code solutions.

Since TÜVIT Trusted Site Infrastructure (TSI) Standard is a generally accepted de-facto standard for the evaluation and certification of data centers and since DBAG's and legal entities' data centers are assessed based on TÜVIT TSI Standard, the control requirements of the chapter 4 are based on the TÜVIT TSI criteria catalogue. The TSI Standard is based on the recommended measures in the IT baseline protection catalogues of the German Federal Office for Information Security (BSI) and takes into account the relevant DIN, EN and ISO standards - in particular DIN EN 50600 and ISO/IEC 22237 - but also VDE regulations and VdS publications. The TSI version used for the chapter 4 is version 4.6. Therefore, compliance with at least version 4.6 must be ensured.

With its different assessment areas, TSI takes a holistic approach that focuses on both the physical infrastructure as well as organizational processes and documentation of data centers. The goal is to optimally secure data centers by implementing and fulfilling the various planning, organizational and technical requirements.

The TSI Standard certification allows a clear classification of the data centers into four different levels, which classifies the quality of the supply systems as well as all other elements. The TSI evaluation level agreed between DBAG and the legal entities is at least TÜV TSI level 3 / ("Level 3, erweitert"), aiming at high protection requirements and high availability. Therefore, compliance with at least level 3 must be ensured. According to TÜVIT TSI level definitions, no single points of failure (SPoF) must exist and increased intrusion detection, protection of supply lines, fire control and the monitoring of conditions must be carried out.

1.2. Basis of this Guideline

The basis for this Guideline is the thematically linked ICT Risk Management Policy.

2. Functional Scope and Target Groups

2.1. Functional scope of applicability

Entity	DBAG and/or adopting LE within DBG
Area	DBAG CIO / COO Division; Chief Risk Officer Area; or any other area that manages or owns Data Center and Physical Protection topic

Table 2: Scope

The control requirements stipulated in this Guideline are applicable for all data centers used by DBAG and/or adopting legal entities as well as to data centers procured via service providers. Locations supposed for connection of DBG customers to DBG's worldwide network, also referred to as Points of Presence (PoP), are out of scope of this Guideline.

2.2. Target groups

Within the scope of the current Data Center and Physical Protection Guideline below is addressed the list of applicable target groups and operation areas²:

Target group	Key message
ICT Risk Oversight	To oversee the development, implementation, and enforcement of physical security policies and ensure that all software changes and developments comply with DBG cybersecurity framework.
ICT Operational Management	To implement and maintain appropriate structures, processes, measures, and controls for the effective management of operations and risk (including physical security of data centers and critical infrastructure).
Business Management	To implement and monitor physical security controls, including surveillance, access controls, and intrusion detection systems, and to coordinate and respond to physical security incidents, ensuring rapid and effective responses that minimize damage and disruption.

² For LE Guidelines adoption process the target groups should be adjusted according to organizational structure of the LE.

Table 3: Target groups

2.3. Transition period

The grace period for new requirements commences from the “valid from” date stated on the cover page. The compliance dates for control requirements defined in this version of the Guideline are defined as follows:

- For unchanged control requirements and new DORA requirements the compliance date equals the “valid from” date.
- For new and changed control requirements that are more stringent than before and are not subject to DORA, the compliance date is generally 90 calendar days after the “valid from” date unless otherwise stated in brackets after the control requirements. These control requirements are marked with.
- For Legal Entities that have not previously approved the IT-related requirements and are therefore addressing these requirements for the first time, a grace period of 90 days may be granted at the discretion of the Legal Entity. DORA requirements are exempt from this grace period.

For a **compliance date** exceeding a 180 calendar days implementation timeline, a Board approval is required.

3. Definitions

3.1. Requirements

Control requirement

The control requirements define the organizational, process or technical controls to be implemented by the control owner to achieve compliance with this Guideline.

Criteria

Criteria define the measures that 'must' or 'should' be taken to fulfill the control requirement.

Level of obligation

With respect to requirements and criteria, the following terms are used to define the level of obligation, provided for the implementation of a particular requirement or criteria:

- **“must”**: Mandatory control requirements / criteria derived directly from law, regulations, or internal specifications that the legal entity must comply with. Incompliance could result in consequences with external regulators and Internal Audit.
- **“should”**: Non-mandatory control requirements / criteria derived from best-practice frameworks or equivalent sources that the legal entity does not have to necessarily comply with. Under specific circumstances there may exist valid reasons to ignore a particular control requirement, but the full implications must be understood and carefully weighed.

Independent of the level of obligation of a given requirement or criteria, it is allowed to deviate from single requirements or criteria in individual cases. However, a control requirement deviation always requires the conduction of a risk assessment and risk management including adequate risk acceptance and/or mitigation.

Any deviation from the Guideline denotes an exemption. The respective Information Owner makes decisions on such exemptions. Information Owners can only decide on risks with impact exclusively in their area of responsibility.

Responsibilities

The responsibility for fulfilling control requirements may be distributed across the organization, e.g., multiple Sections, Units, or Departments. In some cases, one Unit may be responsible for both the design and implementation of measures. In other cases, one Unit may be responsible for the design of measures, and another Unit may be responsible for the implementation of the measures. In addition, multiple Units may be responsible to collectively fulfill one requirement.

The precise responsibilities are to be defined in the underlying Procedure documents (e.g. via RACI matrices).

The ICS, among its various functionalities, registers Process Operators (PO) and Risk Representatives (RRs) mapped to the corresponding processes, controls, and risks which the RRs and/or POs are responsible for managing on behalf of the part of the organization that utilize their services (e.g. Asset Owners). For more information on ICS, please refer to the DBG ICS Guideline.

3.2. Explanation of requirements and key definitions

Control requirements are defined in a standardized format and are structured into the following components:

<Specify ID: xx (version x)>	<Name of control requirement (e.g. Access to production data)>
1	<Description of the control requirement>
1.1 1.1.1	<Lists the criteria applying to the control requirement> <Lists the sub-criteria applying to the control requirement> Asset-Types: <Lists asset types applicable to the control requirement> Key references: <Lists key regulatory references and industry best practice requirements affecting this control requirement (e.g., ISO/IEC 27001:2022 A.5.10, A.8.1)>

The terms in this document are defined in the overall ICT Risk Glossary, which is provided on the Intranet website.

4. Requirements

4.1. Requirements

4.1.1. Data Center

ID: 1 (version 2.0)	Data center security - Environmental requirements
1 DOR.ICT.DCP.EVR.001	Environmental safeguards must be considered for data center locations.
1.1 DOR.ICT.DCP.EVR.002	Areas susceptible to flooding and floodplains must be avoided. (ENV01.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 ENV01.01
1.2 DOR.ICT.DCP.EVR.003	Production and storage facilities or pipelines which are at risk of explosion must be avoided. (ENV02.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 ENV02.01
1.3 DOR.ICT.DCP.EVR.004	Operating and storage facilities with harmful emissions or the release of pollutants must be avoided. (ENV03.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 ENV03.01
1.4 DOR.ICT.DCP.EVR.005	Sources of electromagnetic interference must be avoided. (ENV04.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 ENV04.01
1.5 DOR.ICT.DCP.EVR.006	Sources of vibration must be avoided. (ENV05.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 ENV05.01
1.6 DOR.ICT.DCP.EVR.007	Transport routes with an increased volume of hazardous materials must be avoided. (ENV06.01, ENV06.01I) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 ENV06.01
1.7 DOR.ICT.DCP.EVR.008	Properties in the neighborhood which are at risk of being attacked must be avoided. (ENV07.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 ENV07.01
1.8 DOR.ICT.DCP.EVR.009	Locations in the vicinity of major events and access routes leading to them must be avoided. (ENV08.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 ENV08.01

1.9 DOR.ICT.DCP.EVR.010	Locations must be protected against impairment by structures at risk of collapse. (ENV09.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ENV09.01
1.10 DOR.ICT.DCP.EVR.011	Locations must be outside avalanche areas. (ENV10.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ENV10.01
1.11 DOR.ICT.DCP.EVR.012	Wildfire hazards must be avoided (ENV11.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ENV11.01

ID: 2 (version 2.0)	Data center security - Construction requirements
2 DOR.ICT.DCP.COR.001	Data center locations must meet the following constructional criteria:
2.1 DOR.ICT.DCP.COR.002	Security areas must be in inconspicuous, unexposed position. (CON01.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON01.01
2.2 DOR.ICT.DCP.COR.003	Building areas with potential hazards must be avoided. (CON01.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON01.02
2.3 DOR.ICT.DCP.COR.004	Contiguous security areas must exist. (CON01.03) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON01.03
2.4 DOR.ICT.DCP.COR.005	There must be a functional room layout with fire separation. (CON01.04) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON01.04
2.5 DOR.ICT.DCP.COR.006	Area, height, structural properties, and transportation routes must be sufficiently dimensioned. (CON01.05) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON01.05
2.6 DOR.ICT.DCP.COR.007	Areas of responsibility for the technical and IT personnel must be physically separated. (CON01.06) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON01.06
2.7 DOR.ICT.DCP.COR.008	Perimeter and front area must be secured. (CON01.08) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON01.08
2.8 DOR.ICT.DCP.COR.009	Parking opportunities must not exist along the external walls of IT rooms. (CON01.09) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON01.09
2.9 DOR.ICT.DCP.COR.010	Alternative access routes must be available. (CON01.10A) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON01.10
2.10 DOR.ICT.DCP.COR.011	Reserved areas must be provided if the concept of operation provides for the temporary use of technical installations. (CON01.11) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON01.11

2.11 DOR.ICT.DCP.COR.012	Renting parts of the data center to a third party must be limited. (CON02.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON03.01
2.12 DOR.ICT.DCP.COR.013	Data center buildings must have a lightning protection system. (CON03.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON03.01
2.13 DOR.ICT.DCP.COR.014	Data center buildings must have a protective type of construction. (CON04.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON04.01
2.14 DOR.ICT.DCP.COR.015	IT zones must have intrusion resistant security boundaries. (CON04.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON04.02
2.15 DOR.ICT.DCP.COR.016	Technical zones must be secured in accordance with EN 1627. (CON04.03) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON04.03
2.16 DOR.ICT.DCP.COR.017	Windows in the security area must be avoided. (CON04.04) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON04.04
2.17 DOR.ICT.DCP.COR.018	All access possibilities for individuals to IT and technical rooms must be secured. (CON04.05) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON04.05
2.18 DOR.ICT.DCP.COR.019	Transfer points of supply networks and outdoor installations must be protected. (CON04.06) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON04.06
2.19 DOR.ICT.DCP.COR.020	A protective zone shell model must be implemented. (CON04.07A) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON04.07
2.20 DOR.ICT.DCP.COR.021	Outer protection zone boundaries must be implemented. (CON04.08A) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON04.08
2.21 DOR.ICT.DCP.COR.022	Combustible finishing materials and furnishings must be avoided. (CON05.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON05.01

2.22 DOR.ICT.DCP.COR.023	Doors, windows, and shutters must be secured against fire and smoke. (CON05.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON05.02
2.23 DOR.ICT.DCP.COR.024	Fire stops must be properly executed. (CON05.03) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON05.03
2.24 DOR.ICT.DCP.COR.025	Compliance with temperature and humidity limits must be ensured in the case of ambient fires. (CON05.04) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON05.04
2.25 DOR.ICT.DCP.COR.026	Lithium-Ion batteries must be protected from fire. (CON05.05) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON05.05
2.26 DOR.ICT.DCP.COR.027	Photovoltaic systems must have additional protection. (CON05.06) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON05.06
2.27 DOR.ICT.DCP.COR.028	Critical rooms must have structural water protection. (CON06.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON06.01
2.28 DOR.ICT.DCP.COR.029	Liquid-carrying pipes must be protected against leaking water. (CON06.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON06.02
2.29 DOR.ICT.DCP.COR.030	Escape routes must be marked and include emergency lighting. (CON08.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 CON08.01

ID: 3 (version 2.0)	Data center security - Fire protection and extinguishing system requirements
3 DOR.ICT.DCP.FEX.001	The following criteria apply to fire protection and extinguishing system:
3.1 DOR.ICT.DCP.FEX.002	Advanced and appropriate fire alarm systems must be used. (FIR01.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR01.01
3.2 DOR.ICT.DCP.FEX.003	IT and technical areas must be monitored for fire. (FIR01.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR01.02

3.3 DOR.ICT.DCP.FEX.004	Adjacent rooms must be monitored for fire. (FIR01.03) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR01.03
3.4 DOR.ICT.DCP.FEX.005	The security area (incl. IT rooms) must have sufficient smoke detector density. (FIR01.04) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR01.04
3.5 DOR.ICT.DCP.FEX.006	Smoke detector types must be relative to the form of room use. (FIR01.05) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR01.05
3.6 DOR.ICT.DCP.FEX.007	Very early fire detection systems must be used. (FIR01.06) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR01.06
3.7 DOR.ICT.DCP.FEX.008	CO2 portable fire extinguisher must be installed. (FIR01.07) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR01.07
3.8 DOR.ICT.DCP.FEX.009	Technical rooms must be protected from fire. (FIR01.08) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR01.08
3.9 DOR.ICT.DCP.FEX.010	IT rooms must have firefighting solutions in place. (FIR02.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR02.01
3.10 DOR.ICT.DCP.FEX.011	Extinguishing batteries and oxygen reduction system must be monitored. (FIR02.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR02.02
3.11 DOR.ICT.DCP.FEX.012	Extinguishing batteries and oxygen reduction system must be positioned away from hazards. (FIR02.03) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR02.03
3.12 DOR.ICT.DCP.FEX.013	Fire protection dampers must be controlled via a fire alarm system signal. (FIR02.04) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR02.04
3.13 DOR.ICT.DCP.FEX.014	Smoke and gas extraction systems must be controlled. (FIR02.05A) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR02.05A

3.14 DOR.ICT.DCP.FEX.015	Fire alarm systems, fire extinguishing systems and fire protection shutters must be maintained at least on an annual basis. (FIR03.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 FIR03.01
-----------------------------	--

ID: 4 (version 2.0)	Data center security - Security systems and organizational requirements
4 DOR.ICT.DCP.SSR.001	Security systems and organizational measures must meet the following criteria:
4.1 DOR.ICT.DCP.SSR.002	An appropriate access control system using state-of-the-art technology must be used. (SEC01.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC01.01
4.2 DOR.ICT.DCP.SSR.003	Central data base of the access control system must be protected. (SEC01.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC01.02
4.3 DOR.ICT.DCP.SSR.004	Cables must be laid sabotage-protected and must be monitored. (SEC01.03) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC01.03
4.4 DOR.ICT.DCP.SSR.005	Technical components of the access security system must be provided with a back-up power supply. (SEC01.04) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC01.04
4.5 DOR.ICT.DCP.SSR.006	Suitable readers must be used for the access control system. (SEC01.05) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC01.05
4.6 DOR.ICT.DCP.SSR.007	Identification devices (IDD) of the access control system must be issued and used in a secure way. (SEC01.06) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC01.06
4.7 DOR.ICT.DCP.SSR.008	Access attempts through doors secured with the access control system must be logged and data must be stored for at least 30 days. (SEC01.07) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC01.07
4.8 DOR.ICT.DCP.SSR.009	Besides the IDD, a second factor (knowledge or biometrics) must be used for access to IT rooms or the entire security area. (SEC01.08) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC01.08
4.9 DOR.ICT.DCP.SSR.010	A security zone concept must exist. (SEC01.09) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC01.09
4.10	Doors to rooms which are important for IT or strategically important (e.g. technical security center) must have door open time monitoring including

DOR.ICT.DCP.SSR.011	alarm forwarding to a permanently manned office after 2 minutes. (SEC01.10) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC01.10
4.11 DOR.ICT.DCP.SSR.012	An appropriate state-of-the-art intrusion detection system must be used. (SEC02.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC02.01
4.12 DOR.ICT.DCP.SSR.013	Intrusion detection system in the IT areas must be equipped with motion detectors. (SEC02.03) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC02.03
4.13 DOR.ICT.DCP.SSR.014	All plant rooms or the entire technical area must be monitored. (SEC02.04) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC02.04
4.14 DOR.ICT.DCP.SSR.015	Access to all IT and telecommunication rooms must be incorporated into the intrusion detection system monitoring. (SEC02.05) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC02.05
4.15 DOR.ICT.DCP.SSR.016	Reliable remote data transmission of the intrusion detection system must be ensured. (SEC02.06A) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC02.06
4.16 DOR.ICT.DCP.SSR.017	Corridors and accesses to the IT rooms, as well as readily accessible external areas and external boundaries of the security area, must be monitored with video cameras. (SEC03.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC03.01
4.17 DOR.ICT.DCP.SSR.018	Security zone borders must be monitored. (SEC04.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC04.01
4.18 DOR.ICT.DCP.SSR.019	An effectively implemented single person separation system must be used to provide access to the IT area or to the entire secure area. (SEC05.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC05.01
4.19 DOR.ICT.DCP.SSR.020	Components of the electronic security systems must be maintained at least annually. Components of the access control system must be inspected at least annually. (SEC06.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC06.01

4.20 DOR.ICT.DCP.SSR.021	The issuance of IDD must be carried out in a formalized and transparent manner and unused access cards must be stored in a secure place. (SEC06.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC06.02
4.21 DOR.ICT.DCP.SSR.022	Monitoring of alarms must be regulated and carried out 24/365 a year by a security service provider with a permanently manned control center. (SEC06.03) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC06.03
4.22 4.23 DOR.ICT.DCP.SSR.023	Trained security personnel must be available in close proximity to the data center. (SEC06.04) Optical monitoring or locking systems on the server racks that protect against unauthorized access must be installed. Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 SEC06.04

ID: 5 (version 2.0)	Data center security - Cabling requirements
5 DOR.ICT.DCP.CAB.001	Data center cabling must meet the following criteria:
5.1 DOR.ICT.DCP.CAB.002	WAN routes as far as to the facility transfer point (external network interface) must run on separate paths without any particular hazards due to fire and mechanical influences and external network interface must be redundant. (CAB01.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 CAB01.01
5.2 DOR.ICT.DCP.CAB.003	The communication cabling must run in an adequate manner. (CAB01.02E) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 CAB01.02
5.3 DOR.ICT.DCP.CAB.004	Telecommunication cable routing must be separated and redundant. (CAB01.03E) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 CAB01.03
5.4 DOR.ICT.DCP.CAB.005	Cables must be laid in an organized manner. (CAB01.04) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 CAB01.04
5.5 DOR.ICT.DCP.CAB.006	Rack infeed connection must be secured against accidental loosening. (CAB01.05)

	Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 CAB01.05
5.6 DOR.ICT.DCP.CAB.007	Crossing points must be adequately separated. (CAB01.06E) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 CAB01.06
5.7 DOR.ICT.DCP.CAB.008	Data cables must be protected against sources of interference. (CAB01.07E) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 CAB01.07
5.8 DOR.ICT.DCP.CAB.009	Cabinets and racks must offer appropriate cable routing. (CAB02.01E) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 CAB02.01
5.9 DOR.ICT.DCP.CAB.010	WAN must be supplied by at least two different providers. (CAB03.01E) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 CAB03.01
5.10 DOR.ICT.DCP.CAB.011	The WAN connection must be redundant. (CAB03.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 CAB03.02

ID: 6 (version 2.0)	Data center security - Power requirements
6 DOR.ICT.DCP.POW.001	The power supply in the data centers must meet the following criteria:
6.1 DOR.ICT.DCP.POW.002	The energy supply in the building must be based on a 5-wire network and at least the IT area must be included in the TN-S structure. (POW01.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW01.01
6.2 DOR.ICT.DCP.POW.003	A secondary or an additional power supply must be available in addition to the primary power supply. (POW01.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW01.02
6.3 DOR.ICT.DCP.POW.004	The redundant connection to the mains must be either two supplies from separate and independent primary and secondary sources or two supplies from one primary source. (POW01.02A) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW01.02A
6.4 DOR.ICT.DCP.POW.005	Primary and secondary supply lines must be routed on separate paths. (POW01.03) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW01.03
6.5 DOR.ICT.DCP.POW.006	Secondary of additional supply must automatically take over all critical load if the primary supply fails (and vice versa). (POW01.04) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW01.04
6.6 DOR.ICT.DCP.POW.007	Additional supply must be available for all supply paths. (POW01.05) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW01.05
6.7 DOR.ICT.DCP.POW.008	Power supply for the IT devices must be redundant. (POW01.06) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW01.06
6.8 DOR.ICT.DCP.POW.009	Couplings between redundant low-voltage distributions must be protected against erroneous switching operations. (POW01.07A) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW01.07
6.9 DOR.ICT.DCP.POW.010	Transformers must have sufficient power reserves. (POW01.08A) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW01.08
6.10	Supply lines must be protected against external influences. (POW02.02)

DOR.ICT.DCP.POW.011	Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW02.02
6.11 DOR.ICT.DCP.POW.012	IT power distribution units must have their own supply line without branches. (POW02.03) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW02.03
6.12 DOR.ICT.DCP.POW.013	UPS distribution boards must be without external consumers. (POW02.04) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW02.04
6.13 DOR.ICT.DCP.POW.014	Energy supply must have staggered overvoltage protection. (POW05.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW05.01
6.14 DOR.ICT.DCP.POW.015	All electricity lines must be equipped with appropriate staggered overvoltage protection. (POW05.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW05.02
6.15 DOR.ICT.DCP.POW.016	All metallic objects must be grounded, and floor coverings reduce the risk of electrostatic charges. (POW07.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW07.01
6.16 DOR.ICT.DCP.POW.017	Leakage currents must be monitored. (POW08.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW08.01
6.17 DOR.ICT.DCP.POW.018	Central fault current protection devices and emergency power off switches must be avoided. (POW08.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW08.02
6.18 DOR.ICT.DCP.POW.019	Important measured values of the IT supply network (e.g. voltages, currents, apparent and effective power) must be recorded and monitored. (POW08.03) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW08.03
6.19 DOR.ICT.DCP.POW.020	Voltage quality and design of measuring devices must be recorded and monitored. (POW08.04A) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW08.04
6.20 DOR.ICT.DCP.POW.021	Energy supply to the IT consumers must be secured by a central UPS. (POW09.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW09.01

6.21 DOR.ICT.DCP.POW.022	UPS systems must be able to be decoupled via a manual maintenance bypass. (POW09.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW09.02
6.22 DOR.ICT.DCP.POW.023	UPS system must have a component redundancy of n+1 or a second active supply system available. (POW09.03) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW09.03
6.23 DOR.ICT.DCP.POW.024	Batteries must ensure that risk of individual block failures is minimized. (POW09.07) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW09.07
6.24 DOR.ICT.DCP.POW.025	Additional supplies must have sufficient power reserves. (POW10.04) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW10.04
6.25 DOR.ICT.DCP.POW.026	Sufficient fuel reserve for additional supply must be maintained. (POW10.05) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW10.05
6.26 DOR.ICT.DCP.POW.027	Tank system and fuel pipes to the additional supply must be protected, controlled, and monitored. (POW10.06) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW10.06
6.27 DOR.ICT.DCP.POW.028	Operational readiness of the additional supply must be regularly tested by load test runs. (POW10.07) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW10.07
6.28 DOR.ICT.DCP.POW.029	When the data center load is insufficient and it is therefore not possible to run the system in parallel with the mains for a function check, a load bank must be available. (POW10.07A) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW10.07A
6.29 DOR.ICT.DCP.POW.030	Mains switching control of the additional supply must be securely installed. (POW10.08) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW10.08
6.30 DOR.ICT.DCP.POW.031	A complete calculation of the load flow and short circuit currents must be carried out. (POW11.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 POW11.01

6.31 DOR.ICT.DCP.POW.032	Operating states of the electric power supply and the availability of the supply voltage must be monitored. (POW11.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 POW11.02
6.32 DOR.ICT.DCP.POW.033	Technical fault messages must be reliably transmitted to a permanently manned location. (POW11.03) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 POW11.03
6.33 DOR.ICT.DCP.POW.034	Electrical systems must be maintained at least once a year on the basis of a maintenance agreement and the performance must be logged. (POW11.04) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 POW11.04
6.34 DOR.ICT.DCP.POW.035	Upon initial commissioning, function and integration tests under full and partial load must be carried out. Upon the exchange of systems, at least limited function and integration tests must be carried out. (POW11.05) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 POW11.05

ID: 7 (version 2.0)	Data center security - Air conditioning and ventilation
7 DOR.ICT.DCP.ACV.001	Data centers must meet the following air conditioning and ventilation criteria:
7.1 DOR.ICT.DCP.ACV.002	Data Center areas must comply with secure operational conditions. (ACV01.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV01.01
7.2 DOR.ICT.DCP.ACV.003	Data Center areas and technical components must have sufficient ventilation. (ACV01.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV01.02
7.3 DOR.ICT.DCP.ACV.004	Devices must be installed in an airflow-optimized and hazard-free way. (ACV02.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV02.01
7.4 DOR.ICT.DCP.ACV.005	Leakages must be reliably detected. (ACV03.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV03.01
7.5 DOR.ICT.DCP.ACV.006	Active mechanical components (on the producer, distributor side) must be designed redundantly. (ACV04.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV04.01
7.6 DOR.ICT.DCP.ACV.007	Singular cooling distribution systems or sections must be implemented in high quality and checked by extensive quality assurance measures. (ACV04.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV04.02
7.7 DOR.ICT.DCP.ACV.008	Cooling distribution must be designed in a way that a failure of passive components does not result in a failure of the IT. (ACV04.02E, ACV04.02I) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV04.02A
7.8 DOR.ICT.DCP.ACV.009	The plant must be designed in a way that maintenance can be carried out to active components at any time without interruptions to operations. (ACV04.03) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV04.03
7.9 DOR.ICT.DCP.ACV.010	The routes must be protected against third-party influence and fire. (ACV04.04)

	Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV04.04
7.10 DOR.ICT.DCP.AC.V.011	Circulating air cooling units or comparable technology must be redundant (n+1) for IT and telecommunication rooms as well as singular UPS rooms. (ACV04.05, ACV04.05E, ACV04.05I) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV04.05A
7.11 DOR.ICT.DCP.AC.V.012	Filtering of the room air must be sufficiently dimensioned for the IT rooms. (ACV05.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV05.01
7.12 DOR.ICT.DCP.AC.V.013	External air supply must be protected. (ACV05.03) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV05.03
7.13 DOR.ICT.DCP.AC.V.014	Components in the central mechanical room must be separated. (ACV06.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV06.01
7.14 DOR.ICT.DCP.AC.V.015	Cooling towers must be protected against tampering. (ACV07.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV07.01
7.15 DOR.ICT.DCP.AC.V.016	Cooling towers must be sufficiently dimensioned and installed in an operationally reliable way. (ACV07.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV07.02
7.16 DOR.ICT.DCP.AC.V.017	Cooling systems must be in a plan-compliant design and maintenance-friendly. (ACV08.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV08.01
7.17 DOR.ICT.DCP.AC.V.018	Components of the air-conditioning system must have secure electrical supply. (ACV09.01, ACV09.01I) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV08.01
7.18 DOR.ICT.DCP.AC.V.019	The water supply must be ensured at all times by a redundant connection or storage. (ACV09.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV09.02
7.19 DOR.ICT.DCP.AC.V.020	Water supply systems must be implemented in the same availability as the air conditioning systems whose supply they must ensure. (ACV09.02A) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV09.02A

7.20 DOR.ICT.DCP.ACV.021	After power failures, critical controls must restart automatically after power recovery. (ACV09.03) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV09.03
7.21 DOR.ICT.DCP.ACV.022	When high-level controls are used, the critical subordinate units must be equipped with autonomous controls or redundant systems must operate with their own high-level controls. (ACV09.03A) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV09.03A
7.22 DOR.ICT.DCP.ACV.023	Important operating states of the main components, as well as the pumped media, must be automatically recorded and monitored. (ACV10.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV10.01
7.23 DOR.ICT.DCP.ACV.024	Room temperature and humidity in IT rooms must be monitored. (ACV10.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV10.02
7.24 DOR.ICT.DCP.ACV.025	Temperature and humidity of air supplied from outside must be measured. (ACV10.03E, ACV10.03I) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV10.03
7.25 DOR.ICT.DCP.ACV.026	Tests for tightness, corrosion protection and insulation must be evidenced by acceptance documents. (ACV11.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV11.01
7.26 DOR.ICT.DCP.ACV.027	All components of the air-conditioning system must be maintained at least once per year and regularly inspected. (ACV11.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV11.02
7.27 DOR.ICT.DCP.ACV.028	Technical fault messages must be transmitted securely to a permanently manned office and immediately assessed and rectified by specialized personnel. (ACV11.03) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV11.03
7.28 DOR.ICT.DCP.ACV.029	Upon initial commissioning, full load, function, and integration tests must be performed and documented. Upon the exchange of systems, limited function tests must be carried out and test certificates from the manufacturer must be available. (ACV11.04) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ACV11.04

ID: 8 (version 2.0)	Data center security - Organizational requirements
8 DOR.ICT.DCP.ORG.001	Organizational measures must meet the following criteria:
8.1 DOR.ICT.DCP.ORG.002	Backup data must be transferred to a different fire compartment and at least once per week to a different building. (ORG01.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG01.01
8.2 DOR.ICT.DCP.ORG.003	Secure area must be equipped with smoking ban signs. (ORG02.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG02.01
8.3 DOR.ICT.DCP.ORG.004	IT rooms, all relevant technical rooms, routes, and external installations must undergo a visual inspection at least once a week and the performance of the inspection must be recorded. (ORG03.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG03.01
8.4 DOR.ICT.DCP.ORG.005	Operations must comply in terms of adherence to the rules, tidiness, cleanliness, accessibility, inscriptions, signs, and disposal. (ORG04.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG04.01
8.5 DOR.ICT.DCP.ORG.006	Responsibilities for the implementation of physical security measures must be defined. People authorized to enter protection class 4 must require additional authorization to take people with them. (ORG05.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG05.01
8.6 DOR.ICT.DCP.ORG.007	Relevant parameters of technical component operations must be recorded and regularly evaluated according to defined responsibilities. (ORG05.02E) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG05.02
8.7 DOR.ICT.DCP.ORG.008	With respect to the letting of data center areas there must be – with reference to the customer – rules concerning physical security, energy efficiency, capacity planning, business organization and the exchange of information to which the customer must comply. Compliance must be verified. (ORG05.03E) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG05.03
8.8 DOR.ICT.DCP.ORG.009	Important key indicators (KPI, Key Performance Indicators) must be recorded, evaluated, and used for process improvement. (ORG05.04E) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG05.04

8.9 DOR.ICT.DCP.ORG.010	Processes between IT operation, lifecycle management and facility management must be coordinated. (ORG06.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG06.01
8.10 DOR.ICT.DCP.ORG.011	Maintenance contracts with start of repair work latest on next working day must be concluded for all trades which are relevant to operations. (ORG07.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG07.01
8.11 DOR.ICT.DCP.ORG.012	Operating instructions must be available that describe the method of dealing with third-party personnel, the coordination process for maintenance windows, precautions for specific activities or switching operations, as well as special aspects of maintenance and repair work. (ORG08.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG08.01
8.12 DOR.ICT.DCP.ORG.013	Personnel must be provided with safety instruction at least once per year and new employees at the beginning of their employment contract. (ORG09.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG09.01
8.13 DOR.ICT.DCP.ORG.014	Employees and service providers must be trustworthy and subject to a confidentiality obligation. (ORG09.02) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG09.02
8.14 DOR.ICT.DCP.ORG.015	Technical infrastructure must be inspected by qualified and correspondingly equipped personnel, including deputization rules. (ORG10.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG10.01
8.15 DOR.ICT.DCP.ORG.016	Publication of security-relevant data center information must be avoided. (ORG12.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 ORG12.01

ID: 9 (version 2.0)	Data center security - Documentation requirements
9 DOR.ICT.DCP.DOC.001	The following data center documentation must be available:
9.1 DOR.ICT.DCP.DOC.002	Data center operating manual with security concept. (DOC01.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 DOC01.01

9.2 DOR.ICT.DCP.DOC.003	Risk analysis for the environment of the data center location. (DOC01.02A) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC01.02A
9.3 DOR.ICT.DCP.DOC.004	Alarm plan / emergency concept. (DOC01.03) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC01.03
9.4 DOR.ICT.DCP.DOC.005	Fire protection concept. (DOC01.04) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC01.04
9.5 DOR.ICT.DCP.DOC.006	Site survey in the case of new construction projects. (DOC01.05E) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC01.05
9.6 DOR.ICT.DCP.DOC.007	Site and building plans. (DOC02.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC02.01
9.7 DOR.ICT.DCP.DOC.008	Floor plans for the IT and technical areas. (DOC02.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC02.02
9.8 DOR.ICT.DCP.DOC.009	Route plans of the main supply paths. (DOC03.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC03.01
9.9 DOR.ICT.DCP.DOC.010	Documentation of the telecommunication cabling. (DOC03.02E) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC03.02
9.10 DOR.ICT.DCP.DOC.011	Single-line diagram of the electrical supply. (DOC04.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC04.01
9.11 DOR.ICT.DCP.DOC.012	Cooling and ventilation schematics. (DOC04.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC04.02
9.12 DOR.ICT.DCP.DOC.013	Overviews of fire alarm lines and detectors. (DOC04.03) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC04.03
9.13 DOR.ICT.DCP.DOC.015	Overview of extinguishing and fire prevention equipment. (DOC04.04) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC04.04

9.14 DOR.ICT.DCP.DOC.016	Installation plans and diagrams of the safety equipment. (DOC04.05) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC04.05
9.15 DOR.ICT.DCP.DOC.016	Power requirement calculation and design specifications. (DOC04.06A) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC04.06
9.16 DOR.ICT.DCP.DOC.017	Air-conditioning concept. (DOC04.07A) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC04.07
9.17 DOR.ICT.DCP.DOC.018	Supplementary risk assessment for the design of technical systems and constructions. (DOC04.08A) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC04.08
9.18 DOR.ICT.DCP.DOC.019	Maintenance schedule. (DOC05.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC05.01
9.19 DOR.ICT.DCP.DOC.020	Operating instructions. (DOC06.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC06.01
9.20 DOR.ICT.DCP.DOC.021	List of rooms. (DOC07.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC07.01
9.21 DOR.ICT.DCP.DOC.022	Data sheets of the important technical components. (DOC07.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC07.02
9.22 DOR.ICT.DCP.DOC.023	Verification of the execution of performance and function tests upon commissioning. (DOC08.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DOC08.01

ID: 10 (version 2.0)	Data center security - Dual Site Data Center requirements
10 DOR.ICT.DCP.DSD.001	Dual site data centers must comply with the following criteria:
10.1 DOR.ICT.DCP.DSD.002	The size of the data center IT areas must not differ by more than 1/3. (DDC01.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC01.01

10.2 DOR.ICT.DCP.DSD.003	The data centers must be located in separate buildings and supplied separately with WAN connection, electricity, and cooling. (DDC02.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC02.01
10.3 DOR.ICT.DCP.DSD.004	DC1 and DC2 must be interconnected via redundant data connection. (DDC03.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC03.01
10.4 DOR.ICT.DCP.DSD.005	In the CON area, each data center must fulfil at least level 2. (DDC04.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC04.01
10.5 DOR.ICT.DCP.DSD.006	CON04.01: Both data centers must fulfil at least level 3. (DDC04.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC04.02
10.6 DOR.ICT.DCP.DSD.007	CON04.02: Both data centers must fulfil at least level 3. (DDC04.03) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC04.03
10.7 DOR.ICT.DCP.DSD.008	CON04.05: Each data center must fulfil level 3. (DDC04.05) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC04.05
10.8 DOR.ICT.DCP.DSD.009	In the FIR area, each data center must fulfil at least level 2. (DDC05.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC05.01
10.9 DOR.ICT.DCP.DSD.010	In the SEC area, each data center must fulfil at least level 3. (DDC06.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC06.01
10.10 DOR.ICT.DCP.DSD.011	In the CAB area, each data center must fulfil at least level 2. (DDC07.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC07.01
10.11 DOR.ICT.DCP.DSD.012	In the POW area, each data center must fulfil at least level 2. (DDC08.01) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC08.01e
10.12 DOR.ICT.DCP.DSD.013	POW01.04: At least one of the two data centers must meet level 3 and thus must have a stationary back-up generator. (DDC08.02) Asset-Types: Business Process, Datacenter Key References: TÜVIT TSI v4.4 DDC08.02
10.13 DOR.ICT.DCP.DSD.014	POW10.xx. At least one of the two data centers must fulfil the generator requirements in level 3 with the stationary back-up generator. (DDC08.03)

	Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 DDC08.03
10.14 DOR.ICT.DCP.DSD.015	In the ACV area, each data center must fulfil at least level 2. (DDC09.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 DDC09.01
10.15 DOR.ICT.DCP.DSD.016	In the ORG area, each data center must fulfil at least level 2. (DDC10.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 DDC10.01
10.16 DOR.ICT.DCP.DSD.017	In the DOC area, each data center must fulfil at least level 3. (DDC11.01) Asset-Types: Business Process, Datacenter Key References: TüVIT TSI v4.4 DDC11.01

4.1.2. Physical Protection

This section is not applicable for data centers.

ID: 11 (version 2.0)	Physical security perimeters and zone concepts
11 DOR.ICT.DCP.PEZ.001	It must be ensured that physical security perimeters and zone concepts are in place.
11.1 DOR.ICT.DCP.PEZ.002	Physical security perimeters must be defined and used following a risk-based approach. Asset-Types: Business Process, Building, Room Key References: §8a (1) BSIG 72, ISO/IEC 27002:2022 A.7.1
11.2 DOR.ICT.DCP.PEZ.003	Physical security perimeters and zone concepts must be implemented, maintained, reviewed, and regularly tested following a risk-based approach to ensure separation and monitored transitions between the zones. Asset-Types: Business Process, Building, Room Key References: §8a (1) BSIG 72, ISO/IEC 27002:2022 A.7.1

ID: 12 (version 2.0)	Physical security risk assessments
12 DOR.ICT.DCP.PSR.001	It must be ensured that physical security risk assessments are performed appropriately.
12.1 DOR.ICT.DCP.PSR.002	Periodic physical security risk assessments must be carried out at least annually , follow relevant control requirements outlined in the ICT Risk Management Guideline, and additionally consider changes regarding local topography (natural hazards), urban threats (crime, civil unrest, terrorism) and general risks. Asset-Types: Business Process Key References: ISO/IEC 27002:2022 A.7.5
12.2 DOR.ICT.DCP.PSR.003	Prior to selecting a site, possible consequences resulting from the local topography and urban threats must be assessed. Asset-Types: Business Process Key References: ISO/IEC 27002:2022 A.7.5

ID: 13 (version 2.0)	Site and Infrastructure Security
13 DOR.ICT.DCP.SIS.001	It must be ensured that physical security measures for buildings and rooms are defined and in place.
13.1 DOR.ICT.DCP.SIS.002	Physical protection against physical threats and malicious attacks must be designed and applied based on the overall ICT risk profile (including threat landscape) and the classification of the buildings and rooms. Asset-Types: Business Process, Building, Room Key References: DORA RTS RMF A.18.1
13.2 DOR.ICT.DCP.SIS.003	Where applicable, buildings should be unobtrusive and give minimum indication of their purpose, with no obvious signs, outside or inside the building, identifying the presence of information processing activities. Asset-Types: Information, Business Process, Building Key References: ISO 27001:2022 Cor 202203 A.7.3
13.3 DOR.ICT.DCP.SIS.004	Electromagnetic shielding should also be considered as appropriate. Asset-Types: Business Process, Building Key References: ISO 27001:2022 Cor 202203 A.7.3
13.4 DOR.ICT.DCP.SIS.005	All power and communication lines must be protected against unauthorized access, physical tampering, interception, flash burst, fire and/or damage. Asset-Types: Information, Business Process, Network Connection, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.12
13.5 DOR.ICT.DCP.SIS.006	Adequate health monitoring, tamper detection and physical surveillance of access panels/cabling, critical bridge rooms, etc. must be performed regularly. Asset-Types: Business Process, Network Connection, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.12
13.6 DOR.ICT.DCP.SIS.007	Power and telecommunications lines into information processing facilities must be placed underground, where applicable. Asset-Types: Information, Business Process, Network Connection, Building Key References: ISO 27001:2022 Cor 202203 A.7.12
13.7 DOR.ICT.DCP.SIS.008	Power and telecommunication lines must be separated to prevent interference. Asset-Types: Information, Business Process, Network Connection, Building Key References: ISO 27001:2022 Cor 202203 A.7.12
13.8 DOR.ICT.DCP.SIS.009	Network cabling must be protected from unauthorized interception or damage (by using a conduit or by avoiding routes through public areas). Asset-Types: Business Process, Network Connection, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.12
13.9 DOR.ICT.DCP.SIS.010	Clearly identifiable cable and equipment markings must be used to minimize handling errors.

	Asset-Types: Business Process, Server & Host Hardware, Network Connection, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.12
13.10 DOR.ICT.DCP.SIS.011	Access to patch panels, network wiring closets/cable rooms must be protected against unauthorized entry. Asset-Types: Business Process, Network Connection, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.12
13.11 DOR.ICT.DCP.SIS.012	Initiation of technical sweeps and physical inspections for unauthorized devices being attached to the cables should be performed considering a risk-based approach. Asset-Types: Information, Business Process, Network Connection, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.12
13.12 DOR.ICT.DCP.SIS.013	An up-to-date documented patch list must be used to reduce the possibility of errors. Asset-Types: Information, Business Process, Server & Host Hardware, Network Connection, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.12
13.13 DOR.ICT.DCP.SIS.014	Clear desk rules for papers and clear screen rules for information processing facilities must be in place. Asset-Types: Information, Business Process, End User Device, Mobile Device, Building Key References: DORA RTS RMF A.18.2e)
13.14 DOR.ICT.DCP.SIS.015	Buildings and rooms where KRITIS related services are performed must have a security level that meets the KRITIS requirements for high availability. Asset-Types: Business Process, Network Connection, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.1
13.15 DOR.ICT.DCP.SIS.016	Information processing facilities managed by the organization should be physically separated from those managed by external parties. Asset-Types: Information, Business Process, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.1
13.16 DOR.ICT.DCP.SIS.017	In multi-tenant buildings, enhanced physical access security must be provided to protect primary and relevant secondary assets from other tenants. Asset-Types: Business Process, Building Key References: ISO 27001:2022 Cor 202203 A.7.1
13.17 DOR.ICT.DCP.SIS.018	The exterior roof, walls and flooring of the building should be of solid construction. Asset-Types: Business Process, Building Key References: ISO 27001:2022 Cor 202203 A.7.1

ID: 14 (version 2.0)	Environmental Threats
14 DOR.ICT.DCP.ENV.001	It must be ensured that measures are defined and in place to protect against environmental threats.
14.1 DOR.ICT.DCP.ENV.002	Physical protection against natural disasters must be designed and applied following a risk-based approach. Asset-Types: Business Process, Building, Room Key References: DORA RTS RMF A.18.2b)
14.2 DOR.ICT.DCP.ENV.003	Advice regarding environmental issues and how to deal with them should be obtained. Asset-Types: Business Process, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.5
14.3 DOR.ICT.DCP.ENV.004	Environmental conditions, such as temperature and humidity, must be monitored for conditions which could adversely affect the operation of information processing facilities. Asset-Types: Information, Business Process, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.8
14.4 DOR.ICT.DCP.ENV.005	Lightning protection must be applied to all buildings and lightning protection filters must be fitted to all incoming power and communications lines. Asset-Types: Business Process, Network Connection, Building Key References: ISO 27001:2022 Cor 202203 A.7.8

ID: 15 (version 2.0)	Physical security monitoring and logging
15 DOR.ICT.DCP.MOL.001	It must be ensured that buildings, rooms and sensitive designated areas are monitored for unauthorized physical access and relevant events are logged.
15.1 DOR.ICT.DCP.MOL.002	Buildings, rooms and sensitive designated areas must be continuously monitored for unauthorized physical access by surveillance systems, either managed internally or by a monitoring service provider. Asset-Types: Business Process, Building, Room Key References: ISO 27001:2022 Cor 202203 A7.4
15.2 DOR.ICT.DCP.MOL.003	In accordance with the applicable regulations, business needs and information security objectives, physical access logs must follow a retention period of 2 years. Asset-Types: Business Process Key References: ISO 27001:2022 Cor 202203 A7.4, DORA RTS RMF A.12.2a), A.12.2ci), A.21.1giii)
15.3 DOR.ICT.DCP.MOL.004	In accordance with the applicable regulations, business needs and information security objectives, CCTV logs must follow a minimum retention period of 3 days. If a longer retention period than 3 days is required due to

	the "legitimate interest" provision under Article 6 (1) (f) of the GDPR, it must be approved by the Data Protection Unit. Asset-Types: Business Process, Building, Room Key References: ISO 27001:2022 Cor 202203 A7.4, DORA RTS RMF A.12.2a), A.12.2ci), A.21.1giii)
--	--

ID: 16 (version 2.0)	Physical Access Controls
16 DOR.ICT.DCP.ACC.001	It must be ensured that physical access control measures are defined and in place.
16.1 DOR.ICT.DCP.ACC.002	People with access to buildings, rooms and sensitive designated areas must be identified and logged. The identification and logging process must follow a risk-based approach. Asset-Types: Information, Business Process, Building, Room Key References: DORA RTS RMF A.21.1g.i)
16.2 DOR.ICT.DCP.ACC.003	Physical access rights to critical non-IT Assets must be granted based on the need-to-know and least privilege principles and on an ad-hoc basis. Asset-Types: Business Process, Building, Room Key References: DORA RTS RMF A.21.1g.ii)
16.3 DOR.ICT.DCP.ACC.004	Physical access to buildings, rooms and sensitive designated areas must be monitored. Asset-Types: Business Process, Building, Room Key References: DORA RTS RMF A.21.1g.iii)
16.4 DOR.ICT.DCP.ACC.005	Physical access rights must be reviewed to ensure prompt revoking of unnecessary access rights. Asset-Types: Business Process, Building, Room Key References: DORA RTS RMF A.21.1g.iv)

ID: 17 (version 2.0)	Visitor Management
17 DOR.ICT.DCP.VIS.001	Visitors must be treated specially with regard to physical access to buildings, rooms and sensitive designated areas, if relevant.
17.1 DOR.ICT.DCP.VIS.002	Visitors must be authenticated by appropriate means. Asset-Types: Business Process, Building Key References: DORA RTS RMF A.21.1g), ISO/IEC 27002:2022 A.7.2
17.2 DOR.ICT.DCP.VIS.003	The data and time of entry and departure of the visitors should be recorded. Asset-Types: Business Process, Building Key References: DORA RTS RMF A.21.1g), ISO/IEC 27002:2022 A.7.2
17.3	All visitors must be supervised within the buildings, rooms and, if relevant, sensitive designated areas, of DBG.

DOR.ICT.DCP.VIS.004	Asset-Types: Business Process, Building Key References: DORA RTS RMF A.21.1g), ISO/IEC 27002:2022 A.7.2
17.4 DOR.ICT.DCP.VIS.005	Access for visitors must only be granted for specific, authorized purposes and with instructions on the area and on emergency procedures. Asset-Types: Business Process, Building Key References: DORA RTS RMF A.21.1g), ISO/IEC 27002:2022 A.7.2

ID: 18 (version 2.0)	Sensitive designated areas
18 DOR.ICT.DCP.SDA.001	It must be ensured that measures are in place to protect sensitive designated areas
18.1 DOR.ICT.DCP.SDA.002	Sensitive designated areas must be identified. Asset-Types: Business Process, Building, Room Key References: DORA RTS RMF A.18.2b)
18.2 DOR.ICT.DCP.SDA.003	Specific protection measures to protect sensitive designated areas from attacks, accidents, and environmental threats and hazards must be defined and applied. Asset-Types: Business Process, Building, Room Key References: DORA RTS RMF A.18.2b)
18.3 DOR.ICT.DCP.SDA.005	Arrangements for working in secure areas must cover employees and the external party users. Asset-Types: Business Process, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.6

ID: 19 (version 2.0)	Equipment
19 DOR.ICT.DCP.EQP.001	It must be ensured that measures are defined and in place for protecting equipment accordingly against threats.
19.1 DOR.ICT.DCP.EQP.002	Equipment must be sited and protected to reduce the risks from environmental threats and hazards, opportunities for unauthorized access and with consideration of reduction of viewing information by unauthorized personnel. Asset-Types: Information, Business Process, Hardware Appliance, End User Device, Mobile Device, Processing Peripheral, Storage Media, Other Device, Storage, Server & Host Hardware, Building Key References: ISO 27001:2022 Cor 202203 A.7.8
19.2 DOR.ICT.DCP.EQP.003	The equipment must be adequately managed. Risks arising from outdated ICT Systems must be regularly identified and evaluated (lifecycle management). Asset-Types: Business Process, Hardware Appliance, End User Device, Mobile Device, Processing Peripheral, Storage Media, Other Device, Storage, Server & Host

	Hardware, Network Connection, Building, Room Key References: ISO 27001:2022 Cor 202203 A.7.13
19.3 DOR.ICT.DCP.EQP.004	Equipment must be correctly maintained (according to the maintenance documentation to ensure its continued availability and integrity) to ensure its availability, authenticity, integrity, and confidentiality. Asset-Types: Information, Business Process, Hardware Appliance, End User Device, Mobile Device, Processing Peripheral, Storage Media, Other Device, Storage, Server & Host Hardware, Building Key References: ISO 27001:2022 Cor 202203 A.7.13
19.4 DOR.ICT.DCP.EQP.005	Only authorized maintenance personnel should carry out repairs. Asset-Types: Business Process, Hardware Appliance, End User Device, Mobile Device, Processing Peripheral, Storage Media, Other Device, Storage, Server & Host Hardware, Building Key References: ISO 27001:2022 Cor 202203 A.7.13
19.5 DOR.ICT.DCP.EQP.006	Records should be kept of all suspected or actual faults, and of all preventive and corrective maintenance. Asset-Types: Information, Business Process, Hardware Appliance, End User Device, Mobile Device, Processing Peripheral, Storage Media, Other Device, Storage, Server & Host Hardware, Building Key References: ISO 27001:2022 Cor 202203 A.7.13
19.6 DOR.ICT.DCP.EQP.007	A process should be established to ensure appropriate controls are implemented when equipment is scheduled for maintenance, considering whether this maintenance is performed by personnel on-site or external; where necessary, confidential and strictly confidential information must be cleared from the equipment, or the maintenance personnel must be sufficiently cleared. Asset-Types: Information, Business Process, Hardware Appliance, End User Device, Mobile Device, Processing Peripheral, Storage Media, Other Device, Storage, Server & Host Hardware, Building Key References: ISO 27001:2022 Cor 202203 A.7.13
19.7 DOR.ICT.DCP.EQP.008	Before putting equipment back into operation, it should be inspected based on a risk-based approach. Asset-Types: Business Process, Hardware Appliance, End User Device, Mobile Device, Processing Peripheral, Storage Media, Other Device, Storage, Server & Host Hardware, Building Key References: ISO 27001:2022 Cor 202203 A.7.13
19.8 DOR.ICT.DCP.EQP.009	All remote access for maintenance purposes is subject to the same security requirements as all access to infrastructure of the respective legal entity. Asset-Types: Information, Business Process, Hardware Appliance, Processing Peripheral, Storage Media, Other Device, Storage, Building Key References: ISO 27001:2022 Cor 202203 A.7.13
19.9 DOR.ICT.DCP.EQP.010	IT Assets and physical access control devices must be appropriately maintained. Asset-Types: Business Process, Hardware Appliance, End User Device, Mobile Device, Processing Peripheral, Storage Media, Other Device, Storage, Server & Host Hardware, Building Key References: DORA RTS RMF A.18.2d)

19.10 DOR.ICT.DCP.EQP.011	IT Assets and non-IT Assets must be secured, both within and outside the buildings and rooms, and results of risk assessments must be taken into account. The measures must also include appropriate protection to unattended IT Assets and non-IT Assets. Asset-Types: Business Process, Hardware Appliance, End User Device, Mobile Device, Processing Peripheral, Storage Media, Other Device, Storage, Server & Host Hardware, Network Connection, Building, Room Key References: DORA RTS RMF A.18.2c)
------------------------------	--

5. Roles and Responsibilities

5.1. Creator

The creator of the Data Center and Physical Protection Guideline is the **ICT Risk Governance & Advisory** Unit (Specialist).

The creator of Data Center and Physical Protection Guideline has the responsibility to issue clear, precise, and appropriate written rules to give guidance for implementation to the target group. It is important to ensure that all required information is accurate, up to date and complete.

5.2. Guideline Owner

The owner of the Data Center and Physical Protection Guideline is Head of **ICT Risk Governance & Advisory** Unit.

The most important tasks (not an exhaustive list) within the scope of responsibility are:

- Ensure completeness of the Guideline within functional area of responsibility
- Ensure correctness of content and the Guideline is up to date
- Define and conduct adherence oversight measures for Guidelines on a regular basis
- Assess impact on the Guideline with major focus on requirements as well as roles and responsibilities in the event of organizational changes, new products etc.

The Guideline Owner has at least an Expert or Head of Unit level.

The Guideline Owner is responsible for publishing and updating the Data Center and Physical Protection Guideline according to established procedures within the organization.

6. Appendix

6.1. Contact Information

Written Rule Owner: Head of ICT Risk Framework Governance & Advisory Unit

Please contact **ICT Risk Governance & Advisory** in case of any questions related to this Guideline.

6.2. Document History

Document History

Version	Date	Changes & Background
1.0	17.01.2025	Initial set-up of this Guideline
1.1	15.08.2025	Annual Update Guideline
2.0	19.08.2026	Annual guideline review with material changes

Coordination before publication

Version	Date	Task	Name
2.0	01.04.2026	Creator	ICT Risk Governance & Advisory Unit (Specialist)
	08.07.2026	Content Review	LE CISOs TISOs IT Ameli project
	08.07.2026	Content Confirmation	Head of ICT Risk Governance & Advisory Unit and LE CISOs

Approvals

Version	Date	Task	Name
2.0	13.08.2026	Approval	DBAG Chief Risk Officer.

6.3. Related Written Rules

Superordinated Written Rules	ICT Risk Management Policy
Subordinated Written Rules	n/a

6.4. Abbreviations

The abbreviations in this document are defined in the overall ICT Risk Glossary, which is provided on the Intranet website.

***** END OF DOCUMENT *****
