

Sony a7R V — Full Device Property Dump

Connected over Wi-Fi/SSH (network connection) via cameralink. 431 total properties returned by CrSDK's GetDeviceProperties(). Sorted alphabetically by name. Descriptions are Sony's own text from the CrSDK API Reference documentation (dp_<PropertyName>.html); 14 reserved/undocumented properties have no description available.

Code	Name	Description	Value	Get	Set
0x2	AEL	Get the AELock Indication and control AEL button	1	Yes	Yes
0x121	AF_Area_Position	Set the AF Area Position(x,y)	0	No	Yes
0x190	AFAssist	Get/Set the AF Assist	1	No	No
0x27b	AFFreeSizeAndPositionSetting	Get/Set the AF Free Size and Position Setting	0	No	No
0x25c	AFIlluminator	Get/Set the AF Illuminator	1	Yes	Yes
0x279	AFInFocusMagnifier	Get/Set the AF in Focus Magnifier	2	Yes	Yes
0x18f	AFSubjShiftSens	Get/Set AF Subj Shift Sens	5	No	No
0x11b	AFTrackingSensitivity	Get/Set the AF Tracking Sensitivity(Still)	3	Yes	Yes
0x18e	AFTransitionSpeed	Get/Set AF Transition speed	5	No	No
0x25e	AFWithShutter	Get/Set the AF with shutter	1	Yes	Yes
0x28b	AntidustShutterWhenPowerOff	Get/Set the Anti-dust Shutter When Power Off	1	Yes	Yes
0x25d	ApertureDriveInAF	Get/Set the Aperture Drive in AF	1	Yes	Yes
0x72f	APS_C_or_Full_SwitchingEnableStatus	Get the APS-C or Full Switching Status	1	Yes	No
0x72e	APS_C_or_Full_SwitchingSetting	Get the APS-C or Full Switching Setting	2	Yes	No
0x23d	APS_C_S35	Get/Set the APS-C/Super 35mm Shooting	2	Yes	Yes
0x7b4	AreaTimeZoneSettingVersion	Get the Area TimeZone Setting Version.	100	Yes	No
0x111	AspectRatio	Get/Set the Aspect Ratio	1	Yes	Yes
0x19c	AudioInputMasterLevel	Get/Set the Audio Input Master Level	32	Yes	No
0x19b	AudioRecording	Get/Set the Audio Recording	1	No	No
0x1dd	AudioSignals	Get/Set the Audio Signals	2	Yes	Yes
0x142	AutoPowerOffTemperature	Get/Set the Auto Power OFF Temperature	1	Yes	Yes
0x1dc	AutoReview	Get/Set the Auto Review	0	Yes	Yes
0x20a	AutoSlowShutter	Get/Set the Auto Slow Shutter	2	No	No
0x244	AutoSwitchMedia	Get/Set the Auto Switch Media	2	Yes	Yes

Code	Name	Description	Value	Get	Set
0x5	AWBL	Get the AWB Lock Indication and control AWBL button	1	Yes	Yes
0x703	BatteryLevel	Get the Battery Level Indicator	65540	Yes	No
0x702	BatteryRemain	Get the Battery Remaining (%)	76	Yes	No
0x143	BodyKeyLock	Get/Set the Body Key Lock Set cannot be performed while shooting.	1	Yes	Yes
0x79f	BodySerialNumber	Get the Body Serial Number	0	Yes	No
0x1f8	BracketOrder	Get/Set the Bracket Order	1	Yes	Yes
0x209	BulbExposureTimeSetting	Get/Set the Bulb Exposure Time Setting	60	Yes	Yes
0x208	BulbTimerSetting	Get/Set the Bulb Timer Setting	0	Yes	Yes
0x233	CameraButtonFunction	Get the Camera Button Function	0	Yes	Yes
0x234	CameraButtonFunctionMulti	Get the Camera Button Function(Multi)	0	Yes	Yes
0x78d	CameraButtonFunctionStatus	Get the Camera Button Function Status	1	Yes	No
0x235	CameraDialFunction	Get the Camera Dial Function	0	Yes	Yes
0x78b	CameraErrorCautionStatus	Get the Camera Error Caution Status	1	Yes	No
0x779	CameraOperatingMode	Get the Camera Operating Mode	1	Yes	No
0x72b	CameraSetting_ReadOperationEnableStatus	Get the Camera-Setting Read Operation Enable Status UploadSettingFile() is possible when this property is Enable.	1	Yes	No
0x72a	CameraSetting_SaveOperationEnableStatus	Get the Camera-Setting Save Operation Enable Status DownloadSettingFile() is possible when this property is Enable.	1	Yes	No
0x72c	CameraSetting_SaveRead_State	Get the Camera-Setting Save/Read State	0	Yes	No
0x72d	CameraSettingsResetEnableStatus	Get the Camera Setting Reset Enable State	1	Yes	No
0x770	CameraShakeStatus	Get the Camera Shake Status	2	Yes	No
0x723	Cancel_Media_FormatEnableStatus	Get the status of whether the media format is cancelable or not. This property changes during Full formatting.	0	No	No
0x755	CancelRemoteTouchOperationEnableStatus	Get the Cancel Remote Touch Operation Enable Status	0	No	No
0x1f7	ColorSpace	Get/Set the Color Space(Still Image)	2	Yes	Yes
0x115	Colortemp	Get/Set the Color Temperature For models that support CrDeviceProperty_ColortempStep, the CurrentValue of this device property is also updated by manipulating CrDeviceProperty_ColortempStep.	0	No	No
0x116	ColorTuningAB	Get/Set the Biaxial Fine Tuning A-B Direction	192	Yes	Yes
0x117	ColorTuningGM	Get/Set the Biaxial Fine Tuning G-M Direction	220	Yes	Yes
0x12a	CompressionFileFormatStill	Get/Set the Compression File Format(Still) Depends on this setting, available settings vary at CrDeviceProperty_FileType.	2	Yes	Yes
0x727	ContentsTransferCancelEnableStatus	Get the cancelability status of content transfer.	0	No	No

Code	Name	Description	Value	Get	Set
0x728	ContentsTransferProgress	Gets the handle and progress of the content during transfer	0	No	No
0x726	ContentsTransferStatus	Get the content transfer status	0	No	No
0x28a	ControlForHDMI	Get/Set the Control For HDMI	2	Yes	Yes
0x249	CreateNewFolder	Create a new folder (still).	0	No	Yes
0x794	CreateNewFolderEnableStatus	Get the Create New Folder(Still) Enable Status	1	Yes	No
0x1c5	CreativeLook	Get/Set the Creative Look	257	Yes	Yes
0x1cd	CreativeLook_Clarity	Get/Set the Creative Look Clarity	1	Yes	Yes
0x1c6	CreativeLook_Contrast	Get/Set the Creative Look Contrast	0	Yes	Yes
0x1ce	CreativeLook_CustomLook	Get/Set the Custom Look in Creative Look	1	Yes	Yes
0x1c9	CreativeLook_Fade	Get/Set the Creative Look Fade	4	Yes	Yes
0x1c7	CreativeLook_Highlights	Get/Set the Creative Look Highlights	-6	Yes	Yes
0x1ca	CreativeLook_Saturation	Get/Set the Creative Look Saturation	0	Yes	Yes
0x1c8	CreativeLook_Shadows	Get/Set the Creative Look Shadows	8	Yes	Yes
0x1cb	CreativeLook_Sharpness	Get/Set the Creative Look Sharpness	2	Yes	Yes
0x1cc	CreativeLook_SharpnessRange	Get/Set the Creative Look Sharpness Range	3	Yes	Yes
0x75e	CreativeLookResetEnableStatus	Get the Creative Look Reset Enable Status	1	Yes	No
0x71a	CustomWB_Capturable_Area	Get the Custom WB Capturable Area(x,y)	0	No	No
0x50b	CustomWB_Capture	Execute the Custom WB Capture	0	No	Yes
0x71b	CustomWB_Capture_Frame_Size	Get the Custom WB Capture Frame Size(x,y)	0	No	No
0x71c	CustomWB_Capture_Operation	Get the Custom WB Capture Operation Enable Status	0	No	No
0x509	CustomWB_Capture_Standby	Get the Custom WB Capture Standby Operation	0	No	No
0x50a	CustomWB_Capture_Standby_Cancel	Get the Custom WB Capture Standby Cancel Operation	0	No	No
0x719	CustomWB_Execution_State	Get the Custom WB Execution State	0	Yes	No
0x11e	DateTime_Settings	Set the Date and Time	0	No	Yes
0x2c6	DebugMode	Get/Set the Debug Mode	1	Yes	Yes
0x796	DefaultAFFreeSizeAndPositionSetting	Get the Default AF Free Size and Position Setting	0	No	No
0x7d3	DeleteContentOperationEnableStatusSLOT1	Get the DeleteContent Operation Enable Status■SLOT1■	1	Yes	No

Code	Name	Description	Value	Get	Set
0x7d4	DeleteContentOperationEnableStatusSLOT2	Get the DeleteContent Operation Enable Status■SLOT2■	1	Yes	No
0x760	DeviceOverheatingState	Get the Device Overheating State	0	Yes	No
0x30f	DifferentSetForSQMovie	Get/Set the Different Set for S&Q/Mv	1	No	No
0x284	DisplayQualityFinderMonitor	Get/Set the Display Quality(Finder/Monitor)	0	No	No
0x13f	DispMode	Get/Set the Monitor DISP(Screen Display) Mode You can select one of the items enabled in CrDeviceProperty_DispModeSetting.	6	Yes	Yes
0x730	DispModeCandidate	Get the Monitor DISP(Screen Display) Mode Candidate	0	Yes	No
0x13e	DispModeSetting	Get/Set the Monitor DISP(Screen Display) Mode Setting	222	Yes	Yes
0x10e	DriveMode	Get/Set the Drive Mode (Still Capture Mode)	196610	Yes	Yes
0x10f	DRO	Get/Set the Dynamic Range Optimizer	0	Yes	Yes
0x7da	ElapsedBulbExposureTime	Get the elapsed bulb exposure time.	0	No	No
0x202	ElectricFrontCurtainShutter	Get/Set the Electric Front Curtain Shutter	2	Yes	Yes
0x2c2	EnlargeScreenSetting	Get/Set the Enlarge Screen Setting.	1	Yes	Yes
0x704	EstimatePictureSize	—	143228000	Yes	No
0x101	ExposureBiasCompensation	Get/Set the Exposure Bias Compensation	0	Yes	Yes
0x147	ExposureCtrlType	Get/Set the Exposure Control Type	0	No	No
0x13b	ExposureIndex	Get/Set the Exposure Index	0	No	No
0x105	ExposureProgramMode	Get/Set the Exposure Program Mode Caution: When setting parameters related to shooting a picture such as ShutterSpeed after setting ExposureProgramMode, please wait 500ms before setting.	3	Yes	No
0x2c1	ExposureStep	Get/Set the exposure step width.	30	Yes	No
0x232	ExtendedShutterSpeed	Get/Set the Extended Shutter Speed	1288490188810	Yes	No
0x276	FaceEyeFrameDisplay	Get/Set the Face/Eye Frame Display	1	Yes	Yes
0x259	FacePriorityInMultiMetering	Get/Set the Face Priority in Multi Metering	1	Yes	No
0x3	FEL	Get the FEL Lock Indication and control FEL button	1	Yes	Yes
0x24e	FileSettingsTitleNameSettings	Get/Set the File Settings Title Name Settings	0	Yes	Yes
0x106	FileType	Get/Set the File Format(Still) Before setting this, check if CrDeviceProperty_CompressionFileFormatStill is set properly.	2	Yes	Yes
0x7b1	FirmwareUpdateCommandVersion	Get the enabled status and command dataset version (firmware update).	101	Yes	No
0x102	FlashCompensation	Get/Set the Flash Compensation	0	Yes	Yes
0x10b	FlashMode	Get/Set the Flash Mode	3	Yes	Yes
0x1d9	FlickerLessShooting	Get/Set the Flicker Less Shooting	1	Yes	Yes

Code	Name	Description	Value	Get	Set
0x78e	FlickerLessShootingStatus	Get the Flicker Less Shooting Status	0	No	No
0x769	FlickerScanEnableStatus	Get the Flicker Scan Enable Status	0	No	No
0x768	FlickerScanStatus	Get the Flicker Scan Status	1	Yes	No
0x100	FNumber	Get/Set the Aperture Value (F-Number)	1000	Yes	No
0x149	FocalDistanceInMeter	Get/Set the Focal Distance in Meter	4294967295	Yes	No
0x11d	Focus_Magnifier_Setting	Get/Set the Focus Magnifier Setting	20250873	Yes	Yes
0x113	FocusArea	Get/Set the Focus Area	3	Yes	Yes
0x1fa	FocusBracketExposureLock1stImg	Get/Set the Focus Bracket Exposure Lock 1st Image	1	Yes	Yes
0x196	FocusBracketFocusRange	Get/Set the Focus Bracket Focus Range	4	Yes	Yes
0x1fb	FocusBracketIntervalUntilNextShot	Get/Set the Focus Bracket Interval Until Next Shot	65535	Yes	Yes
0x1f9	FocusBracketOrder	Get/Set the Focus Bracket Order	1	Yes	Yes
0x24f	FocusBracketRecordingFolder	Get/Set the Focus Bracket Recording Folder	1	Yes	Yes
0x758	FocusBracketShootingStatus	Get the Focus Bracket Shooting Status	0	Yes	No
0x195	FocusBracketShotNumber	Get/Set the Focus Bracket Shot Num	3	Yes	No
0x767	FocusDrivingStatus	Get the Focus Driving Status(Absolute) This value changes only when the CrDeviceProperty_FocusPositionSetting operation.	1	Yes	No
0x707	FocusIndication	Get the Focus Indication	1	Yes	No
0x212	FocusMagnificationTime	Get/Set the Focus Magnification Time	255	Yes	Yes
0x277	FocusMap	Get/Set the Focus Map	1	No	No
0x109	FocusMode	Get/Set the Focus Mode	2	Yes	Yes
0x179	FocusModeSetting	Get/Set the Focus Mode Setting	0	No	No
0x766	FocusPositionCurrentValue	Get the Absolute Focus Position Current Value	2048	Yes	No
0x20e	FocusPositionSetting	Get/Set the Absolute Focus Position	0	Yes	Yes
0x73b	FocusTouchSpotStatus	Get the Focus TouchSpot Status	1	Yes	No
0x73c	FocusTrackingStatus	Get the Focus Tracking Status	1	Yes	No
0x757	FollowFocusPositionCurrentValue	Get the Follow Focus Position Current Value	0	Yes	No
0x194	FollowFocusPositionSetting	Get/Set the Follow Focus Position	0	Yes	No
0x795	ForcedFileNumberResetEnableStatus	Get/Set the Forced File Number Reset Enable Status	1	Yes	No
0x219	FTP_AutoTransfer	Get/Set the FTP Auto Transfer	1	Yes	Yes

Code	Name	Description	Value	Get	Set
0x21a	FTP_AutoTransferTarget	Get/Set the FTP Auto Transfer Target FileType (Still/Movie)	1	Yes	Yes
0x280	FTP_AutoTransferTarget_StillImage	Get/Set the Auto FTP Transfer Target(Still)	1	Yes	Yes
0x714	FTP_ConnectionErrorInfo	Get the FTP Connection Error Info	0	No	No
0x713	FTP_ConnectionStatus	Get the FTP Connection Status	4	No	No
0x218	FTP_Function	Get/Set the FTP Function	1	Yes	Yes
0x21e	FTP_PowerSave	Get/Set the FTP Power Save	1	Yes	Yes
0x27f	FTP_TransferStillImageQualitySize	Get/Set the FTP Transfer Still Image Quality Size	2	Yes	Yes
0x21c	FTP_TransferTarget	Get/Set the FTP Transfer Target(Still)	1	Yes	Yes
0x76b	FTPServerSettingOperationEnableStatus	Get the FTP Server Setting Operation Enable Status	1	Yes	No
0x76a	FTPServerSettingVersion	Get the FTP Server Setting Version	102	Yes	No
0x76d	FTPTransferSetting_ReadOperationEnableStatus	Get the FTP Transfer Setting Read Operation Enable Status	1	Yes	No
0x76c	FTPTransferSetting_SaveOperationEnableStatus	Get the FTP Transfer Setting Save Operation Enable Status	1	Yes	No
0x76e	FTPTransferSetting_SaveRead_State	Get the FTP Transfer Setting Save/Read State	0	Yes	No
0x25f	FullTimeDMF	Get/Set the Full Time DMF	1	Yes	Yes
0x1d1	FunctionOfTouchOperation	Get/Set the Function of Touch Operation	1	Yes	Yes
0x138	GainControlSetting	Get/Set the Gain Control Setting	0	No	No
0x286	GammaDisplayAssist	Get/Set the Gamma Display Assist	1	Yes	Yes
0x287	GammaDisplayAssistType	Get/Set the Gamma Display Assist Type	1	Yes	Yes
0x252	GridLineDisplay	Get/Set the Grid Line Display	2	Yes	Yes
0x30e	GridLineType	Get/Set the Grid Line Type	1	Yes	Yes
0x1de	HDMIResolutionStillPlay	Get/Set the HDMI Resolution(Still/Play)	65535	Yes	Yes
0x1f5	HighIsoNR	Get/Set the High ISO NR	1	Yes	Yes
0x763	HighResolutionShutterSpeed	Get the High Resolution Shutter Speed	0	No	No
0x32f	HighResolutionShutterSpeedAdjust	Execute the high resolution SS adjust.	0	No	Yes
0x330	HighResolutionShutterSpeedAdjustInIntegralMultiples	Execute the high resolution SS adjust in integral multiples.	0	No	Yes
0x1d2	HighResolutionShutterSpeedSetting	Get/Set the High Resolution Shutter Speed Setting	0	Yes	No

Code	Name	Description	Value	Get	Set
0x1f6	HLGStillImage	Get/Set the HLG Still Image	1	Yes	No
0x145	ImageID_Num	Get/Set the Image ID(Numerical Value) See "GPS information and shooting image link" in Tips / Trouble shooting for how to use it.	0	Yes	Yes
0x144	ImageID_Num_Setting	Get/Set the Image ID(Numerical) Setting See "GPS information and shooting image link" in Tips / Trouble shooting for how to use it.	1	Yes	Yes
0x146	ImageID_String	Get/Set the Image ID(String) See "GPS information and shooting image link" in Tips / Trouble shooting for how to use it.	0	Yes	Yes
0x110	ImageSize	Get/Set the Image Size	2	Yes	No
0x1a3	ImageStabilizationSteadyShot	Get/Set the Image Stabilization Steady Shot	1	Yes	Yes
0x230	ImageStabilizationSteadyShotAdjust	Get/Set the Image Stabilization Steady Shot Adjust	1	Yes	No
0x231	ImageStabilizationSteadyShotFocalLength	Get/Set the Image Stabilization Steady Shot Focal Length	0	No	No
0x278	InitialFocusMagnifier	Get/Set the Initial Focus Magnifier(Still)	31	Yes	Yes
0x505	Interval_Rec_Mode	Get/Set the Interval REC Mode	1	Yes	Yes
0x718	Interval_Rec_Status	Get the Interval REC Status	1	Yes	No
0x200	IntervalRec_AETrackingSensitivity	Get/Set the IntervalREC(Still) AE Tracking Sensitivity	3	Yes	Yes
0x1ff	IntervalRec_NumberOfShots	Get/Set the IntervalREC(Still) Number of Shots	30	Yes	Yes
0x1fd	IntervalRec_ShootingInterval	Get/Set the IntervalREC(Still) Shooting Interval	30	Yes	Yes
0x1fc	IntervalRec_ShootingStartTime	Get/Set the IntervalREC(Still) Shooting Start Time	1	Yes	Yes
0x1fe	IntervalRec_ShootIntervalPriority	Get/Set the IntervalREC(Still) Shoot Interval Priority	1	Yes	Yes
0x201	IntervalRec_ShutterType	Get/Set the IntervalREC(Still) Shutter Type	3	Yes	Yes
0x136	IrisModeSetting	Get/Set the Iris Mode Setting In ILC, enabled when CrDeviceProperty_ExposureCtrlType is in "Flexible Exposure Mode".	0	No	No
0x20c	IsoAutoMinShutterSpeedManual	Get/Set the Iso Auto Min Shutter Speed Manual	0	No	No
0x20b	IsoAutoMinShutterSpeedMode	Get/Set the Iso Auto Min Shutter Speed Mode	1	Yes	Yes
0x20d	IsoAutoMinShutterSpeedPreset	Get/Set the Iso Auto Min Shutter Speed Preset	3	Yes	Yes
0x258	IsoAutoRangeLimitMax	Get/Set the ISO Auto Range Limit(Max)	3200	No	No
0x257	IsoAutoRangeLimitMin	Get/Set the ISO Auto Range Limit(Min)	100	No	No
0x729	IsoCurrentSensitivity	Get the ISO Current Sensitivity	0	No	No
0x104	IsoSensitivity	Get/Set the ISO Sensitivity	400	Yes	Yes
0x241	LensCompensationBreathing	Get/Set the Lens Compensation Breathing	1	No	No
0x23f	LensCompensationChromaticAberration	Get/Set the Lens Compensation Chromatic Aberration	2	Yes	Yes

Code	Name	Description	Value	Get	Set
0x240	LensCompensationDistortion	Get/Set the Lens Compensation Distortion	2	Yes	No
0x23e	LensCompensationShading	Get/Set the Lens Compensation Shading	2	Yes	Yes
0x756	LensInformationEnableStatus	Get the Lens Information Enable Status Valid only in movie mode.	0	Yes	No
0x765	LensModelName	Get the Lens Model Name	0	Yes	No
0x75f	LensVersionNumber	Get the Lens Version Number	0	Yes	No
0x715	LiveView_Area	—	0	Yes	No
0x508	LiveView_Image_Quality	Get/Set the LiveView Image Quality	1	Yes	Yes
0x118	LiveViewDisplayEffect	Get/Set the Live View Display Effect	1	Yes	Yes
0x50d	LiveViewProtocol	Get/Set the Live View Protocol	1	Yes	Yes
0x706	LiveViewStatus	LiveView Status	2	Yes	No
0x1f4	LongExposureNR	Get/Set the Long Exposure NR	1	Yes	Yes
0x7b0	MaximumNumberOfBytes	Get the maximum number of bytes for data payload on dat packet.	4194292	Yes	No
0x7cc	MaximumSizeOfImageIDString	Get the Maximum size of Image ID String	128	Yes	No
0x712	Media_FormatProgressRate	Get the Media Format Progress Rate	0	No	No
0x7a5	MediaSLOT1_ContentsInfoListEnableStatus	Get the media slot 1 ContentsInfoList enabled status.	1	Yes	No
0x7a7	MediaSLOT1_ContentsInfoListRegenerateUpdateTime	Get the media slot 1 ContentsInfoList regenerate update time.	1787534716633	Yes	No
0x7a9	MediaSLOT1_ContentsInfoListUpdateTime	Get the media slot 1 ContentsInfoList update time.	1787534716633	Yes	No
0x12b	MediaSLOT1_FileType	Get/Set the File Format(Still) of media(SLOT1) This property is effective when Recording Media for still images is set to "Sort Recording". For ILCE-1 : MENU > Shooting > Media > Rec. Media Settings > Recording Media This setting is related to "CrDeviceProperty_CompressionFileFormatStill".	65535	No	No
0x70b	MediaSLOT1_FormatEnableStatus	Get the Media Full Format Enable Status(SLOT1)	1	Yes	No
0x12d	MediaSLOT1_ImageQuality	Get/Set the Image Quality of media(SLOT1) This property is effective when Recording Media for still images is set to "Sort Recording", and CrDeviceProperty_MediaSLOT1_FileType is set to "CrFileType_Jpeg" or "CrFileType_Heif". For ILCE-1 : MENU > Shooting > Image Quality > Image Quality Settings > JPEG Quality/HEIF Quality This setting is related to "CrDeviceProperty_CompressionFileFormatStill".	65535	No	No
0x12f	MediaSLOT1_ImageSize	Get/Set the Image Size of media(SLOT1) This property is effective when Recording Media for still images is set to "Sort Recording", and CrDeviceProperty_MediaSLOT1_FileType is set to "CrFileType_Jpeg" or "CrFileType_Heif". For ILCE-1 : MENU > Shooting > Image Quality > Image Quality Settings > JPEG Image Size/HEIF Image Size This setting is related to "CrDeviceProperty_CompressionFileFormatStill".	65535	No	No
0x721	MediaSLOT1_QuickFormatEnableStatus	Get the Media Quick Format Enable Status(SLOT1)	1	Yes	No
0x132	MediaSLOT1_RAW_FileCompressionType	Get/Set the compression type of RAW file in media(SLOT1) This property is effective when Recording Media for still images is set to "Sort Recording", and CrDeviceProperty_MediaSLOT1_FileType is set to "CrFileType_Raw". For ILCE-1 : MENU > Shooting > Image Quality > Image Quality Settings > File Format/RAW File Type	65535	No	No

Code	Name	Description	Value	Get	Set
0x709	MediaSLOT1_RemainingNumber	Get the Remaining number shots of Media (SLOT1) Please set the function of camera "Rec. Media Settings: Recording Mode" to Standard when using ILCE-7RM4 and ILCE-7RM4A.	2203	Yes	No
0x70a	MediaSLOT1_RemainingTime	Get the Remaining shooting time of Media (SLOT1) Please set the function of camera "Rec. Media Settings: Recording Mode" to Standard when using ILCE-7RM4 and ILCE-7RM4A.	0	No	No
0x708	MediaSLOT1_Status	Get the Media (SLOT1) Status Please set the function of camera "Rec. Media Settings: Recording Mode" to Standard when using ILCE-7RM4 and ILCE-7RM4A.	0	Yes	No
0x773	MediaSLOT1_WritingState	Get the Media SLOT1 Writing State	1	Yes	No
0x7a6	MediaSLOT2_ContentsInfoListEnableStatus	Get the media slot 2 ContentsInfoList enabled status.	1	Yes	No
0x7a8	MediaSLOT2_ContentsInfoListRegenerateUpdateTime	Get the media slot 2 ContentsInfoList regenerate update time.	1786499896348	Yes	No
0x7aa	MediaSLOT2_ContentsInfoListUpdateTime	Get the media slot 2 ContentsInfoList update time.	1786499896348	Yes	No
0x12c	MediaSLOT2_FileType	Get/Set the File Format(Still) of media(SLOT2) This property is effective when Recording Media for still images is set to "Sort Recording". For ILCE-1 : MENU > Shooting > Media > Rec. Media Settings > Recording Media This setting is related to "CrDeviceProperty_CompressionFileFormatStill".	65535	No	No
0x70e	MediaSLOT2_FormatEnableStatus	Get the Media Full Format Enable Status(SLOT2)	1	Yes	No
0x12e	MediaSLOT2_ImageQuality	Get/Set the Image Quality of media(SLOT2) This property is effective when Recording Media for still images is set to "Sort Recording", and CrDeviceProperty_MediaSLOT2_FileType is set to "CrFileType_Jpeg" or "CrFileType_Heif". For ILCE-1 : MENU > Shooting > Image Quality > Image Quality Settings > JPEG Quality/HEIF Quality This setting is related to "CrDeviceProperty_CompressionFileFormatStill".	65535	No	No
0x130	MediaSLOT2_ImageSize	Get/Set the Image Size of media(SLOT2) This property is effective when Recording Media for still images is set to "Sort Recording", and CrDeviceProperty_MediaSLOT2_FileType is set to "CrFileType_Jpeg" or "CrFileType_Heif". For ILCE-1 : MENU > Shooting > Image Quality > Image Quality Settings > JPEG Image Size/HEIF Image Size This setting is related to "CrDeviceProperty_CompressionFileFormatStill".	65535	No	No
0x722	MediaSLOT2_QuickFormatEnableStatus	Get the Media Quick Format Enable Status(SLOT2)	1	Yes	No
0x133	MediaSLOT2_RAW_FileCompressionType	Get/Set the compression type of RAW file in media(SLOT2) This property is effective when Recording Media for still images is set to "Sort Recording", and CrDeviceProperty_MediaSLOT2_FileType is set to "CrFileType_Raw". For ILCE-1 : MENU > Shooting > Image Quality > Image Quality Settings > File Format/RAW File Type	65535	No	No
0x70f	MediaSLOT2_RemainingNumber	Get the Remaining number shots of Media (SLOT2) Please set the function of camera "Rec. Media Settings: Recording Mode" to Standard when using ILCE-7RM4 and ILCE-7RM4A.	2199	Yes	No
0x710	MediaSLOT2_RemainingTime	Get the Remaining shooting time of Media (SLOT2) Please set the function of camera "Rec. Media Settings: Recording Mode" to Standard when using ILCE-7RM4 and ILCE-7RM4A.	0	No	No
0x70d	MediaSLOT2_Status	Get the Media (SLOT2) Status Please set the function of camera "Rec. Media Settings: Recording Mode" to Standard when using ILCE-7RM4 and ILCE-7RM4A.	0	Yes	No
0x774	MediaSLOT2_WritingState	Get the Media SLOT2 Writing State	1	Yes	No
0x799	MeteredManualLevel	Get the Metered Manual Level	-700	No	No
0x10a	MeteringMode	Get/Set the Exposure Metering Mode	5	Yes	Yes
0x7b2	ModelName	Get the camera model name.	0	Yes	No
0x283	MonitorBrightnessManual	Get/Set the Monitor Brightness Manual	0	No	No

Code	Name	Description	Value	Get	Set
0x282	MonitorBrightnessType	Get/Set the Monitor Brightness Type	2	Yes	Yes
0x7a3	MonitoringAvailableFormat	Get the format available for distribution	0	No	No
0x786	MonitoringDeliveringStatus	Get the Monitoring Delivering Status	65535	Yes	No
0x789	MonitoringDeliveryTypeSupportInfo	Get the Monitoring Delivery Type Support Information	0	No	No
0x7a4	MonitoringFormatSupportInformation	Get the format Support Information	0	Yes	No
0x787	MonitoringIsDelivering	Get the Delivering Condition	0	Yes	No
0x1e8	MonitoringOutputDisplayHDMI	Get/Set the Monitoring Output Display HDMI(Movie)	2	Yes	Yes
0x788	MonitoringSettingVersion	Get the Monitoring Setting Version	101	Yes	No
0x7a2	MonitoringTransportProtocol	Get the Monitoring Transport Protocol	0	No	No
0x148	MonitorLUTSetting	Get/Set the Monitor LUT Setting	1	No	No
0x127	Movie_File_Format	Get/Set the File Format(Movie)	3	Yes	Yes
0x21b	Movie_FTP_AutoTransferTarget	Get/Set the FTP Auto Transfer Target(Movie)	1	Yes	Yes
0x21d	Movie_FTP_TransferTarget	Get/Set the FTP Transfer Target(Movie)	1	Yes	Yes
0x1e1	Movie_HDMIOutput4KSetting	Get/Set the HDMI Output 4K Setting(Movie)	0	No	No
0x1e9	Movie_HDMIOutputAudioCH	Get/Set the Audio Output HDMI Monitor CH	3	Yes	Yes
0x1e4	Movie_HDMIOutputColorGamutForRAWOut	Get/Set the HDMI Output Color Gamut for RAW Out(Movie)	0	No	No
0x1e2	Movie_HDMIOutputRAW	Get/Set the HDMI Output RAW(Movie)	1	Yes	Yes
0x1e3	Movie_HDMIOutputRawSetting	Get/Set the HDMI Output Raw Setting(Movie)	0	No	No
0x1e6	Movie_HDMIOutputRecControl	Get/Set the HDMI Output REC Control(Movie)	0	No	No
0x1df	Movie_HDMIOutputRecMedia	Get/Set the HDMI Output Rec Media(Movie)	2	Yes	Yes
0x1e0	Movie_HDMIOutputResolution	Get/Set the HDMI Output Resolution(Movie)	65535	Yes	Yes
0x1e5	Movie_HDMIOutputTimeCode	Get/Set the HDMI Output Time Code(Movie)	1	Yes	Yes
0x1a4	Movie_ImageStabilizationSteadyShot	Get/Set the Image Stabilization Steady Shot(Movie)	0	No	No
0x1cf	Movie_ProxyFileFormat	Get/Set the Proxy File Format(Movie)	3	Yes	Yes
0x129	Movie_Recording_FrameRateSetting	Get/Set the Recording Frame Rate Setting(Movie)	3	Yes	Yes
0x128	Movie_Recording_Setting	Get/Set the Recording Setting(Movie)	63	Yes	Yes
0x246	Movie_RecordingFileNumber	Get/Set the Recording File Number (Movie)	2	Yes	Yes

Code	Name	Description	Value	Get	Set
0x243	Movie_RecordingMedia	Get/Set the Recording Media (Movie)	257	Yes	Yes
0x11f	NearFar	Set the Focus Near/Far	0	No	No
0x2c5	OSDImageMode	Get/Set the OSD image mode	0	Yes	Yes
0x1aa	PictureProfile	Get/Set the Picture Profile	0	Yes	Yes
0x1ae	PictureProfile_BlackGammaLevel	Get/Set the Picture Profile Black Gamma Level	0	No	No
0x1ad	PictureProfile_BlackGammaRange	Get/Set the Picture Profile Black Gamma Range	0	No	No
0x1ab	PictureProfile_BlackLevel	Get/Set the Picture Profile Black Level	0	No	No
0x1b9	PictureProfile_ColorDepthBlue	Get/Set the Picture Profile Color Depth Blue	0	No	No
0x1ba	PictureProfile_ColorDepthCyan	Get/Set the Picture Profile Color Depth Cyan	0	No	No
0x1b8	PictureProfile_ColorDepthGreen	Get/Set the Picture Profile Color Depth Green	0	No	No
0x1bb	PictureProfile_ColorDepthMagenta	Get/Set the Picture Profile Color Depth Magenta	0	No	No
0x1b7	PictureProfile_ColorDepthRed	Get/Set the Picture Profile Color Depth Red	0	No	No
0x1bc	PictureProfile_ColorDepthYellow	Get/Set the Picture Profile Color Depth Yellow	0	No	No
0x1b4	PictureProfile_ColorMode	Get/Set the Picture Profile Color Mode	0	No	No
0x1b6	PictureProfile_ColorPhase	Get/Set the Picture Profile Color Phase	0	No	No
0x1c4	PictureProfile_Copy	Get/Set the Copy Picture Profile	0	No	No
0x1c0	PictureProfile_DetailAdjustBWBalan ce	Get/Set the Picture Profile Detail Adjust B/W Balance	0	No	No
0x1c2	PictureProfile_DetailAdjustCrispen ing	Get/Set the Picture Profile Detail Adjust Crispening	0	No	No
0x1c3	PictureProfile_DetailAdjustHiLight Detail	Get/Set the Picture Profile Detail Adjust Hi-Light Detail	0	No	No
0x1c1	PictureProfile_DetailAdjustLimit	Get/Set the Picture Profile Detail Adjust Limit	0	No	No
0x1be	PictureProfile_DetailAdjustMode	Get/Set the Picture Profile Detail Adjust Mode	0	No	No
0x1bf	PictureProfile_DetailAdjustVHBala nce	Get/Set the Picture Profile Detail Adjust V/H Balance	0	No	No
0x1bd	PictureProfile_DetailLevel	Get/Set the Picture Profile Detail Level	0	No	No
0x1ac	PictureProfile_Gamma	Get/Set the Picture Profile Gamma	0	No	No
0x1b0	PictureProfile_KneeAutoSet_MaxP oint	Get/Set the Picture Profile Knee AutoSet MaxPoint	0	No	No
0x1b1	PictureProfile_KneeAutoSet_Sensi tivity	Get/Set the Picture Profile Knee AutoSet Sensitivity	0	No	No

Code	Name	Description	Value	Get	Set
0x1b2	PictureProfile_KneeManualSet_Point	Get/Set the Picture Profile Knee ManualSet Point	0	No	No
0x1b3	PictureProfile_KneeManualSet_Slope	Get/Set the Picture Profile Knee ManualSet Slope	0	No	No
0x1af	PictureProfile_KneeMode	Get/Set the Picture Profile Knee Mode	0	No	No
0x1b5	PictureProfile_Saturation	Get/Set the Picture Profile Saturation	0	No	No
0x75d	PictureProfileResetEnableStatus	Get the Picture Profile Reset Enable Status	0	Yes	No
0x759	PixelMappingEnableStatus	Get the Pixel Mapping Enable Status	1	Yes	No
0x13d	PlaybackMedia	Get/Set the Playback Media	1	Yes	No
0x1db	PlaybackVolumeSettings	Get/Set the Playback Volume Settings	0	Yes	Yes
0x27d	PlaySetOfMultiMedia	Get/Set the Play Set of Multi Media	1	Yes	Yes
0x7ab	PostViewTransferResourceStatus	Get the set PostView enabled status.	2	Yes	No
0x260	PreAF	Get/Set the Pre-AF	1	Yes	Yes
0x11a	PriorityKeySettings	Get/Set the Position Key Setting	1	Yes	Yes
0x211	PrioritySetInAF_C	Get/Set the Priority Set in AF-C	3	Yes	Yes
0x210	PrioritySetInAF_S	Get/Set the Priority Set in AF-S	3	Yes	Yes
0x25a	PrioritySetInAWB	Get/Set the Priority Set in AWB	1	Yes	Yes
0x798	ProgramShiftStatus	Get the Program Shift Status	0	No	No
0x281	ProtectImageInFTPTransfer	Get/Set the Protect Image in FTP Transfer	1	Yes	Yes
0x1d0	ProxyRecordingSetting	Get/Set the Proxy Record Setting	3	Yes	No
0x7e0	PullPostViewImageStatus	Gets the status of the postview image data can be retrieved via RAM.	0	Yes	No
0x131	RAW_FileCompressionType	Get/Set the compression type of RAW file This setting is related to "CrDeviceProperty_CompressionFileFormatStill".	0	Yes	Yes
0x507	RAW_J_PC_Save_Image	Get/Set the RAW+J PC Save Image	0	No	No
0x214	RecognitionTarget	Get/Set the Recognition Target	2	Yes	Yes
0x73e	RecorderClipName	Get Recorder Clip Name Create by The Next Rec.	0	No	No
0x164	RecorderControlProxySetting	Get/Set the Recorder Control Proxy Setting	0	Yes	Yes
0x245	RecordingFileNumber	Get/Set the Recording File Number (Still)	2	Yes	Yes
0x248	RecordingFolderFormat	Get/Set the Recording Folder Format	2	Yes	Yes
0x242	RecordingMedia	Get/Set the Recording Media (Still image)	257	Yes	Yes
0x204	RecordingSelfTimer	Get/Set the Movie Rec Self timer	0	No	No

Code	Name	Description	Value	Get	Set
0x206	RecordingSelfTimerContinuous	Get/Set the Movie Recording Self timer Continuous	0	Yes	Yes
0x205	RecordingSelfTimerCountTime	Get/Set the Movie Recording Self timer Count time	3	Yes	Yes
0x207	RecordingSelfTimerStatus	Get the Movie Recording Self timer Status	0	Yes	No
0x247	RecordingSettingFileName	Get/Set the Recording Setting File Name	0	Yes	Yes
0x705	RecordingState	Get the Movie Recording State	0	Yes	No
0x10d	RedEyeReduction	Get/Set the Red Eye Reduction	0	Yes	Yes
0x251	ReleaseWithoutCard	Get/Set the Release without Card	2	Yes	Yes
0x250	ReleaseWithoutLens	Get/Set the Release without Lens	2	Yes	Yes
0x7db	RemainingBulbExposureTime	Get the remaining bulb exposure time.	0	No	No
0x7dc	RemainingNoiseReductionTime	Get the remaining noise reduction time.	0	No	No
0x50c	Remocon_Zoom_Speed_Type	Get/Set the Remocon Zoom Speed Type.	1	Yes	Yes
0x27e	RemoteSaveImageSize	Get/Set the Remote Save Image Size	1	Yes	Yes
0x193	RemoteTouchOperation	Execute remote touch operation (x, y).	0	No	Yes
0x754	RemoteTouchOperationEnableStatus	Get the Remote Touch Operation Enable Status	0	No	No
0x501	reserved10	—	1	Yes	No
0x502	reserved11	—	65535	No	No
0x503	reserved12	—	1	No	No
0x504	reserved13	—	1	Yes	No
0x70c	reserved20	—	0	No	No
0x711	reserved22	—	0	No	No
0x716	reserved26	—	1	Yes	No
0x717	reserved27	—	0	Yes	No
0x114	reserved4	—	1	Yes	No
0x120	reserved7	—	1	Yes	Yes
0x215	RightLeftEyeSelect	Get/Set the Right/Left Eye Select	1	Yes	No
0x1	S1	Control shutter half-release (S1) button.	1	Yes	Yes
0x500	S2	Get/Set the Shutter button release	1	Yes	Yes
0x7d5	SceneFileCommandVersion	Get the enabled status and dataset version (SceneFile).	0	No	No

Code	Name	Description	Value	Get	Set
0x725	SdkControlMode	Get the Sdk Control Mode.	0	Yes	No
0x79c	SecondBatteryLevel	Get the Second Battery Level Indicator	4294967294	No	No
0x79b	SecondBatteryRemain	Get the Second Battery Remaining (%)	-1	No	No
0x141	SelectFinderMonitor	Get/Set the Finder/Monitor Setting	1	Yes	Yes
0x216	SelectFTPServer	Get/Set the Select FTP Server	1	Yes	Yes
0x24a	SelectIPTCMetadata	Get/Set the Select IPTC Metadata	0	Yes	No
0x1d5	SelectUserBaseLookToSetInPPLUT	Set/Get to Select UserBaseLook to Set in PPLUT Can only be set in movie mode.	0	Yes	Yes
0x75c	SensorCleaningEnableStatus	Get the Sensor Cleaning Enable Status	1	Yes	No
0x24d	SetCopyright	Get/Set the Copyright name	0	Yes	Yes
0x24c	SetPhotographer	Get/Set the Photographer Name	0	Yes	Yes
0x793	ShootingSelfTimerStatus	Get the Shooting Self timer Status	1	Yes	No
0x28e	ShootingTimingPreNotificationMode	Get/Set the HW signal shooting timing pre-notification.	1	Yes	Yes
0x137	ShutterModeSetting	Get/Set the Shutter Mode Setting In ILC, enabled when CrDeviceProperty_ExposureCtrlType is in "Flexible Exposure Mode".	0	No	No
0x103	ShutterSpeed	Get/Set the Shutter Speed	19660810	Yes	No
0x1a9	ShutterType	Get/Set the Shutter Type	2	Yes	Yes
0x1a5	SilentMode	Get/Set the Silent Mode	1	Yes	Yes
0x1a6	SilentModeApertureDriveInAF	Get/Set the Silent Mode Aperture Drive in AF	2	Yes	Yes
0x1a8	SilentModeAutoPixelMapping	Get/Set the Silent Mode Auto Pixel Mapping	2	Yes	Yes
0x1a7	SilentModeShutterWhenPowerOff	Get/Set the Silent Mode Shutter When Power Off	2	Yes	Yes
0x701	SnapshotInfo	Get the Shooting File Info	0	Yes	No
0x20f	SoftSkinEffect	Get/Set the Soft Skin Effect	1	Yes	No
0x751	SoftwareVersion	Software Version.	0	Yes	No
0x199	SQFrameRate	Get/Set the S&Q Frame Rate	120	Yes	Yes
0x198	SQRecordingFrameRateSetting	Get/Set the S&Q Recording Frame Rate Setting	3	Yes	Yes
0x19a	SQRecordingSetting	Get/Set the S&Q Recording Setting	63	Yes	Yes
0x506	Still_Image_Trans_Size	Get/Set the Still Image Trans Size	1	Yes	Yes
0x107	StillImageQuality	Get/Set the Still Image Quality	65535	No	No
0x119	StillImageStoreDestination	Get/Set the information of Still Image Save Destination	3	Yes	Yes

Code	Name	Description	Value	Get	Set
0x18d	SubjectRecognitionAF	Get/Set Face Subject Recognition AF	3	Yes	Yes
0x263	SubjectRecognitionAnimalBirdDetectionParts	Get/Set the Subject Recognition Animal+Bird Detection Parts	1	Yes	Yes
0x262	SubjectRecognitionAnimalBirdPriority	Get/Set the Subject Recognition Animal+Bird Priority	1	Yes	Yes
0x267	SubjectRecognitionAnimalDetectionParts	Get/Set the Subject Recognition Animal(Still) Detection Parts	1	Yes	Yes
0x266	SubjectRecognitionAnimalDetectionSensitivity	Get/Set the Subject Recognition Animal(Still) Detection Sensitivity	3	Yes	Yes
0x265	SubjectRecognitionAnimalTrackingSensitivity	Get/Set the Subject Recognition Animal(Still) Tracking Sensitivity	3	Yes	Yes
0x264	SubjectRecognitionAnimalTrackingSubjectShiftRange	Get/Set the Subject Recognition Animal(Still) Tracking Subject Shift Range	3	Yes	Yes
0x26b	SubjectRecognitionBirdDetectionParts	Get/Set the Subject Recognition Bird Detection Parts	1	Yes	Yes
0x26a	SubjectRecognitionBirdDetectionSensitivity	Get/Set the Subject Recognition Bird Detection Sensitivity	3	Yes	Yes
0x269	SubjectRecognitionBirdTrackingSensitivity	Get/Set the Subject Recognition Bird Tracking Sensitivity	3	Yes	Yes
0x268	SubjectRecognitionBirdTrackingSubjectShiftRange	Get/Set the Subject Recognition Bird Tracking Subject Shift Range	3	Yes	Yes
0x271	SubjectRecognitionCarTrainDetectionSensitivity	Get/Set the Subject Recognition Car/Train Detection Sensitivity	3	Yes	Yes
0x270	SubjectRecognitionCarTrainTrackingSensitivity	Get/Set the Subject Recognition Car/Train Tracking Sensitivity	3	Yes	Yes
0x26f	SubjectRecognitionCarTrainTrackingSubjectShiftRange	Get/Set the Subject Recognition Car/Train Tracking Subject Shift Range	3	Yes	Yes
0x213	SubjectRecognitionInAF	Get/Set the Subject Recognition in AF	2	Yes	Yes
0x26e	SubjectRecognitionInsectDetectionSensitivity	Get/Set the Subject Recognition Insect Detection Sensitivity	3	Yes	Yes
0x26d	SubjectRecognitionInsectTrackingSensitivity	Get/Set the Subject Recognition Insect Tracking Sensitivity	3	Yes	Yes
0x26c	SubjectRecognitionInsectTrackingSubjectShiftRange	Get/Set the Subject Recognition Insect Tracking Subject Shift Range	3	Yes	Yes
0x261	SubjectRecognitionPersonTrackingSubjectShiftRange	Get/Set the Subject Recognition Person Tracking Subject Shift Range	3	Yes	Yes
0x274	SubjectRecognitionPlaneDetectionSensitivity	Get/Set the Subject Recognition Plane Detection Sensitivity	3	Yes	Yes
0x273	SubjectRecognitionPlaneTrackingSensitivity	Get/Set the Subject Recognition Plane Tracking Sensitivity	3	Yes	Yes
0x272	SubjectRecognitionPlaneTrackingSubjectShiftRange	Get/Set the Subject Recognition Plane Tracking Subject Shift Range	3	Yes	Yes

Code	Name	Description	Value	Get	Set
0x275	SubjectRecognitionPriorityOnRegisteredFace	Get/Set the Subject Recognition Priority on Registered Face	1	Yes	No
0x78c	SystemErrorCautionStatus	Get the System Error Caution Status	1	Yes	No
0x285	TCUBDisplaySetting	Get/Set the TC/UB Display Setting	1	Yes	Yes
0x19e	TimeCodeFormat	Get/Set the Time Code Format	1	No	No
0x1a0	TimeCodeMake	Get/Set the Time Code Make	1	No	No
0x19d	TimeCodePreset	Get/Set the Time Code Preset	0	No	No
0x75a	TimeCodePresetResetEnableStatus	Get the Time Code Preset Reset Enable Status	0	Yes	No
0x19f	TimeCodeRun	Get/Set the Time Code Run	1	No	No
0x79e	TotalBatteryLevel	Get the Total Battery Level Indicator	65540	Yes	No
0x79d	TotalBatteryRemain	Get the Total Battery Remaining (%)	76	Yes	No
0x140	TouchOperation	Get/Set the Touch Operation Setting	2	Yes	Yes
0x797	TrackingOnAndAFOnEnableStatus	Get the Tracking On + AF On Enable Status	0	No	No
0x581	unknown(0x581)	—	0	Yes	No
0x582	unknown(0x582)	—	0	Yes	No
0x771	UpdateBodyStatus	Get the Update Body Status	1	Yes	No
0x7ae	UploadDatasetVersion	Get the UploadDataset version of UploadData command.	100	Yes	No
0x1f3	USBPowerSupply	Get/Set the USB Power Supply	2	Yes	Yes
0x1d7	UserBaseLookAELevelOffset	Set/Get to UserBaseLook AE Level Offset	0	No	No
0x1d6	UserBaseLookInput	Set/Get to UserBaseLook Input	0	No	No
0x1a1	UserBitPreset	Get/Set the User Bit Preset	0	No	No
0x75b	UserBitPresetResetEnableStatus	Get the User Bit Preset Reset Enable Status	0	Yes	No
0x1a2	UserBitTimeRec	Get/Set the User Bit Time Rec	1	No	No
0x108	WhiteBalance	Get/Set the WhiteBalance	17	Yes	Yes
0x203	WindNoiseReduct	Get/Set the Wind Noise Reduction	0	No	No
0x10c	WirelessFlash	Get/Set the Wireless Flash Setting	0	Yes	Yes
0x24b	WriteCopyrightInfo	Get/Set the Write Copyright info	2	Yes	Yes
0x71f	Zoom_Bar_Information	Get the zoom bar information.	16777216	No	No

Code	Name	Description	Value	Get	Set
0x126	Zoom_Operation	Execute the zoom operation. It may not be possible to operate depending on the model and lens type. refs Zoom Operation / Zoom Scale. For models that support CrDeviceProperty_Zoom_Speed_Range, link with Range(min/max/step) of CrDeviceProperty_Zoom_Speed_Range.	0	No	Yes
0x71e	Zoom_Operation_Status	Get the Zoom Operation Enable Status	0	No	No
0x124	Zoom_Scale	Get/Set the Zoom Scale. It may not be possible to operate depending on the model and lens type. refs Zoom Operation / Zoom Scale.	1000	No	No
0x125	Zoom_Setting	Get/Set the Zoom Setting. It may not be possible to operate depending on the model and lens type. refs Zoom Operation / Zoom Scale.	1	Yes	No
0x724	Zoom_Speed_Range	Get the Zoom Speed Range.	0	Yes	No
0x720	Zoom_Type_Status	Get the Zoom Type Status	1	No	No
0x135	ZoomAndFocusPosition_Load	Get/Set the Load Zoom&FocusPosition Preset.	0	No	No
0x134	ZoomAndFocusPosition_Save	Get/Set the Save Zoom&FocusPosition Preset.	0	Yes	Yes
0x79a	ZoomAndFocusPresetDataVersion	Get the Zoom&Focus Preset Data Version	100	Yes	No
0x27c	ZoomAndFocusPresetZoomOnly_Set	Set the Zoom&Focus Preset Zoom-only	0	No	Yes
0x14d	ZoomDistance	Get/Set the Zoom Distance	40000	Yes	No
0x792	ZoomDrivingStatus	Get the Zoom Driving Status This value changes only when the CrDeviceProperty_ZoomPositionSetting operation.	1	Yes	No
0x7a1	ZoomPositionCurrentValue	Get the absolute zoom position current value.	16384	Yes	No
0x2bc	ZoomPositionSetting	Get/Set the absolute zoom position.	0	No	No