



The PS-6300SA is an all-in-one, high performance presentation switcher featuring a built-in auto-scaling and PIP (picture-in-picture) technology for dynamic video display. Together with PureLink's Don't Blink™ Seamless Switching Technology at every output, as well as user-friendly configuration and operation, the PS-6300SA provides full flexibility and convenience in any multimedia presentation environment.

## Key Feature

- All-in-one device – matrix switcher, scaler, analog to digital converter, amplifier, and audio DSP
- Bi-directional 2K scaling with Don't Blink Seamless Switching
- PIP Image Insertion Technology
- 4x3 built-in Balanced/Unbalanced Audio Matrix
- Advanced EDID management
- RS-232/LAN control

## Technical Specifications

<b>INPUTS</b>	4 HDMI 2 DVI-U
<b>OUTPUTS</b>	2 HDMI 1 DVI-U
<b>INPUT AUDIO</b>	4 Balanced/Un-balanced analog audio (5-pin phoenix connector)
<b>OUTPUT AUDIO</b>	3 Balanced/Un-balanced analog audio (5-pin phoenix connector) 1 S/PDIF digital audio (LP-CM-2Ch, Dolby Digital, or DTS only)
<b>PC RESOLUTION</b>	Up to 1920x1200@ 60Hz
<b>HDTV RESOLUTION</b>	Up to 1080p@ 60Hz
<b>CONNECTOR TYPE</b>	DVI-U : Supports both analog and digital signals (HDMI, DVI, RGBHV, YPbPr)
<b>MTBF</b>	95,000 hours
<b>SUPPORTED FORMAT</b>	HDMI 1.3 DVI 1.0
<b>COMPLIANCE</b>	Yes, HDCP
<b>OPERATING STORAGE</b>	32° ~ 117° F (0° to 47° C) - 40° ~ 158° F (-40° to 70° C)
<b>HUMIDITY</b>	0 ~ 90% non-condensing
<b>ACCESSORIES</b>	DC 12V, 5A, 60W (power supply)
<b>DIMENSIONS</b> (W x D x H)	19" x 8.0" x 1.75" in. 482.6 x 203.2 x 44.45 mm
<b>WEIGHT</b>	6.7 lbs (3.04 kg)

