



University
of Exeter

Centre for Smart Grid

程序代写代做 CS编程辅导

Optim Power Flow



WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Power Flow

Power flow is well known as “load flow.” This is the name given to a network solution that shows currents, voltages, and real and reactive power flows at every bus in the system.



1. The line flows
2. The bus voltages and system voltage profile
3. The effect of changes in circuit configuration, and incorporating new circuits on system loading
4. The effect of temporary loss of transmission capacity and (or) generation on system loading and accompanied effects
5. The effect of in-phase and quadrature boost voltages on system loading.
6. Economic system operation
7. system transmission loss minimization
8. Transformer tap settings for economic operation and
9. Possible improvements to an existing system by change of conductor sizes and system voltages.

程序代写代做CS编程辅导

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Power Flow

In the network at each bus or node there are four variables

- (i) Voltage magnitude
- (ii) Voltage phase angle
- (iii) Real power and
- (iv) Reactive power.



WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Bus	Specified variables	Computed variables
Slack – bus	Voltage magnitude and its phase angle	Real and reactive powers
Generator bus (PV – bus or voltage controlled bus)	Magnitudes of bus voltages and real powers (limit on reactive powers)	Voltage phase angle and reactive power.
Load bus	Real and reactive powers	Magnitude and phase angle of bus voltages

Power Flow

程序代写代做CS编程辅导

$$S_i = P_i + jQ_i = V_i \sum_{k=1}^n Y_{ik}^* V_k^* = \sum_{k=1}^n |V_i| |V_k| e^{j\theta_{ik}} (G_{ik} - jB_{ik})$$

$$= \sum_{k=1}^n |V_i| |V_k| (\cos \theta_{ik} + j \sin \theta_{ik}) (G_{ik} - jB_{ik})$$

WeChat: cstutorcs

Resolving into the real and imaginary parts:

Assignment Project Exam Help

Email: tutorcs@163.com

$$P_i = P_{Gi} - P_{Di} = \sum_{k=1}^n |V_i| |V_k| (G_{ik} \cos \theta_{ik} + B_{ik} \sin \theta_{ik})$$

QQ: 749389476

<https://tutorcs.com>

$$Q_i = Q_{Gi} - Q_{Di} = \sum_{k=1}^n |V_i| |V_k| (G_{ik} \sin \theta_{ik} - B_{ik} \cos \theta_{ik})$$



University
of Exeter

Centre for Smart Grid

程序代写代做 CS编程辅导



Optimal Power Flow Definition

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Optimal Power Flow Definition

Optimal load flow studies are concerned with economic operation of the system in all aspects.



The goal of OPF is to find the optimal settings of a given power system network that optimizes the system objective functions such as total generation cost, system loss, bus voltage deviation, emission of generating units, number of control actions, and load shedding while satisfying its power flow equations, system security, and equipment operating limits.

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Optimal Power Flow Overview

- Optimization problem
- Classical objective function
 - Minimize the cost of generation
- Equality constraints
 - Power balance at each node - power flow equations
- Inequality constraints
 - Network operating limits (line flows, voltages)
 - Limits on control variables

程序代写代做 CS编程辅导



WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>



University
of Exeter

Centre for Smart Grid

程序代写代做 CS编程辅导



Mathematical Formulation of the OPF

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Mathematical Formulation of the OPF

- Optimization problem

$$\min_u f(u)$$



$$\text{Subject to: } G(x, u, y) = 0$$

$$H(x, u, y) \geq 0$$

QQ: 749389476

<https://tutorcs.com>

程序代写代做 CS编程辅导

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

Mathematical Formulation of the OPF

- Optimization problem

- Classical objective function



- Classical objective function:

– Minimize total generating cost: $\min_u \sum_{i=1}^{N_G} C_i(P_i)$

- Many other objective functions are possible

– Minimize changes in controls: $\min_u \sum_{i=1}^{N_G} c_i |u_i - u_i^0|$

– Minimize system losses

– ...

QQ: 749389476

<https://tutorcs.com>

Mathematical Formulation of the OPF

- Decision variables (control variables)
 - Active power output of generating units
 - Voltage at the generator
 - Position of the transformer taps
 - Position of the phase shifter (quad booster) taps
 - Status of the switched capacitors and reactors
 - Control of power electronics (HVDC, FACTS)
 - Amount of load disconnected
- Vector of control variables: u

程序代写代做CS编程辅导



WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Mathematical Formulation of the OPF

- Equality constraints: 程序代写代做 CS编程辅导

– Power balance at node - power flow equations



$$P_k^G - P_k^L = \sum_{i=1}^N V_k V_i [G_{ki} \cos(\theta_k - \theta_i) + B_{ki} \sin(\theta_k - \theta_i)]$$

$$Q_k^G - Q_k^L = \sum_{i=1}^N V_k V_i [G_{ki} \sin(\theta_k - \theta_i) - B_{ki} \cos(\theta_k - \theta_i)] \quad k = 1, \dots, N$$

- Compact expression:

$$G(x, u, y) = 0$$

QQ: 749389476

<https://tutorcs.com>

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

Mathematical Formulation of the OPF

- Inequality constraints: 程序代写代做 CS编程辅导

- Limits on the control variables: $\underline{u} \leq u \leq \bar{u}$

- Operating limits on flows: $|F_{ij}| \leq \bar{F}_{ij}$

WeChat: cstutorcs

- Operating limits on voltages: $\underline{V}_j \leq V_j \leq \bar{V}_j$

Email: tutorcs@163.com

- Compact expression: $H(x, u, y) \geq 0$

QQ: 749389476

<https://tutorcs.com>

程序代写代做 CS编程辅导

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Mathematical Formulation of the OPF

According to the selected objective functions and constraints, there are different mathematical formulations for the OPF problem. They can be broadly classified as follows



1. Linear problem in which objectives and constraints are given in linear forms with continuous control variables.
2. Nonlinear problem where either objectives or constraints or both combined are nonlinear with continuous control variables.
3. Mixed-integer linear problems with both discrete and continuous control variables.

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Mathematical Formulation of the OPF

程序代写代做 CS编程辅导

$$\min_u f(u)$$



Subject to: $G(x, u, y) = 0$

$H(x, u, y) \geq 0$

QQ: 749389476

<https://tutorcs.com>

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com



University
of Exeter

Centre for Smart Grid

程序代写代做 CS编程辅导



Solving the OPF

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Solving the OPF

- Optimization problem
- Classical objective function
- Equality constraints
- Inequality constraints

程序代写代做 CS编程辅导



WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Various techniques were developed to solve the OPF problem. The algorithms may be classified into three groups: (1) conventional optimization methods, (2) intelligence search methods, and (3) nonquantitative approach to address uncertainties in objectives and constraints.



University
of Exeter

Centre for Smart Grid

程序代写代做 CS编程辅导



OPF Challenges

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

OPF Challenges

- Size of the problem程序代写代做 CS编程辅导
 - 1000' s of lines, hundreds of controls
 - Which inequality constraints are binding?
- Problem is non-linear
- Problem is non-convex
- Some of the variables are discrete
 - Position of transformer and phase shifter taps
 - Status of switched capacitors or reactors



WeChat: cstutorcs

Assignment Project Exam Help

Email: tutores@163.com

QQ: 749389476

<https://tutorcs.com>



University
of Exeter

Centre for Smart Grid

程序代写代做 CS编程辅导

Optim Power Flow

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

<https://tutorcs.com>

Questions and answers