Art Guard®
The Next Level In Asset Protection Technology

Programming Art Guard's MAP 345 wireless sensor into DMP's XR550 panel for protection of valuable assets

Hardware Requirements:
- XR550DN, V243, with a 1100XH V208 and a 1100T V201070221

Notes:
- 1100T must be installed first.
- Programming must be done from the local keypad. We recommend device #1.
- Set frequency to **Honeywell**.
- Zone programming of the MAP V2 must be from the keypad.
- Battery must be removed from the MAP sensor before programming.
- No repeaters can be installed on the system.

In the DMP Programming Mode:
1. Go to **Zone Information.**
2. Go to **Add Zone**.
3. Choose an open wireless zone number that is appropriate.
4. Name the zone.
5. Choose zone type that is appropriate (we have tested with DAY, NIGHT and AUX zone types)
6. Press **NO** for **Next Zone** to get to **Wireless Options**
7. Press **NO** for **DMP Wireless**
8. Press **YES** for **Competitor Wireless**
19. Choose learn **(LRN)** for **serial number.**
10. On the MAP V2 sensor, insert a battery to power up. (only 1 is needed to learn)
11. Wait for serial number to populate (normally 10-15 seconds)
12. Once populated hit command **(CMD)** button
13. **Transmitter Contact** - Change to **2**
14. **Transmitter Supervision** time set to **0**
15. **Next Zone** press **YES.**
16. Go to the next zone to add multiple devices or exit programming.
17. Set the MAP sensor to the desired mode (hanging, seated, accelerometer) per MAP V2 instructions.

Contact us for any questions at 212-989-1594 or [*bill@artguard.net*](mailto:bill@artguard.net)

Art Guard   https://www.artguard.net