




	I	G	F	E	D	C	B	A																																																			
4	RG-58 CABLE SPECIFICATION : 1) Inner Conductor Material and Plating 2) Dielectric Type 3) Shield Materials 4) Jacket Material and Color 5) Impedance, Ohms 6) Velocity of Propagation, % 7) Maximum Operating Frequency, GHz 8) Capacitance, pF/m 9) Maximum Operating Voltage, Vrms 10)Operating Range, deg C 11)Material 12)Diameter, mm - Copper Clad Steel, Silver - PE - Silver Plated Copper Braid - FEP (BLUE JACKET) - 50 - 69.90 - DC TO 6 GHz - 95 - 1,900 - -40 to +80 - Copper Clad Steel - 4.35 								4																																																		
3									3																																																		
2	BNC CONNECTOR SPECIFICATION : 1) INSULATORS 2) BODY 3) CRIMP SLEEVE 4) HEAT SHRINK SLEEVE 5) CONTACT PIN - PTFE - SS BODY - SEAMLESS LOWLEAD BRASS TUBE, ALLOY 330, SOFT ANNEAL TEMPER - RNF100 - BERYLIUM COPPER								2																																																		
1	<table><tr><td colspan="2">DESIGNED BY: GURU BIRADAR</td><td colspan="2" rowspan="3">RF LOW LOSS CABLE ASSEMNLy BNC MALE TO BNC MALE</td><td>I</td><td>-</td></tr><tr><td colspan="2">DATE: 07/03/2017</td><td>H</td><td>-</td></tr><tr><td colspan="2">CHECKED BY: Mr. S. METRI</td><td>G</td><td>-</td></tr><tr><td colspan="2">DATE: 07/03/2017</td><td colspan="2"></td><td>F</td><td>-</td></tr><tr><td>SIZE A4</td><td></td><td colspan="2">ANAND TECHNOLOGIES</td><td>E</td><td>-</td></tr><tr><td>SCALE 1:1</td><td>WEIGHT (kg) NA</td><td colspan="2">DRAWING NUMBER AT-CA-BNC-BNcM-402-2000</td><td>D</td><td>-</td></tr><tr><td colspan="2"></td><td colspan="2">SHEET 1 / 1</td><td>C</td><td>-</td></tr><tr><td colspan="4">This drawing is our property; it can't be reproduced or communicated without our written agreement.</td><td>B</td><td>-</td></tr><tr><td colspan="4"></td><td>A</td><td>-</td></tr></table>								DESIGNED BY: GURU BIRADAR		RF LOW LOSS CABLE ASSEMNLy BNC MALE TO BNC MALE		I	-	DATE: 07/03/2017		H	-	CHECKED BY: Mr. S. METRI		G	-	DATE: 07/03/2017				F	-	SIZE A4		ANAND TECHNOLOGIES		E	-	SCALE 1:1	WEIGHT (kg) NA	DRAWING NUMBER AT-CA-BNC-BNcM-402-2000		D	-			SHEET 1 / 1		C	-	This drawing is our property; it can't be reproduced or communicated without our written agreement.				B	-					A	-	1
DESIGNED BY: GURU BIRADAR		RF LOW LOSS CABLE ASSEMNLy BNC MALE TO BNC MALE		I	-																																																						
DATE: 07/03/2017				H	-																																																						
CHECKED BY: Mr. S. METRI				G	-																																																						
DATE: 07/03/2017				F	-																																																						
SIZE A4		ANAND TECHNOLOGIES		E	-																																																						
SCALE 1:1	WEIGHT (kg) NA	DRAWING NUMBER AT-CA-BNC-BNcM-402-2000		D	-																																																						
		SHEET 1 / 1		C	-																																																						
This drawing is our property; it can't be reproduced or communicated without our written agreement.				B	-																																																						
				A	-																																																						
	H	G					B	A																																																			