E2iPTV Lab User Guide

For version 0.1-20261109c · November 2026

What E2iPTV Lab is

E2iPTV Lab is an IPTV player plugin for Enigma2 set-top boxes. It plays **Xtream Codes** and **Stalker / Ministra (MAC)** providers on its own, with no other plugins needed. It installs as **E2iPTV Lab**, with its own settings and data, so it can sit beside the standard E2iPTV without either affecting the other.

What it does:

- **Live TV** with a full EPG grid, a mini TV and a full-screen player
- **Movies and Series**, with posters, details, seasons, episodes, sorting and resume
- **Catch-up** on Xtream providers, from the guide
- **Recording**, one-off and repeat, with a recordings browser, bookmarks and a recycle bin
- **Favourites**, **Search** across providers, and your own **bouquets** built from channels of any provider
- **Music** from your own music folder or NAS, with browsing by artist, genre, year and album, search, playlists and tracker music (MOD, S3M, XM, IT)
- **Colour themes**: Dark (default) or Sky Blue (the original E2iPTV colours)
- A nightly guide refresh, channel order and hiding, and a per-provider EPG offset

Tested on a Vu+ Solo4K with OpenATV 8.0.1 and 8.0.2 (development), OpenATV 7.6, OpenBH 6.0.001 and OpenViX 6.9.003. It also runs on OpenPLi (Scarthgap) from version 0.1-20261108a, with square rather than rounded list highlights.

You need:

- A box with a current Python 3 image
- A hard disk or USB stick for the plugin's data (strongly recommended; see the next section)
- At least one IPTV provider (Xtream or Stalker)

On OpenBH the image keeps the EPG key for itself. In the EPG grid, use **0** instead.

Installing and updating

Installing and updating are the same: copy the new `.ipk` to the box and install it over the old one. Your settings, providers and data are kept.

1. Download the latest `.ipk` from the **Releases** section of the GitHub page.
2. Copy it to the box's `/tmp` folder, for example with FTP or WinSCP, or with the box's network share.
3. Connect to the box by telnet or SSH and run, using the real file name:

```
opkg install --force-reinstall /tmp/enigma2-plugin-extensions-
e2iptvlab_<version>_all.ipk && killall -9 enigma2
```

4. The box's screen restarts. Open **E2iPTV Lab** from the **Plugins** menu.

The version you're running is shown in **Settings → About**.

Where the plugin keeps its data

The plugin keeps its guide, channel lists, bouquets, settings and music index in one folder, **E2iPTVLab_Data**, on the first hard disk or USB stick it finds (`/media/hdd` , `/media/usb` and so on).

Without a disk or USB stick, it keeps everything in the box's memory (`/tmp/e2iptv_data`) and shows a notice when it opens. It still works, but the guide and lists are lost at every restart. To fix it, plug in a USB stick, or choose a folder in **Settings → Other → Data Folder**.

Folder	What's in it
`E2iPTVLab_Data/cache/`	Settings, channel lists, last channel, favourites, music playlists
`E2iPTVLab_Data/epg/`	Guide data and the nightly EPG log
`E2iPTVLab_Data/order/`	Channel order files, which you can edit
`E2iPTVLab_Data/bouquets/`	Your bouquets
`E2iPTVLab_Data/recordings/`	Scheduled and repeat recordings
`E2iPTVLab_Data/music_index/`	The music index
`E2iPTVLab_Data/music_cache/`	Tracker tunes converted for playing (the last 20)
`/etc/enigma2/E2iPTVLab/`	Your playlist file and the data folder setting

To **remove** the plugin: `opkg remove enigma2-plugin-extensions-e2iptvlab && killall -9 enigma2` . The data folder stays on the disk until you delete it.

Adding your providers

Your providers go in one text file, **playlists.txt**, one provider per line. The first time the plugin opens, it creates `/etc/enigma2/E2iPTVLab/playlists.txt` with examples in it.

Edit the file on a computer (FTP, WinSCP or the box's network share). Put the name you want shown after a `#` at the end of each line:

```
http://server:port/get.php?username=USER&password=PASS&type=m3u_plus #My
Xtream
http://portal-address/c/?mac=00:1A:79:XX:XX:XX #My Stalker
```

- **Xtream** lines are your provider's M3U link (with `username=` and `password=`).
- **Stalker / Ministra** lines are the portal address with your box's MAC address (`mac=`).
- **To switch a provider off** without deleting it, put `#` straight in front of `http`.
- **After editing,** restart the GUI so the plugin reads the file again.

Keeping the file somewhere else: choose a different playlist folder in **Settings → Other → Playlists**. This is useful if you share one playlist file between several plugins.

Checking a provider works

Go to **Settings → Playlists**, choose the provider, then **Test Connection**. A panel shows whether the provider is working, with any details it sends back. The result is also written to the plugin's log.

Settings for each provider

Settings → Playlists → (provider) has:

Setting	What it does
Enabled	Switch the provider on or off
Live TV / Movies / Series	Choose which categories show for each
Refresh Interval	How often the channel lists are refreshed
EPG Offset	Move the guide by whole hours if this provider's times are out
Update Now	Refresh the channel lists straight away
Update EPG	Fetch this provider's guide now; the time of the last update shows next to it
Test Connection	Check the provider answers

Stalker portals allow one session per MAC address. If you use the same MAC on another box or app at the same time, one of them will be cut off.

Getting around

Everything starts from the **icon rail**, the column of icons down the left of the screen. Press **Left** on most screens (or **Menu** over a full-screen picture or the EPG grid) to bring it up, move **Up / Down** to an entry and press **OK**.

Icon rail entry	What it opens
Search	Search films and series, in one provider or all of them
Live TV	The last channel you watched, full screen
EPG Grid	The guide grid, on the last channel's category
Movies	Films from your providers
Series	Series from your providers
Music	Your own music folder
Recordings	Your recordings
Favourites	Channels, films and series you've saved
Settings	All the plugin's settings

Icon rail entry	What it opens
Exit / Close	Close the plugin

Opening the plugin goes back to the section you used last. If that was Live TV, it opens straight on your last channel, full screen; if it was the EPG grid, it opens the grid on that channel's category.

Keys that work everywhere

Key	What it does
Up / Down	Move through a list; lists wrap round from bottom to top
CH+ / CH−	Move a page at a time
OK	Open or choose the highlighted entry
Left	Back to the icon rail (from the left-hand panel or the top of a list)
Exit	Go back one step
Menu	The icon rail over a full-screen picture or the EPG grid; options for the highlighted entry in Music
Green / Yellow / Blue	Shown at the bottom of the screens that use them

Pop-up messages and choices appear as a rounded panel in the middle of the screen. **OK** or **Exit** closes a message; **Up / Down** and **OK** pick from a list of choices.

Live TV

Live TV shows your providers and their categories on the left, with a **mini TV** playing the highlighted channel. From there you go into the **EPG grid** to pick a channel, or straight to **full screen**.

The category list

Key	What it does
OK on a provider	Open or close its list of categories
OK on a category	Open the EPG grid for that category

Key	What it does
0	Full screen on whatever the mini TV is playing
Left	The icon rail

The EPG grid

The grid shows the channels of one category down the side and their programmes across the screen, with the mini TV in the corner.

Key	What it does
Up / Down	Move through the channels (the list wraps round)
Left / Right	Move through the programmes in time
OK	Options for the highlighted programme or channel: watch, record, Move Channel, Hide Channel, Copy to Bouquet, Show Hidden Channels and more
0 (or EPG)	Jump to now; press again to go back to the categories
Menu	The icon rail, over the grid

On OpenBH, use **0** rather than EPG, because the image keeps the EPG key for itself.

Full screen

Press **Menu** to bring up the icon rail over the picture. A live channel keeps playing while the rail is open.

Catch-up

On **Xtream** providers that offer it, programmes that have already been shown can be played back from the EPG grid: highlight a past programme and press **OK**. In the grid, programmes you can catch up are shown in a different colour. Catch-up isn't available on Stalker providers.

Channel order and hidden channels

Use **Move Channel** and **Hide Channel** in the grid's OK menu, or edit the order files on a computer. Each category has a text file in `E2iPTVLab_Data/order/`:

- Move lines up or down to change the order.

- Put `-` in front of a line to hide that channel.

Your order survives provider refreshes. **Show Hidden Channels** in the grid's OK menu brings hidden ones back into view.

If a channel freezes

With **Settings → Playback → Auto-restart frozen channels** set to **Yes**, the plugin watches the live picture and restarts the channel by itself if it freezes for about 2 seconds.

Choosing the player

Settings → Playback → Live TV player chooses how live channels are played. If one has problems (sound drifting out of sync, freezing, a box locking up), try another:

Player	Notes
Standard (GStreamer)	The default; works on every image
Box TV decoder	Uses the box's own TV decoder; not stable on some HiSilicon boxes
ServiceApp exteplayer3	Needs ServiceApp installed; often the smoothest
ServiceApp gstplayer	Needs ServiceApp installed

Leaving the plugin

When you close the plugin, the box goes back to the channel it was showing before you opened it (a satellite or cable channel). If that was also an internet stream, it stays on the screen you left.

The TV guide (EPG)

The plugin fetches the guide from your providers itself, with no other plugins needed. It refreshes every night at the time you choose, and you can update one provider at any time.

Settings → EPG

Setting	What it does
Refresh Time	The time of the nightly guide refresh

Setting	What it does
Refresh All	Refresh every provider's guide now
Status	What the last refresh did
Picons / Clear Picon Cache	Where channel logos are kept, and clearing the saved copies
Fill Guide Gaps	Use another provider's guide for channels that have none
Fill Gaps From	Which provider(s) to borrow guide data from
Fill Gaps Now	Run the gap filling straight away

One provider only: Settings → Playlists → (provider) → Update EPG. The time of its last update appears next to it, or "failed - see EPG log" if it didn't work.

If the guide is a few hours out

Set that provider's **EPG Offset** in **Settings → Playlists → (provider)**. It moves the whole guide by whole hours, for that provider only.

Checking the nightly refresh

Settings → Status & Logs has an **EPG refresh summary**: one line per provider, with how many channels were refreshed and whether it worked. Only providers in your current playlist are listed. The full log is `E2iPTVLab_Data/epg/nightly_refresh.log`.

Good to know:

- A provider with a very large channel list may not finish in one night, because each provider has a time limit.
- If you have **both E2iPTV and E2iPTV Lab** installed, both run a nightly refresh. That doubles the load on your providers, and Stalker providers may cut one off. Keep only one installed, or set them to different refresh times.
- The nightly refresh runs even if the plugin hasn't been opened since the box restarted.

Movies and Series

Movies and Series list your providers' films and programmes by category, with the poster and details of the highlighted one on the right.

- **Left panel:** the categories. **OK** opens one.

- **Right panel:** the films or series in that category, with the poster, year and plot of the highlighted one.
- **Series:** OK on a series shows its seasons and episodes; OK on an episode plays it.
- **Left** at the top of the list goes back to the icon rail.

OK on a film or series

OK opens a short menu:

Choice	What it does
Watch	Play it
Download	Save the film to your recordings folder (films only)
Add to Favourites / Remove from Favourites	Keep it in Favourites
Sort this list	Change the order of the list

Sort this list offers: Provider's order, A to Z, Z to A, Newest added first, Year – newest first, Year – oldest first. The choice is remembered.

Carrying on where you stopped

If you stop a film or episode part-way, playing it again asks **Resume** or **Restart from beginning**. Pressing **Menu** during a film brings up the icon rail; the film remembers where you got to.

Some 4K films use a video format (H.264 at 4K) that some boxes, such as the Vu+ Solo4K, can't decode. They play sound only or no picture. 4K films in HEVC (H.265) play normally.

Recordings

You can record live channels once or on repeat, and watch them back in the Recordings screen.

Setting up a recording

In the **EPG grid**, highlight a programme, press **OK** and choose to record it. You can record it once or as a **repeat recording** (the same programme each time it's on). The recording starts and ends a little early and late, to allow for programmes that don't run to time. Set those margins in **Settings → Other**.

Recordings are saved in the recordings folder chosen in **Settings → Other** (the box's `movie` folder unless you change it). Downloaded films go there too.

The Recordings screen

- **Left panel:** your recordings folder, your bookmarked folders and the recycle bin.
- **Right panel:** the recordings in the chosen place, with details of the highlighted one.
- **OK on a recording** offers **Play** or **Delete**. Deleted recordings go to the recycle bin first.
- **In the recycle bin**, OK offers **Restore** or **Delete permanently**.
- **Bookmarks:** add folders you use often, so they're one press away. OK on a bookmark offers **Open** or **Remove bookmark**.

Recordings in progress and scheduled

OK on a recording that's running or scheduled offers:

- **Stop recording now**
- **Stop repeat recording** (for repeats)
- **Cancel this recording** (one not yet started)

If a recording has sound problems

Sometimes the sound stops, the length is wrong, or skipping jumps about. That happens when the provider restarts its stream mid-programme. Recordings are corrected as they're written, but for older ones there are two repair tools. Run them by telnet:

```
python3
/usr/lib/enigma2/python/Plugins/Extensions/E2iPTVLab/tools/ts_audio_check.py
"<file>.ts"
python3
/usr/lib/enigma2/python/Plugins/Extensions/E2iPTVLab/tools/ts_fix_audio.py "
<file>.ts"
```

The first reports where the sound changes. The second writes a repaired copy, `<file>(fixed).ts`, next to the original, which is left alone.

Favourites, Search and your own bouquets

Favourites

Favourites keeps the films and series you want to find again quickly, with their posters and details.

- **To add one:** in Movies, Series or Search, press **OK** on it and choose **Add to Favourites**.
- **To remove one:** press **OK** on it and choose **Remove from Favourites**.
- Open **Favourites** from the icon rail. The left panel groups them, and the right panel shows the poster and details of the highlighted one.

Search

Search finds **films and series** by name, in one provider or across all of them.

1. Open **Search** from the icon rail.
2. Choose films or series, and which provider (or all).
3. Type part of the name.

Results are ranked: exact matches first, then names that start with what you typed, then names that contain it. OK on a result plays it or opens it, with the same options as in Movies and Series.

To search your own music, use **Search** inside Music instead (see the Music section).

Your own bouquets

A bouquet is your own list of channels, taken from any of your providers, for example all your news or sports channels in one place.

1. In the **EPG grid**, highlight a channel and press **OK**.
2. Choose **Copy to Bouquet**.
3. Pick an existing bouquet, or **New bouquet...** and type a name.

Once you have a bouquet, **My Bouquets** appears in the Live TV list alongside your providers. Bouquets are kept in `E2iPTVLab_Data/bouquets/`.

Music

Music plays your own music from a folder on the box, a USB stick or a NAS. It handles large collections (tested with over 170,000 tracks) and remembers where you were when you come back.

Setting it up

1. Choose your music folder in **Settings → Playback → Music folder**, for example a NAS share mounted on the box, such as `/media/autofs/<share>/Music`.
2. Open **Music** from the icon rail.

Music works best with this folder layout, though Folders view plays anything:

```
Music / Artist / Genre / 2018 - Album name / 01 - Track name.mp3
```

- The year comes from `2018 -` at the start of the album folder's name.
- The track number and name come from the file name, e.g. `01 - Track name.mp3`.
- Discs inside an album (`CD1`, `CD 02/...`) are played in order, as one album.
- Other layouts can be chosen: Genre / Artist / Album, or Artist / Album (see below).

The Music screen

- **Left panel:** where to go and what to do: Now playing, Play / Shuffle this list, Stop music, Tracker Files, Search, Playlists, Browse, Browse sort and rescan, Music folder. Below it, the cover and details of the highlighted entry.
- **Right panel:** the list.
- **Bottom line:** what's playing, or what Music is doing.

Key	What it does
OK	Open a folder or album; play a track (the rest of the list follows)
Green	Play the highlighted folder, album, artist or genre
Yellow	Shuffle the highlighted folder, album, artist or genre
Blue	Now Playing
Red	Search
Menu	Options for the highlighted entry (playlists, delete)
Stop	Stop the music
CH+ / CH−	Page up / down
Exit	Go back one step

Music keeps playing when you leave the Music screen. When you come back, it opens where you left off, on the same entry.

Browsing: Folders, or by Artist, Genre, Year

Browse, sort and rescan → Browse by chooses how the right panel lists your music:

Browse by	What you see
Folders (as on disk)	Your folders, A–Z, exactly as on the disk or NAS
Artist › Album	Artists, then their albums
Genre › Artist › Album	Genres, then artists, then albums
Year › Artist › Album	Years, then artists, then albums
All albums	Every album in one list

- **Sort albums:** A–Z, Z–A, Oldest first or Newest first.
- **Music folder** in the left panel always shows your actual folders A–Z, whichever Browse by you've chosen.
- **Browse: (your choice)** in the left panel takes you to the top of the Artist, Genre or Year view.
- Genres are grouped regardless of capitals, so "hard rock" and "Hard Rock" count as one.

The music index

The Artist, Genre, Year and Album views, and Search, use a **music index**: a list of every album and track, built from the folder and file names (the music files are never opened).

- **The first build** starts the first time you choose a Browse by option other than Folders. The bottom line shows its progress. For about 170,000 tracks on a NAS, it takes around 2 minutes.
- **Keeping it up to date:** each time you open Music, it checks for new or changed folders in the background (at most every 10 minutes) and re-reads only those.
- **Rescan music now** (in Browse, sort and rescan) reads everything again from scratch. Use it after big changes, or after adding tracks deep inside an existing box set.
- **Folder layout** (in Browse, sort and rescan) tells the index how your folders are arranged: Artist / Genre / Album, Genre / Artist / Album, or Artist / Album.

Search

Open **Search** from the left panel, or press **Red**. Fill in one or more rows, then choose **Search now**:

Row	How it works
Search everything	One word, matched against artist, genre, year, album and track name
Artist / Genre	Type part of a name (or nothing, for the full list), then press OK to tick the ones you want, and choose Done
Year	A Year from and a Year to; or Just one year, or Any later year
Album name / Track name	Part of the name

- **Every row you fill must match** (AND): e.g. Genre Rock and Year 1980–1989.
- **Within a row, any one will do** (OR): several ticked artists, or words separated by commas, e.g. `love, heart`.
- Capitals, accents and the different kinds of dash and quote are ignored.
- **Clear all** empties the rows. Your rows are remembered until you clear them.

Results show the matching **albums** and **tracks**. OK on a track plays the results from there; Green or Yellow plays or shuffles them all. Exit goes back to where you were. Track results stop at 2,000.

Playlists

Make your own playlists from anything in Music:

- **Menu** on a track, album, artist, genre or year → **Add … to a playlist**, or **Add the whole list to a playlist** (e.g. all your search results).
- Choose **New playlist…** and type a name, or pick an existing playlist. Tracks already in it aren't added twice.
- **Playlists** in the left panel lists them. OK opens one; Green / Yellow plays or shuffles it.
- **Menu inside a playlist:** Remove from this playlist, Move up, Move down, Add to another playlist.
- **Menu on a playlist:** Play, Shuffle, Rename, Delete this playlist (asks first; the music itself is never touched).

If you rename or move an album folder, playlists that include it will no longer find those tracks.

Deleting a track

Menu on a track → **Delete this track**, then **Yes, delete it**. The file is moved into a **Deleted** folder inside your music folder (keeping its folder path), not removed for good. It disappears from the lists and your playlists straight away. Empty the Deleted folder yourself, from a computer, when you're sure. To restore a track, move it back.

Tracker music (MOD, S3M, XM, IT ...)

Music also plays tracker files from Amiga, PC and Atari demo and game music. The box can't play them directly, so Music converts each tune to sound just before it plays, using the image's own libmodplug library (no extra install). The bottom line shows **Preparing: (tune) ...** for the moment it takes; the next tune is prepared while the current one plays. The last 20 converted tunes are kept, so replays start straight away.

For the easiest setup, make a folder called **Tracker Files** at the top of your music folder, with a folder per format:

```
Music / Tracker Files / MOD / ...
Music / Tracker Files / S3M / ...
Music / Tracker Files / XM / ...
```

- Each folder inside Tracker Files appears as an album, under the artist **Tracker Files** and the genre **Tracker**.
- A **Tracker Files** entry appears in the left panel, which goes straight there.
- Inside Tracker Files, files are recognised by what's in them, so files with no extension, or Amiga-style names like `mod.axelf` (shown as axelf, type MOD), work as they are.
- The tune's own title, stored inside the file, is used where it has one.

What plays

Plays	Doesn't play
MP3, FLAC, OGG, M4A, M4R, MP4 (audio), WAV, AAC, WMA, Opus and the other usual types	CMF, SID, SNDH, SAP, VGM (chip music formats need players the box doesn't have)
Tracker: MOD, S3M, XM, IT, MTM, AMF, STM, 669, ULT, FAR, OKT, PTM, MDL, DMF, DBM, MED	ProTrekkr (.ptk)
	Anything still packed in a ZIP, RAR or LHA archive

Files Music can't play are simply left out of the lists.

Settings

Open **Settings** from the icon rail. The sections are listed on the left; the chosen section opens on the right. **<** (Left) from the sections list goes back to the icon rail.

Section	What's in it
Status & Logs	What the plugin is doing, the EPG refresh summary, and its log files to read on the TV
Playlists	Your providers: switch on or off, choose categories, refresh, Update EPG, EPG Offset, Test Connection
EPG	Nightly refresh time, refresh all, picons, filling guide gaps
Appearance	The colour theme
Playback	Live TV player, auto-restart of frozen channels, opening at start-up, music folder
Parental Controls	Hide categories behind a PIN
Other	Folders (recordings, playlists, picons, data), and the recording and catch-up start and end margins
About	The version you're running

Themes

Settings → Appearance offers two themes:

- **Dark** (the default): a dark, modern look.
- **Sky Blue:** the colours of the original E2iPTV.

A new theme takes effect after a GUI restart, which the plugin offers to do for you.

Playback

Setting	What it does
Live TV player	Standard (GStreamer), Box TV decoder, ServiceApp exteplayer3 or ServiceApp gstplayer; try another if sound drifts or a channel misbehaves

Setting	What it does
Auto-restart frozen channels	Restart a live channel by itself if its picture freezes
Open E2iPTV at start-up	Open the plugin automatically when the box starts
Music folder	Where your music is

Logs on the TV

In **Settings → Status & Logs**, open a log to read it on screen. **Red** clears it; **Green** reads it again.

Troubleshooting

Common problems

Problem	What to try
The guide and lists are gone after every restart	There's no disk or USB stick; fit one, or choose a folder in Settings → Other → Data Folder
A provider shows no channels	Settings → Playlists → (provider) → Test Connection; check the line in playlists.txt and that it doesn't start with `#`
A Stalker provider keeps dropping	Only one box or app can use a MAC address at a time; close it elsewhere
The guide is a few hours out	Settings → Playlists → (provider) → EPG Offset
The guide is empty for some channels	Settings → EPG → Fill Guide Gaps, from another provider
A channel freezes, stutters or the sound drifts	Try another Live TV player in Settings → Playback; keep Auto-restart frozen channels on
The box locks up when starting a channel	Try Standard (GStreamer); on HiSilicon boxes (e.g. SF8008) avoid Box TV decoder
A 4K film has sound but no picture	The film is H.264 4K, which some boxes can't decode; HEVC 4K films play

Problem	What to try
New music doesn't appear	Open Music and wait a minute for the check, or use Browse, sort and rescan → Rescan music now
A music folder doesn't appear in Artist / Genre views	It isn't in the Artist / Genre / Album layout; it still shows in Music folder (Folders view)
The box crashes in its own menus with a third-party skin	Some skins made for OpenATV aren't compatible with OpenPLi; use the image's own skin

Logs

Most logs can be read on the TV in **Settings → Status & Logs**. The files are:

Log	What's in it
`/tmp/e2iptv_live.log`	Live TV, including freezes and restarts
`/tmp/e2iptv_music.log`	Music, the music index, searches and tracker conversion
`/tmp/e2iptv_slow.log`	Anything on screen that took too long
`/tmp/e2iptv_catchup.log`	Catch-up requests
`/tmp/e2iptv_xtream.log`	Failed Xtream requests
`E2iPTVLab_Data/epg/nightly_refresh.log`	The nightly guide refresh

For full debug logging, create an empty file `/etc/enigma2/E2iPTVLab/debug` and restart the GUI. Delete it again afterwards.

If the box freezes completely, this records everything the GUI does into a file on the disk. Run it by telnet, make the problem happen, then power-cycle the box:

```
init 4; sleep 3; enigma2 > /media/hdd/e2_debug.log 2>&1
```

The box's own crash logs are in `/home/root/logs/` (on most images).

Sharing logs safely

Box logs can contain your provider's full stream address, **including your username and password**. Before sharing any log or crash file, blank the addresses out:

```
sed -E 's#(https?(:|%3a)//)[^ "]*#\1***#gI' crash.log > crash_clean.log
```

Then share `crash_clean.log`. **Never share `playlists.txt`**, which holds all your logins.

Reporting a problem

Please include:

1. Your box and image, with its version (e.g. Vu+ Solo4K, OpenATV 8.0.1).
2. The plugin version from **Settings → About**.
3. What you did, step by step, and what happened.
4. The cleaned-up log or crash file, if there is one.