

Standard Setup

Find signal

Connect probe to signal of interest

Connect probe clip ground

Turn off trigger

[Mode/Coupling] → Mode → Auto

Horizontal (scale) → x units/div {10ms}

Horizontal (position) → 2nd left reticle

Ch1 (scale) → y units/div {2V}

Ch1 (position) → 2nd low reticle

Set trigger level

(Trigger level) → 1/2 max signal level

Set trigger attributes

[Trigger] → Trigger Type → Edge

[Trigger] → Source → 1

[Trigger] → Slope → 1 (rising)

Turn on trigger (optional)

[Mode/Coupling] → Mode → Normal

Note:
Underline → soft key
[Bracket] → hard key
{Brace} → typical value
(Parenthesis) → knob

Save to USB

Insert USB stick

[Save] → Save → Format → 24-bit Bit... (*.bmp)

[Save] → Save → Press to Save

Measure

[Meas] → Clear Meas → Clear All → [Back]

[Meas] → Type → (Select) → Add

FFT

[Math] → Function: f() → Operator: FFT

Display Math → check

Span → (Select), Center → (Select)

Average waveforms

[Acquire] → AcqMode → Averaging

[Acquire] → #Avg: (Select)

Trouble shooting tips

Reconnect probe's BNC connection

Ch1 active [Select]

[Run/Stop] should be green

Horizontal position in middle

Set trigger to Mode → Auto

Standard Setup

Find signal

Connect probe to signal of interest

Connect probe clip ground

Turn off trigger

[Mode/Coupling] → Mode → Auto

Horizontal (scale) → x units/div {10ms}

Horizontal (position) → 2nd left reticle

Ch1 (scale) → y units/div {2V}

Ch1 (position) → 2nd low reticle

Set trigger level

(Trigger level) → 1/2 max signal level

Set trigger attributes

[Trigger] → Trigger Type → Edge

[Trigger] → Source → 1

[Trigger] → Slope → 1 (rising)

Turn on trigger (optional)

[Mode/Coupling] → Mode → Normal

Note:
Underline → soft key
[Bracket] → hard key
{Brace} → typical value
(Parenthesis) → knob

Save to USB

Insert USB stick

[Save] → Save → Format → 24-bit Bit... (*.bmp)

[Save] → Save → Press to Save

Measure

[Meas] → Clear Meas → Clear All → [Back]

[Meas] → Type → (Select) → Add

FFT

[Math] → Function: f() → Operator: FFT

Display Math → check

Span → (Select), Center → (Select)

Average waveforms

[Acquire] → AcqMode → Averaging

[Acquire] → #Avg: (Select)

Trouble shooting tips

Reconnect probe's BNC connection

Ch1 active [Select]

[Run/Stop] should be green

Horizontal position in middle

Set trigger to Mode → Auto

Standard Setup

Find signal

Connect probe to signal of interest

Connect probe clip ground

Turn off trigger

[Mode/Coupling] → Mode → Auto

Horizontal (scale) → x units/div {10ms}

Horizontal (position) → 2nd left reticle

Ch1 (scale) → y units/div {2V}

Ch1 (position) → 2nd low reticle

Set trigger level

(Trigger level) → 1/2 max signal level

Set trigger attributes

[Trigger] → Trigger Type → Edge

[Trigger] → Source → 1

[Trigger] → Slope → 1 (rising)

Turn on trigger (optional)

[Mode/Coupling] → Mode → Normal

Note:
Underline → soft key
[Bracket] → hard key
{Brace} → typical value
(Parenthesis) → knob

Save to USB

Insert USB stick

[Save] → Save → Format → 24-bit Bit... (*.bmp)

[Save] → Save → Press to Save

Measure

[Meas] → Clear Meas → Clear All → [Back]

[Meas] → Type → (Select) → Add

FFT

[Math] → Function: f() → Operator: FFT

Display Math → check

Span → (Select), Center → (Select)

Average waveforms

[Acquire] → AcqMode → Averaging

[Acquire] → #Avg: (Select)

Trouble shooting tips

Reconnect probe's BNC connection

Ch1 active [Select]

[Run/Stop] should be green

Horizontal position in middle

Set trigger to Mode → Auto

Standard Setup

Find signal

Connect probe to signal of interest

Connect probe clip ground

Turn off trigger

[Mode/Coupling] → Mode → Auto

Horizontal (scale) → x units/div {10ms}

Horizontal (position) → 2nd left reticle

Ch1 (scale) → y units/div {2V}

Ch1 (position) → 2nd low reticle

Set trigger level

(Trigger level) → 1/2 max signal level

Set trigger attributes

[Trigger] → Trigger Type → Edge

[Trigger] → Source → 1

[Trigger] → Slope → 1 (rising)

Turn on trigger (optional)

[Mode/Coupling] → Mode → Normal

Note:
Underline → soft key
[Bracket] → hard key
{Brace} → typical value
(Parenthesis) → knob

Save to USB

Insert USB stick

[Save] → Save → Format → 24-bit Bit... (*.bmp)

[Save] → Save → Press to Save

Measure

[Meas] → Clear Meas → Clear All → [Back]

[Meas] → Type → (Select) → Add

FFT

[Math] → Function: f() → Operator: FFT

Display Math → check

Span → (Select), Center → (Select)

Average waveforms

[Acquire] → AcqMode → Averaging

[Acquire] → #Avg: (Select)

Trouble shooting tips

Reconnect probe's BNC connection

Ch1 active [Select]

[Run/Stop] should be green

Horizontal position in middle

Set trigger to Mode → Auto

