The Karhunen-Loeve Stochastic Processes Representation

Following [1],a rigorous exposition of the basic concepts of the theory of representation for random processes can be formulated (Parzen, 1959). This theory is quite rich and mature mathematical subject. The development of the theory parallels that of the modern theory of random processes, and has had its origin in the need for more sophisticated models in applied statistics. Most of the related results have been derived for the class of second order processes. Perhaps the most important result is the spectral representation of random processes (Gel'fand and Vilenkin, 1964), which, in its most general form, can be stated as

$$w\,(x,\theta) = \int g(x)\,d\,\mu(\theta) \tag{1}$$

where $w\,(x,\theta)$ is a stochastic process whose covariance function $C_{ww}(x_1,x_2)$ admits of the decomposition

$$C_{ww}(x_1,x_2) = \int g(x_1)\,g(x_2)\,d\,\mu_1(\theta)\,d\,\mu_2(\theta) \tag{2}$$

In equation (2.1), $g(x)$ is a deterministic function. Further, $d\,\mu(\theta)$ is an orthogonal set function, also termed orthogonal stochastic measure, defined on the σ-field Ψ of random events. An important specialization of the spectral decomposition occurs if the process $w\,(x,\theta)$ is wide stationary. In this case, equation (2.1) can be shown to reduce to the Wiener-Khintchine relation (Yaglom, 1962) and the following equations hold

$$w\,(x,\theta) = \int_{-\infty}^{\infty} e^{i\omega^T x}\,d\,\mu(\omega,\theta) \tag{3}$$

and

$$C_{ww}(x_1,x_2) = \int_{-\infty}^{\infty} e^{i(\omega^1 x_1 - \omega^2 x_2)^T} S(\omega)\,d\,\omega \tag{4}$$

Here, the symbol T denotes vector transposition, $S(\omega)$ is the usual spectral density of the stationary process, and ω is the wave number vector.

The preceding representations have had a strong impact on the subsequent development of the theory of random processes. However, their applications have been restricted to randomly excited deterministic systems. This is largely attributed to the fact that all of these representations involve differentials of random functions, and are therefore set in an infinite dimensional space, not readily amenable to computational algorithms. An alternative formulation of the spectral representation, and one which is extensively used in the sequel, is the Karhunen-Loeve expansion whereby a random process $w\,(x,\theta)$ can be expanded in terms of a denumerable set of orthogonal random variables in the form

$$w\,(x,\theta) = \sum_{i=1}^{\infty} \mu_i(\theta)\,g_i(x) \tag{5}$$

where $\{\mu_i(\theta)\}$ is a set of orthogonal random variables and $\{g_i(x)\}$ are deterministic functions, which can be related to the covariance kernel of $w(x,\theta)$. Note that since equation (2.5) constitutes a representation of the random process in terms of a denumerable set of random variables, it may be regarded as an abstract discretization of the random process. It is important to note that this equation can be viewed as a representation of the process $w(x,\theta)$ as a curve in the Hilbert space spanned by the set $\{g_i(x)\}$. The random process $w(x,\theta)$ is expressed as a direct sum of orthogonal projections in this Hilbert space whereby the magnitudes of the projections on successive basis vectors are proportional to the corresponding eigenvalues of the covariance function associated with the process $w(x,\theta)$. Collectively, the representations discussed up to [1, 2.2] can be thought of as linear operators or filters acting on processes with independent increments (Doob, 1953). Given the crucial role that the Karhunen-Loeve expansion has in relation to the methods discussed in [1, 2.3] the essential features shall be reiterated.

1 Karhunen-Loeve Expansion

1.1 Derivation

One of the major difficulties associated with the numerical incorporation of random processes in finite element analyses, is the necessity to deal with abstract measures spaces that have limited physical intuitive support. The major conceptual difficulty from the viewpoint of the class of problems considered herein, involves the treatment of functions defined on these abstract spaces, namely random variables defined on the σ-field of random events. The most widely used method, the Monte Carlo simulation, consists of sampling these functions at randomly chosen elements of this σ-field, in a random, collocation-like, scheme. Obviously, a quite large number of points needs to be sampled if a good approximation is to be achieved. A theoretically more sound and more appealing approach would be to expand these functions in a Fourier-type series as

$$w(x,\theta) = \sum_{n=0}^{\infty} \sqrt{\lambda_n}\, \xi_n(\theta)\, f_n(x) \tag{6}$$

where $\{\xi_n(\theta)\}$ is a set of random variables to be determined, λ_n is some constant, and $\{f_n(x)\}$ is an orthonormal set of deterministic functions. This is exactly what the Karhunen-Loeve expansion achieves. The expansion was derived independently by a number of investigators (Karhunen, 1947; Loeve, 1948; Kac and Siegert, 1947).

Let $w(x,\theta)$ be a random process, function of the position vector x defined over the domain D, with θ belonging to the space of random events Ω. Let $\bar{w}(x)$ denote the expected value of $w(x,\theta)$ over all possible realizations of the process, and $C(x_1,x_2)$ denote its covariance function. By definition of the covariance function, it is bounded, symmetric and positive definite. Thus, it has the spectral decomposition (Courant and Hilbert, 1953)

$$C(x_1,x_2) = \sum_{n=0}^{\infty} \lambda_n\, f_n(x_1)\, f_n(x_2) \tag{7}$$

where λ_n and $f_n(x)$ are the eigenvalue and the eigenfunction of the covariance kernel. And, specifically, that they are the solution to the integral equation

$$\int_D C(x_1, x_2)\, f_n(x_1)\, d\, x_1 = \lambda_n\, f_n(x_2) \tag{8}$$

Due to the symmetry and the positive definiteness of the covariance kernel (Loeve, 1977), its eigenfunctions are orthogonal and form a complete set. They can be normalized according to the following criterion

$$\int_D f_n(x)\, f_m(x)\, d\, x = \delta_{nm} \tag{9}$$

where δ_{nm} is the Kronecker delta. Clearly, $w(x, \theta)$ can be written as

$$w\,(x, \theta) = \bar{w}(x) + \alpha(x, \theta) \tag{10}$$

where $\alpha(x, \theta)$ is a process with zero mean and covariance function $C(x_1, x_2)$

The process $\alpha(x, \theta)$ can be expanded in terms of the eigenfunctions $f_n(x)$ as

$$\alpha(x, \theta) = \sum_{n=0}^{\infty} \xi_n(\theta) \sqrt{\lambda_n}\, f_n(x) \tag{11}$$

Second order properties of the random variables ξ_n can be determined by multiplying both sides of equation (2.11) by $\alpha(x_2, \theta)$ and taking the expectation on both sides. Specifically, it is found that

$$C(x_1, x_2) = \langle \alpha(x_1, \theta)\, \alpha(x_2, \theta) \rangle = \sum_{n=0}^{\infty} \sum_{m=0}^{\infty} \langle \xi_n(\theta)\, \xi_m(\theta) \rangle \sqrt{\lambda_n\, \lambda_m}\, f_n(x_1)\, f_m(x_2) \tag{12}$$

Then, multiplying both sides of equation (2.12) by $f_k(x_2)$, integrating over the domain D, and making use of the orthogonality of the eigenfunctions, yields

$$\begin{aligned} \int_D C(x_1, x_2)\, f_k(x_2)\, d\, x_2 &= \lambda_k\, f_k(x_1) \\ &= \sum_{n=0}^{\infty} \langle \xi_n(\theta)\, \xi_k(\theta) \rangle \sqrt{\lambda_n\, \lambda_k}\, f_n(x_1) \end{aligned} \tag{13}$$

Multiplying once more by $f_l(x_1)$ and integrating over D gives

$$\int_D \int_D f_l(x_1)\, f_k(x_1)\, d\, x_1 = \sum_{n=0}^{\infty} E\, \langle \xi_n(\theta)\, \xi_k(\theta) \rangle \sqrt{\lambda_n\, \lambda_k}\, \delta_{nl} \tag{14}$$

Then, using equation (2.9) leads to

$$\lambda_k\, \delta_{kl} = \sqrt{\lambda_k\, \lambda_l}\, \langle \xi_k(\theta)\, \xi_l(\theta) \rangle \tag{15}$$

Equation (2.15) can be rearranged to give

$$\langle \xi_k(\theta)\, \xi_l(\theta) \rangle = \delta_{kl} \tag{16}$$

Thus, the random process $w\,(x,\theta)$ can be written as

$$w\,(x,\theta) = \bar{w}(x) + \sum_{n=0}^{\infty} \xi_n(\theta) \sqrt{\lambda_n}\, f_n(x) \tag{17}$$

where

$$\langle \xi_n(\theta) \rangle = 0 \tag{18}$$

$$\langle \xi_n(\theta)\, \xi_m(\theta) \rangle = \delta_{nm} \tag{19}$$

and λ_n, $f_n(x)$ are solution to equation (2.8). Truncating the series in equation (2.17) at the Mth term, gives

$$w\,(x,\theta) = \bar{w}(x) + \sum_{n=0}^{M} \xi_n(\theta) \sqrt{\lambda_n}\, f_n(x) \tag{20}$$

An explicit expression for $\xi_n(\theta)$ can be obtained by multiplying equation (2.11) by $f_n(x)$ and integrating over the domain D. That is,

$$\xi_n(\theta) = \frac{\int_D \alpha(x,\theta)\, f_n(x)\, d\,x}{\sqrt{\lambda_n}} \tag{21}$$

1.1.1 Reproducing Kernel Hilbert Spaces (RKHS)

The essential thing that the Reproducing Kernel Hilbert Space (RKHS) (Aronszajn, 1950; Parzen, 1959), either of equations (2.11) or (2.20), is an expression for the congruence that maps the Hilbert space spanned by the functions $f_n(x)$ to the Hilbert space spanned by the random process, or equivalently, the space spanned by the set of random variables $\{\xi_n(\theta)\}$.

It is this congruence along with the covariance function of the process that determines uniquely the random process $w\,(x,\theta)$. Observe the similarity of equations (2.11) and (2.20) with equations (2.7) and (2.8), respectively. Indeed, it can be shown (Parzen, 1959) that if a function can be represented in terms of linear operations on the family $\{C(\,\cdot, x_2)\}$, then f belongs to the RKHS corresponding to the kernel $C(x_1, x_2)$, and the congruence between the two Hilbert spaces means of the same linear operations used to represent f in terms of $\{C(\,\cdot, x_2)\}$, $x_2 \in D$.

Another point of practical importance is that the expansion given by equation (2.19) can be used in a numerical simulation scheme to obtain numerical realizations of the random process. It is optimal in the Fourier sense, as it minimizes the mean square error resulting from truncation after a finite number of terms.

It is well known from functional analysis that the steeper a bilinear form decays to zero as a function of one of its arguments, the more terms are needed in its spectral representation in order to reach a preset accuracy. Noting that the Fourier transform operator is a spectral representation, it may be concluded that the faster the autocorrelation function tends to zero, the broader is the corresponding spectral density, and the greater the number of requisite terms to represent the underlying random process by the Karhunen-Loeve expansion.

It may seem that any complete set of functions can be used in lieu of the eigenfunctions of the covariance kernel in the expansion (2.11). However, the Karhunen-Loeve expansion as described above, has some desirable properties that make it the the optimal choice.

1.2 Properties

1.2.1 Error Minimizing Property

Lemma 1

Error Minimizing Property

The generalized coordinate system defined by the eigenfunctions of the covariance kernel is optimal in the sense that the mean-square error resulting from a finite representation of the process $w(x,\theta)$ is minimized.

Proof. Given a complete orthonormal set of functions $h_n(x)$, the process $w(x,\theta)$ can be approximated in a convergent series of the form

$$w(x,\theta) = \sum_{n=0}^{\infty} \lambda_n \, \xi_n(\theta) \, h_n(x). \tag{22}$$

Truncating equation (2.21) at the Mth term results in an error ϵ_M equal to

$$\epsilon_M = \sum_{n=M+1}^{\infty} \lambda_n \, \xi_n(\theta) \, h_n(x). \tag{23}$$

Multiplying equation (2.21) by $h_m(x)$ and integrating throughout gives

$$\xi_m(\theta) = \frac{\int_D w(x,\theta) \, h_m(x) \, d\,x}{\sqrt{\lambda_m}} \tag{24}$$

where use is made of the orthogonality property of the set $h_n(x)$. Substituting equation (2.23) for $\xi_m(\theta)$ back into equation (2.22), the mean-square error ϵ_M^2 can be written as

$$\epsilon_M^2 = \left[\sum_{m=M+1}^{\infty} \sum_{n=M+1}^{\infty} \int_D \int_D \langle \xi_m(\theta) \, \xi_n(\theta) \rangle \, h_m(x_1) \, h_n(x_2) \, d\,x_1 \, d\,x_2 \right]^2 \tag{25}$$

Integrating equation (2.24) over D and using the orthonormality of the set $\{h_i(x)\}$ yields

$$\int_D \epsilon_M^2 \, d\,x = \sum_{m=M+1}^{\infty} \int_D \int_D R_{ww}(x_1, x_2)\, h_m(x_1)\, h_m(x_2)\, d\,x_1\, d\,x_2 \tag{26}$$

The problem, then, is to minimize $\int_D \epsilon_M^2$ subject to the orthonormality of the functions $h_n(x)$. In other words, the solution minimizes the functional given by the equation

$$\mathcal{F}[h(x)] = \sum_{m=M+1}^{\infty} \int_D \int_D R_{ww}(x_1, x_2)\, h_m(x_1)\, h_m(x_2)\, d\,x_1\, d\,x_2 - \lambda_m \left[\int_D h_m(x)\, h_m(x)\, d\,x - 1 \right] \tag{27}$$

Differentiating equation (2.26) with respect to $h_i(x)$ and setting the result equal to zero, gives

$$\frac{\partial\, \mathcal{F}[h(x)]}{\partial\, h_i(x)} = \int_D \int_D R_{ww}(x_1, x_2)\, h_i(x_1)\, d\,x_1 - \lambda_i\, h_i(x_2)\, d\,x_2 = 0 \tag{28}$$

which is satisfied when

$$\int_D R_{ww}(x_1, x_2)\, h_i(x_2)\, d\,x_2 = \lambda_i\, h_i(x_1) \tag{29}$$ □

1.2.2 Uniqueness of the Expansion

Lemma 2

Uniqueness of the Expansion

The random variables appearing in an expansion of the kind given by equation (2.10) are orthonormal if and only if the orthonormal functions $\{f_n(x)\}$ and the constants $\{\lambda_n\}$ are respectively the eigenfunctions and the eigenvalues of the covariance kernel as given by equation (2.8).

Proof. The "if" part is an immediate consequence of equation (2.11). To show the "only if" part, equation (2.12) can be used with

$$\langle \xi_n(\theta)\, \xi_m(\theta) \rangle = \delta_{nm} \tag{30}$$

to obtain

$$C(x_1, x_2) = \sum_{n=0}^{\infty} \lambda_n\, f_n(x_1)\, f_n(x_2) \tag{31}$$

Multiplying both sides by $f_m(x_2)$ and integrating over D gives

$$\int_D C(x_1, x_2)\, f_m(x_2)\, d\,x_2 = \sum_{n=0}^{\infty} \lambda_n\, f_n(x_1)\, \delta_{nm} = \lambda_m\, f_m(x_1) \tag{32}$$ □

1.2.3 Expansion of Gaussian Processes

Let $w(x,\theta)$ be a Gaussian process with covariance function $C(x_1,x_2)$. Then $w(x,\theta)$ has the Karhunen-Loeve decomposition given by equation (2.17) with the random variables $\xi_i(\theta)$ forming a Gaussian vector. That is, any subset of $\{\xi_i(\theta)\}$ is jointly Gaussian. Since these random variables are uncorrelated, their Gaussian property implies their independence. Some important consequences derive from this property. Specifically,

$$\langle \xi_1(\theta), \ldots, \xi_{2n+1}(\theta) \rangle = 0 \tag{33}$$

and

$$\langle \xi_1(\theta), \ldots, \xi_{2n}(\theta) \rangle = \sum \prod \langle \xi_i(\theta)\, \xi_j(\theta) \rangle \tag{34}$$

where the summation extends over all the partitions of the set $\{\xi_i(\theta)\}_{i=1}^{2n}$ into sets of two elements, and the product is over all such sets in a given partition. Furthermore, it can be shown (Loeve, 1977) that for Gaussian processes, the Karhunen-Loeve expansion is almost surely convergent.

1.2.4 Minimum Representation Entropy

Other Properties

The minimum representation of entropy property is worth mentioning even though it only references and no details were given in [1].

4 Solution of the Integral Equation

The usefulness of the Karhunen-Loeve expansion hinges on the ability to solve the integral equation of the form

$$\int_D C(x_1, x_2)\, f(x_2)\, d\, x_2 = \lambda\, f(x_1) \tag{35}$$

where $C(x_1, x_2)$ is an autocovariance function. Equation (35) is a homogeneous Fredholm integral equation of the second kind. The theory underlying this kind of equations has been extensively investigated and is well documented in a number of monographs (Mikhlin, 1957). Being an autocovariance function, the kernel $C(x_1, x_2)$ is bounded, symmetric, and positive definite. This fact simplifies the ensuing analysis considerably in

4.1 Irrational Spectra

There is no general method for the solution of the integral equation (35) corresponding to irrational spectra. Several of these equations have been investigated and explicit solutions have been obtained for certain covariance kernels.

4.1.1 The Triangular Kernel

The method described in the previous section may be applied successfully to a number of these kernels as will be demonstrated for the case of the triangular kernel given by the equation

$$C(x_1, x_2) = 1 - d\,|x_1 - x_2| \forall |x_1 - x_2| \in [0, d^{-1}] \tag{36}$$

Here, d is a parameter which can be used to adjust the distance of null correlation between $w\,(x_1, \theta)$ and $w\,(x_2, \theta)$. Consider realizations of this process on the interval $[0, a]$. The eigenfunctions and eigenvalues of $C(x_1, x_2)$ are obtained as the solution to the integral equation

$$\int_0^a (1 - d\,|x_1 - x_2|)\, f_n(x_2)\, d\,x_2 = \lambda_n\, f_n(x_1) \tag{37}$$

Differentiating equation (37) twice with respect to x_2, the following equivalent differential equation is obtained

$$f_n''(x) + \omega_n^2\, f_n(x) = 0 \forall \quad 0 \le x \le a. \tag{38}$$

The associated boundary conditions are given by the equations

$$f_n'(a) = -f_n'(0) \tag{39}$$

and

$$f_n'(0) = \frac{f_n(0) + f_n(a)}{2 - \frac{a}{d}} \tag{40}$$

and

$$\omega_n = \sqrt{\frac{2\,d}{\lambda_n}} \tag{41}$$

The solution of equation (2.58) subjected to the boundary conditions described by equations (2.59) and (2.60) is

$$f_n(x) = \begin{cases} \sqrt{\frac{a}{2}}\, \dfrac{\cos(\omega_n\, x)}{\sqrt{\frac{a}{2} + \frac{\sin(2\,\omega_n\, a)}{4\,\omega_n}}} & n \text{ even} \\ \sqrt{\frac{a}{2}}\, \dfrac{\cos(\omega_n\, x) + \tan\left(\frac{\omega_n\, a}{2}\right) \tan\left(\frac{\omega_n\, a}{2}\right) \sin(\omega_n\, x)}{\sqrt{\frac{a}{2} + \frac{\tan^2\left(\frac{\omega_n\, a}{2}\right) - 1}{4\,\omega_n} \sin(2\,\omega_n\, a) + \frac{\sin^2(\omega_n\, a)}{\omega_n} \tan\left(\frac{\omega_n\, a}{2}\right)}} & n \text{ odd} \end{cases} \tag{42}$$

where ω_n is defined implicitly as the solution to $\tan\left(\frac{\omega_n\, a}{2}\right) = \omega_n\left(\frac{2}{a} - a\right)$ when n is even and explicitly when n is odd

$$\omega_n = \begin{cases} \left\{\omega_n : \tan\left(\frac{\omega_n\, a}{2}\right) = \omega_n\left(\frac{2}{a} - a\right)\right\} & n \text{ even} \\ \frac{\pi\, n}{a} & n \text{ odd} \end{cases} \tag{43}$$

Another kernel that may be treated by the same method is the kernel of the Wiener process. It is given by the equation

$$C(x_1, x_2) = \min(x_1, x_2) \forall (x_1, x_2) \in [0, T] \times [0, T] \tag{44}$$

The resulting normalized eigenfunctions and eigenvalues are

$$f_n(x_1) = \sqrt{2} \sin\left(\frac{n \pi x_1}{T}\right) \tag{45}$$

Bibliography

[1] Roger G. Ghanem and Pol D. Spanos. *Stochastic finite elements: a spectral approach*. Springer-Verlag, Berlin, Heidelberg, 1991.