

AnyCam 3.7.4 Audit Report

Release audit - 07 October 2026 - Microseven live view, stuck cameras, no hardware HEVC, go2rtc API password - tag 3.7.4

Scope confirmed by CrystalHeeler on 2026-10-06 and 2026-10-07: version 3.7.4 with every open B item except B29 and B33: B47 (design A), B46, B6 and B32 as one feature, B37 option A. Added during the build, with the reason below: go2rtc's API password for local programs. Not field-tested; built, not pushed.

Changes

#	Cause (from the field tests)	Change
B47	Chrome's media log for the Microseven: "coded size: [4,0]" (H.265) and "Unrecognized video codec profile" (H.264): go2rtc built an invalid MSE init segment; ffmpeg read the same stream at 3840x2160 (go2rtc issues 2361, 2529).	go2rtc's ffmpeg module; the Hipcam/Microseven brand entry sets live_ffmpeg_copy: source ffmpeg:<rtsp>#video=copy#audio=copy. Other cameras unchanged.
API	Checking design A: go2rtc skips its API password for 127.0.0.1, and AnyCam uses the host network, so any program on the Pi could add an ffmpeg source (running ffmpeg with its own arguments in this full_access add-on) or read every camera password from /api/streams.	api.username/password, new at each start, with local_auth: true; AnyCam's sessions send it. Pinned in the release gate.
B6, B32	The stuck Microseven accepted connections and answered nothing; each live and classic try failed in turn (about 50 s) and kept connecting.	Stuck after the classic view gives up on RTSP, or two live failures with a dropped connection in 2 min: no RTSP, HTTP snapshots, a "Power-cycle camera" badge, a check every 5 min inside the cooldown.
B37	Green on every camera and size on both systems.	hevc_drm is never picked automatically; the picture test still runs it by hand.
B46	The Microseven: a WebRTC retry with no stream at all.	Retry only when the session reached MSE.

Tests run

Suite	Result	Scope
Release gate	PASS	Eight gates; the go2rtc contract now pins the module list with ffmpeg and the API password.
Python integration	PASS	638 of 638; section AM new (21 checks); two go2rtc config checks and AJ4 updated.
JavaScript behaviour	PASS	191 of 191; B46 new.
Not run	NOTED	No field test: the ffmpeg copy has not met the Microseven; the stuck state and its check have not met a stuck camera; go2rtc's local_auth ran only against a stand-in server.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*. Rows this change touches; the rest carry from the 3.7.0 audit.

Standard	Check applied	Result	Note
6.1 Security	Least privilege	PASS	ffmpeg loaded only with the API password required from every caller; the browser can still name only streams AnyCam registered.
6.1 Security	Secrets	PASS	Camera passwords stay percent-encoded inside the ffmpeg source; logs strip them.
1.3 Async	Blocking calls	PASS	The stuck check runs the socket validator in the thread pool.
1.12 Logging	Truth	PASS	"hevc_drm: not used" with the reason; stuck and recovered lines.
1.18 Testing	New tests	PASS	21 server checks, 1 page check.
Rule 9 (privacy)	New text	PASS	Made-up addresses; no device serials.

Known issues

- **B48:** go2rtc's RTSP server does not ask local programs for its password; other programs on the Pi can read camera video. Decision open.
- **B6:** the day-long check with no new lock-out waits for the camera.
- **B33:** one Amcrest camera can get two cards; under investigation.

Acceptance (field test)

- Update in place (no uninstall): the Microseven plays live in Chrome and LibreWolf.
- The start-up log says "hevc_drm: not used".
- A Lorex channel in LibreWolf's classic view: no green start.
- A stuck Microseven: "Power-cycle camera" badge and still pictures; live view back within 5 minutes after a power cycle.

Files changed

File	Change
anycam_go2rtc.py	ffmpeg module, copy source, API password, stuck state.
camera_db.py	live_ffmpeg_copy on the Hipcam/Microseven entry.

File	Change
anycam_snap.py	HTTP snapshots while stuck; marks stuck.
anycam_focus.py	No live view while stuck.
camera_discovery.py	HW_NOT_AUTOMATIC; rtsp_stuck in the camera list; 3.7.4.
page_script.py	B46; the "Power-cycle camera" badge.
verify_release.py	The go2rtc security contract.
tests/	Section AM; page check; updated config checks.
CHANGELOG.md, config.yaml, docs	3.7.4; build plan.