

AnyCam 2.6.4 Audit Report

Release audit - 02 October 2026 - live view always on - tag 2.6.4

2.6.4 makes live view the default and only behaviour for Enhanced View and removes the Live View option. It is a small change: five files, 75 lines added and 47 removed, most of it changelog. It completes build plan item A3.

What 2.6.3 confirmed working

Field evidence from CrystalHeeler on both Raspberry Pi 4 / HAOS systems.

Component	Evidence
Live H.265, Lorex DVR	2026-09-28: 3840x2160 channels played smoothly in Chrome on the test system B.
Live H.265, Hikvision	2026-09-29: 2.6.3 installed on the test system A; the 2560x1440 stream plays live and looks good.
Home Assistant ingress	2026-09-29: a live feed stayed up for more than 10 minutes. This was the largest unknown in the 2.6.3 audit: ingress cut multipart streams after 10 to 24 frames in 1.6.0.
Freezes	2026-09-29: none in live view.
Root cause	2026-09-29: in Chrome, on the same camera, Classic bogs down while Live is smooth. The Pi's decode-and-JPEG pipeline was the cause of the poor feeds, not the browser.
Fallback	2026-09-28: Firefox fell back to classic on H.265 within 1 s, as designed. go2rtc's table lists desktop Firefox as H.264-only.

Change

Live view is always on

go2rtc now starts with the add-on on every install. The option, its environment variable and its checks are removed from the server and the page. Enhanced View always tries live view first.

Nothing is lost by removing the option. Its off setting sent every camera to the classic view. Each camera still falls back to the classic view on its own when go2rtc is not running, the browser cannot play the codec, or no video arrives within 12 s. The Classic button still switches views for a session.

The trap this release had to avoid

run.sh passes each setting to the program with bashio::config. For a setting that does not exist, bashio returns the text null (verified in bashio's lib/config.sh). Removing the option from config.yaml alone would have left run.sh exporting null, which the old code read as off: live view would have been silently disabled by the release meant to enable it. config.yaml, run.sh and the translation file change together, and a check confirmed every setting run.sh reads exists in config.yaml and the other way round.

Upgrading a system that had the option saved

Home Assistant keeps saved options until they are next saved. Supervisor source (supervisor/apps/options.py) logs a saved setting that is missing from the schema as a warning and drops it, then starts the add-on:

Option 'go2rtc_live_view' does not exist in the schema for AnyCam

Harmless, and documented in the changelog so it is not mistaken for a fault.

Tests run

Suite	Result	Scope
Release gate	PASS	All five gates; 24 function contracts; go2rtc API host check.
Python integration	PASS	81 of 81, up from 79: three new checks confirm the option is gone, no setting is present, and live view is still offered. One old check that turned the option off was removed with the option.
JavaScript behaviour	PASS	46 of 46, run with no CFG_GO2RTC defined, so any leftover reference would have thrown.
Page build	PASS	Syntax check on the full page script; no new unreplaced placeholder.
Settings consistency	PASS	run.sh reads, config.yaml options and config.yaml schema all match.
Package	PASS	Zip byte-identical to tag 2.6.4; POSIX paths; no CRLF; option absent from the packaged config and run.sh.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*. CLAUDE.md rule 1 requires this section in every audit. It was present through 2.3.2 and dropped during the 2.4.x cycle. It is restored and stays.

Scope note. That document contains Parts 1 to 5 and a Sources Summary. It has no Part 6. CLAUDE.md describes a "Part 6 - Project Engineering" covering security, dependency management and version control, so the working agreement and the document disagree. Rows below marked *outside Parts 1-5* were checked against ordinary engineering practice, not against a written AnyCam standard.

Standard	Check applied	Result	Note
1.1 Truncated function	AST plus duplicate-def scan	PASS	153 top-level definitions, no duplicates.
1.2 Syntax errors	compile() to bytecode	PASS	Gate 1.
1.4 Async/await	The startup change	PASS	The supervisor task is created unconditionally, kept in <code>_GO2RTC_TASK</code> and cancelled at shutdown, as before.
1.5 Dead code	Searched for leftovers	PASS	No reference to the option remains in any shipped file; the JS test would throw on one.
1.5 Line length	Measured every added line	NOTED	2 of 15 added lines exceed 79 characters: a section banner comment at 81, and an existing <code>run.sh</code> log line, now shorter than before.
Part 2 JavaScript	Removed guards and constant	PASS	Syntax check and 46 behaviour checks pass.
Parts 3 and 4	No markup or CSS changed	PASS	Not applicable.
5.1 Escaping context	Removed a page placeholder	PASS	No new unreplaced placeholder in the built page.
Outside Parts 1-5: security	Exposure now present on every install	NOTED	<code>go2rtc</code> now runs everywhere, where before it ran only with the option on. Its four controls are unchanged and still pinned by the gate: API on 127.0.0.1, no command-running modules, RTSP server off, proxy allowlist. The WebRTC media port 28555 is now always open.
Outside Parts 1-5: configuration	Settings consistency	NOTED	Checked by hand this release. No gate checks it; logged as build plan F7.

Known issues carried forward

- **Firefox and LibreWolf** show a red Live view unavailable message once per H.265 camera per page load, then use the classic view. With the option gone this can no longer be switched off. Build plan C10.
- **Slow-starting streams** fall back after 12 s with the same message, seen on the Oak-D H.264 camera. Build plan B13, logs first.
- Unchanged from 2.6.3: Skip Non-Reference Frames breaks the cameras it applies to (B3); hardware decode falls back to software (B11); a motion recording may not stop (B1).

Not verified

- **The image was not built here.** The Dockerfile is unchanged from 2.6.3, which built on both systems, so build risk is low.
- **The upgrade warning** is inferred from Supervisor source, not seen on a real upgrade.

Acceptance

- The Configuration tab no longer shows Live View (Enhanced View).
- The startup log shows go2rtc: ready, with no option set.
- Enhanced View opens live in Chrome on both systems, as with 2.6.3 and the option on.
- At most one Supervisor warning about go2rtc_live_view after the upgrade.

Files changed

File	Change
camera_discovery.py	Removed CFG_GO2RTC, its checks in the focus API, the proxy and startup, and its page constant and guards. go2rtc supervised unconditionally. Version 2.6.4.
config.yaml	Removed the go2rtc_live_view option and schema entry. Version 2.6.4.
run.sh	Stopped reading go2rtc_live_view; dropped it from the startup config log line.
translations/en.yaml	Removed the Live View description.
CHANGELOG.md	2.6.4 entry.