

AnyCam 2.6.8 Audit Report

Release audit - 02 October 2026 - wrong home location check - tag 2.6.8

2.6.8 carries one item, build plan C16. Scope confirmed by CrystalHeeler on 2026-10-02: C16 only, the location re-read every 6 hours, push and publish when done. camera_discovery.py: 44 lines added, 7 removed.

Evidence

Fact	Value	Source
Notification on the test system B	'Still in night mode (IR) an hour after sunrise (00:42)'	CrystalHeeler's screenshot, 2026-10-02
Home Assistant home location	Amsterdam (the default), time zone Central	CrystalHeeler's screenshot of Home information
Amsterdam sunrise, 2026-10-02	05:42 UTC = 00:42 Central	AnyCam's own _sun_events_utc
Sunrise spread inside the Central zone, 21 December	06:41 (Pensacola) to 08:23 (New York): 1 h 42 min	Same function; why the time zone cannot replace the location

Design

Part	Design
Rule	A time zone's own longitude is 15 degrees for each hour of its standard offset from UTC. A home location more than 52.5 degrees (3.5 h) from it is wrong. 3.5 h accepts western China (75.9 E in UTC+8) and western Spain.
Time zone	The time_zone name from Home Assistant's /api/config, through Python's zoneinfo, standard time (summer time removed). If the name is missing or unknown: the add-on's own zone, which the Supervisor sets.
When wrong	No location is kept, so no sunrise or sunset events and no notifications. One log warning. The cog panel's note line shows the reason. Night boost itself works from the picture's colour and is not affected.
Refresh	Every 6 hours (was 12); every 5 minutes until Home Assistant answers.
Also	The cog's recording-folder help said SFTP and FTP were planned for 2.6.8; now 'a later version' (C14 is parked).

Tests run

Suite	Result	Scope
Release gate	PASS	Seven gates, 46 contracts (1 new, 1 updated), 19 settings in agreement, Dockerfile inputs online.

Suite	Result	Scope
Python integration	PASS	278 of 278, 13 new. Amsterdam with a Central zone rejected; New York, Chicago, Amsterdam, Sydney, Honolulu, western China, Spain, Fiji and Samoa accepted; standard time used; unknown zone name; the refresh: check off, one warning, cog note, 6 h; no second warning; corrected location turns it on.
JavaScript behaviour	PASS	110 of 110. No page change except one help sentence.
Not run	NOTED	zoneinfo needs the time zone database in the add-on image; it was not checked there (no Docker on the build PC). If it is missing, the add-on's own zone is used. Not tested against a real Home Assistant.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*, Parts 1 to 6. Only the rows this change touches are scored; the rest carry from the 2.6.7 audit.

Standard	Check applied	Result	Note
1.1 Truncated function	AST, duplicates, 46 contracts	PASS	No duplicates.
1.2 Syntax	compile()	PASS	Gate 1.
1.6 Function design	New helpers	PASS	_tz_std_offset_h and _ha_location_plausible: one job each.
1.7 Mutability	Shared state	NOTED	One more key in the module-level _HA_LOC_STATE dict.
1.10 Exceptions	Broad catch	NOTED	_tz_std_offset_h catches Exception: zoneinfo raises several types (missing database, bad key, bad type) and every one has the same safe fallback.
1.12 Logging	New line	PASS	One WARNING per mismatch, with the location, the zone and the fix.
1.17 Stdlib first	Time zones	PASS	zoneinfo is in the standard library; no package added.
1.18 Testing	Behavioural tests	NOTED	388 checks, still in the session scratchpad; E7 in 3.0.0-rc1.0 moves them into the repository.
6.1 Security	Input from Home Assistant	PASS	Latitude and longitude converted with float(); the zone name goes only to zoneinfo, inside the catch.
6.3 Version control	Commits and gate	PASS	One release commit; gate run before it; tag after.

Known issues carried forward

- A location that is wrong but inside the right time zone is not detected.

- The night and day colour thresholds are estimates (A13).
- The Microseven on the test system A needs a power cycle (B6).
- The Lorex DVR beeping on the test system B: cause unknown; waiting for the add-on log and the DVR's event entry.
- Skip Non-Reference Frames breaks H.264 cameras (B3).

Acceptance

- With the Amsterdam default: the log shows 'does not match its time zone' once, the cog shows the note, and no sunrise or sunset notifications arrive.
- After setting the real location: within 6 hours (or after a restart) the log shows 'Home Assistant location received' with local sunrise and sunset times.

Files changed

File	Change
camera_discovery.py	Location check, 6 h refresh, cog note, help text. Version 2.6.8.
config.yaml	Version 2.6.8.
verify_release.py	1 new contract, 1 updated.
docs	Build plan: C16 done, C14 parked, section E planned for 3.0.0-rc1.0.
CHANGELOG.md	2.6.8 entry, short format.