

AnyCam 3.0.0-rc1.2 Audit Report

Release audit - 02 October 2026 - module split: go2rtc - tag 3.0.0-rc1.2

3.0.0-rc1.2 is the third step of build plan E1. AnyCam's behaviour is meant to stay the same. Scope confirmed by CrystalHeeler on 2026-10-02: go2rtc only; B19 follows alone as 3.0.0-rc1.3; then tests for the scan and the scan's move. 3.0.0-rc1.1 passed his field test the same day.

What moved

File	Content	Lines
anycam_go2rtc.py	15 functions, 11 constants and state objects: the configuration, the supervisor and its log pump, stream names and registration, the relay URL, the card stream, the WebSocket proxy, the player script endpoint	434
camera_discovery.py	11,667 lines in 3.0.0-rc1.1	11,299

Stayed in the main file on purpose: `_focus_set_go2rtc` and `api_go2rtc_focus`. They are the Enhanced View engine: they assign `_FOCUSED_CAMERA` and `_FOCUS_ENGINE` under a global statement, and the main file owns those values. The split script refuses to move a function that would assign a main-file value. `_GO2RTC_TASK` also stayed: only `main()` uses it.

Values replaced at run time

Value	Owner now	How the other file reads it
<code>_GO2RTC_PROC</code> , <code>_GO2RTC_READY</code>	anycam_go2rtc.py (the supervisor assigns them)	camera_discovery.py reads anycam_go2rtc._GO2RTC_PROC (3 places, shutdown) and anycam_go2rtc._GO2RTC_READY (1 place, the focus engine)
<code>_GO2RTC_PLAYER_BYTES</code>	anycam_go2rtc.py	Used only inside it
<code>_FOCUSED_CAMERA</code> , <code>_FOCUS_ENGINE</code>	camera_discovery.py	The moved go2rtc functions do not use them

anycam_motion.py took `_go2rtc_profiles` from the main file through `NEEDS`. That function moved, so anycam_motion.py now imports it from anycam_go2rtc.py directly. It is a function and is never replaced.

Evidence that nothing changed

Check	Result
Every definition, text for text	362 definitions in 3.0.0-rc1.1 (all 6 files). After: 0 missing, 0 new, 0 changed, apart from the anycam_go2rtc. prefix on the two values above. 231 in the main file, 26 in anycam_go2rtc.py.
Built page	Same SHA-256 as 3.0.0-rc1.1's, each built in its own Python process.
Routes	The same 56 method and path pairs.
Packaged zip	Imported from its own folder.

Tests run

Suite	Result	Scope
Release gate	PASS	Eight gates; 7 files compiled; module list matches the imports and the Dockerfile; 211 top-level definitions; 48 contracts; 30 NEEDS names checked. New: no file imports a name that its owner assigns under global.
Gate self-test	PASS	'from anycam_go2rtc import _GO2RTC_READY' added to the main file: the new check failed and named the line, and the behaviour tests failed too. Restored.
Python integration	PASS	289 of 289. They include the supervisor with a real subprocess, registration against a fake go2rtc, and the WebSocket proxy end to end.
JavaScript behaviour	PASS	110 of 110.
Undefined names	NOTED	7 files, 0 new, 4 known (B19).
Not run	NOTED	The add-on was not started on the build PC and the image was not built. No real go2rtc binary ran. The field test (A16) is the first real run.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*, Parts 1 to 6. Rows this change touches; the rest carry from the 3.0.0-rc1.1 audit.

Standard	Check applied	Result	Note
1.1 Truncated function	AST, contracts, undefined names	FAIL	Unchanged: probe_http_identity (B19); the fix is 3.0.0-rc1.3.
1.2 Syntax	compile() per file	PASS	7 files.
1.6 Function design	File size	NOTED	Main file 11,299 lines, 38% under 2.6.8.
1.7 Mutability	Values replaced at run time	PASS	Each such value has one owner file; other files read owner.name; the gate enforces it.
1.16 Refactoring	Behaviour kept	PASS	Text comparison of all 362 definitions; page hash; routes.
6.1 Security	go2rtc API address	PASS	The gate's check that GO2RTC_API_HOST is 127.0.0.1 reads the joined files and still passes after the move.
6.3 Version control	Commits and gate	PASS	One commit; the gate run before it; tag after.

Known issues carried forward

- **B19** (HTTP identity check): 3.0.0-rc1.3, alone.
- **B20** (late pictures): right after 3.0.0.

- **E1:** the scan, password entry, the snapshot loop and the Enhanced View engine are still in the main file.
- The Lorex DVR answers 404 for the sub-stream of channels 4 and 7.
- Skip Non-Reference Frames breaks H.264 cameras (B3).

Acceptance (field test A16)

- The add-on starts and the log shows go2rtc ready.
- Enhanced View plays live; closing and reopening it works.
- Cards play live where they did in 3.0.0-rc1.1.
- The add-on stops cleanly on restart (no go2rtc process left).
- The log has no line with 'not defined' or 'has not run yet'.

Files changed

File	Change
camera_discovery.py	go2rtc code moved out; reads anycam_go2rtc._GO2RTC_PROC and _GO2RTC_READY. Version 3.0.0-rc1.2.
anycam_go2rtc.py	New.
anycam_motion.py	Imports _go2rtc_profiles from anycam_go2rtc.py.
anycam_modules.py, Dockerfile	One more file.
verify_release.py	Check for imported names that the owner replaces.
docs, CLAUDE.md, README	The rule for such values; build plan.
CHANGELOG.md	3.0.0-rc1.2 entry.