

AnyCam 3.7.3 Audit Report

Release audit - 06 October 2026 - real first frames, WebRTC retry, classic view pictures, request rate - tag 3.7.3

Scope confirmed by CrystalHeeler on 2026-10-06: version 3.7.3 with B41 (cards and Enhanced View), B42 (option A), B43, B44, B45 and B37's small-stream run. Built and pushed on CrystalHeeler's order; not published. Not field-tested.

Changes

#	Cause (from the field tests)	Change
B41	LibreWolf, Oak-D card (profile 244): played true, readyState 1, 0 frames, width 1280, black for good. Firefox Enhanced View: "Live (MSE): ... 0 fps" for 90 s; the 'playing' event counted as a frame.	_videoHasFrame: a width and decoded frames (or readyState 2 or more), for cards and Enhanced View.
B42	Five still-picture cards asked every 125 ms (about 40 requests a second); each channel gives about 0.8 pictures a second.	?after=N holds the answer up to 2 s until a newer picture; the page fetches blobs and sends the number it shows.
B43	A fresh install's log named no version.	"AnyCam 3.7.3 on :8099".
B44	Classic view, channels 7 and 2: 1,550 and 1,850 identical JPEGs; ffmpeg "More than 1000 frames duplicated".	-fps_mode passthrough: each decoded picture once.
B45	Firefox: the cards play H.265 over WebRTC (video only); Enhanced View asks for sound, gets MSE, and shows nothing.	No picture in 15 s and not on WebRTC: a second player, WebRTC and video only, before the classic view.
B37	All three hardware ways failed ("Decode fail") with 127 and 211 MB of CMA free.	A fifth run: the hardware decoder on the smallest H.265 stream.

Tests run

Suite	Result	Scope
Release gate	PASS	Eight gates; 17 files; build inputs checked online.
Python integration	PASS	617 of 617; section AL new (14 checks).
JavaScript behaviour	PASS	190 of 190; B41, B45 and [T] (B42) new.
Not run	NOTED	No field test. WebRTC in Firefox was inferred from socket timing and VideoRTC's code, not measured. -fps_mode ran only against a stand-in ffmpeg; the Pi's ffmpeg 5.1.9 documents the option.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*. Rows this change touches; the rest carry from the 3.7.0 audit.

Standard	Check applied	Result	Note
1.3 Async	Waits	PASS	The hold sleeps 50 ms at a time and ends at 2 s.
2 JavaScript	Async hygiene	PASS	A stopped snapshot run drops its answer (run number).
1.12 Logging	Truth	PASS	The version at start-up; the WebRTC retry has its own line.
1.18 Testing	New tests	PASS	14 server and 20 page checks.
6.1 Security	Input at the boundary	PASS	after must be digits; /api/live_fail takes three places only.
Rule 9 (privacy)	New text	PASS	Made-up addresses only.

Known issues

- **B37:** hardware HEVC decode fails on the Pi; software is used.
- **B33:** one Amcrest camera can get two cards; under investigation.
- **B32, B29:** wait for CrystalHeeler's tests.

Acceptance (field test)

- LibreWolf, Oak-D add-on 3.0.0: the Oak-D card shows still pictures within 15 s.
- Firefox: Enhanced View on a Lorex channel plays after the WebRTC retry.
- LibreWolf: the classic view of a Lorex channel moves.
- Browser console: about one request a second per still-picture card.
- The start-up line names 3.7.3.

Files changed

File	Change
page_script.py	B41, B42 (startSnap), B45.
anycam_snap.py	B42 hold and header; B44; B37 small stream.
anycam_go2rtc.py	B45 log line.
camera_discovery.py	B43; version 3.7.3.
tests/	Section AL; page checks.
CHANGELOG.md, config.yaml, docs	3.7.3; build plan.