

AnyCam 3.2.0-rc1.0 Audit Report

Release audit - 04 October 2026 - sound in live view, WebRTC and RTSP-over-WebSocket cameras - tag 3.2.0-rc1.0

Scope: phase 3.2.0 of the build plan (live view): C5 and C6, with CrystalHeeler's decisions of 2026-10-04: C5 muted by default with an unmute button; C6 built without further input. C3 was dropped on 2026-10-04. Built in the untested run on top of 3.1.0-rc1.0. This build is not field-tested.

1. Sound in Enhanced View (C5)

- The live player asks for media 'video,audio'. VideoRTC tells go2rtc which audio codecs this browser plays (MediaSource.isTypeSupported for MSE; the WebRTC offer), so go2rtc sends sound only in a codec the browser plays. Sound the browser cannot play is left out; the video is not affected.
- The video starts muted: browsers block sound that starts on its own. A Sound button in the Enhanced View bar turns it on; a click is the gesture browsers need. If the browser still refuses, the video stays muted.
- The button is grey before the first frame and when the stream has no sound (no audio codec in the MSE codec list, no live audio track on WebRTC). It is redrawn only when its state changes, not every second.
- Cards stay video only: no sound from a grid of cards, and less data.

2. WebRTC and RTSP-over-WebSocket cameras (C6)

Before 3.2.0 both had an information card. go2rtc 1.9.14 plays both with the modules AnyCam already loads (api, ws, rtsp, webrtc, mp4), so the go2rtc security model is unchanged. Source formats from go2rtc's README for v1.9.14.

Camera	go2rtc source
WebRTC (WHEP: an HTTP address that takes an SDP offer, which probe_webrtc finds)	webrtc:http://user:pass@ip:port/path
RTSP over WebSocket	rtsp://user:pass@ip:554/#transport=ws://ip:port/path
Both play in the card and in Enhanced View (profile 0 only). These cameras have no still pictures, so a card whose live view fails shows the reason instead of polling snapshots.	

Tests run

Suite	Result	Scope
Release gate	PASS	Eight gates; 15 files; build inputs checked online.
Python integration	PASS	503 of 503; 9 new in section AC.
JavaScript behaviour	PASS	139 of 139; new section C5; the mount check now expects video and sound.
Undefined names	PASS	15 files, 0.
Not run	NOTED	No field test (CrystalHeeler's order). The image was not built. No test system has a camera known to send sound, a WebRTC camera, or an RTSP-over-WebSocket camera; go2rtc was a stand-in in the tests.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*, Parts 1 to 6. Rows this change touches; the rest carry from the 3.1.0-rc1.0 audit.

Standard	Check applied	Result	Note
1.1 Truncated function	AST, contracts, undefined names	PASS	15 files.
1.18 Testing	New tests	PASS	9 server and 7 page checks.
2.x JavaScript	Promises, DOM	PASS	play() refusal caught; the button is redrawn only on a change.
6.1 Security	go2rtc modules	PASS	No module added; the passwords go into the source URL, percent-encoded, never to the page.
Rule 9 (privacy)	New text	PASS	Tests use made-up addresses only.

Known issues carried forward

- Cards play no sound.
- An RTSP-over-WebSocket camera of an unknown brand gets the root stream path.
- **B6**: the Microseven waits until CrystalHeeler unlocks it.
- **C21**: the classic engine stays as the fallback.

Acceptance (field test)

- Enhanced View on a camera with a microphone: the Sound button turns the sound on and off; on a camera without one, the button is grey.
- Chrome and Firefox on Windows both play the video as in 3.1.0-rc1.0.
- A WebRTC or RTSP-over-WebSocket camera, when one is available, plays in its card and in Enhanced View.

Files changed

File	Change
anycam_go2rtc.py	_go2rtc_native_source; card and Enhanced View use it.
page_script.py	Sound button; video and sound; WebRTC and WS-RTSP cards.
camera_discovery.py, config.yaml	Version 3.2.0-rc1.0.
tests/	Section AC; page section C5.
CHANGELOG.md, docs	3.2.0-rc1.0; build plan.