

AnyCam 3.0.0-rc1.4 Audit Report

Release audit - 02 October 2026 - empty page text, scan tests, scan split - tag 3.0.0-rc1.4

Scope confirmed by CrystalHeeler on 2026-10-02: three things in one build. (1) Build plan B21, the empty page text. (2) Tests for the scan. (3) The scan's move to its own files, build plan E1. Item 1 changes what the page shows. Items 2 and 3 change no behaviour.

1. Empty page text (B21)

State	Text
No cameras, a scan is running	No Cameras Found Yet
No cameras, no scan running	No cameras found. Click Scan Network to discover cameras on your subnet. (unchanged)

The scan status poll, which already shows and hides the Cancel button, sets the text. 6 checks: 2 on the page markup, 4 on the script.

2. Tests for the scan

The scan had no tests. 25 checks now run the real `run_scan` and `_probe_host_port`. Stand-ins replace only the functions that touch the network: ARP, multicast discovery, nmap, and the single-port probers.

Checks	What they pin
U1-U2	Every live host goes to the port scan, sorted; the gateway, Docker and link-local addresses do not. The RTSP port is probed first; a blacklisted port is skipped; after the RTSP port answers, the host's other ports skip the RTSP path walk.
U3-U4	Saved cameras stay, unsaved old cards go. One card for each device. A device found by the port scan and by ONVIF keeps one card.
U5	A device found by ONVIF only: a password card; its brand read from its web page (the function restored in 3.0.0-rc1.3).
U6-U7	End state: not running, 100%, counts, one save. A failure inside the scan is reported and the scan is not left running.
U8-U12	The port prober: RTSP open, RTSP needing a password, MJPEG, HLS, nothing found, not a camera, RTMP; the order of the probers.
U13	The status and cancel endpoints.

Defect found while writing the tests (build plan B22)

The Cancel endpoint sets a flag named `_SCAN_CANCELLED`. The scan reads `SCAN_CANCELLED`, a different name that the scan creates itself. The status line changes to 'Cancelling scan...' and the scan runs to its end. Not fixed in this build: the scope was fixed at three items, and the fix changes behaviour. No test pins the broken behaviour.

3. The move

File	Content	Lines
anycam_probe.py	26 functions, 8 tables: the RTSP probe and path walks, MJPEG, HLS, RTMP, WebRTC, the RTSP fingerprint, the HTTP identity check, the ONVIF calls	2,657
anycam_scan.py	18 functions, 5 tables and state objects: subnet and gateway, ARP, SSDP, mDNS and ONVIF discovery, nmap, the port prober, the scan, the verification scan, the port scanner	2,040
camera_discovery.py	11,303 lines in 3.0.0-rc1.3	6,780

Link	Detail
anycam_scan.py to anycam_probe.py	Direct import of 15 prober functions. anycam_probe.py imports nothing from anycam_scan.py.
Values replaced at run time	ARP_HOSTS and PENDING_CAMERAS moved with run_scan, the only function that replaces them. camera_discovery.py reads anycam_scan.ARP_HOSTS (1 place) and anycam_scan.PENDING_CAMERAS (4 places).
Left in the main file	The manufacturer database (OUI). The probers and the scan both use it; moving it with the scan would make the two new files import each other.
NEEDS lists	67 names across all split files, checked by the gate.

Evidence that the move changed nothing

Check	Result
Every definition, text for text	363 before, 363 after; 0 missing, 0 changed, apart from the anycam_scan. prefix on the two values above. 175 in the main file, 34 in anycam_probe.py, 23 in anycam_scan.py.
Built page and routes	Same page hash; the same 56 routes.
The scan tests	Written and passing before the move; passing unchanged after it.
Packaged zip	Imported from its own folder.

The first attempt at the second move stopped half way, on a Dockerfile pattern in the split tool. The repository was reset to the last commit and both moves were run again with the corrected tool.

Tests run

Suite	Result	Scope
Release gate	PASS	Eight gates; 9 files compiled; module list matches the imports and the Dockerfile; 212 top-level definitions; 48 contracts; 67 NEEDS names.
Python integration	PASS	321 of 321, 27 new.
JavaScript behaviour	PASS	114 of 114, 4 new.
Undefined names	PASS	9 files, 0.

Suite	Result	Scope
Not run	NOTED	No scan ran on a real network from the build PC, and the image was not built. The scan tests use stand-ins for the probers, so the probers' own network code is not tested. The field test (A18) is the first real scan with the moved code.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*, Parts 1 to 6. Rows this change touches; the rest carry from the 3.0.0-rc1.3 audit.

Standard	Check applied	Result	Note
1.1 Truncated function	AST, contracts, undefined names	PASS	9 files.
1.2 Syntax	compile() per file	PASS	9 files.
1.3 Runtime errors	Names	FAIL	B22: the cancel flag has two names. Found, recorded, not fixed.
1.6 Function design	File size	NOTED	Main file 6,780 lines, 63% under 2.6.8. run_scan (714 lines) and _probe_rtsp_paths_single_socket (657) moved whole.
1.7 Mutability	Values replaced at run time	PASS	One owner file for each; the gate enforces it.
1.16 Refactoring	Behaviour kept	PASS	Text comparison of 363 definitions; page hash; routes; scan tests before and after.
1.18 Testing	New tests	PASS	25 for the scan, written before the move.
2.x JavaScript	New function	PASS	_setEmptyText: no error when the elements are absent; tested.
6.3 Version control	Commits and gate	PASS	Three commits, one for each item; the gate run before the last.
Rule 9 (privacy)	New text	PASS	Tests and documents use made-up addresses only.

Known issues carried forward

- **B22:** the Cancel button does not stop a scan.
- **B20** (late pictures, insects on the fallback): right after 3.0.0.
- **C17** (detection zones): design discussion pending.
- **E1:** password entry, the snapshot loop, the Enhanced View engine and the manufacturer database are still in the main file.
- Skip Non-Reference Frames breaks H.264 cameras (B3).

Acceptance (field test A18)

- The add-on starts; the start-up scan finds the same cameras as before.
- During a scan with an empty page: 'No Cameras Found Yet', and no 'Click Scan Network' line.
- Entering a camera password works (that path calls the moved probers).
- The log has no line with 'not defined' or 'has not run yet'.

Files changed

File	Change
camera_discovery.py	Scan and probers moved out; empty page markup. Version 3.0.0-rc1.4.
anycam_probe.py, anycam_scan.py	New.
page_script.py	_setEmptyText.
anycam_modules.py, Dockerfile	Two more files.
tests/	27 server checks and 4 page checks.
docs, CLAUDE.md, README	Module list; build plan.
CHANGELOG.md	3.0.0-rc1.4 entry.