

RW BLE Android SDK User Manual

1. Introduction

This document mainly explains the functional interfaces and usage scenarios provided in the SDK.

This document is only applicable to RW's Bluetooth devices.

1.1 Applicable platforms and languages

- Android 8.0 and above, language Kotlin.

1.2 Related terms

- App: This article refers to applications running on mobile phones or tablets;
- Device: This article refers to wearable hardware devices: such as watches, rings, etc.;

1.3 Precautions

1. It is best to use this SDK in conjunction with the sample project `RW_SDK_DEMO`; for reference, just focus on the two pages of `NewMainActivity` and `ScanActivity`.
2. Most of the command operations of `DHBluetooth` are implemented by subscribing to the corresponding callback `DHBluetooth.subscribeData()`; when no longer in use, please unsubscribe `DHBluetooth.dispose()`;

2. Quick Start

Step 1: Get the latest version of Android Studio.

To use the RW BLE SDK for Android in your development project, you need to install Android Studio.

Step 2: Manually deploy and add the dependency libraries.

Import the AAR file into your project's build.gradle file.

```
implementation files('libs/blesdk_rwfit_release_260130.aar')
```

Step 3: You need to enable Bluetooth on your phone and grant Bluetooth and location permissions.

```
private fun getBluePermissions(): List<String> {
    val permissions = mutableListOf<String>()
    permissions += Permission.BLUETOOTH_SCAN
    permissions += Permission.BLUETOOTH_ADVERTISE
    permissions += Permission.BLUETOOTH_CONNECT
    permissions += Permission.ACCESS_COARSE_LOCATION
    permissions += Permission.ACCESS_FINE_LOCATION
    return permissions
}
```

Step 4: Initialize the SDK

```
DHBleSdk.initSDK(this)
```

⚠ Caution

Bluetooth log files will be saved by default in the `Data/appid/logger/devices/` folder. This can be disabled using `XLogUtils.setLogEnable(false)`.

To avoid conflicts with the SDK, please add the following configuration to your Proguard obfuscation file:

```
-keep class com.example.blesdk.DHBleSdk {
    *;
}
-keep class com.example.blesdk.ble.ScanBleService {
    *;
}
-keep class com.example.blesdk.bean.** {
    *;
}
-keep class com.example.blesdk.ble.** {
    *;
}
-keep class com.example.blesdk.callback.** {
    *;
}
-keep class com.example.blesdk.utils.** {
    *;
}
```

3. API Reference

3.1 Device search and connection, binding and reconnection.

3.1.1 Search for Bluetooth devices

Interface description: To search for Bluetooth devices, you need to initialize `ScanBleService` first and implement the `ScanDeviceCallback` callback interface.

```
// 1. Initialize and register the callback.
ScanBleService.getService().initBle(this)
ScanBleService.getService().registerScanBleCallback(this)

// 2. Start searching
ScanBleService.getService().startScan(true, null)

//3. The ScanDeviceCallback interface will provide callbacks for the discovered
Bluetooth devices.
public interface ScanDeviceCallback {
    public void onScanDevice(BleDevice device);
    public void onScanFinish();
    public void onError(int errorCode, Exception e);
}

//4. Unregister callback
ScanBleService.getService().unRegisterScanBleCallback()
```

3.1.2 Stop searching

Interface description: Stop searching for Bluetooth devices.

```
ScanBleService.getService().stopScan()
```

3.1.3 Device connection and status monitoring

Interface description: Connects to the specified device and monitors the device's connection status.

```
// 1. Initialize and register the callback.
DHBLESdk.setConnectBleCallback(this)

// 2. Connect devices
DHBLESdk.connectDeviceWithModel(bleDevice)

// 3. Implement and receive callbacks for Bluetooth connection status.
interface RingConnectBleCallback {
    fun onRingConnecting()
    fun onRingConnected()
    fun onRingConnectFailed(reason: RingBleError = RingBleError.UNKNOWN)

    fun onRingDidFunctionMenu(supportMenuBean: SupportMenuBean)
}
```

`RingConnectBleCallback` Interface Description:

方法	说明
onRingConnecting	Connecting
onRingConnected	After calling <code>connectDeviceWithModel</code> , the function will return upon successful connection.
onRingConnectFailed	A callback function will be triggered when the Bluetooth connection is disconnected.
onRingDidFunctionMenu	The function will return after successfully obtaining the device configuration table; business operations should be performed after this point.

Tip

After connecting, business operations should only be performed after the `onRingDidFunctionMenu` event.

3.1.4 Disconnect the device.

Interface description: Disconnect the currently connected device and monitor the device connection status.

```
DHBLESdk.disconnect()
```

3.1.5 Local binding and automatic reconnection, unbinding

Important

Android local binding requires manual implementation of automatic reconnection; this SDK does not provide this functionality. After a successful connection, you can save the MAC address and necessary configuration information for convenient display and reconnection on the user interface.

3.1.6 Equipment Function Configuration Table

Important

Due to the variety of device models and their differing supported features, a feature list has been introduced to allow users to check the supported features of each device. Please refer to the `SupportMenuBean` class for details. You can save the feature list content according to your specific business requirements.

```
fun onRingDidFunctionMenu(supportMenuBean: SupportMenuBean)
```

DeviceFuncV2Model class attribute definitions:

SupportMenuBean attribute	illustrate
isPushMsgEnableSwitch	Enable or disable the message control switch?
isAlarm	Does it support an alarm clock?
isBrightScreenSleepTime	Does it support screen sleep time settings?
isBrightScreenTime	Does it support screen-on time adjustment?
isNewSport	Does it support multiple sports modes?
isRememberSwitch	Does it support enabling/disabling Muslim prayers?
isSupportHrReminder	Does it support HR (heart rate) alarm notification function?
isSupportBoReminder	Does it support SpO2 alarm notification functionality?
isSupportMotoVibrationLevel	Does it support motor vibration alerts?
isStep	Does it support step counting?
isHr	Does it support heart rate monitoring?
isBloodPress	Does it support blood pressure measurement?
isSleep	Does it support sleep mode?
isBloodOxy	Does it support blood oxygen monitoring?
isHrv	Does it support heart rate variability?
isPressure	Does it support pressure?
isBloodSugar	Does it support blood glucose monitoring?
isMuslimCountData	Do you support praise?

3.2 Device function operation

3.2.1 Basic function command interface

3.2.1.1 Get SDK Version

Get the SDK version number.

Method Description:

```
DHBLESdk.getSDKVersion()
```

Example of usage:

```
Log.e("RWSdk", DHBLESdk.getSDKVersion())
```

3.2.1.2 Set user information

User information settings are related to step count, calories burned, and distance. During device initialization, the default settings are: gender 1, age 18, height 170cm, and weight 65 kg.

Subscribe to `CommonStatusCallback` to receive the results.

Method Description:

```
fun setUserInfo(personBean: PersonBean)
```

Parameter Description:

parameter	type	illustrate	
personBean	PersonBean	class	gender: Gender (0. Female, 1. Male) height: Height in cm, floating-point number weight: Weight in kg, floating-point number age: Age

Example of usage:

```
DHbleSdk.subscribeStatus(object : CommonStatusCallback{
    override fun onSuccess(id: Int) {
        Log.e("RWSDK", "user info set ok")
    }

    override fun onFail(id: Int, errorCode: Int) {
        Log.e("RWSDK", "user info set failed")
    }
})

val personBean = PersonBean()
personBean.measureUnit = 0
personBean.gender = 1
personBean.height = 170.5f
personBean.weight = 80f
personBean.age = 20
DHbleSdk.setUserInfo(personBean)
```

3.2.1.3 Obtaining Device Information

Interface Description: Obtain firmware model, firmware version number, and UI version number;

Subscribe to `FirmwareCallback` to get the results.

```
//1. Subscribe to LoginDeviceCallback callback
DHbleSdk.subscribeData(object : FirmwareCallback {
    override fun onSuccess() {
    }
    override fun onFail(errorCode: Int) {
    }
})
```

```

onAppend("ERROR CODE $errorCode")
}
override fun onResult(data: FirmVersionBean?) {
    data?.let {
        onAppend("Firmware Version --> \n$it")
    }
}
})

//2. Send data, the result will be obtained in FirmwareCallback.
DHBLESdk.getFirmwareVersionJL()

//3. Unsubscribe
DHBLESdk.dispose(FirmwareCallback)

//FirmVersionBean entity class
public class FirmVersionBean extends BLESendBean {
    private String deviceClazz = ""; //Device model
    private String deviceNo = "1.0.0"; //Device version number
    private int screenType; //0 square, 1 round
    private int screenWidth; //Device width
    private int screenHeight; //Device height
    private String uiVersion; //UI version number
}

```

3.2.1.4 Get Battery Level

Interface Description: The app retrieves the device's battery level.

Subscribe to `PowerCallback` to get the result.

```

//1. Subscribe to the PowerCallback callback
DHBLESdk.subscribeData(object : PowerCallback {
    override fun onSuccess() {
    }

    override fun onFail(errorCode: Int) {
        onAppend("ERROR CODE $errorCode")
    }

    override fun onResult(data: PowerBean?) {
        data?.let {
            onAppend("Device battery level --> \n$it")
        }
    }
})

//2. Send data, the result will be obtained in PowerCallback.
DHBLESdk.getPowerJL()

//3. Unsubscribe
DHBLESdk.dispose(PowerCallback)

```

```
//PowerBean entity class
public class PowerBean implements Parcelable {
    private boolean isLowPower; // Low power status
    private int powerStatus; // Charging status, 0 not charging, 1 charging, 2
charging complete
    private int power; // Battery level 0-100
}
```

3.2.1.5 Getting and Setting Video Control Switch

Sets whether to enable ring gesture control for watching videos; This function requires Bluetooth HID pairing. HID pairing can be done using `BlueToothUtils.createOrRemoveBond` (type 1 for pairing, 2 for unpairing), or you can implement it yourself.

Subscribe to `videoHidCallback` to get the result.

Method Description:

```
fun setVideoHidJL(videoHidBean: VideoHidBean)
```

Parameter Description:

Parameter	Type	Description	Value
videoHidBean	VideoHidBean	Class	hidOpen: 0. Off 1. Video On 2. Book 3. Music

Example of usage:

```
// Set video control switch
DHBLESdk.subscribeData(videoHidCallback)
val videoHidBean = VideoHidBean()
videoHidBean.hidOpen = 1 //Whether to open short video control
DHBLESdk.setVideoHidJL(videoHidBean)

// Get video control switch
DHBLESdk.subscribeData(videoHidCallback)
DHBLESdk.getVideoHidJL()
```

3.2.1.6 Getting and Setting LED Screen Brightness

Configuration table attribute: `isLEDLight`;

Subscribe to `BrightLedLevelCallback` to get the result.

Method Description:

```
fun setRingLedLevel(brightScreenBean: BrightScreenLedBean)
```

Parameter Description:

Parameter	Type	Description	Value
brightScreenBean	BrightScreenLedBean	Class	isOpen: false for off, true for (1-3 Level) LcdLevel: 1 Dim light, 2 Soft light, 3 Strong light

Example of usage:

```
// Get LED screen brightness
DHBLESdk.subscribeData(brightLedLevelCallback)
DHBLESdk.getRingLedLevel()

// Set LED screen brightness
DHBLESdk.subscribeData(brightLedLevelCallback)
val tBrightScreenLedBean = BrightScreenLedBean()
tBrightScreenLedBean.isOpen = true //false is off, true is (1-3Level)
tBrightScreenLedBean.lcdLevel = 3 //1-3Level: 1 low 2 mid 3 high
DHBLESdk.setRingLedLevel(tBrightScreenLedBean)
```

3.2.1.7 Getting and Setting Wearing Position

Configuration table attribute: `isWearDir`;

Subscribe to `WearHandCallback` to get the result.

```
// Get wearing position
DHBLESdk.subscribeData(ringWearHandCallback)
DHBLESdk.getRingWearDir()

// Set wearing position
DHBLESdk.subscribeData(ringWearHandCallback)
DHBLESdk.setRingWearHand(false) // False is left hand, true is right hand
```

3.2.1.8 Starting and Stopping Photo Taking

After starting the photo taking function, the device can control the app's custom camera to take photos through gestures.

Subscribe to `TakePhotoCallback` to receive photo taking notifications from the device.

Configuration table attribute: `isTakePhoto`;

```
// APP enters the camera interface. 1 controls the device to enter the
corresponding interface, 0 controls the device to exit.
DHBLESdk.subscribeData(takePhotoCallback)
DHBLESdk.controlTakePhotoJL(1) // Open Photo

// 0 controls the device to exit
DHBLESdk.dispose(takePhotoCallback)
DHBLESdk.controlTakePhotoJL(0) // Close photo taking

// Listen for photo taking commands from the device
/**
 * Camera control monitoring
 */
private val takePhotoCallback by lazy {
    object : TakePhotoCallback {
        override fun onSuccess() {
            Log.e("qob", "Output: TakePhotoCallback onSuccess")
        }
    }
}
```

```

        override fun onFail(errorCode: Int) {

        }

        override fun onResult(data: Int?) {
            Log.e("qob", "Output: TakePhotoCallback onResult " + data)
            data.let {
                when (it){
                    2 -> {
                        // TODO Start the phone's custom camera to take photos
                    }
                }
            }
        }
    }
}

```

3.2.1.9 Finding the Device

After calling the find function, the device's light or screen will light up.

Method Description:

```
fun controlFindDeviceJL()
```

Example of usage:

```
DHbleSdk.controlFindDeviceJL()
```

3.2.1.10 Shutdown, Factory Reset

Subscribe to `DeviceControlCallback` to get the result.

Method Description:

```
fun setPowerOffJL(type: Int)
```

Parameter Description:

Parameter	Type	Description	Value
type	Int	Integer	Shutdown: Constants.CONTROL_DEVICE_POWER_OFF Factory Reset: Constants.CONTROL_DEVICE_RECOVERY

Example of usage:

```

// Shutdown
DHbleSdk.setPowerOffJL(Constants.CONTROL_DEVICE_POWER_OFF) //Shutdown

// Factory Reset
DHbleSdk.setPowerOffJL(Constants.CONTROL_DEVICE_RECOVERY) //Factory Reset

// You can subscribe to the DeviceControlCallback callback

```

3.2.1.11 Alarm Clock

3.2.1.11.1 Getting Set Alarms

Configuration table attribute: `isAlarm`

Subscribe to the `AlarmCallback` callback;

Method Description:

```
DHBleSdk.getAlarmRemindJL();
```

Example of usage:

```
// Get the alarms saved on the device
DHBleSdk.subscribeData(alarmCallback)
DHBleSdk.getAlarmRemindJL()
```

3.2.1.11.2 Setting Alarms

The current protocol does not support modifying alarms individually. Any operation to switch on/off or delete a single alarm requires resending all alarm configurations.

**

Subscribe to the `AlarmCallback` callback;

Method Description:

```
fun setAlarmRemindJL(reminderBeans: List<AlarmRemainderBean>)
```

Parameter Description:

Parameter	Type	Description	Value
reminderBeans	List	Alarm array	isOpen: true/false repeatModel: IntArray(7) Sunday to Saturday, set to 1 for days to repeat startHour: Alarm start hour startMin: Alarm start minute alarmTag: Set to an empty string;

Example of usage:

```
// Set alarm
DHBleSdk.subscribeData(alarmCallback)

val params = mutableListOf<AlarmRemainderBean>()
val alarmRemainderBean = AlarmRemainderBean()
alarmRemainderBean.alarmTag = ""
alarmRemainderBean.repeatModel = IntArray(7) // Single time; Sunday to Saturday, set to 1 for days to repeat
alarmRemainderBean.startHour = 7
alarmRemainderBean.startMin = 0
alarmRemainderBean.isOpen = true
alarmRemainderBean.alarmId = 0
params += alarmRemainderBean

val alarmRemainderBean2 = AlarmRemainderBean()
alarmRemainderBean2.alarmTag = ""
```

```
alarmRemainderBean2.repeatModel = IntArray(7) // Single time; Sunday to Saturday,
set to 1 for days to repeat
alarmRemainderBean2.startHour = 8
alarmRemainderBean2.startMin = 0
alarmRemainderBean2.isOpen = false
alarmRemainderBean2.alarmId = 0
params += alarmRemainderBean2

DHBleSdk.setAlarmRemindJL(params)
```

3.2.1.11.3 Delete All Alarms

```
DHBleSdk.deleteAllAlarmRemindJL;
```

Subscribe to the `AlarmCallback` callback;

Method Description:

```
DHBleSdk.deleteAllAlarmRemindJL
```

```
//Subscribe to callback
DHBleSdk.subscribeData(alarmCallback)
//Delete all alarms
DHBleSdk.deleteAllAlarmRemindJL()
```

3.2.1.12 Vibration Count Setting and Getting

Configuration table attribute: `isSupportMotoVibrationLevel`

Device vibration count;

Subscribe to the `VibrationCountCallback` callback.

Method Description:

```
fun setVibrationCount(level:Int, count: Int)
```

```
fun getVibrationCount()
```

Parameter Description:

Parameter	Type	Description	Value
level	Int	Integer	Vibration intensity, 0: Off 1: Low 2: Medium 3: High; <i>Can be ignored if this function is not defined</i>
count	Int	Integer	The number of vibrations can be set (0-6 times), initial default is 2 times. Setting to 0 means no vibration

Example of usage:

```
//Setting
DHBLESdk.subscribeData(vibrationCountCallback)
DHBLESdk.setVibrationCount(1, 2) //Vibration count 2 times

//Getting
DHBLESdk.subscribeData(vibrationCountCallback)
DHBLESdk.getVibrationCount()
```

3.2.1.13 Screen Sleep Mode Setting and Getting

Sets screen sleep on/off and time;

Configuration table attribute: `isBrightScreenSleepTime`

Subscribe to `BrightTimeCallback` to get the result.

Method Description:

```
fun setRingBrightScreenSleepTime(briScreenTime: BrightScreenTimeBean)
```

```
fun getRingBrightScreenSleepTime()
```

Parameter Description:

Parameter	Type	Description	Value
BrightScreenTimeBean	Class		isOpen, Switch ON YES or OFF NO startHour, start time hour startMin, start time minute endHour, end time hour endMin, end time minute

Example of usage:

```
// Subscribe
DHBLESdk.subscribeData(brightTimeCallback)

// Set
val briScreenTime = BrightScreenTimeBean()
briScreenTime.isOpen = true
briScreenTime.startHour = 20 // Sleep from 8 PM to 8 AM
briScreenTime.startMin = 0
briScreenTime.endHour = 8
briScreenTime.endMin = 0

DHBLESdk.setRingBrightScreenSleepTime(briScreenTime)

// Get
DHBLESdk.getRingBrightScreenSleepTime()
```

3.2.1.14 Message Push Switch Setting and Getting

Message push switch;

Configuration table attributes: `isPushMsgEnableSwitch`, `pushMsgSwitchValue` to determine which applications the device supports.

Method Description:

```
fun setPushMsgJL(msgPushBean: MsgPushBean)
```

Parameter Description:

Parameter	Type	Description	Value
MsgPushBean	Class		See MsgPushBean class definition

Example of usage:

```
// Set
val messageBean = MsgPushBean()
messageBean.appId = "com.ten.wenxin"
messageBean.title = "1111"
messageBean.content = "8888"
DHBLESdk.setPushMsgJL(messageBean)
```

3.2.1.14 Getting and Setting whether the Reminder Function is Enabled

Set whether the reminder function is enabled;

Configuration table attribute: `isRememberSwitch`

Subscribe to `MuslimCountSwitchCallback` to get the result.

Method Description:

```
fun deviceRememberSwitch(status: Int)
```

```
fun deviceRememberSwitchGet()
```

Parameter Description:

Parameter	Type	Description	Value
status	Int		0: Off 1: On

Example of usage:

```
//set up
DHBLESdk.subscribeData(muslimCountSwitchCallback)
DHBLESdk.deviceRememberSwitch(1)

//Get
DHBLESdk.deviceRememberSwitchGet()
```

3.2.1.15 Getting and Setting Heart Rate/Blood Oxygen Alarm Configuration

This function sets the heart rate and blood oxygen notification alarm data; alarm notifications will be sent in real-time via `HrBoActualReminderCallback`.

Configuration table attribute: `isSupportHrReminder`

Subscribe to `HrReminderCallback` and `BoReminderCallback` to get the results.

Method Description:

```
fun deviceGetHrAlertCmd()
```

```
fun deviceSetHrAlertCmd(status: Int, value: Int, underValue: Int)
```

```
fun deviceGetBoAlertCmd()
```

```
fun deviceSetBoAlertCmd(status: Int, value: Int)
```

Parameter Description:

Parameter	Type	Description	Value
status	Int		1: On, 0: Off; overValue: Alarm value, default value is heart rate exceeding 160, blood oxygen below 94%,
value	Int		Exceeding alarm value, default value is heart rate exceeding 160
underValue	Int		Below value alarm; If the retrieved value is 0xff, it means this function is not supported;

Note: If `underValue` obtained through `deviceGetHrAlertCmd()` is 0xff, it means this function is not supported.

Real-time alarm return value `HrBoActualReminderBean` description:

HrBoActualReminderBean Parameter	Type	Description	Value
type	Int		0: Heart rate exceeding alarm, 1: Blood oxygen alarm; 2: Heart rate below alarm
remindValue	Int		Alarm value

Example of usage:

```
//Setting
DHBleSdk.subscribeData(hrReminderCallback)
DHBleSdk.deviceSetHrAlertCmd(1, 140, 0xff)

//Getting
DHBleSdk.subscribeData(hrReminderCallback)
DHBleSdk.deviceGetHrAlertCmd()
```

```
//Alarm result notification push
DHBLESdk.subscribeData(hrBoActualReminderCallback) //Alert Message

private val hrBoActualReminderCallback by lazy {
    ``````kotlin
 object : HrBoActualReminderCallback {
 override fun onResult(data: HrBoActualReminderBean) {
 Log.e("RWSdk", "output: HrBoActualReminderCallback data " + data.type + " value "
 + data.remindValue)
 if (data.type == 0) { // HR Over Value Alarm

 } else if (data.type == 1) { // SP02 Over Value Alarm

 } else if (data.type == 2) { // HR Under Value Alarm

 }

 }

 override fun onFail(errorCode: Int) {
 Log.e("RWSdk", "output: HrBoActualReminderCallback errorCode " + errorCode)
 }

 override fun onSuccess() {
 Log.e("RWSdk", "output: HrBoActualReminderCallback onSuccess")
 }

 }
}
```

### 3.2.1.16 Get and Set Screen Brightness Duration

Configuration table attribute: `isBrightScreenTime`

Subscribe to `BrightTimeCallback` to get the result.

Method Description:

```
fun getBrightScreenTimeJL()
```

```
fun setBrightScreenTimeJL(briScreenTime: BrightScreenTimeBean)
```

Parameter Description:

BrightScreenTimeBean Parameter	Type	Description	Value
timeSecond	Int	Screen brightness duration, in seconds (s), range 0-30s;	
durationNums	String	Supported duration values by the device, separated by commas if available;	

Example of usage:



```
// Set
val briScreenTime = BrightScreenTimeBean()
briScreenTime.timeSecond = 10 // Screen brightness for 10s
DHBLESdk.subscribeData(brightTimeCallback)
DHBLESdk.setBrightScreenTimeJL(briScreenTime)

// Get
DHBLESdk.getBrightScreenTimeJL()
```

### 3.2.1.17 Getting and Setting Wrist-Raise Screen Activation Time

Configuration table attribute: `isRaiseBrightScreen`

Subscribe to `BrightCallback` to get the result.

Method Description:

```
fun getRaiseBrightScreenJL()
```

```
fun setRaiseBrightScreenJL(brightScreenBean: BrightScreenBean)
```

Parameter Description:

BrightScreenBean Parameter	Type	Description	Value
isOpen	Int	true: enabled; false: disabled	
startHour	Int	Start time hour	
startMin	Int	Start time minute	
endHour	Int	End time hour	
endMin	Int	End time minute	

Example of usage:

```
// Setting
val rasieScreenTime = BrightScreenBean()
rasieScreenTime.isOpen = true
rasieScreenTime.startHour = 8 // Wrist-raise screen activation from 8 AM to 8 PM
rasieScreenTime.startMin = 0
rasieScreenTime.endHour = 20
rasieScreenTime.endMin = 0
DHBLESdk.subscribeData(raiseBrightTimeCallback)
DHBLESdk.setRaiseBrightScreenJL(rasieScreenTime)

// Getting
DHBLESdk.getRaiseBrightScreenJL()
```

### 3.2.1.18 Set Time Format (12-Hour / 24-Hour)

This setting only applies to devices with a display.

Subscribe to `CommonStatusCallback` to get the result.

Method Description:

```
fun ringSetTimeformat(type: Int)
```

Parameter Description:

Parameter	Type	Description	
timeformat	Int	0: 24-hour 1: 12-hour	

Example of usage:

```
DHbleSdk.subscribeStatus(object : CommonStatusCallback{
 override fun onSuccess(id: Int) {
 Log.e("RWSDK", "time format set ok")
 }

 override fun onFail(id: Int, errorCode: Int) {
 Log.e("RWSDK", "time format set failed")
 }
})
DHbleSdk.ringSetTimeformat(0) //24-hour
```

## 3.2.2 Health Data Synchronization (Real-time Single Measurement and All-day Monitoring)

There are two ways to detect health data: real-time single measurement and all-day monitoring. Health data includes heart rate, blood oxygen, stress, HRV, sleep, etc. **Sleep data does not have real-time measurement.**

(1) Real-time single measurement: The APP starts the device to perform a single measurement, and the result is returned immediately after the measurement is completed.

(2) All-day monitoring: The interval time can be set, for example, 30 minutes or 60 minutes, and the device will perform the measurement and save the value; **if the app does not synchronize continuously, the device can save 3-6 days of data.**

### 3.2.2.1 Real-time Detection - Starting and Stopping Device Health Data Detection

Start health data detection (heart rate, blood oxygen, HRV, stress, blood sugar, etc.);

Subscribe to `HealthDataBroCallback` for notification from the device to the app upon test completion;

Subscribe to `HealthDataControlCallback` for real-time value notifications from the device to the app during testing;

#### Method Description:

```
fun controlHealthDataJL(healthType: Byte, testStatus: Byte)
```

#### Parameter Description:

Parameter	Type	Description	Value
healthType	Byte	Health data type	Heart Rate: CmdConstants.JL_HR_DATA_TRANSFER_KEY Blood Oxygen: CmdConstants.JL_BO_DATA_TRANSFER_KEY HRV: CmdConstants.JL_HRV_DATA_TRANSFER_KEY Stress: CmdConstants.JL_PRESSURE_DATA_TRANSFER_KEY Blood Sugar: CmdConstants.JL_BLOODSUGAR_DATA_TRANSFER_KEY
testStatus	Byte	Start/Stop	Start: 1 Stop: 0

#### Example of usage:

```
// Start heart rate test
DHBLESdk.subscribeData(healthDataBroCallback) // Monitor real-time health data
return
DHBLESdk.subscribeData(testHrCallback) // Monitor control command results
DHBLESdk.controlHealthDataJL(CmdConstants.JL_HR_DATA_TRANSFER_KEY, 1)

// Stop heart rate test
DHBLESdk.subscribeData(testHrCallback)
DHBLESdk.controlHealthDataJL(CmdConstants.JL_HR_DATA_TRANSFER_KEY, 0)

// Monitor real-time value changes during measurement
private val healthDataBroCallback by lazy {
 object : HealthDataBroCallback{
 override fun onResult(data: HealthDataSyncBean?) {
 data?.let {
 when (it.dataType) {
 Constants.RingHealthType.HR -> { //Heart Rate
 Log.e("qob", "Output: hr Value " + it.hrPartData.last().hr)
 }
 Constants.RingHealthType.HRV -> { //HRV
 Log.e("qob", "Output: HRV Value " + it.hrPartData.last().hr)
 }
 Constants.RingHealthType.BLOOD_OXY -> { //Blood Oxygen (blood oxygen)
 Log.e("qob", "Output: Blood Oxygen Value " + it.boPartData.last().bo)
 }
 Constants.RingHealthType.PRESSURE -> { //Pressure Stress
 Log.e("qob", "Output: Stress Value " +
 it.pressurePartData.last().pressure)
 }
 Constants.RingHealthType.BLOOD_SUGAR -> { //blood sugar BloodSugar
 Log.e("qob", "Output: BloodSugar Value " +
 it.tempPartData.last().temp)
 }
 Constants.RingHealthType.MUSLIM_COUNT -> { //Muslim Count
 Log.e("qob", "Zan Nian Value " + it.muslimCountPartData.count)
 }
 }
 }
 }
 }
}
```

```

 else -> {

 }
 }
}
}
override fun onFail(errorCode: Int) {

}

override fun onSuccess() {

}

}
}

//Listen to the test completion results
private val testHrCallback by lazy {
 object : HealthDataControlCallback {
 override fun onSuccess() {
 Log.e("qob", "Output: HealthDataControlCallback Control onSuccess")
 }

 override fun onResult(data: Int?) {
 Log.e("qob", "Output: HealthDataControlCallback onResult " + data)
 data?.let {
 if (data >= 10){
 Log.e("qob", "Output: Measurement completed")
 }
 }
 }

 override fun onFail(errorCode: Int) {

 }
 }
}

```

### 3.2.2.2 Continuous monitoring - Set the interval for continuous monitoring of health data.

Set the monitoring interval for health data (heart rate, blood oxygen, HRV, stress, blood glucose) throughout the day, in minutes.

**Note: Currently, only the heart rate interval can be set to 30 minutes or 60 minutes. Other parameters (blood oxygen, HRV, stress, blood glucose) can only be set to on or off; the start and end times are fixed to cover the entire day and cannot be modified.**

#### 3.2.2.2.1 Heart rate detection settings and retrieval

The interval can only be set to 30 minutes or 60 minutes for heart rate; Subscription callback: `TimedHeartRateCallback`;

Method Description:

```
fun setTimedHeartRateJL(reminderBean: DrinkReminderBean)
```

```
fun getTimedHeartRateJL()
```

Parameter Description:

Parameter	Type	Description	Value
reminderBean	DrinkReminderBean	class	isOpen: true (on) / false (off) remindDuration: Interval time 30 or 60 minutes startHour: 0 (fixed, cannot be modified) startMin: 0 (fixed, cannot be modified) endHour: 23 (fixed, cannot be modified) endMin: 59 (fixed, cannot be modified);

Example of usage:

```
// 1. Set HeartRate Monitor(设置心率监听)
DHBleSdk.subscribeData(hrMonitorCallback)
val hrMonitorBean = DrinkReminderBean()
hrMonitorBean.isOpen = true //Heart rate monitoring switch
hrMonitorBean.remindDuration = 60 //Heart rate monitoring interval unit is
minutes, only 30 minutes and 60 minutes
hrMonitorBean.startHour = 0 //fixed
hrMonitorBean.startMin = 0 //fixed
hrMonitorBean.endHour = 23 //fixed
hrMonitorBean.endMin = 59 //fixed
DHBleSdk.setTimedHeartRateJL(hrMonitorBean)

//1. get HeartRate Monitor
DHBleSdk.subscribeData(hrMonitorCallback)
DHBleSdk.getTimedHeartRateJL()
```

### 3.2.2.2 Blood oxygen monitoring settings and data retrieval

Interval blood oxygen measurement can only be set to 60 minutes; Subscription callback:

```
TimedBloodOxygenCallback;
```

Configuration table properties: `isBloodOxy`;

Method Description:

```
fun setTimedBloodOxygenJL(reminderBean: DrinkReminderBean)
```

```
fun getTimedBloodOxygenJL()
```

Parameter Description:

Parameter	Type	Description	Value
reminderBean	DrinkReminderBean	Class	isOpen: true/false (on/off) remindDuration: Interval time, fixed at 60 minutes startHour: 0 (fixed, cannot be modified) startMin: 0 (fixed, cannot be modified) endHour: 23 (fixed, cannot be modified) endMin: 59 (fixed, cannot be modified);

Example of usage:

```
// 2. Set Blood Oxygen Monitor
DHBLESdk.subscribeData(timedBloodOxygenCallback)
val healthMonitorBean = DrinkReminderBean()
healthMonitorBean.isOpen = true //Blood oxygen monitoring switch
healthMonitorBean.remindDuration = 60 //fixed 60 minutes
healthMonitorBean.startHour = 0 //fixed
healthMonitorBean.startMin = 0 //fixed
healthMonitorBean.endHour = 23 //fixed
healthMonitorBean.endMin = 59 //fixed
DHBLESdk.setTimedBloodOxygenJL(healthMonitorBean)

//2. Get Blood Oxygen Monitor settings
DHBLESdk.subscribeData(timedBloodOxygenCallback)
DHBLESdk.getTimedBloodOxygenJL()
```

### 3.2.2.2.3 Heart Rate Variability (HRV) Detection Settings and Retrieval

The HRV interval can only be set to 60 minutes; Subscription callback: `TimedHrvCallback`;

Configuration table properties: `isHrv`;

Method Description:

```
fun setTimedHRVJL(reminderBean: DrinkReminderBean)
```

```
fun getTimedHRVJL()
```

Parameter Description:

Parameter	Type	Description	Value
reminderBean	DrinkReminderBean	Class	isOpen: true/false remindDuration: Interval time, fixed at 60 minutes startHour: 0 (fixed, cannot be modified) startMin: 0 (fixed, cannot be modified) endHour: 23 (fixed, cannot be modified) endMin: 59 (fixed, cannot be modified);

Example of usage:

```
// 3. Set HRV Monitor
DHBLESdk.subscribeData(hrvDataCallback)
val healthMonitorBean = DrinkReminderBean()
healthMonitorBean.isOpen = true
healthMonitorBean.remindDuration = 60 //fixed 60 minutes
healthMonitorBean.startHour = 0 //fixed
healthMonitorBean.startMin = 0 //fixed
healthMonitorBean.endHour = 23 //fixed
healthMonitorBean.endMin = 59 //fixed
DHBLESdk.setTimedHRVJL(healthMonitorBean)

//3. Get HRV Monitor
DHBLESdk.subscribeData(hrvDataCallback)
DHBLESdk.getTimedHRVJL()
```

### 3.2.2.2.4 Stress Detection Settings and Retrieval

The interval pressure can only be set to 60 minutes; Subscription callback:

```
TimedStressCallback;
```

Configuration table properties: `isPressure` ;

Method Description:

```
fun setTimedStressJL(reminderBean: DrinkReminderBean)
```

```
fun getTimedStressJL()
```

Parameter Description:

Parameter	Type	Description	Value
reminderBean	DrinkReminderBean	Class	isOpen: true/false (on/off) remindDuration: fixed interval of 60 minutes startHour: 0 (fixed, cannot be modified) startMin: 0 (fixed, cannot be modified) endHour: 23 (fixed, cannot be modified) endMin: 59 (fixed, cannot be modified);

Example of usage:

```
// 4. Set stress monitoring
DHBLESdk.subscribeData(stressDataCallback)
val healthMonitorBean = DrinkReminderBean()
healthMonitorBean.isOpen = true //Stress monitoring switch
healthMonitorBean.remindDuration = 60 //fixed 60 minutes
healthMonitorBean.startHour = 0 //fixed
healthMonitorBean.startMin = 0 //fixed
healthMonitorBean.endHour = 23 //fixed
healthMonitorBean.endMin = 59 //fixed
DHBLESdk.setTimedStressJL(healthMonitorBean)

//4. Get stress monitoring
DHBLESdk.subscribeData(stressDataCallback)
DHBLESdk.getTimedStressJL()
```

### 3.2.2.2.5 Blood Glucose Monitoring Settings and Retrieval

The blood glucose measurement interval can only be set to 60 minutes; Subscription callback: `TimedBloodSugarCallback`;

Configuration table properties: `isBloodSugar` ;

Method Description:

```
fun setTimedBloodSugarJL(reminderBean: DrinkReminderBean)
```

```
fun getTimedBloodSugarJL()
```

Parameter Description:

Parameter	Type	Description	Value
reminderBean	DrinkReminderBean	Class	isOpen: true/false remindDuration: Fixed interval of 60 minutes startHour: 0 (fixed, cannot be modified) startMin: 0 (fixed, cannot be modified) endHour: 23 (fixed, cannot be modified) endMin: 59 (fixed, cannot be modified);

Example of usage:

```
// 5. Set blood sugar monitoring
DHBLESdk.subscribeData(bloodSugarDataCallback)
val healthMonitorBean = DrinkReminderBean()
healthMonitorBean.isOpen = true //Blood sugar monitoring switch
healthMonitorBean.remindDuration = 60 //fixed 60 minutes
healthMonitorBean.startHour = 0 //fixed
healthMonitorBean.startMin = 0 //fixed
healthMonitorBean.endHour = 23 //fixed
healthMonitorBean.endMin = 59 //fixed
DHBLESdk.setTimedBloodSugarJL(healthMonitorBean)

//5. Get blood sugar monitoring
DHBLESdk.subscribeData(bloodSugarDataCallback)
DHBLESdk.getTimedBloodSugarJL()
```

### 3.2.2.3 All-day Monitoring - Synchronize Health History Data

Synchronizing all health history data will **automatically retrieve health data of supported types according to the configuration table**; calling `syncAllHealthData` will retrieve health data sequentially and provide the results through the `HealthDataSyncCallback` callback.

`fun removeHealthDataCallBack(syncCallback: HealthDataSyncCallback)` removes the callback;

Interface Description:

```
DHBLESdk.syncAllHealthData(this)
```

Example of usage:

```
DHBLESdk.syncAllHealthData(this)

public interface HealthDataSyncCallback {
 void onSyncProgress(int var1); // Sync progress

 void onSyncFinish(); // Sync complete

 void onSyncError(int var1);

 void onSyncStep(List<StepSyncBean> var1);

 void onSyncSleep(List<SleepSyncBean> var1);

 void onSyncHr(List<HeartRateSyncBean> var1); // Heart rate
```



```

void onSyncBp(List<BloodPressSyncBean> var1);

void onSyncBo(List<BloodOxySyncBean> var1); // Blood oxygen

void onSyncTemp(List<BodyTempSyncBean> var1);

void onSyncPressure(List<PressureSyncBean> var1); // Pressure

void onSyncBloodSugar(List<BloodSugarSyncBean> var1); // Blood sugar

void onSyncBreath(List<BreatheSyncBean> var1);

void onSyncHrv(List<HrvSyncBean> var1); // HRV

void onSyncMuslimCount(List<MuslimCountSyncBean> var1); // Dhikr count
}

```

### 3.2.2.3.1 Obtaining Single Health Data Content

#### ⚠ Caution

The device must support the corresponding health data type; unsupported types will not be synchronized;

Interface Description:

```
fun syncHealthDataByType(type: Int, syncCallback: HealthDataSyncCallback)
```

Parameter Description:

Parameter	Type	Description	Value
type	Int	Integer	See the definitions in <code>RingHealthType</code> ;

Example of usage:

```

// Get today's step data
DHBleSdk.syncHealthDataByType(Constants.RingHealthType.TODAY_STEP, this)

```

### 3.2.2.4 All-Day Monitoring - Health Data Description

1. Today's and historical step count data void onSyncStep(List var1)

#### ⚠ Caution

If there is historical data, the callback will be triggered twice. The first time is for today's data, which will only contain one day's data; the second time is for historical step count data, which may return data for multiple days;

```

public class StepSyncBean {
 private long time; // Date timestamp
 private int totalSteps; // Total steps
}

```

```

private int totalCalorie; // Total calories (cal)
private int totalDistance; // Total distance (m)
private int itemCount; // Number of data points
private List<StepItemBean> items; // Step details, hourly step count data;

private String date;
private String hour;
}

public class StepItemBean {
 private int index; // Hour index (0-23, representing 0-23 hours)
 private int steps; // Steps
 private int calorie; // Calories
 private int distance; // Distance
}

```

2. void onSyncSleep(List var1);

#### ⚠ Caution

Returns all sleep status data for multiple days from the device;

```

public class SleepSyncBean {
 private long time; // Sleep day timestamp in seconds (s)
 private long totalSleepTime; // Total sleep duration in minutes (min)
 private long asleepTime; // Sleep start timestamp
 private long awakeTime; // Sleep end timestamp
 private int itemCount; // Number of sleep states
 private List<SleepItemBean> items; // Detailed sleep state values
}

public class SleepItemBean {
 private int len; // Duration of the current sleep type in minutes (min)
 private int sleepType; // Sleep type: 0 for awake, 1 for light sleep, 2 for
deep sleep, 3 for REM
}

```

3. Heart rate data void onSyncHr(List var1)

#### ⚠ Caution

Returns data for multiple days (today and historical); distinguish between days based on the time.

```

public class HeartRateSyncBean {
 private long time; // Date timestamp
 int itemCount; // Data quantity

 private List<HeartRateItemBean> items; // Data items, corresponding to heart
rate values for each day
}

```

```

}

public class HeartRateItemBean {
 private long timeMills; // Timestamp
 private int hr;

 private String date;
 private String hour;
}

```

**Heart Rate Variability (HRV)** `HrvSyncBean`, **Blood Oxygen** `BloodOxySyncBean`, **Blood Pressure** `BloodPressSyncBean`, **Blood Sugar** `BloodSugarSyncBean` are similar to heart rate and will not be described individually.

4. Dhikr Data void onSyncMuslimCount(List var1)

```

public class MuslimCountSyncBean {
 private long time; // Date timestamp
 private int itemCount; // Data quantity
 private int totalCount; // Total data quantity
 private List<MuslimCountItemBean> items;
}

public class MuslimCountItemBean {
 private long timeMills; // Test time timestamp (seconds)
 private int count; // Count; cumulative Dhikr count per hour;

 private String date;
 private String hour;
}

```

### 3.2.3 OTA Upgrade

#### Note

The OTA update file must be obtained from the manufacturer and tested thoroughly before proceeding with the update. This is to prevent update errors and device malfunction.

```

PXIOtaService.startPXIFileSyncing(otaPath, dialTransferCallback);

/**
 * File transfer progress monitoring
 */
private val dialTransferCallback by lazy {
 object : OnFileTransferCallback {
 override fun onProgress(pro: Float) {
 }

 override fun onFinish() {
 }

 override fun onFail(code: Int) {
 }
 }
}

```

```
}
```

### 3.2.4 Sport Workout

#### ⚠ Caution

The configuration table property supporting multiple sports is `isNewSport`. After enabling multi-sport mode, the device will enter exercise mode. Neither disconnecting the app nor closing it will stop the activity; it can only be stopped manually through the app or the device itself. Therefore, for devices with multi-sport functionality, please check the status after connecting to determine if it is currently in exercise mode, as this may affect the use of other functions.

#### 3.2.4.1 Obtain the device's multiple motion states.

Check if the device is currently engaged in multiple activities; only start a new activity if it's not currently engaged in any activity.

Subscribe to `SportGetControlCallback` to receive the results.

Method Description:

```
fun controlGetSportJLData()
```

Parameter Description:

WorkoutControlType Enum	Type	Description	Value
Workout_Begin	Int	Integer	Start workout
Workout_Continue	Int	Integer	Continue workout
Workout_Pause	Int	Integer	Pause workout
Workout_Finish	Int	Integer	End workout

Example of usage:

```
private val sportGetCallback by lazy {
 object : SportGetControlCallback {
 override fun onSuccess() {
 Log.e("RWSDK", "SportGetControlCallback onSuccess")
 }

 override fun onFail(errorCode: Int) {

 }

 override fun onResult(data: NewSportBean) {
```

```

 val bleActivityMode = BleActivityMode.fromValue(data.sportType)
 val tControlType = WorkoutControlType.fromValue(data.status)

 Log.e("RWSDK", "SportGetControlCallback onResult " + bleActivityMode + " "
+ tControlType)

 //0x01 Start 0x03 Pause 0x02 Continue 0x04 End
 if (tControlType?.isInRunning == true) {
 // In workout, directly enter the workout activity

 val intent = Intent(this@WorkoutTypeActivity,
WorkoutRunningActivity::class.java).apply {
 putExtra("bleActivityMode", bleActivityMode?.value)
 putExtra("controlType", tControlType.value)
 }
 startActivity(intent)
 }
 else{
 if (isItemClick){
 isItemClick = false

 DHBleSdk.subscribeData(sportControlCallback)
 DHBleSdk.controlSportJL(mBleActivityMode!!.value.toByte(),

WorkoutControlType.Workout_Begin.value.toByte())
 }
 }
 }
}

DHBleSdk.subscribeData(sportGetCallback)
DHBleSdk.controlGetSportJLData()

```

### 3.2.4.2 Control the device to enter multi-sport mode

The control device enters multi-motion mode and starts the motion.

Changes in sports data are received through subscriptions via `SportDataPushCallback` notifications.

Subscribe to `SportControlCallback` to receive the results.

Method Description:

```
fun controlSportJL(sportType: Byte, sportStatus: Byte)
```

Parameter Description:

Parameter	Type	Description	Value
sportType	BleActivityMode	Sport Type	sportType: Refer to BleActivityMode
sportStatus	WorkoutControlType	Sport Status	sportStatus: Start, Pause, Resume, End; Refer to WorkoutControlType

SportDataPushCallback Sport data change notification return data SportDataPushBean  
description:

SportDataPushBeanParameter	Type	Description	Value
ActivityTime	Int	Integer	Duration of exercise, unit seconds (s);
ActivitySteps	Int	Integer	Number of steps during exercise
ActivityDistance	Int	Integer	Distance covered during exercise, unit meters (m);
ActivityCalorie	Int	Integer	Calories burned during exercise, unit calories (cal);
ActivityHr	Int	Integer	Dynamic heart rate during exercise

Example of usage:

```
DHBleSdk.subscribeData(sportControlCallback)
DHBleSdk.controlSportJL(mBleActivityMode!!.value.toByte(),
 WorkoutControlType.Workout_Begin.value.toByte())

private val sportRealPushCallback by lazy {
 object : SportDataPushCallback {
 override fun onSuccess() {
 Log.e("RWSDK", "SportDataPushCallback onSuccess")
 }

 override fun onFail(errorCode: Int) {
 Log.e("RWSDK", "SportDataPushCallback onFail: $errorCode")
 }

 override fun onResult(data: SportDataPushBean) {
 runOnUiThread {
 // Update sport type and control status
 updateData(data)
 }
 }
 }
}

// Subscribe to real-time sport data
DHBleSdk.subscribeData(sportRealPushCallback)
```

**Note:** The corresponding names for BleActivityMode can be found in the example Demo strings.xml file: `<string-array name="j1running_string_array">`

### 3.2.4.3 Control enabling/disabling real-time sport data notifications from the device

Control the real-time notification of motion data when the device is turned on/off;

Changes in sports data are received through subscriptions via `SportDataPushCallback` notifications. Sometimes, when the app is closed or running in the background, you can instruct the device to stop sending data notifications.

Method Description:

```
fun setExerciseMore(type: Int)
```

Parameter Description:

Parameter	Type	Description	Value
type	Int	Integer	1: Enable notification of exercise data; 0: Disable notification of exercise data;

Example of usage:

```
// Exit exercise interface
DHBleSdk.setExerciseMore(0)
```

#### 3.2.4.4 Get Multi-Sport Data Report

Subscribe to `BrightLedLevelCallback` to receive the results.

Method Description:

```
fun getSport3ResultJL()
```

return SportResultBean Parameter Description:

SportResultBean Parameter	Type	Value
startTime	long	Exercise start time timestamp, in seconds (s)
exerciseTime	long	Exercise duration, in seconds (s)
workModel	BleActivityMode	Type of exercise
step	Int	Number of steps, unit: steps
distance	Int	Distance, meters (m)
calorie	Int	calories, cal
viewType	Int	Current exercise types include/exclude steps, cadence, pace, and distance: With cadence: viewTypeHaveStepFaq: Without step count: viewTypeNoStepNum: With pace: viewTypeHavePace: Without distance: viewTypeNoDistance:
newSportHrs	Array	The current list of heart rates generated during exercise, saved every minute;
.....		Other attributes can be found in the class documentation.

Example of usage:

```
private val sportResult3Callback by lazy {
 object : Sport3ResultCallback {
 override fun onSuccess() {
 Log.e("RWSDK", "Sport3ResultCallback onSuccess")
 }

 override fun onFail(errorCode: Int) {
 Log.e("RWSDK", "Sport3ResultCallback onFail " + errorCode)
 finish()
 }

 override fun onResult(data: List<SportResultBean>) {
 Log.e("RWSDK", "Sport3ResultCallback onResult " + data.size)
 //Save Data
 finish()
 }
 }
}
```

## Summary of Adaptation Changes for SDK V2.0.0

### Important

SDK V2.0.0 mainly introduces a **feature configuration table**, optimizes Bluetooth data transmission, supports **automatic synchronization of supported health data without blocking**, and allows **sending other data simultaneously**.

It also adds new APIs such as **multi-sport support**.

Customers who need to integrate the new version should adapt to the following differences.

The detailed changes are listed below:

1. Device connection API has been changed  
from `ConnectBleService.getService().connectDevice()` to  
`DHBleSdk.connectDeviceWithModel()`.
2. Device disconnection API has been changed from  
`ConnectBleService.getService().disconnect()` to  
`DHBleSdk.disconnect()`.
3. Connection callback registration has been changed from  
`ConnectBleService.getService().registerScanBleCallback(this)`  
to  
`DHBleSdk.setConnectBleCallback(this)`.
4. Connection callback interface has been changed from `ConnectBleCallback` to  
`RingConnectBleCallback`.
5. The **login and time synchronization APIs have been removed**.  
Time synchronization is now performed automatically after the device is connected.



6. A **feature configuration table** has been added.  
App UI display and feature usage should now be determined based on the device's supported features via `SupportMenuBean`.
7. The manual interface for selecting which health data types to synchronize has been removed and replaced with **automatic recognition**.  
The following interface has been deprecated:

```
fun syncAllHealthData(
 supportStress: Boolean, // Support stress
 supportBloodSugar: Boolean, // Support blood sugar
 supportMuslimPraise: Boolean, // Support Muslim praise
 syncCallback: HealthDataSyncCallback // Callback
)
```

## SDK修订记录

版本	内容描述	修订日期
blesdk-release-241201.aar	1. 添加电子烟新功能;	2024.12.01
blesdk-release-250418.aar	2. 添加戒指产品功能;	2025.04.08
blesdk-release-250723.aar	3. 添加Muslim定制产品相关功能;	2025.07.23
blesdk-release-250811.aar	1. 添加muslim定制接口; 2. 添加健康数据文档说明;	2025.08.12
blesdk-release-250821.aar	1. 赞念可设置测试值; 2. 睡眠从onSyncSleep返回; 3. 启动单次赞念也实时同步数据; 4. 获取目标与模式时返回模式值;	2025.08.21
blesdk-release-250827.aar	1. Vape 修改;	2025.08.27
blesdk-release-260105.aar	1. 设置亮屏时长导致睡眠模式问题;	2026.01.05
blesdk-release-260130.aar	V2.0.0_20260130 1. 加sdk 版本号接口; 2. 加功能配置表; 3. 加震动,睡眠模式,亮屏时长,抬腕亮屏, 消息推送,心率血氧报警等设置新功能指令; 4. 加多运动功能;	2026.01.30

