A8.3 User-defined signaling

Optionally, the AXI4 interface signal set can include a set of User-defined signals, called the User signals, on each AXI4 channel.

Generally, this specification recommends that the User signals are not used, because the AXI protocol does not define the functions of these signals and this can lead to interoperability issues if two components use the same User signals in an incompatible manner.

A8.3.1 Signal naming

The User signal names defined for each AXI4 channel are:

AWUSER Write address channel User signals.

ARUSER Read address channel User signals.

WUSER Write data channel User signals.

RUSER Read data channel User signals.

BUSER Write response channel User signals.

In this specification, **AxUSER** indicates **AWUSER** or **ARUSER**.

A8.3.2 Usage considerations

Where User signals are implemented it is not required that User signals are supported on all channels. That is, the design decision whether to include User signals is made independently for each channel.

This specification recommends including User signals on an interconnect, however, there is no requirement to include them on masters or slaves.

This specification recommends that interconnect components include support for User signals, so that they can be passed between master and slave components. The width of the User-defined signals is IMPLEMENTATION DEFINED and can be different for each of the channels.

Copyright © 2003, 2004, 2010, 2011 ARM. All rights reserved.
Non-Confidential

Chapter A9
Low-power Interface

This chapter describes the AXI low-power interface that can provide control, during entry into and exit from a low-power state. It contains the following sections:

- *About the low-power interface* on page A9-102
- *Low-power clock control* on page A9-103.

Copyright © 2003, 2004, 2010, 2011 ARM. All rights reserved.
Non-Confidential