C2.1 Changes to existing AXI4 channels

The following subsections introduce the additional signals defined by ACE on the AXI4 channels:

- *Read address channel (AR) signals*
- *Write address channel (AW) signals*
- *Read data channel (R) signals*.

Note

There are no additional signals on the write data channel (W) or the Write response channel (B).

See Chapter A2 *Signal Descriptions* for the remaining signals on the AXI4 channels.

C2.1.1 Read address channel (AR) signals

Table C2-1 shows the additional signals on the read address channel. See *Read and write address channel signaling* on page C3-158.

Table C2-1 Read address channel signals

Signal	Source	Description
ARSNOOP[3:0]	Master	This signal indicates the transaction type for shareable read transactions.
ARDOMAIN[1:0]	Master	This signal indicates the shareability domain of a read transaction.
ARBAR[1:0]	Master	This signal indicates a read barrier transaction.

C2.1.2 Write address channel (AW) signals

Table C2-2 shows the additional signals on the write address channel. See *Read and write address channel signaling* on page C3-158.

Table C2-2 Write address channel signals

Signal	Source	Description
AWSNOOP[2:0]	Master	This signal indicates the transaction type for shareable write transactions.
AWDOMAIN[1:0]	Master	This signal indicates the shareability domain of a write transaction.
AWBAR[1:0]	Master	This signal indicates a write barrier transaction.

C2.1.3 Read data channel (R) signals

Table C2-3 shows the additional signals on the read data channel. See *Read data channel signaling* on page C3-167.

Table C2-3 Read data channel signals

Signal	Source	Description
RRESP[3:2]	Interconnect	Read response. The additional read response bits provide the information required to complete a shareable read transaction.

Copyright © 2003, 2004, 2010, 2011 ARM. All rights reserved.
Non-Confidential