

[Type here]



LESTER B. PEARSON
Pearson Electrotechnology Centre

Installation and Repair of Telecommunications Equipment
Module 21
Telephone network systems installation

VOIP lab experiment#5

Installing IP Phone

Installation and Repair of Telecommunications Equipment

Name of student:_____

Group Number:_____

Date:_____

[Type here]



LESTER B. PEARSON
Pearson Electrotechnology Centre

Installation and Repair of Telecommunications Equipment

Module 21

Telephone network systems installation

The purpose of the lab is to install an IP Phone in the PBX.

Install a patch cable to make the IP Phone work.

Check the phone IP address using the menu key then status (1)

Open Google Chrome and type the IP address.

1- The default User is admin and the password is admin

← → ↻ ⚠ Not secure | https://192.168.100.120/servlet?m=mod_listener&p=login&q=loginForm&jumpto=status

Login

Classic IP Phone SIP-T31P

Username

Password

[Type here]



LESTER B. PEARSON
Pearson Electrotechnology Centre

Installation and Repair of Telecommunications Equipment

Module 21

Telephone network systems installation

The image shows the Yealink T31P web interface for configuring an account. The top navigation bar includes 'Status', 'Account', 'Network', 'Dsskey', 'Features', and 'Settings'. The 'Account' tab is selected. On the left, there is a sidebar with 'Register', 'Basic', 'Codec', and 'Advanced' options. The main content area is titled 'Account' and shows a dropdown for 'Account1'. Below this, there are fields for 'Register status' (Registered), 'Line Active' (Enabled), 'Label' (Teacher), 'Display Name' (Teacher), 'Register Name' (1000), 'Username' (1000), and 'Password' (masked with dots). Under the 'SIP Server 1' section, there are fields for 'Server Host' (192.168.100.10), 'Port' (5060), 'Transport' (UDP), 'Server Expires' (3600), and 'Server Retry Counts' (3). A warning message at the top right states 'Default password is in use. Please change it.'.

Account	
Register status	Registered
Line Active	Enabled
Label	Teacher
Display Name	Teacher
Register Name	1000
Username	1000
Password	*****
SIP Server 1	
Server Host	192.168.100.10
Port	5060
Transport	UDP
Server Expires	3600
Server Retry Counts	3

- 2- Complete all information based on extension that you created
- 3- Click Confirm