**FUSES (PDC)**

| FUSE NO. | AMPS | FUSED CIRCUIT | FUNCTION |
|---|---|---|---|
| 1 | 40A | A502 12RD/LG | FUSED B(+) |
| 2 | 40A | A902 12RD | FUSED B(+) |
| 3 | 40A | A906 12RD | FUSED B(+) |
| 4 | 40A | A16 12GY (2.4L) | FUSED B(+) |
| 5 | 20A | A30 16RD/WT (A/T) | FUSED B(+) |
| 6 | 40A | A8 14RD | FUSED B(+) |
| 7 | - | - | - |
| 8 | 40A | A107 12TN/RD (ABS) | FUSED B(+) |
| 9 | 20A | A209 18RD/YL | FUSED B(+) |
| 9 | 20A | A209 18RD (42RLE) | FUSED B(+) |
| 9 | 20A | A209 18RD/YL (NA1) | FUSED B(+) |
| 10 | 40A | A940 12RD | FUSED B(+) |
| 11 | - | - | - |
| 12 | 30A | A111 12DG/RD (ABS) | FUSED B(+) |
| 13 | 40A | A991 12RD | FUSED B(+) |
| 14 | - | - | - |
| 15 | 50A | INTERNAL | FUSED B(+) |
| 16 | - | - | - |
| 17 | 20A | A205 18RD/OR | FUSED B(+) |
| 18 | 20A | A43 18RD/DG | FUSED B(+) |
| 18 | 20A | A43 18RD/DG | FUSED B(+) |
| 19 | 20A | A39 18RD/DG (OPTION 1) | FUSED B(+) |
| 19 | 20A | A39 16RD/DG (OPTION 2) | FUSED B(+) |
| 20 | 15A | F306 16DB/PK | FUSED B(+) |
| 21 | 10A | A926 20RD | FUSED B(+) |
| 22 | 25A | A1 16RD | FUSED B(+) |
| 23 | 20A | A930 18RD | FUSED B(+) |
| 24 | 20A | INTERNAL (OFF-ROAD PACKAGE) | FUSED B(+) |
| 25 | - | - | - |
| 26 | 10A | M21 20YL/BR | FUSED B(+) |
| 27 | 20A | A701 18BR/RD | FUSED B(+) |
| 28 | 10A | K900 20DB/DG | SENSOR GROUND |
| 28 | 10A | Y3 18LG | FUSED SENSOR GROUND |
| 28 | 10A | Y3 20LG | FUSED SENSOR GROUND |

**FOG LAMP RELAY (IN PDC)**

| CAV | CIRCUIT | FUNCTION |
|---|---|---|
| B16 | L139 18WT/YL | FOG LAMP SWITCH SIGNAL |
| B17 | - | - |
| B18 | L300 14LG/WT | DIMMER SWITCH HIGH BEAM OUTPUT |
| B18 | L340 14WT/OR (DRL) | HIGH BEAM INDICATOR DRIVER |
| B19 | L39 18WT/OR | FOG LAMP RELAY OUTPUT |
| B20 | Z901 18BK | GROUND |

**FRONT LOCKER RELAY (OFF-ROAD PACKAGE)**

| CAV | CIRCUIT | FUNCTION |
|---|---|---|
| D10 | INTERNAL | FUSED B(+) |
| D11 | G304 20VT/DB | FRONT LOCKER REQUEST |
| D12 | - | - |
| D13 | INTERNAL | FUSED B(+) |
| D14 | A750 18TN/RD | FRONT LOCKER RELAY OUTPUT |