

Error Codes

Contents

Error Codes

- SYSCON Error Codes
- Generic errors
- PSN Network errors
- System Update errors with HTTP Server
- Subdisplay errors (PSP/Remoteplay)
- Network errors
- SSC SPU errors
- SSC GPU errors
- AV Chat 2 errors
- Gameupdate errors
- Sysutil Accesspoint errors (PSP/Remoteplay)
- Background Download Utility errors
- Video Upload Utility errors
- USB PSP Connection Manager errors (PSP/Remoteplay)
- USB errors
- LIBMIXER errors
- SYNTH2 errors
- SND3 errors
- AUDIO errors
- VOICE errors
- MicIn errors
- CAMERA errors
- MicIn DSP errors
- Face Recognition errors
- Head Tracker errors
- Face Tracker errors
- Debug errors
- DEC13 errors
- FIOS errors
- CXML errors
- SPASM errors/warnings
- Game Content Utility errors
- System Cache Utility errors
- Ftp Service events
- File System errors
- Flash errors
- Cg Compiler errors
- CG API errors
- GCM errors
- PSGL HW Cursor errors
- Resizer errors
- DBG_RSX errors
- NVShaderPerf errors
- Font errors
- Gifdec errors
- Jpgdec errors
- Jpgenc errors
- Pngdec errors
- Pngenc errors
- GLES errors
 - EGL errors
 - GL errors
- PSGL errors
- PSGL Utility errors
- Content Search Utility errors
- Music Decode errors
- Music Playback errors
 - Using memory container
 - Not using memory container
- Music Export Utility errors
- Photo Utility errors
 - Export errors
 - Import errors
 - Decode errors
- Screenshot Utility errors
- Video Utility errors
- Hash Function errors
- KB errors
- PAD errors
- MOUSE errors
- K2C errors
- PADFILTER errors

- GEM errors
- PERF errors
- Home coordination utility errors
- IMEJP utility errors
- L10n errors
- Pthread errors
- Scream / MultiStream errors
- Realtimeclock errors
- USERINFO errors
- Print Utility errors
 - Print ErrorStatus
 - Print Error
- Multistream errors
- Record Utility Error
- PRX Error
- Sysmodule Error
- System Utility Error
- System BGM Control Error
- COMBOPLAY errors
- SYSTEMPARAM errors
- MsgDialog Error
- SAVEDATA errors
- OSKDIALOG errors
- WEBBROWSER errors
- SYSCONF errors
- SYSCACHE errors
- STORAGEDATA errors
- CXML Error
- Media? Player Video Player Error
- DMA errors
- SYNC errors
- SHEAP errors
- OVIS errors
- Daisy errors (libdaisy)
- SPUDLL errors
- SPURS errors
- SWCACHE errors
- SYNC2 errors
- Fiber errors
- ADEC errors
- VDEC errors
- DMUX errors
- ATRAC errors
- PAMF errors
- VPOST errors
 - VPOST Library (PPM) errors
 - VPOST Library (Entry Module) errors
 - VPOST Library (IPC) errors
 - VPOST Library (Video Scaler) errors
 - VPOST Library (CSC) errors
- SAIL errors
- ATRACMULTI errors
- LPCM errors
- AT3 errors
- ATX errors
- M4AAC errors
- AC3 errors
- MP3 errors
- M2BC errors
- CELP errors
- CELP8 errors
- CELPENC errors
- CELP8ENC errors
- Console errors
- Other errors (not specified above)

Error Codes

Please update this page with any error codes you find the meaning for.

SYS CON Error Codes

Errorcode	Name
F0000000	Packet length is too long
F0000001	Wrong command format
F0000002	Command length > 11 / Wrong checksum
F0000003	Unknown Command
F0000004	?
F0000005	Not allowed/Not authorized
F0000006	Invalid arguments
F00000FF	BOOTENABLE failed
E00000A0	EEPROM GET/SET failed
E00000A1	R8/W8/R16/W16/R32/W32/RBE/WBE failed
E00000B0	VID GET failed
E00000B1	VID GET failed
E00000B2	CID GET failed
E00000B3	ECID GET failed
E00000B4	REV SB failed
E00000B5	KSV failed
E00000C0	AUTH1/2 failed
E00000C2	AUTHVER GET failed
E00000C3	AUTHVER SET failed
E00000D0	FAN START/STOP failed
E00000D1	FAN START/STOP failed

- Valid only for the CXR Variant

Generic errors

Name	Errorcode	Remarks
EAGAIN	0x80010001	The resource is temporarily unavailable
EINVAL	0x80010002	Invalid argument or flag.
ENOSYS	0x80010003	The feature is not yet implemented // (on Retail/CEX or Debug/DEX) sys_fsw_connect_event() or sys_fsw_disconnect_event() was executed on a machine other than the Reference Tool
ENOMEM	0x80010004	Memory allocation failed.
ESRCH	0x80010005	The resource with the specified identifier does not exist.
ENOENT	0x80010006	The file does not exist Note : This error can happen when you try to install a pkg that have an invalid name.
ENOEXEC	0x80010007	The file is in unrecognized format / The file is not a valid ELF file. (running a self from a higher sdk version on a lower fw version causes this)
EDEADLK	0x80010008	Resource deadlock is avoided
EPERM	0x80010009	Operation not permitted An error occurred during the start operation (e.g.: debug self on retail)
EBUSY	0x8001000A	The device or resource is busy
ETIMEDOUT	0x8001000B	The operation is timed out
EABORT	0x8001000C	The operation is aborted
EFAULT	0x8001000D	Invalid memory access
ECHILD	0x8001000E	Try to access a non existing child process
ESTAT	0x8001000F	State of the target thread is invalid
EALIGN	0x80010010	Alignment is invalid
EKRESOURCE	0x80010011	Shortage of the kernel resources
EISDIR	0x80010012	The file is a directory
ECANCELED	0x80010013	Operation canceled
EEXIST	0x80010014	Entry already exists.(e.g.:"An error occurred during internal memory card creation."(80010014))
EISCONN	0x80010015	Port is already connected
ENOTCONN	0x80010016	Port is not connected
EAUTHFAIL	0x80010017	Failure in authorizing SELF. Program authentication fail (Error starting BluRay game)
ENOTMSELF	0x80010018	The file is not MSELF
ESYSVER	0x80010019	System version error
EAUTHFATAL	0x8001001A	Fatal system error occurred while authorizing SELF. SELF auth failure
EDOM	0x8001001B	Math domain violation
ERANGE	0x8001001C	Math range violation
EILSEQ	0x8001001D	Illegal multi-byte sequence in input
EFPOS	0x8001001E	File position error.
EINTR	0x8001001F	Syscall was interrupted.
EFBIG	0x80010020	File too large.
EMLINK	0x80010021	Too many links.
ENFILE	0x80010022	File table overflow.
ENOSPC	0x80010023	No space left on device.
ENOTTY	0x80010024	Not a TTY.
EPIPE	0x80010025	Broken pipe.
EROFS	0x80010026	Read-only filesystem (write fail).
ESPIPE	0x80010027	Illegal seek (e.g. seek on pipe).
E2BIG	0x80010028	Arg list too long.
EACCES	0x80010029	Access violation.
EBADF	0x8001002A	Invalid file descriptor.
EIO	0x8001002B	Filesystem mounting failed (actually IO error...EIO)
EMFILE	0x8001002C	Too many files open.
ENODEV	0x8001002D	No device.
ENOTDIR	0x8001002E	Not a directory.
ENXIO	0x8001002F	No such device or IO.
EXDEV	0x80010030	Cross-device link error.
EBADMSG	0x80010031	Bad Message.
EINPROGRESS	0x80010032	In progress.
EMSGSIZE	0x80010033	Message size error.
ENAMETOOLONG	0x80010034	Name too long.

Name	Errorcode	Remarks
ENOLCK	0x80010035	No lock.
ENOTEMPTY	0x80010036	Not empty.
EUNSUP	0x80010037	Not supported.
EFSSPECIFIC	0x80010038	File-system specific error.
EOVERFLOW	0x80010039	Overflow occurred.
ENOTMOUNTED	0x8001003A	Filesystem not mounted. "An error occurred during the install operation". E.G.: unplugged usb during install.
ENOTSDATA	0x8001003B	Not SData.
ESDKVER	0x8001003C	Incorrect version in sys_load_param.
ENOLICDISC	0x8001003D	Pointer is null. When related to PARAM.SFO : "to play this game, you must insert the following disc. Insert the disc, and then start the game again. (8001003D)": can be resolved by pointing to (only) other PARAM.SFO with Lxx folder. In this case, it's similar than 0x8001003E but with some PARAM.SFO parameter (TITLE_ID?) embedded. Refresh it by using this Lxx or others Tricks .
ENOLICENT	0x8001003E	Pointer is null. When related to DISC.SFO (and PARAM.SFO) : "to play this game, you must insert the following disc. Insert the disc, and then start the game again. (8001003E) Install disc" : can be resolved by launching BD emulator, or remove the disc.sfo if there are one, using the original disc or using the L** folder
	0x8001003F	

PSN Network errors

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_AUTH_EINVAL	0x8002A002	
SCE_NP_AUTH_ENOMEM	0x8002A004	
SCE_NP_AUTH_ESRCH	0x8002A005	
SCE_NP_AUTH_EBUSY	0x8002A00A	
SCE_NP_AUTH_EABORT	0x8002A00C	
SCE_NP_AUTH_EEXIST	0x8002A014	
SCE_NP_AUTH_EINVALID_ARGUMENT	0x8002A015	
Community client library error (0x8002a100 - 0x8002a1ff)		
SCE_NP_COMMUNITY_ERROR_ALREADY_INITIALIZED	0x8002A101	
SCE_NP_COMMUNITY_ERROR_NOT_INITIALIZED	0x8002A102	
SCE_NP_COMMUNITY_ERROR_OUT_OF_MEMORY	0x8002A103	
SCE_NP_COMMUNITY_ERROR_INVALID_ARGUMENT	0x8002A104	
SCE_NP_COMMUNITY_ERROR_NO_TITLE_SET	0x8002A105	
SCE_NP_COMMUNITY_ERROR_NO_LOGIN	0x8002A106	
SCE_NP_COMMUNITY_ERROR_TOO_MANY_OBJECTS	0x8002A107	
SCE_NP_COMMUNITY_ERROR_TRANSACTION_STILL_REFERENCED	0x8002A108	(obsolete)
SCE_NP_COMMUNITY_ERROR_ABORTED	0x8002A109	
SCE_NP_COMMUNITY_ERROR_NO_RESOURCE	0x8002A10A	
SCE_NP_COMMUNITY_ERROR_BAD_RESPONSE	0x8002A10B	Shows up when trying to view friends trophies, prc etc.
SCE_NP_COMMUNITY_ERROR_BODY_TOO_LARGE	0x8002A10C	
SCE_NP_COMMUNITY_ERROR_HTTP_SERVER	0x8002A10D	"An error occurred during communication with the server"/Shows up when trying to view friends profile person may be having internet service problems
SCE_NP_COMMUNITY_ERROR_INVALID_SIGNATURE	0x8002A10E	Issue syncing trophy data; trophy servers may be
SCE_NP_COMMUNITY_ERROR_TIMEOUT	0x8002A10F	Server timeout
SCE_NP_COMMUNITY_ERROR_INSUFFICIENT_ARGUMENT	0x8002A1A1	
SCE_NP_COMMUNITY_ERROR_UNKNOWN_TYPE	0x8002A1A2	
SCE_NP_COMMUNITY_ERROR_INVALID_ID	0x8002A1A3	
SCE_NP_COMMUNITY_ERROR_INVALID_ONLINE_ID	0x8002A1A4	Not signed into PSN
SCE_NP_COMMUNITY_ERROR_INVALID_TICKET	0x8002A1A5	
SCE_NP_COMMUNITY_ERROR_CLIENT_ALREADY_EXISTS SCE_NP_COMMUNITY_ERROR_CLIENT_HANDLE_ALREADY_EXISTS	0x8002A1A6	
SCE_NP_COMMUNITY_ERROR_INSUFFICIENT_BUFFER	0x8002A1A7	
SCE_NP_COMMUNITY_ERROR_INVALID_TYPE	0x8002A1A8	
SCE_NP_COMMUNITY_ERROR_TRANSACTION_ALREADY_END	0x8002A1A9	
SCE_NP_COMMUNITY_ERROR_TRANSACTION_BEFORE_END	0x8002A1AA	
SCE_NP_COMMUNITY_ERROR_BUSY_BY_ANOTHER_TRANSACTION	0x8002A1AB	
SCE_NP_COMMUNITY_ERROR_INVALID_ALIGNMENT	0x8002A1AC	
SCE_NP_COMMUNITY_ERROR_TOO_MANY_NPID	0x8002A1AD	
SCE_NP_COMMUNITY_ERROR_TOO_LARGE_RANGE	0x8002A1AE	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_COMMUNITY_ERROR_INVALID_PARTITION	0x8002A1AF	
SCE_NP_COMMUNITY_ERROR_TOO_MANY_SLOTID	0x8002A1B1	
SCE_NP_COMMUNITY_ERROR_INVALID_PSHANDLE	0x8002A1A4	obsolete (replaced by SCE_NP_COMMUNITY_ERROR_INVALID_ONLINE)
NP Authentication Error (server returned errors)		
SCE_NP_AUTH_ERROR_SERVICE_END	0x8002A200	Issue accessing PSN; PSN may be down or problem with internet connection; if issues continue, possible issue with SEN account
SCE_NP_AUTH_ERROR_SERVICE_DOWN	0x8002A201	
SCE_NP_AUTH_ERROR_SERVICE_BUSY	0x8002A202	PSN is busy
SCE_NP_AUTH_ERROR_SERVER_MAINTENANCE	0x8002A203	Server down due to maintenance
SCE_NP_AUTH_ERROR_INVALID_DATA_LENGTH	0x8002A210	
SCE_NP_AUTH_ERROR_INVALID_USER_AGENT	0x8002A211	
SCE_NP_AUTH_ERROR_INVALID_VERSION	0x8002A212	"An error has occurred. You have been signed out PSN" (8002A212)
SCE_NP_AUTH_ERROR_INVALID_SERVICE_ID	0x8002A220	Invalid ID
SCE_NP_AUTH_ERROR_INVALID_CREDENTIAL	0x8002A221	Invalid login (incorrect password or ID)
SCE_NP_AUTH_ERROR_INVALID_ENTITLEMENT_ID	0x8002A222	
SCE_NP_AUTH_ERROR_INVALID_CONSUMED_COUNT	0x8002A223	
SCE_NP_AUTH_ERROR_INVALID_CONSOLE_ID	0x8002A224	"An error has occurred. You have been signed out PSN" (8002A224) // Happens when you try to sign retail environment with CEX2DEX'ed console. Verify your console is using a valid IDPS.
SCE_NP_AUTH_ERROR_CONSOLE_ID_SUSPENDED	0x8002A227	"You cannot use PSN with this account" or "Access SEN from this system has been banned or temporarily suspended" // Console banned/suspended for Terms of Service and User Agreement violations
SCE_NP_AUTH_ERROR_ACCOUNT_CLOSED	0x8002A230	SEN account deleted
SCE_NP_AUTH_ERROR_ACCOUNT_SUSPENDED	0x8002A231	"You cannot use PSN with this account" or "Access SEN from this system has been banned or temporarily suspended" // Account suspended/banned
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_EULA	0x8002A232	Need to accept Terms of Service and User Agreement
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT1	0x8002A240	Need to accept updated PSN Terms of Service
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT2	0x8002A241	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT3	0x8002A242	Need to accept Terms of Service and User Agreement
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT4	0x8002A243	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT5	0x8002A244	Invalid console ID?
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT6	0x8002A245	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT7	0x8002A246	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT8	0x8002A247	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT9	0x8002A248	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT10	0x8002A249	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT11	0x8002A24A	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT12	0x8002A24B	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT13	0x8002A24C	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT14	0x8002A24D	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT15	0x8002A24E	
SCE_NP_AUTH_ERROR_ACCOUNT_RENEW_ACCOUNT16	0x8002A24F	
SCE_NP_AUTH_ERROR_SUB_ACCOUNT_RENEW_EULA		
SCE_NP_AUTH_ERROR_SUB_ACCOUNT_PW_???	0x8002A260	Occurs when you try to log in with wrong?/old? or renewed? password. fix: xmb->psn->forgot my password>reset via email->confirm
SCE_NP_AUTH_ERROR_PASSWORD_RESET_REQUIRED		
SCE_NP_AUTH_ERROR_UNKNOWN	0x8002A280	When privacypatching with MFW Builder partly an sign in spoofed
NP Core Server Error		
SCE_NP_CORE_SERVER_ERROR_BASE	0x8002A300	
SCE_NP_CORE_SERVER_ERROR_BAD_FORMAT	0x8002A301	
SCE_NP_CORE_SERVER_ERROR_BAD_NAMESPACE_PREFIX	0x8002A302	
SCE_NP_CORE_SERVER_ERROR_CONFLICT	0x8002A303	Already logged into another console
SCE_NP_CORE_SERVER_ERROR_CONNECTION_TIMEOUT	0x8002A304	
SCE_NP_CORE_SERVER_ERROR_HOST_GONE	0x8002A305	
SCE_NP_CORE_SERVER_ERROR_HOST_UNKNOWN	0x8002A306	
SCE_NP_CORE_SERVER_ERROR_IMPROPER_ADDRESSING	0x8002A307	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_CORE_SERVER_ERROR_INTERNAL_SERVER_ERROR	0x8002A308	PSN dropped out with this error after pulled 4.45-1 before 4.45-2-CEX release
SCE_NP_CORE_SERVER_ERROR_INVALID_FROM	0x8002A309	
SCE_NP_CORE_SERVER_ERROR_INVALID_ID	0x8002A30A	
SCE_NP_CORE_SERVER_ERROR_INVALID_NAMESPACE	0x8002A30B	
SCE_NP_CORE_SERVER_ERROR_INVALID_XML	0x8002A30C	
SCE_NP_CORE_SERVER_ERROR_NOTAUTHORIZED	0x8002A30D	
SCE_NP_CORE_SERVER_ERROR_POLICY_VIOLATION	0x8002A30E	
SCE_NP_CORE_SERVER_ERROR_REMOTE_CONNECTION_FAILED	0x8002A30F	
SCE_NP_CORE_SERVER_ERROR_RESOURCE_CONSTRAINT	0x8002A310	
SCE_NP_CORE_SERVER_ERROR_RESTRICTED_XML	0x8002A311	
SCE_NP_CORE_SERVER_ERROR_SEE_OTHER_HOST	0x8002A312	
SCE_NP_CORE_SERVER_ERROR_SYSTEM_SHUTDOWN	0x8002A313	
SCE_NP_CORE_SERVER_ERROR_UNDEFINED_CONDITION	0x8002A314	
SCE_NP_CORE_SERVER_ERROR_UNSUPPORTED_ENCODING	0x8002A315	
SCE_NP_CORE_SERVER_ERROR_UNSUPPORTED_STANZA_TYPE	0x8002A316	
SCE_NP_CORE_SERVER_ERROR_UNSUPPORTED_VERSION	0x8002A317	
SCE_NP_CORE_SERVER_ERROR_XML_NOT_WELL_FORMED	0x8002A318	
SCE_NP_CORE_SERVER_ERROR_UNSUPPORTED_CLIENT_VERSION	0x8002A319	
SCE_NP_CORE_SERVER_ERROR_INVALID_ACCOUNT_ID	0x8002A31A	
SCE_NP_CORE_SERVER_ERROR_INVALID_JID_NODE	0x8002A31B	
SCE_NP_CORE_SERVER_ERROR_BANNED_TICKET	0x8002A31C	
SCE_NP_CORE_SERVER_ERROR_SASL_ABORTED	0x8002A320	
SCE_NP_CORE_SERVER_ERROR_SASL_INCORRECT_ENCODING	0x8002A321	
SCE_NP_CORE_SERVER_ERROR_SASL_INVALID_AUTHORIZED	0x8002A322	
SCE_NP_CORE_SERVER_ERROR_SASL_INVALID_MECHANISM	0x8002A323	
SCE_NP_CORE_SERVER_ERROR_SASL_MECHANISM_TOO_WEAK	0x8002A324	
SCE_NP_CORE_SERVER_ERROR_SASL_NOT_AUTHORIZED	0x8002A325	
SCE_NP_CORE_SERVER_ERROR_SASL_TEMPORARY_AUTH_FAILURE	0x8002A326	
SCE_NP_CORE_SERVER_ERROR_SASL_INVALID_TICKET_SIGNATURE	0x8002A327	
SCE_NP_CORE_SERVER_ERROR_SASL_EXPIRED_TICKET	0x8002A328	
SCE_NP_CORE_SERVER_ERROR_SASL_BANNED	0x8002A329	
SCE_NP_CORE_SERVER_ERROR_SASL_DOMAIN_NOT_SUPPORTED	0x8002A32A	
SCE_NP_CORE_SERVER_ERROR_SASL_INVALID_JID	0x8002A32B	
SCE_NP_CORE_SERVER_ERROR_STANZA_BAD_REQUEST	0x8002A330	Comes up when responding to friend request or direct message from someone from block list
SCE_NP_CORE_SERVER_ERROR_STANZA_CONFLICT	0x8002A331	
SCE_NP_CORE_SERVER_ERROR_STANZA_FEATURE_NOT_IMPLEMENTED	0x8002A332	
SCE_NP_CORE_SERVER_ERROR_STANZA_FORBIDDEN	0x8002A333	
SCE_NP_CORE_SERVER_ERROR_STANZA_GONE	0x8002A334	
SCE_NP_CORE_SERVER_ERROR_STANZA_INTERNAL_SERVER_ERROR	0x8002A335	Network error; contact Sony if issues continue
SCE_NP_CORE_SERVER_ERROR_STANZA_ITEM_NOT_FOUND	0x8002A336	
SCE_NP_CORE_SERVER_ERROR_STANZA_JID_MALFORMED	0x8002A337	
SCE_NP_CORE_SERVER_ERROR_STANZA_NOT_ACCEPTABLE	0x8002A338	
SCE_NP_CORE_SERVER_ERROR_STANZA_NOT_ALLOWED	0x8002A339	
SCE_NP_CORE_SERVER_ERROR_STANZA_NOT_AUTHORIZED	0x8002A33A	
SCE_NP_CORE_SERVER_ERROR_STANZA_PAYMENT_REQUIRED	0x8002A33B	
SCE_NP_CORE_SERVER_ERROR_STANZA_RECIPIENT_UNAVAILABLE	0x8002A33C	
SCE_NP_CORE_SERVER_ERROR_STANZA_REDIRECT	0x8002A33D	
SCE_NP_CORE_SERVER_ERROR_STANZA_REGISTRATION_REQUIRED	0x8002A33E	
SCE_NP_CORE_SERVER_ERROR_STANZA_REMOTE_SERVER_NOT_FOUND	0x8002A33F	"The message to [person] could not be sent (8002 // DNS error
SCE_NP_CORE_SERVER_ERROR_STANZA_REMOTE_SERVER_TIMEOUT	0x8002A340	
SCE_NP_CORE_SERVER_ERROR_STANZA_RESOURCE_CONSTRAINT	0x8002A341	
SCE_NP_CORE_SERVER_ERROR_STANZA_SERVICE_UNAVAILABLE	0x8002A342	
SCE_NP_CORE_SERVER_ERROR_STANZA_SUBSCRIPTION_REQUIRED	0x8002A343	
SCE_NP_CORE_SERVER_ERROR_STANZA_UNDEFINED_CONDITION	0x8002A344	
SCE_NP_CORE_SERVER_ERROR_STANZA_UNEXPECTED_REQUEST	0x8002A345	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_CORE_SERVER_ERROR_STANZA_NO SUCH LOBBY	0x8002A346	
SCE_NP_CORE_SERVER_ERROR_STANZA_NO SUCH ROOM	0x8002A347	
SCE_NP_CORE_SERVER_ERROR_STANZA_NO SUCH USER	0x8002A348	
SCE_NP_CORE_SERVER_ERROR_STANZA_MUC_NO SPACE	0x8002A349	
SCE_NP_CORE_SERVER_ERROR_STANZA_MAX_ROSTER	0x8002A34A	Maximum number of friends reached
SCE_NP_CORE_SERVER_ERROR_STANZA_MUC_SERVICE_UNAVAILABLE	0x8002A34B	
SCE_NP_CORE_SERVER_ERROR_STANZA_MUC_RESOURCE_CONSTRAINT	0x8002A34C	
SCE_NP_CORE_SERVER_ERROR_STANZA_MUC_NOTAUTHORIZED	0x8002A34D	
SCE_NP_CORE_SERVER_ERROR_STANZA_MUC_ROOM_UNAVAILABLE	0x8002A34E	
SCE_NP_CORE_SERVER_ERROR_STANZA_MUC_MAX	0x8002A34F	
SCE_NP_CORE_SERVER_ERROR_STANZA_BAN	0x8002A350	
SCE_NP_CORE_SERVER_ERROR_STANZA_FRIENDLIST_MISMATCH	0x8002A351	
SCE_NP_CORE_SERVER_ERROR_STANZA_FRIENDLIST_MAINTENANCE	0x8002A352	
SCE_NP_CORE_SERVER_ERROR_STANZA_FRIENDLIST_NOT_FOUND	0x8002A353	Comes up when trying to delete or accept friend request
SCE_NP_CORE_SERVER_ERROR_STANZA_OPTIONAL	0x8002A3ff	
NP Community Server error (0x8002A400 - 0x8002A4FF)		
SCE_NP_COMMUNITY_SERVER_ERROR_BAD_REQUEST	0x8002A401	Issue with game attempting to access PSN
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_TICKET	0x8002A402	Issue accessing PSN
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_SIGNATURE	0x8002A403	
SCE_NP_COMMUNITY_SERVER_ERROR_EXPIRED_TICKET	0x8002A404	
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_NPID	0x8002A405	
SCE_NP_COMMUNITY_SERVER_ERROR_FORBIDDEN	0x8002A406	
SCE_NP_COMMUNITY_SERVER_ERROR_INTERNAL_SERVER_ERROR	0x8002A407	
SCE_NP_COMMUNITY_SERVER_ERROR_VERSION_NOT_SUPPORTED	0x8002A408	
SCE_NP_COMMUNITY_SERVER_ERROR_SERVICE_UNAVAILABLE	0x8002A409	
SCE_NP_COMMUNITY_SERVER_ERROR_PLAYER_BANNED	0x8002A40A	Player banned
SCE_NP_COMMUNITY_SERVER_ERROR_CENSORED	0x8002A40B	Text contains inappropriate words; rephrase what entered
SCE_NP_COMMUNITY_SERVER_ERROR_RANKING_RECORD_FORBIDDEN	0x8002A40C	Account banned from using score ranking
SCE_NP_COMMUNITY_SERVER_ERROR_USER_PROFILE_NOT_FOUND	0x8002A40D	User doesn't exist? Profile may have been deleted
SCE_NP_COMMUNITY_SERVER_ERROR_UPLOADER_DATA_NOT_FOUND	0x8002A40E	Attached file deleted from server
SCE_NP_COMMUNITY_SERVER_ERROR_QUOTA_MASTER_NOT_FOUND	0x8002A40F	
SCE_NP_COMMUNITY_SERVER_ERROR_RANKING_TITLE_NOT_FOUND	0x8002A410	
SCE_NP_COMMUNITY_SERVER_ERROR_BLACKLISTED_USER_ID	0x8002A411	User ID blacklisted
SCE_NP_COMMUNITY_SERVER_ERROR_GAME_RANKING_NOT_FOUND	0x8002A412	
SCE_NP_COMMUNITY_SERVER_ERROR_RANKING_STORE_NOT_FOUND	0x8002A414	
SCE_NP_COMMUNITY_SERVER_ERROR_NOT_BEST_SCORE	0x8002A415	
SCE_NP_COMMUNITY_SERVER_ERROR_LATEST_UPDATE_NOT_FOUND	0x8002A416	
SCE_NP_COMMUNITY_SERVER_ERROR_RANKING_BOARD_MASTER_NOT_FOUND	0x8002A417	
SCE_NP_COMMUNITY_SERVER_ERROR_RANKING_GAME_DATA_MASTER_NOT_FOUND	0x8002A418	Game has no ranking data or data was lost
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_ANTICHEAT_DATA	0x8002A419	
SCE_NP_COMMUNITY_SERVER_ERROR_TOO_LARGE_DATA	0x8002A41A	
SCE_NP_COMMUNITY_SERVER_ERROR_NO SUCH USER_NPID	0x8002A41B	Online ID does not exist; ID may be incorrect
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_ENVIRONMENT	0x8002A41D	
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_ONLINE_NAME_CHARACTER	0x8002A41F	
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_ONLINE_NAME_LENGTH	0x8002A420	
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_ABOUT_ME_CHARACTER	0x8002A421	
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_ABOUT_ME_LENGTH	0x8002A422	
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_INVALID_SCORE	0x8002A423	
SCE_NP_COMMUNITY_SERVER_ERROR_OVER THE RANKING LIMIT	0x8002A424	
SCE_NP_COMMUNITY_SERVER_ERROR_FAIL TO CREATE SIGNATURE	0x8002A426	
SCE_NP_COMMUNITY_SERVER_ERROR_RANKING_MASTER_INFO_NOT_FOUND	0x8002A427	
SCE_NP_COMMUNITY_SERVER_ERROR_OVER THE GAME DATA LIMIT	0x8002A428	Too much data being uploaded
SCE_NP_COMMUNITY_SERVER_ERROR_SELF DATA NOT FOUND	0x8002A42A	
SCE_NP_COMMUNITY_SERVER_ERROR_USER NOT ASSIGNED	0x8002A42B	
SCE_NP_COMMUNITY_SERVER_ERROR_GAME DATA ALREADY EXISTS	0x8002A42C	
SCE_NP_COMMUNITY_SERVER_ERROR_TOO MANY RESULTS	0x8002A42D	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_COMMUNITY_SERVER_ERROR_NOT_RECORDABLE_VERSION	0x8002A42E	
SCE_NP_COMMUNITY_SERVER_ERROR_USER_STORAGE_TITLE_MASTER_NOT_FOUND	0x8002A448	
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_VIRTUAL_USER	0x8002A449	
SCE_NP_COMMUNITY_SERVER_ERROR_USER_STORAGE_DATA_NOT_FOUND	0x8002A44A	
SCE_NP_COMMUNITY_SERVER_ERROR_INVALID_AVATAR_PAP	0x8002A457	
SCE_NP_COMMUNITY_SERVER_ERROR_NON_PLUS_MEMBER	0x8002A45D	
SCE_NP_COMMUNITY_SERVER_ERROR_UNMATCH_SEQUENCE	0x8002A45E	
SCE_NP_COMMUNITY_SERVER_ERROR_SAVEDATA_NOT_FOUND	0x8002A45F	
SCE_NP_COMMUNITY_SERVER_ERROR_TOO_MANY_SAVEDATA_FILES	0x8002A460	
SCE_NP_COMMUNITY_SERVER_ERROR_TOO MUCH_TOTAL_SAVEDATA_SIZE	0x8002A461	
SCE_NP_COMMUNITY_SERVER_ERROR_NOT_YET_DOWNLOADABLE	0x8002A462	
SCE_NP_COMMUNITY_SERVER_ERROR_BLACKLISTED_TITLE	0x8002A468	
SCE_NP_COMMUNITY_SERVER_ERROR_TOO_LARGE_ICONDATA	0x8002A469	
SCE_NP_COMMUNITY_SERVER_ERROR_TOO_LARGE_SAVEDATA	0x8002A46A	
SCE_NP_COMMUNITY_SERVER_ERROR_UNMATCH_SIGNATURE	0x8002A46B	
SCE_NP_COMMUNITY_SERVER_ERROR_UNMATCH_MD5SUM	0x8002A46C	
SCE_NP_COMMUNITY_SERVER_ERROR_TOO MUCH_SAVEDATA_SIZE	0x8002A46D	
SCE_NP_COMMUNITY_SERVER_ERROR_CONDITIONS_NOT_SATISFIED	0x8002A473	
SCE_NP_COMMUNITY_SERVER_ERROR_UNSUPPORTED_PLATFORM	0x8002A478	
SCE_NP_COMMUNITY_SERVER_ERROR_MATCHING_BEFORE_SERVICE	0x8002A4A0	
SCE_NP_COMMUNITY_SERVER_ERROR_MATCHING_END_OF_SERVICE	0x8002A4A1	
SCE_NP_COMMUNITY_SERVER_ERROR_MATCHING_MAINTENANCE	0x8002A4A2	
SCE_NP_COMMUNITY_SERVER_ERROR_RANKING_BEFORE_SERVICE	0x8002A4A3	
SCE_NP_COMMUNITY_SERVER_ERROR_RANKING_END_OF_SERVICE	0x8002A4A4	Score ranking discontinued
SCE_NP_COMMUNITY_SERVER_ERROR_RANKING_MAINTENANCE	0x8002A4A5	Score ranking under maintenance
SCE_NP_COMMUNITY_SERVER_ERROR_NO SUCH_TITLE	0x8002A4A6	
SCE_NP_COMMUNITY_SERVER_ERROR_TROPHY_BEFORE_SERVICE	0x8002A4A7	
SCE_NP_COMMUNITY_SERVER_ERROR_TROPHY_END_OF_SERVICE	0x8002A4A8	
SCE_NP_COMMUNITY_SERVER_ERROR_TROPHY_MAINTENANCE	0x8002A4A9	
SCE_NP_COMMUNITY_SERVER_ERROR_TITLE_USER_STORAGE_BEFORE_SERVICE	0x8002A4AA	
SCE_NP_COMMUNITY_SERVER_ERROR_TITLE_USER_STORAGE_END_OF_SERVICE	0x8002A4AB	
SCE_NP_COMMUNITY_SERVER_ERROR_TITLE_USER_STORAGE_MAINTENANCE	0x8002A4AC	
SCE_NP_COMMUNITY_SERVER_ERROR_FSR_BEFORE_SERVICE	0x8002A4AD	
SCE_NP_COMMUNITY_SERVER_ERROR_FSR_END_OF_SERVICE	0x8002A4AE	
SCE_NP_COMMUNITY_SERVER_ERROR_FSR_MAINTENANCE	0x8002A4AF	
SCE_NP_COMMUNITY_SERVER_ERROR_UBS_BEFORE_SERVICE	0x8002A4B0	
SCE_NP_COMMUNITY_SERVER_ERROR_UBS_END_OF_SERVICE	0x8002A4B1	
SCE_NP_COMMUNITY_SERVER_ERROR_UBS_MAINTENANCE	0x8002A4B2	
SCE_NP_COMMUNITY_SERVER_ERROR_BASIC_BLACKLISTED_USER_ID	0x8002A4B3	
Unspecified Error		
SCE_NP_COMMUNITY_SERVER_ERROR_UNSPECIFIED	0x8002A4FF	
NP Core Error		
SCE_NP_CORE_UTIL_ERROR_INVALID_ARGUMENT	0x8002A501	
SCE_NP_CORE_UTIL_ERROR_OUT_OF_MEMORY	0x8002A502	
SCE_NP_CORE_UTIL_ERROR_INSUFFICIENT	0x8002A503	
SCE_NP_CORE_UTIL_ERROR_PARSER_FAILED	0x8002A504	
SCE_NP_CORE_UTIL_ERROR_INVALID_PROTOCOL_ID	0x8002A505	
SCE_NP_CORE_UTIL_ERROR_INVALID_EXTENSION	0x8002A506	
SCE_NP_CORE_UTIL_ERROR_INVALID_TEXT	0x8002A507	
SCE_NP_CORE_UTIL_ERROR_UNKNOWN_TYPE	0x8002A508	
SCE_NP_CORE_UTIL_ERROR_UNKNOWN	0x8002A509	
SCE_NP_CORE_PARSER_ERROR_NOT_INITIALIZED	0x8002A511	
SCE_NP_CORE_PARSER_ERROR_ALREADY_INITIALIZED	0x8002A512	
SCE_NP_CORE_PARSER_ERROR_OUT_OF_MEMORY	0x8002A513	
SCE_NP_CORE_PARSER_ERROR_INSUFFICIENT	0x8002A514	
SCE_NP_CORE_PARSER_ERROR_INVALID_FORMAT	0x8002A515	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_CORE_PARSER_ERROR_INVALID_ARGUMENT	0x8002A516	
SCE_NP_CORE_PARSER_ERROR_INVALID_HANDLE	0x8002A517	
SCE_NP_CORE_PARSER_ERROR_INVALID_ICON	0x8002A518	
SCE_NP_CORE_PARSER_ERROR_UNKNOWN	0x8002A519	
SCE_NP_CORE_ERROR_ALREADY_INITIALIZED	0x8002A521	
SCE_NP_CORE_ERROR_NOT_INITIALIZED	0x8002A522	
SCE_NP_CORE_ERROR_INVALID_ARGUMENT	0x8002A523	
SCE_NP_CORE_ERROR_OUT_OF_MEMORY	0x8002A524	System memory too low. Reboot console.
SCE_NP_CORE_ERROR_ID_NOT_AVAILABLE	0x8002A525	
SCE_NP_CORE_ERROR_USER_OFFLINE	0x8002A526	
SCE_NP_CORE_ERROR_SESSION_RUNNING	0x8002A527	
SCE_NP_CORE_ERROR_SESSION_NOT_ESTABLISHED	0x8002A528	
SCE_NP_CORE_ERROR_SESSION_INVALID_STATE	0x8002A529	
SCE_NP_CORE_ERROR_SESSION_ID_TOO_LONG	0x8002A52A	
SCE_NP_CORE_ERROR_SESSION_INVALID_NAMESPACE	0x8002A52B	
SCE_NP_CORE_ERROR_CONNECTION_TIMEOUT	0x8002A52C	
SCE_NP_CORE_ERROR_GETSOCKOPT	0x8002A52D	
SCE_NP_CORE_ERROR_SSL_NOT_INITIALIZED	0x8002A52E	
SCE_NP_CORE_ERROR_SSL_ALREADY_INITIALIZED	0x8002A52F	
SCE_NP_CORE_ERROR_SSL_NO_CERT	0x8002A530	
SCE_NP_CORE_ERROR_SSL_NO_TRUSTWORTHY_CA	0x8002A531	
SCE_NP_CORE_ERROR_SSL_INVALID_CERT	0x8002A532	
SCE_NP_CORE_ERROR_SSL_CERT_VERIFY	0x8002A533	
SCE_NP_CORE_ERROR_SSL_CN_CHECK	0x8002A534	
SCE_NP_CORE_ERROR_SSL_HANDSHAKE_FAILED	0x8002A535	
SCE_NP_CORE_ERROR_SSL_SEND	0x8002A536	
SCE_NP_CORE_ERROR_SSL_RECV	0x8002A537	"An error has occurred. You have been signed out PSN" (8002A537)
SCE_NP_CORE_ERROR_SSL_CREATE_CTX	0x8002A538	
SCE_NP_CORE_ERROR_PARSE_PEM	0x8002A539	
SCE_NP_CORE_ERROR_INVALID_INITIATE_STREAM	0x8002A53A	
SCE_NP_CORE_ERROR_SASL_NOT_SUPPORTED	0x8002A53B	
SCE_NP_CORE_ERROR_NAMESPACE_ALREADY_EXISTS	0x8002A53C	
SCE_NP_CORE_ERROR_FROM_ALREADY_EXISTS	0x8002A53D	
SCE_NP_CORE_ERROR_MODULE_NOT_REGISTERED	0x8002A53E	
SCE_NP_CORE_ERROR_MODULE_FROM_NOT_FOUND	0x8002A53F	
SCE_NP_CORE_ERROR_UNKNOWN_NAMESPACE	0x8002A540	
SCE_NP_CORE_ERROR_INVALID_VERSION	0x8002A541	
SCE_NP_CORE_ERROR_LOGIN_TIMEOUT	0x8002A542	Connection to PSN timed out
SCE_NP_CORE_ERROR_TOO_MANY_SESSIONS	0x8002A543	
SCE_NP_CORE_ERROR_SENLIST_NOT_FOUND	0x8002A544	
SCE_NP_CORE_ERROR_NO_ID	0x8002A545	
SCE_NP_CORE_ERROR_LOAD_CERTS	0x8002A546	
SCE_NP_CORE_ERROR_NET_SELECT	0x8002A547	
SCE_NP_CORE_ERROR_DISCONNECTED	0x8002A548	"An error has occurred. You have been signed out PSN (8002A548)." / PSN down, internet connectic issues, ISP issues, network equipment issues or c issues
SCE_NP_CORE_ERROR_TICKET_TOO_SMALL	0x8002A549	
SCE_NP_CORE_ERROR_INVALID_TICKET	0x8002A54A	
SCE_NP_CORE_ERROR_INVALID_ONLINEID	0x8002A54B	
SCE_NP_CORE_ERROR_INVALID_PSHANDLE	0x8002A54C	
SCE_NP_CORE_ERROR_GETHOSTBYNAME	0x8002A54D	
SCE_NP_CORE_ERROR_UNDEFINED_STREAM_ERROR	0x8002A5FF	
SCE_NP_CORE_ERROR_INTERNAL	0x8002AD01	
SCE_NP_CORE_NET_ERROR_EPERM	0x8002AD02	
SCE_NP_CORE_NET_ERROR_ENOENT	0x8002AD03	
SCE_NP_CORE_NET_ERROR_ESRCH	0x8002AD03	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_CORE_NET_ERROR_EINTR	0x8002AD04	
SCE_NP_CORE_NET_ERROR_EIO	0x8002AD05	
SCE_NP_CORE_NET_ERROR_ENXIO	0x8002AD06	
SCE_NP_CORE_NET_ERROR_E2BIG	0x8002AD07	
SCE_NP_CORE_NET_ERROR_ENOEXC	0x8002AD08	
SCE_NP_CORE_NET_ERROR_EBADF	0x8002AD09	
SCE_NP_CORE_NET_ERROR_ECHILD	0x8002AD0A	
SCE_NP_CORE_NET_ERROR_EDEADLK	0x8002AD0B	
SCE_NP_CORE_NET_ERROR_ENOMEM	0x8002AD0C	Network memory running low. Reboot console.
SCE_NP_CORE_NET_ERROR_EACCES	0x8002AD0D	
SCE_NP_CORE_NET_ERROR_EFAULT	0x8002AD0E	
SCE_NP_CORE_NET_ERROR_ENOTBLK	0x8002AD0F	
SCE_NP_CORE_NET_ERROR_EBUSY	0x8002AD10	
SCE_NP_CORE_NET_ERROR_EEXIST	0x8002AD11	
SCE_NP_CORE_NET_ERROR_EXDEV	0x8002AD12	
SCE_NP_CORE_NET_ERROR_ENODEV	0x8002AD13	
SCE_NP_CORE_NET_ERROR_ENOTDIR	0x8002AD14	
SCE_NP_CORE_NET_ERROR_EISDIR	0x8002AD15	
SCE_NP_CORE_NET_ERROR_EINVAL	0x8002AD16	
SCE_NP_CORE_NET_ERROR_ENFILE	0x8002AD17	
SCE_NP_CORE_NET_ERROR_EMFILE	0x8002AD18	
SCE_NP_CORE_NET_ERROR_ENOTTY	0x8002AD19	
SCE_NP_CORE_NET_ERROR_EXTBSY	0x8002AD1A	
SCE_NP_CORE_NET_ERROR_EFBIG	0x8002AD1B	
SCE_NP_CORE_NET_ERROR_ENOSPC	0x8002AD1C	
SCE_NP_CORE_NET_ERROR_ESPIPE	0x8002AD1D	
SCE_NP_CORE_NET_ERROR_EROFS	0x8002AD1E	
SCE_NP_CORE_NET_ERROR_EMLINK	0x8002AD1F	
SCE_NP_CORE_NET_ERROR_EPIPE	0x8002AD20	
SCE_NP_CORE_NET_ERROR_EDOM	0x8002AD21	
SCE_NP_CORE_NET_ERROR_ERANGE	0x8002AD22	Issue connecting to PSN; possible congestion in ir connection
SCE_NP_CORE_NET_ERROR_EAGAIN	0x8002AD23	"An error has occurred. You have been signed out PSN" (8002AD23) // Issue connecting to PSN
SCE_NP_CORE_NET_ERROR_EINPROGRESS	0x8002AD24	
SCE_NP_CORE_NET_ERROR_EALREADY	0x8002AD25	Issue connecting to PSN
SCE_NP_CORE_NET_ERROR_ENOTSOCK	0x8002AD26	
SCE_NP_CORE_NET_ERROR_EDESTADDRREQ	0x8002AD27	
SCE_NP_CORE_NET_ERROR_EMSGSIZE	0x8002AD28	
SCE_NP_CORE_NET_ERROR_EPROTOTYPE	0x8002AD29	
SCE_NP_CORE_NET_ERROR_ENOPROTOOPT	0x8002AD2A	
SCE_NP_CORE_NET_ERROR_EPROTONOSUPPORT	0x8002AD2B	
SCE_NP_CORE_NET_ERROR_ESOCKTNOSUPPORT	0x8002AD2C	
SCE_NP_CORE_NET_ERROR_EOPNOTSUPP	0x8002AD2D	
SCE_NP_CORE_NET_ERROR_EPFNOSUPPORT	0x8002AD2E	
SCE_NP_CORE_NET_ERROR_EAFNOSUPPORT	0x8002AD2F	
SCE_NP_CORE_NET_ERROR_EADDRINUSE	0x8002AD30	
SCE_NP_CORE_NET_ERROR_EADDRNOTAVAIL	0x8002AD31	
SCE_NP_CORE_NET_ERROR_ENETDOWN	0x8002AD32	
SCE_NP_CORE_NET_ERROR_ENETUNREACH	0x8002AD33	
SCE_NP_CORE_NET_ERROR_ENETRESET	0x8002AD34	
SCE_NP_CORE_NET_ERROR_ECONNABORTED	0x8002AD35	
SCE_NP_CORE_NET_ERROR_ECONNRESET	0x8002AD36	Login to PSN was reset
SCE_NP_CORE_NET_ERROR_ENOBUFS	0x8002AD37	
SCE_NP_CORE_NET_ERROR_EISCONN	0x8002AD38	
SCE_NP_CORE_NET_ERROR_ENOTCONN	0x8002AD39	
SCE_NP_CORE_NET_ERROR_ESHUTDOWN	0x8002AD3A	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_CORE_NET_ERROR_ETOOMANYREFS	0x8002AD3B	
SCE_NP_CORE_NET_ERROR_ETIMEDOUT	0x8002AD3C	
SCE_NP_CORE_NET_ERROR_ECONNREFUSED	0x8002AD3D	"An error has occurred. You have been signed out PSN" (8002AD3D) // network error; unable to connect to server
SCE_NP_CORE_NET_ERROR_ELOOP	0x8002AD3E	
SCE_NP_CORE_NET_ERROR_ENAMETOOLONG	0x8002AD3F	
SCE_NP_CORE_NET_ERROR_EHOSTDOWN	0x8002AD40	
SCE_NP_CORE_NET_ERROR_EHOSTUNREACH	0x8002AD41	
SCE_NP_CORE_NET_ERROR_ENOTEMPTY	0x8002AD42	
SCE_NP_CORE_NET_ERROR_EPROCLIM	0x8002AD43	
SCE_NP_CORE_NET_ERROR_EUSERS	0x8002AD44	
SCE_NP_CORE_NET_ERROR_EDQUOT	0x8002AD45	
SCE_NP_CORE_NET_ERROR_ESTALE	0x8002AD46	
SCE_NP_CORE_NET_ERROR_EREMOTE	0x8002AD47	
SCE_NP_CORE_NET_ERROR_EBADRPC	0x8002AD48	
SCE_NP_CORE_NET_ERROR_ERPCMISMATCH	0x8002AD49	
SCE_NP_CORE_NET_ERROR_EPROGUNAVAIL	0x8002AD4A	
SCE_NP_CORE_NET_ERROR_EPROGMISMATCH	0x8002AD4B	
SCE_NP_CORE_NET_ERROR_EPROCUNAVAIL	0x8002AD4C	
SCE_NP_CORE_NET_ERROR_ENOLCK	0x8002AD4D	
SCE_NP_CORE_NET_ERROR_ENOSYS	0x8002AD4E	
SCE_NP_CORE_NET_ERROR_EFTYPE	0x8002AD4F	
SCE_NP_CORE_NET_ERROR_EAUTH	0x8002AD50	
SCE_NP_CORE_NET_ERROR_ENEEDAUTH	0x8002AD51	
SCE_NP_CORE_NET_ERROR_EIDRM	0x8002AD52	
SCE_NP_CORE_NET_ERROR_ENOMSG	0x8002AD53	
SCE_NP_CORE_NET_ERROR_EOVERFLOW	0x8002AD54	
SCE_NP_CORE_NET_ERROR_EILSEQ	0x8002AD55	
SCE_NP_CORE_NET_ERROR_ENOTSUP	0x8002AD56	
SCE_NP_CORE_NET_ERROR_ECANCELED	0x8002AD57	
SCE_NP_CORE_NET_ERROR_EBADMSG	0x8002AD58	
SCE_NP_CORE_NET_ERROR_ENODATA	0x8002AD59	
SCE_NP_CORE_NET_ERROR_ENOSR	0x8002AD5A	
SCE_NP_CORE_NET_ERROR_ENOSTR	0x8002AD5B	
SCE_NP_CORE_NET_ERRORETIME	0x8002AD5C	
NP Core DNS Error		
SCE_NP_CORE_ERROR_DNS_HOST_NOT_FOUND	0x8002AF01	
SCE_NP_CORE_ERROR_DNS_TRY AGAIN	0x8002AF02	
SCE_NP_CORE_ERROR_DNS_NO_RECOVERY	0x8002AF03	
SCE_NP_CORE_ERROR_DNS_NO_DATA	0x8002AF04	
SCE_NP_CORE_ERROR_DNS_NO_ADDRESS	0x8002AFFF	
NP Basic Error		
SCE_NP_BASIC_ERROR_ALREADY_INITIALIZED	0x8002A661	
SCE_NP_BASIC_ERROR_NOT_INITIALIZED	0x8002A662	
SCE_NP_BASIC_ERROR_NOT_SUPPORTED	0x8002A663	
SCE_NP_BASIC_ERROR_OUT_OF_MEMORY	0x8002A664	
SCE_NP_BASIC_ERROR_INVALID_ARGUMENT	0x8002A665	
SCE_NP_BASIC_ERROR_BAD_ID	0x8002A666	
SCE_NP_BASIC_ERROR_IDS_DIFFER	0x8002A667	
SCE_NP_BASIC_ERROR_PARSER_FAILED	0x8002A668	
SCE_NP_BASIC_ERROR_TIMEOUT	0x8002A669	Server timed out; PSN may be down or having connectivity problems
SCE_NP_BASIC_ERROR_NO_EVENT	0x8002A66A	
SCE_NP_BASIC_ERROR_EXCEEDS_MAX	0x8002A66B	
SCE_NP_BASIC_ERROR_INSUFFICIENT	0x8002A66C	
SCE_NP_BASIC_ERROR_NOT_REGISTERED	0x8002A66D	
SCE_NP_BASIC_ERROR_DATA_LOST	0x8002A66E	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_BASIC_ERROR_BUSY	0x8002A66F	
SCE_NP_BASIC_ERROR_STATUS	0x8002A670	
SCE_NP_BASIC_ERROR_CANCEL	0x8002A671	
SCE_NP_BASIC_ERROR_INVALID_MEMORY_CONTAINER	0x8002A672	
SCE_NP_BASIC_ERROR_INVALID_DATA_ID	0x8002A673	
SCE_NP_BASIC_ERROR_BROKEN_DATA	0x8002A674	
SCE_NP_BASIC_ERROR_BLOCKLIST_ADD_FAILED	0x8002A675	
SCE_NP_BASIC_ERROR_BLOCKLIST_IS_FULL	0x8002A676	
SCE_NP_BASIC_ERROR_SEND_FAILED	0x8002A677	
SCE_NP_BASIC_ERROR_NOT_CONNECTED	0x8002A678	
SCE_NP_BASIC_ERROR_INSUFFICIENT_DISK_SPACE	0x8002A679	
SCE_NP_BASIC_ERROR_INTERNAL_FAILURE	0x8002A67A	
SCE_NP_BASIC_ERROR_DOES_NOT_EXIST	0x8002A67B	
SCE_NP_BASIC_ERROR_INVALID	0x8002A67C	
SCE_NP_BASIC_ERROR_ABORT	0x8002A67D	
SCE_NP_BASIC_ERROR_UNKNOWN	0x8002A6BF	
SCE_NP_EXT_ERROR_CONTEXT_DOES_NOT_EXIST	0x8002A6A1	
SCE_NP_EXT_ERROR_CONTEXT_ALREADY_EXISTS	0x8002A6A2	
SCE_NP_EXT_ERROR_NO_CONTEXT	0x8002A6A3	
SCE_NP_EXT_ERROR_NO_ORIGIN	0x8002A6A4	
NP Matching Error		
SCE_NP_MATCHING_ERROR_NOT_INITIALIZED	0x8002A701	
SCE_NP_MATCHING_ERROR_ALREADY_INITIALIZED	0x8002A702	
SCE_NP_MATCHING_ERROR_INVALID_ARG	0x8002A703	
SCE_NP_MATCHING_ERROR_TERMINATED	0x8002A704	
SCE_NP_MATCHING_ERROR_TIMEOUT	0x8002A705	Server timeout
SCE_NP_MATCHING_ERROR_OUT_OF_MEMORY	0x8002A706	
SCE_NP_MATCHING_ERROR_CTXID_NOT_AVAIL	0x8002A707	
SCE_NP_MATCHING_ERROR_CTX_ALREADY_EXIST	0x8002A708	
SCE_NP_MATCHING_ERROR_CTX_NOT_FOUND	0x8002A709	
SCE_NP_MATCHING_ERROR_LOBBY_NOT_FOUND	0x8002A70A	
SCE_NP_MATCHING_ERROR_ROOM_NOT_FOUND	0x8002A70B	Room no longer exists
SCE_NP_MATCHING_ERROR_MEMBER_NOT_FOUND	0x8002A70C	
SCE_NP_MATCHING_ERROR_TOO_BIG_VALUE	0x8002A70D	
SCE_NP_MATCHING_ERROR_INVALID_ATTR_TYPE	0x8002A70E	
SCE_NP_MATCHING_ERROR_INVALID_ATTR_ID	0x8002A70F	
SCE_NP_MATCHING_ERROR_ALREADY_REQUESTED	0x8002A710	
SCE_NP_MATCHING_ERROR_LIMITTED_SEATING	0x8002A711	Room is full
SCE_NP_MATCHING_ERROR_LOCKED	0x8002A712	
SCE_NP_MATCHING_ERROR_CTX_STILL_RUNNING	0x8002A713	
SCE_NP_MATCHING_ERROR_INSUFFICIENT_BUFFER	0x8002A714	
SCE_NP_MATCHING_ERROR_REQUEST_NOT_ALLOWED	0x8002A715	
SCE_NP_MATCHING_ERROR_CTX_MAX	0x8002A716	
SCE_NP_MATCHING_ERROR_INVALID_REQ_ID	0x8002A717	
SCE_NP_MATCHING_ERROR_RESULT_NOT_FOUND	0x8002A718	
SCE_NP_MATCHING_ERROR_BUSY	0x8002A719	
SCE_NP_MATCHING_ERROR_ALREADY_JOINED_ROOM	0x8002A71A	
SCE_NP_MATCHING_ERROR_ROOM_MAX	0x8002A71B	Maximum number of rooms reached
SCE_NP_MATCHING_ERROR_QUICK_MATCH_PLAYER_NOT_FOUND	0x8002A71C	No players found
SCE_NP_MATCHING_ERROR_COND_MAX	0x8002A71D	
SCE_NP_MATCHING_ERROR_INVALID_COND	0x8002A71E	
SCE_NP_MATCHING_ERROR_INVALID_ATTR	0x8002A71F	
SCE_NP_MATCHING_ERROR_COMP_OP_INEQUALITY_MAX	0x8002A720	
SCE_NP_MATCHING_ERROR_RESULT_OVERFLOWED	0x8002A721	
SCE_NP_MATCHING_ERROR_HTTPXML_TIMEOUT	0x8002A722	
SCE_NP_MATCHING_ERROR_CANCELED	0x8002A723	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_MATCHING_ERROR_SEARCH_JOIN_ROOM_NOT_FOUND	0x8002A724	No rooms found
SCE_NP_MATCHING_ERROR_INVALID_COMP_OP	0x8002A725	
SCE_NP_MATCHING_ERROR_INVALID_COMP_TYPE	0x8002A726	
SCE_NP_MATCHING_ERROR_REQUEST_NOT_FOUND	0x8002A727	
SCE_NP_MATCHING_ERROR_INTERNAL_ERROR	0x8002A728	
SCE_NP_MATCHING_ERROR_INVALID_PROTOCOL_ID	0x8002A729	
SCE_NP_MATCHING_ERROR_ATTR_NOT_SPECIFIED	0x8002A72A	
SCE_NP_MATCHING_ERROR_SYSUTIL_INVALID_RESULT	0x8002A72B	
SCE_NP_MATCHING_ERROR_PLUGIN_LOAD_FAILURE	0x8002A72C	
SCE_NP_MATCHING_ERROR_INVALID_ATTR_VALUE	0x8002A72D	
SCE_NP_MATCHING_ERROR_DUPLICATE	0x8002A72E	
SCE_NP_MATCHING_ERROR_INVALID_MEMORY_CONTAINER	0x8002A72F	
SCE_NP_MATCHING_ERROR_SHUTDOWN	0x8002A730	
SCE_NP_MATCHING_ERROR_SYSUTIL_SERVER_BUSY	0x8002A731	
SCE_NP_MATCHING_ERROR_SEND_INVITATION_PARTIALLY_FAILED	0x8002A732	
SCE_NP_MATCHING_ERROR.Utility_UNAVAILABLE	0x8002A733	
SCE_NP_MATCHING_SERVER_ERROR_OUT_OF_SERVICE	0x8002A740	Matching service ended
SCE_NP_MATCHING_SERVER_ERROR_MAINTENANCE	0x8002A741	Matching service under maintenance
SCE_NP_MATCHING_SERVER_ERROR_SERVER_BUSY	0x8002A742	Matching server down
SCE_NP_MATCHING_SERVER_ERROR_ACCESS_FORBIDDEN	0x8002A743	Account banned from matching service
SCE_NP_MATCHING_SERVER_ERROR_NO SUCH SERVER	0x8002A744	
SCE_NP_MATCHING_SERVER_ERROR_NO SUCH LOBBY	0x8002A745	
SCE_NP_MATCHING_SERVER_ERROR_NO SUCH ROOM	0x8002A746	Room no longer exists
SCE_NP_MATCHING_SERVER_ERROR_NO SUCH USER	0x8002A747	
SCE_NP_MATCHING_SERVER_ERROR_NOT_ALLOWED	0x8002A748	
SCE_NP_MATCHING_SERVER_ERROR_UNKNOWN	0x8002A749	
SCE_NP_MATCHING_SERVER_ERROR_BAD_REQUEST_STANZA	0x8002A74A	
SCE_NP_MATCHING_SERVER_ERROR_REQUEST_FORBIDDEN	0x8002A74B	
SCE_NP_MATCHING_SERVER_ERROR_INTERNAL_ERROR	0x8002A74C	
SCE_NP_MATCHING_SERVER_ERROR_ROOM_OVER	0x8002A74D	Maximum number of rooms reached
SCE_NP_MATCHING_SERVER_ERROR_ROOM_CLOSED	0x8002A74E	
NP Signaling Error		
SCE_NP_SIGNALING_ERROR_NOT_INITIALIZED	0x8002A801	
SCE_NP_SIGNALING_ERROR_ALREADY_INITIALIZED	0x8002A802	
SCE_NP_SIGNALING_ERROR_OUT_OF_MEMORY	0x8002A803	
SCE_NP_SIGNALING_ERROR_CTXID_NOT_AVAILABLE	0x8002A804	
SCE_NP_SIGNALING_ERROR_CTX_NOT_FOUND	0x8002A805	
SCE_NP_SIGNALING_ERROR_REQID_NOT_AVAILABLE	0x8002A806	
SCE_NP_SIGNALING_ERROR_REQ_NOT_FOUND	0x8002A807	
SCE_NP_SIGNALING_ERROR_PARSER_CREATE_FAILED	0x8002A808	
SCE_NP_SIGNALING_ERROR_PARSER_FAILED	0x8002A809	
SCE_NP_SIGNALING_ERROR_INVALID_NAMESPACE	0x8002A80A	
SCE_NP_SIGNALING_ERROR_NETINFO_NOT_AVAILABLE	0x8002A80B	
SCE_NP_SIGNALING_ERROR_PEER_NOT_RESPONDING	0x8002A80C	
SCE_NP_SIGNALING_ERROR_CONNID_NOT_AVAILABLE	0x8002A80D	
SCE_NP_SIGNALING_ERROR_CONN_NOT_FOUND	0x8002A80E	
SCE_NP_SIGNALING_ERROR_PEER_UNREACHABLE	0x8002A80F	
SCE_NP_SIGNALING_ERROR_TERMINATED_BY_PEER	0x8002A810	
SCE_NP_SIGNALING_ERROR_TIMEOUT	0x8002A811	
SCE_NP_SIGNALING_ERROR_CTX_MAX	0x8002A812	
SCE_NP_SIGNALING_ERROR_RESULT_NOT_FOUND	0x8002A813	
SCE_NP_SIGNALING_ERROR_CONN_IN_PROGRESS	0x8002A814	
SCE_NP_SIGNALING_ERROR_CONN_NOT_ACTIVE	0x8002A815	
SCE_NP_SIGNALING_ERROR_INVALID_ARGUMENT	0x8002A816	
SCE_NP_SIGNALING_ERROR_OWN_NP_ID	0x8002A817	
SCE_NP_SIGNALING_ERROR_TOO_MANY_CONN	0x8002A818	
SCE_NP_SIGNALING_ERROR_TERMINATED_BY_MYSELF	0x8002A819	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
NP Manager Error		
SCE_NP_ERROR_NOT_INITIALIZED	0x8002AA01	
SCE_NP_ERROR_ALREADY_INITIALIZED	0x8002AA02	
SCE_NP_ERROR_INVALID_ARGUMENT	0x8002AA03	
SCE_NP_ERROR_OUT_OF_MEMORY	0x8002AA04	
SCE_NP_ERROR_ID_NO_SPACE	0x8002AA05	
SCE_NP_ERROR_ID_NOT_FOUND	0x8002AA06	
SCE_NP_ERROR_SESSION_RUNNING	0x8002AA07	
SCE_NP_ERROR_LOGINID_ALREADY_EXISTS	0x8002AA08	
SCE_NP_ERROR_INVALID_TICKET_SIZE	0x8002AA09	
SCE_NP_ERROR_INVALID_STATE	0x8002AA0A	
SCE_NP_ERROR_ABORTED	0x8002AA0B	
SCE_NP_ERROR_OFFLINE	0x8002AA0C	Cannot use while offline (appears in the ingame network settings menu of "way of the samurai 4" when no internet cable is connected)
SCE_NP_ERROR_VARIANT_ACCOUNT_ID	0x8002AA0D	Signing in using another PSN account
SCE_NP_ERROR_GET_CLOCK	0x8002AA0E	
SCE_NP_ERROR_INSUFFICIENT_BUFFER	0x8002AA0F	
SCE_NP_ERROR_EXPIRED_TICKET	0x8002AA10	
SCE_NP_ERROR_TICKET_PARAM_NOT_FOUND	0x8002AA11	
SCE_NP_ERROR_UNSUPPORTED_TICKET_VERSION	0x8002AA12	
SCE_NP_ERROR_TICKET_STATUS_CODE_INVALID	0x8002AA13	
SCE_NP_ERROR_INVALID_TICKET_VERSION	0x8002AA14	
SCE_NP_ERROR_ALREADY_USED	0x8002AA15	
SCE_NP_ERROR_DIFFERENT_USER	0x8002AA16	
SCE_NP_ERROR_ALREADY_DONE	0x8002AA17	
SCE_NP_ERROR_SESSION_INVALID_STATE	0x8002AA81	
SCE_NP_ERROR_CTX_NOT_FOUND	0x8002AA82	
SCE_NP_ERROR_UNKNOWN_PROTOCOL_EVENT	0x8002AA83	
SCE_NP_ERROR_REGISTRY	0x8002AA84	
SCE_NP_ERROR_BAD_ACCOUNTID	0x8002AA85	
SCE_NP_ERROR_INTERNAL	0x8002AAFF	
NP Utility Error		
SCE_NP_UTIL_ERROR_INVALID_ARGUMENT	0x8002AB01	
SCE_NP_UTIL_ERROR_OUT_OF_MEMORY	0x8002AB02	
SCE_NP_UTIL_ERROR_INSUFFICIENT	0x8002AB03	
SCE_NP_UTIL_ERROR_PARSER_FAILED	0x8002AB04	
SCE_NP_UTIL_ERROR_INVALID_PROTOCOL_ID	0x8002AB05	
SCE_NP_UTIL_ERROR_INVALID_NP_ID	0x8002AB06	
SCE_NP_UTIL_ERROR_INVALID_NP_LOBBY_ID	0x8002AB07	
SCE_NP_UTIL_ERROR_INVALID_NP_ROOM_ID	0x8002AB08	
SCE_NP_UTIL_ERROR_INVALID_NP_ENV	0x8002AB09	
SCE_NP_UTIL_ERROR_INVALID_TITLEID	0x8002AB0A	
SCE_NP_UTIL_ERROR_INVALID_CHARACTER	0x8002AB0B	
SCE_NP_UTIL_ERROR_INVALID_ESCAPE_STRING	0x8002AB0C	
SCE_NP_UTIL_ERROR_UNKNOWN_TYPE	0x8002AB0D	
SCE_NP_UTIL_ERROR_UNKNOWN	0x8002AB0E	
SCE_NP_UTIL_ERROR_NOT_MATCH	0x8002AB0F	
SCE_NP_UTIL_ERROR_UNKNOWN_PLATFORM_TYPE	0x8002AB10	
NP Friendlist Error		
SCE_NP_FRIENDLIST_ERROR_ALREADY_INITIALIZED	0x8002AB20	
SCE_NP_FRIENDLIST_ERROR_NOT_INITIALIZED	0x8002AB21	
SCE_NP_FRIENDLIST_ERROR_OUT_OF_MEMORY	0x8002AB22	
SCE_NP_FRIENDLIST_ERROR_INVALID_MEMORY_CONTAINER	0x8002AB23	
SCE_NP_FRIENDLIST_ERROR_INSUFFICIENT	0x8002AB24	
SCE_NP_FRIENDLIST_ERROR_CANCEL	0x8002AB25	
SCE_NP_FRIENDLIST_ERROR_STATUS	0x8002AB26	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_FRIENDLIST_ERROR_BUSY	0x8002AB27	
SCE_NP_FRIENDLIST_ERROR_INVALID_ARGUMENT	0x8002AB28	
SCE_NP_FRIENDLIST_ERROR_ABORT	0x8002AB29	
NP Profile Error		
SCE_NP_PROFILE_ERROR_ALREADY_INITIALIZED	0x8002AB40	
SCE_NP_PROFILE_ERROR_NOT_INITIALIZED	0x8002AB41	
SCE_NP_PROFILE_ERROR_OUT_OF_MEMORY	0x8002AB42	
SCE_NP_PROFILE_ERROR_NOT_SUPPORTED	0x8002AB43	
SCE_NP_PROFILE_ERROR_INSUFFICIENT	0x8002AB44	
SCE_NP_PROFILE_ERROR_CANCEL	0x8002AB45	
SCE_NP_PROFILE_ERROR_STATUS	0x8002AB46	
SCE_NP_PROFILE_ERROR_BUSY	0x8002AB47	
SCE_NP_PROFILE_ERROR_INVALID_ARGUMENT	0x8002AB48	
SCE_NP_PROFILE_ERROR_ABORT	0x8002AB49	
NP Commerce Error		
SCE_NP_COMMERCE_ERROR_NOT_INITIALIZED	0x80029401	
SCE_NP_COMMERCE_ERROR_ALREADY_INITIALIZED	0x80029402	
SCE_NP_COMMERCE_ERROR_OUT_OF_MEMORY	0x80029403	
SCE_NP_COMMERCE_ERROR_UNSUPPORTED_VERSION	0x80029404	
SCE_NP_COMMERCE_ERROR_CTX_MAX	0x80029405	
SCE_NP_COMMERCE_ERROR_CTX_NOT_FOUND	0x80029406	
SCE_NP_COMMERCE_ERROR_CTXID_NOT_AVAILABLE	0x80029407	
SCE_NP_COMMERCE_ERROR_REQ_MAX	0x80029408	
SCE_NP_COMMERCE_ERROR_REQ_NOT_FOUND	0x80029409	
SCE_NP_COMMERCE_ERROR_REQID_NOT_AVAILABLE	0x8002940A	
SCE_NP_COMMERCE_ERROR_INVALID_CATEGORY_ID	0x8002940B	
SCE_NP_COMMERCE_ERROR_INVALID_LANG_CODE	0x8002940C	
SCE_NP_COMMERCE_ERROR_REQ_BUSY	0x8002940D	
SCE_NP_COMMERCE_ERROR_INSUFFICIENT_BUFFER	0x8002940E	
SCE_NP_COMMERCE_ERROR_INVALID_REQ_STATE	0x8002940F	
SCE_NP_COMMERCE_ERROR_INVALID_CTX_STATE	0x80029410	
SCE_NP_COMMERCE_ERROR_UNKNOWN	0x80029411	
SCE_NP_COMMERCE_ERROR_INVALID_REQ_TYPE	0x80029412	
SCE_NP_COMMERCE_ERROR_INVALID_MEMORY_CONTAINER	0x80029413	
SCE_NP_COMMERCE_ERROR_INSUFFICIENT_MEMORY_CONTAINER	0x80029414	
SCE_NP_COMMERCE_ERROR_INVALID_DATA_FLAG_TYPE	0x80029415	
SCE_NP_COMMERCE_ERROR_INVALID_DATA_FLAG_STATE	0x80029416	
SCE_NP_COMMERCE_ERROR_DATA_FLAG_NUM_NOT_FOUND	0x80029417	
SCE_NP_COMMERCE_ERROR_DATA_FLAG_INFO_NOT_FOUND	0x80029418	
SCE_NP_COMMERCE_ERROR_INVALID_PROVIDER_ID	0x80029419	
SCE_NP_COMMERCE_ERROR_INVALID_DATA_FLAG_NUM	0x8002941A	
SCE_NP_COMMERCE_ERROR_INVALID_SKU_ID	0x8002941B	
SCE_NP_COMMERCE_ERROR_INVALID_DATA_FLAG_ID	0x8002941C	
SCE_NP_COMMERCE_ERROR_GPC_SEND_REQUEST	0x8002941D	
SCE_NP_COMMERCE_ERROR_GDF_SEND_REQUEST	0x8002941E	
SCE_NP_COMMERCE_ERROR_SDF_SEND_REQUEST	0x8002941F	
SCE_NP_COMMERCE_ERROR_PARSE_PRODUCT_CATEGORY	0x80029421	
SCE_NP_COMMERCE_ERROR_CURRENCY_INFO_NOT_FOUND	0x80029422	
SCE_NP_COMMERCE_ERROR_CATEGORY_INFO_NOT_FOUND	0x80029423	
SCE_NP_COMMERCE_ERROR_CHILD_CATEGORY_COUNT_NOT_FOUND	0x80029424	
SCE_NP_COMMERCE_ERROR_CHILD_CATEGORY_INFO_NOT_FOUND	0x80029425	
SCE_NP_COMMERCE_ERROR_SKU_COUNT_NOT_FOUND	0x80029426	
SCE_NP_COMMERCE_ERROR_SKU_INFO_NOT_FOUND	0x80029427	
SCE_NP_COMMERCE_ERROR_PLUGIN_LOAD_FAILURE	0x80029428	
SCE_NP_COMMERCE_ERROR_INVALID_SKU_NUM	0x80029429	
SCE_NP_COMMERCE_ERROR_INVALID_GPC_PROTOCOL_VERSION	0x8002942a	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_COMMERCE_ERROR_CHECKOUT_UNEXPECTED	0x80029430	
SCE_NP_COMMERCE_ERROR_CHECKOUT_OUT_OF_SERVICE	0x80029431	
SCE_NP_COMMERCE_ERROR_CHECKOUT_INVALID_SKU	0x80029432	
SCE_NP_COMMERCE_ERROR_CHECKOUT_SERVER_BUSY	0x80029433	
SCE_NP_COMMERCE_ERROR_CHECKOUT_MAINTENANCE	0x80029434	
SCE_NP_COMMERCE_ERROR_CHECKOUT_ACCOUNT_SUSPENDED	0x80029435	
SCE_NP_COMMERCE_ERROR_CHECKOUT_OVER_SPENDING_LIMIT	0x80029436	
SCE_NP_COMMERCE_ERROR_CHECKOUT_NOT_ENOUGH_MONEY	0x80029437	
SCE_NP_COMMERCE_ERROR_CHECKOUT_UNKNOWN	0x80029438	
SCE_NP_COMMERCE_BROWSE_SERVER_ERROR_UNKNOWN	0x80029600	
SCE_NP_COMMERCE_BROWSE_SERVER_ERROR_INVALID_CREDENTIALS	0x80029601	
SCE_NP_COMMERCE_BROWSE_SERVER_ERROR_INVALID_CATEGORY_ID	0x80029602	
SCE_NP_COMMERCE_BROWSE_SERVER_ERROR_SERVICE_END	0x80029603	
SCE_NP_COMMERCE_BROWSE_SERVER_ERROR_SERVICE_STOP	0x80029604	
SCE_NP_COMMERCE_BROWSE_SERVER_ERROR_SERVICE_BUSY	0x80029605	
SCE_NP_COMMERCE_BROWSE_SERVER_ERROR_UNSUPPORTED_VERSION	0x80029606	
SCE_NP_COMMERCE_BROWSE_SERVER_ERROR_INTERNAL_SERVER	0x80029680	
SCE_NP_COMMERCE_GDF_SERVER_ERROR_UNKNOWN	0x80029D00	
SCE_NP_COMMERCE_GDF_SERVER_ERROR_INVALID_CREDENTIALS	0x80029D01	
SCE_NP_COMMERCE_GDF_SERVER_ERROR_INVALID_FLAGLIST	0x80029D02	
SCE_NP_COMMERCE_GDF_SERVER_ERROR_SERVICE_END	0x80029D03	
SCE_NP_COMMERCE_GDF_SERVER_ERROR_SERVICE_STOP	0x80029D04	
SCE_NP_COMMERCE_GDF_SERVER_ERROR_SERVICE_BUSY	0x80029D05	
SCE_NP_COMMERCE_GDF_SERVER_ERROR_UNSUPPORTED_VERSION	0x80029D06	
SCE_NP_COMMERCE_SDF_SERVER_ERROR_UNKNOWN	0x80029E00	
SCE_NP_COMMERCE_SDF_SERVER_ERROR_INVALID_CREDENTIALS	0x80029E01	
SCE_NP_COMMERCE_SDF_SERVER_ERROR_INVALID_FLAGLIST	0x80029E02	
SCE_NP_COMMERCE_SDF_SERVER_ERROR_SERVICE_END	0x80029E03	
SCE_NP_COMMERCE_SDF_SERVER_ERROR_SERVICE_STOP	0x80029E04	
SCE_NP_COMMERCE_SDF_SERVER_ERROR_SERVICE_BUSY	0x80029E05	
SCE_NP_COMMERCE_SDF_SERVER_ERROR_UNSUPPORTED_VERSION	0x80029E06	
NP DRM error		
SCE_NP_DRM_ERROR_OUT_OF_MEMORY	0x80029501	Connection issue
SCE_NP_DRM_ERROR_INVALID_PARAM	0x80029502	
SCE_NP_DRM_ERROR_SERVER_RESPONSE	0x80029509	PSN down for maintenance
SCE_NP_DRM_ERROR_NO_ENTITLEMENT	0x80029513	This content cannot be accessed on your account case of an edat for unlock a demo/purchase game error might not be returned, turn the NPDRM Debug option to OFF to get entitlement for unlock the full
SCE_NP_DRM_ERROR_BAD_ACT	0x80029514	Activate console (if already activated for game can de-activate and re-activate it); if issues continue then contact Sony
SCE_NP_DRM_ERROR_BAD_FORMAT	0x80029515	
SCE_NP_DRM_ERROR_NO_LOGIN	0x80029516	Sign in to PLAYSTATION-Network (needed for some games or processes - have to sign in to use them)
SCE_NP_DRM_ERROR_INTERNAL	0x80029517	
SCE_NP_DRM_ERROR_BAD_PERM	0x80029519	Bad Permission - when trying to open FSELF PKG Retail/starting npdrm fself without installing first.
SCE_NP_DRM_ERROR_UNKNOWN_VERSION	0x8002951A	
SCE_NP_DRM_ERROR_TIME_LIMIT	0x8002951B	
SCE_NP_DRM_ERROR_DIFFERENT_ACCOUNT_ID	0x8002951C	
SCE_NP_DRM_ERROR_DIFFERENT_DRM_TYPE	0x8002951D	
SCE_NP_DRM_ERROR_SERVICE_NOT_STARTED	0x8002951E	"This content is not available before the start date."
SCE_NP_DRM_ERROR_BUSY	0x80029520	
SCE_NP_DRM_ERROR_LICENSE_NOT_FOUND	0x80029521	
SCE_NP_DRM_ERROR_IO	0x80029525	
SCE_NP_DRM_ERROR_FORMAT	0x80029530	"An error occurred during the copy operation." e.g. using export function to PSP (mal formed iso.bin.edat/EBOOT.PBP). "An error occurred during the start operation CONTENT_ID don't match."

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_DRM_ERROR_???	0x80029532	no titleID
SCE_NP_DRM_ERROR_FILENAME	0x80029533	
SCE_NP_DRM_ERROR_K_LICENSEE	0x80029534	
SCE_NP_DRM_INSTALL_ERROR_CHECK	0x80029564	Invalid package - Package files are corrupted - Pa requirements are not fulfilled (files were not created make_package_npdrm)
SCE_NP_DRM_???	0x80029565	Package install error -
SCE_NP_DRM_INSTALL_ERROR_UNSUPPORTED	0x80029566	"An error occurred during the install operation." Pa install error - Unsupported format - Filename exceeds 512 bytes
SCE_NP_DRM_???	0x80029567	Package install error - You get this error on Retail/Shop/Kiosk firmwares on unpatched firmware (or \ payload) - e.g. Kmeaw/Fluke1's 3.55 + psf1ght mac PKGs. You also get this error when using geohot F on Debug/Dex.
SCE_NP_DRM_SERVER_ERROR_SERVICE_IS_END	0x80029700	
SCE_NP_DRM_SERVER_ERROR_SERVICE_STOPS_TEMPORARILY	0x80029701	
SCE_NP_DRM_SERVER_ERROR_SERVICE_IS_BUSY	0x80029702	
SCE_NP_DRM_SERVER_ERROR_INVALID_USER_CREDENTIAL	0x80029721	
SCE_NP_DRM_SERVER_ERROR_INVALID_PRODUCT_ID	0x80029722	
?	0x80029724	PSN/activation related, not possible to download content from PSN. Known solution is to restore file system
SCE_NP_DRM_SERVER_ERROR_ACCOUNT_IS_CLOSED	0x80029730	
SCE_NP_DRM_SERVER_ERROR_ACCOUNT_IS_SUSPENDED	0x80029731	
SCE_NP_DRM_SERVER_ERROR_ACTIVATED_CONSOLE_IS_FULL	0x80029750	Too many PSP's activated to PSN account
SCE_NP_DRM_SERVER_ERROR_CONSOLE_NOT_ACTIVATED	0x80029751	Console not activated
SCE_NP_DRM_SERVER_ERROR_PRIMARY_CONSOLE_CANNOT_CHANGE	0x80029752	Content being played on two different consoles. Wait hours before attempting to play the content on a different console
SCE_NP_DRM_SERVER_ERROR_UNKNOWN	0x80029780	e.g. when spoofed on 3.55 without PSN+ and trying to download/activate PSN+ content
NP Matching2 error		
SCE_NP_MATCHING2_ERROR_OUT_OF_MEMORY	0x80022301	
SCE_NP_MATCHING2_ERROR_ALREADY_INITIALIZED	0x80022302	
SCE_NP_MATCHING2_ERROR_NOT_INITIALIZED	0x80022303	
SCE_NP_MATCHING2_ERROR_CONTEXT_MAX	0x80022304	
SCE_NP_MATCHING2_ERROR_CONTEXT_ALREADY_EXISTS	0x80022305	Software could not be loaded
SCE_NP_MATCHING2_ERROR_CONTEXT_NOT_FOUND	0x80022306	
SCE_NP_MATCHING2_ERROR_CONTEXT_ALREADY_STARTED	0x80022307	
SCE_NP_MATCHING2_ERROR_CONTEXT_NOT_STARTED	0x80022308	
SCE_NP_MATCHING2_ERROR_SERVER_NOT_FOUND	0x80022309	
SCE_NP_MATCHING2_ERROR_INVALID_ARGUMENT	0x8002230A	
SCE_NP_MATCHING2_ERROR_INVALID_CONTEXT_ID	0x8002230B	
SCE_NP_MATCHING2_ERROR_INVALID_SERVER_ID	0x8002230C	
SCE_NP_MATCHING2_ERROR_INVALID_WORLD_ID	0x8002230D	
SCE_NP_MATCHING2_ERROR_INVALID_LOBBY_ID	0x8002230E	
SCE_NP_MATCHING2_ERROR_INVALID_ROOM_ID	0x8002230F	
SCE_NP_MATCHING2_ERROR_INVALID_MEMBER_ID	0x80022310	
SCE_NP_MATCHING2_ERROR_INVALID_ATTRIBUTE_ID	0x80022311	
SCE_NP_MATCHING2_ERROR_INVALID_CASTTYPE	0x80022312	
SCE_NP_MATCHING2_ERROR_INVALID_SORT_METHOD	0x80022313	
SCE_NP_MATCHING2_ERROR_INVALID_MAX_SLOT	0x80022314	
SCE_NP_MATCHING2_ERROR_INVALID_OPT_SIZE	0x80022315	
SCE_NP_MATCHING2_ERROR_INVALID_MATCHING_SPACE	0x80022316	
SCE_NP_MATCHING2_ERROR_INVALID_PUSH_INDICATION	0x80022317	
SCE_NP_MATCHING2_ERROR_INVALID_BLOCK_KICK_FLAG	0x80022318	
SCE_NP_MATCHING2_ERROR_INVALID_MESSAGE_TARGET	0x80022319	
SCE_NP_MATCHING2_ERROR_RANGE_FILTER_MAX	0x8002231A	
SCE_NP_MATCHING2_ERROR_INSUFFICIENT_BUFFER	0x8002231B	
SCE_NP_MATCHING2_ERROR_DESTINATION_DISAPPEARED	0x8002231C	
SCE_NP_MATCHING2_ERROR_REQUEST_TIMEOUT	0x8002231D	Connection timed out

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_MATCHING2_ERROR_INVALID_ALIGNMENT	0x8002231E	
SCE_NP_MATCHING2_ERROR_REQUEST_CB_QUEUE_OVERFLOW	0x8002231F	
SCE_NP_MATCHING2_ERROR_EVENT_CB_QUEUE_OVERFLOW	0x80022320	
SCE_NP_MATCHING2_ERROR_MSG_CB_QUEUE_OVERFLOW	0x80022321	
SCE_NP_MATCHING2_ERROR_CONNECTION_CLOSED_BY_SERVER	0x80022322	Could not connect to the server
SCE_NP_MATCHING2_ERROR_SSL_VERIFY_FAILED	0x80022323	
SCE_NP_MATCHING2_ERROR_SSL_HANDSHAKE	0x80022324	
SCE_NP_MATCHING2_ERROR_SSL_SEND	0x80022325	
SCE_NP_MATCHING2_ERROR_SSL_RECV	0x80022326	
SCE_NP_MATCHING2_ERROR_JOINED_SESSION_MAX	0x80022327	
SCE_NP_MATCHING2_ERROR_ALREADY_JOINED	0x80022328	
SCE_NP_MATCHING2_ERROR_INVALID_SESSION_TYPE	0x80022329	
SCE_NP_MATCHING2_ERROR_CLAN_LOBBY_NOT_EXIST	0x8002232A	
SCE_NP_MATCHING2_ERROR_NP_SIGNED_OUT	0x8002232B	
SCE_NP_MATCHING2_ERROR_CONTEXT_UNAVAILABLE	0x8002232C	
SCE_NP_MATCHING2_ERROR_SERVER_NOT_AVAILABLE	0x8002232D	
SCE_NP_MATCHING2_ERROR_NOT_ALLOWED	0x8002232E	
SCE_NP_MATCHING2_ERROR_ABORTED	0x8002232F	
SCE_NP_MATCHING2_ERROR_REQUEST_NOT_FOUND	0x80022330	
SCE_NP_MATCHING2_ERROR_SESSION_DESTROYED	0x80022331	
SCE_NP_MATCHING2_ERROR_CONTEXT_STOPPED	0x80022332	
SCE_NP_MATCHING2_ERROR_INVALID_REQUEST_PARAMETER	0x80022333	
SCE_NP_MATCHING2_ERROR_NOT_NP_SIGN_IN	0x80022334	
SCE_NP_MATCHING2_ERROR_ROOM_NOT_FOUND	0x80022335	
SCE_NP_MATCHING2_ERROR_ROOM_MEMBER_NOT_FOUND	0x80022336	
SCE_NP_MATCHING2_ERROR_LOBBY_NOT_FOUND	0x80022337	
SCE_NP_MATCHING2_ERROR_LOBBY_MEMBER_NOT_FOUND	0x80022338	
SCE_NP_MATCHING2_ERROR_EVENT_DATA_NOT_FOUND	0x80022339	
SCE_NP_MATCHING2_ERROR_KEEPALIVE_TIMEOUT	0x8002233A	Issue connecting to the internet
SCE_NP_MATCHING2_ERROR_TIMEOUT_TOO_SHORT	0x8002233B	
SCE_NP_MATCHING2_ERROR_TIMEDOUT	0x8002233C	Connection timed out
SCE_NP_MATCHING2_ERROR_CREATE_HEAP	0x8002233D	
SCE_NP_MATCHING2_ERROR_INVALID_ATTRIBUTE_SIZE	0x8002233E	
SCE_NP_MATCHING2_ERROR_CANNOT_ABORT	0x8002233F	
Matching2 Resolver errors		
SCE_NP_MATCHING2_RESOLVER_ERROR_NO_DNS_SERVER	0x800223A2	DNS server is not set
SCE_NP_MATCHING2_RESOLVER_ERROR_INVALID_PACKET	0x800223AD	received DNS response was invalid
SCE_NP_MATCHING2_RESOLVER_ERROR_TIMEOUT	0x800223B0	timeout
SCE_NP_MATCHING2_RESOLVER_ERROR_NO_RECORD	0x800223B1	no record for this query
SCE_NP_MATCHING2_RESOLVER_ERROR_RES_PACKET_FORMAT	0x800223B2	server could not recognize DNS query packet
SCE_NP_MATCHING2_RESOLVER_ERROR_RES_SERVER_FAILURE	0x800223B3	Server failure
SCE_NP_MATCHING2_RESOLVER_ERROR_NO_HOST	0x800223B4	there is no entry for this hostname
SCE_NP_MATCHING2_RESOLVER_ERROR_RES_NOT_IMPLEMENTED	0x800223B5	Kind of query is not supported
SCE_NP_MATCHING2_RESOLVER_ERROR_RES_SERVER_REFUSED	0x800223B6	Refused by server
SCE_NP_MATCHING2_RESOLVER_ERROR_RESP_TRUNCATED	0x800223BC	the response was truncated
NP Matching2 Server error		
SCE_NP_MATCHING2_SERVER_ERROR_BAD_REQUEST	0x80022B01	
SCE_NP_MATCHING2_SERVER_ERROR_SERVICE_UNAVAILABLE	0x80022B02	
SCE_NP_MATCHING2_SERVER_ERROR_BUSY	0x80022B03	
SCE_NP_MATCHING2_SERVER_ERROR_END_OF_SERVICE	0x80022B04	
SCE_NP_MATCHING2_SERVER_ERROR_INTERNAL_SERVER_ERROR	0x80022B05	
SCE_NP_MATCHING2_SERVER_ERROR_PLAYER_BANNED	0x80022B06	Player banned from matching service
SCE_NP_MATCHING2_SERVER_ERROR_FORBIDDEN	0x80022B07	
SCE_NP_MATCHING2_SERVER_ERROR_BLOCKED	0x80022B08	
SCE_NP_MATCHING2_SERVER_ERROR_UNSUPPORTED_NP_ENV	0x80022B09	
SCE_NP_MATCHING2_SERVER_ERROR_INVALID_TICKET	0x80022B0A	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_MATCHING2_SERVER_ERROR_INVALID_SIGNATURE	0x80022B0B	
SCE_NP_MATCHING2_SERVER_ERROR_EXPIRED_TICKET	0x80022B0C	
SCE_NP_MATCHING2_SERVER_ERROR_ENTITLEMENT_REQUIRED	0x80022B0D	
SCE_NP_MATCHING2_SERVER_ERROR_NO SUCH_CONTEXT	0x80022B0E	
SCE_NP_MATCHING2_SERVER_ERROR_CLOSED	0x80022B0F	
SCE_NP_MATCHING2_SERVER_ERROR_NO SUCH_TITLE	0x80022B10	
SCE_NP_MATCHING2_SERVER_ERROR_NO SUCH_WORLD	0x80022B11	Software could not be loaded
SCE_NP_MATCHING2_SERVER_ERROR_NO SUCH_LOBBY	0x80022B12	
SCE_NP_MATCHING2_SERVER_ERROR_NO SUCH_ROOM	0x80022B13	
SCE_NP_MATCHING2_SERVER_ERROR_NO SUCH_LOBBY_INSTANCE	0x80022B14	
SCE_NP_MATCHING2_SERVER_ERROR_NO SUCH_ROOM_INSTANCE	0x80022B15	Room no longer exists
SCE_NP_MATCHING2_SERVER_ERROR_PASSWORD_MISMATCH	0x80022B17	
SCE_NP_MATCHING2_SERVER_ERROR_LOBBY_FULL	0x80022B18	
SCE_NP_MATCHING2_SERVER_ERROR_ROOM_FULL	0x80022B19	Room is full
SCE_NP_MATCHING2_SERVER_ERROR_GROUP_FULL	0x80022B1B	
SCE_NP_MATCHING2_SERVER_ERROR_NO SUCH_USER	0x80022B1C	
SCE_NP_MATCHING2_SERVER_ERROR_TITLE_PASSPHRASE_MISMATCH	0x80022B1E	
SCE_NP_MATCHING2_SERVER_ERROR_INVALID_SIGNED_USER_INFO	0x80022B1F	
SCE_NP_MATCHING2_SERVER_ERROR_INVALID_SIGNED_USER_INFO_SIGNATURE	0x80022B20	
SCE_NP_MATCHING2_SERVER_ERROR_INVALID_SIGNED_INSTANCE_INFO	0x80022B21	
SCE_NP_MATCHING2_SERVER_ERROR_INVALID_SIGNED_INSTANCE_INFO_SIGNATURE	0x80022B22	
SCE_NP_MATCHING2_SERVER_ERROR_INVALID_SIGNED_INSTANCE_CONFIGURATION	0x80022B23	
SCE_NP_MATCHING2_SERVER_ERROR_INVALID_SIGNED_INSTANCE_CONFIGURATION_SIGNATURE	0x80022B24	
SCE_NP_MATCHING2_SERVER_ERROR_DUPLICATE_LOBBY	0x80022B25	
SCE_NP_MATCHING2_SERVER_ERROR_DUPLICATE_ROOM	0x80022B26	
SCE_NP_MATCHING2_SERVER_ERROR_BANNED_CONSOLE	0x80022B28	Console banned from matching service
SCE_NP_MATCHING2_SERVER_ERROR_NO JOIN_GROUP_LABEL	0x80022B29	
SCE_NP_MATCHING2_SERVER_ERROR_NO SUCH_GROUP	0x80022B2A	
SCE_NP_MATCHING2_SERVER_ERROR_NO_PASSWORD	0x80022B2B	
SCE_NP_MATCHING2_SERVER_ERROR_MAX_OVER_SLOT_GROUP	0x80022B2C	
SCE_NP_MATCHING2_SERVER_ERROR_MAX_OVER_PASSWORD_MASK	0x80022B2D	
SCE_NP_MATCHING2_SERVER_ERROR_DUPLICATE_GROUP_LABEL	0x80022B2E	
SCE_NP_MATCHING2_SERVER_ERROR_REQUEST_OVERFLOW	0x80022B2F	
SCE_NP_MATCHING2_SERVER_ERROR_ALREADY_JOINED	0x80022B30	
SCE_NP_MATCHING2_SERVER_ERROR_NAT_TYPE_MISMATCH	0x80022B31	
SCE_NP_MATCHING2_SERVER_ERROR_ROOM_INCONSISTENCY	0x80022B32	
SCE_NP_MATCHING2_SERVER_ERROR_BLOCKED_USER_IN_ROOM	0x80022B33	
NP Clans Error		
SCE_NP_CLANS_ERROR_ALREADY_INITIALIZED	0x80022701	
SCE_NP_CLANS_ERROR_NOT_INITIALIZED	0x80022702	
SCE_NP_CLANS_ERROR_NOT_SUPPORTED	0x80022703	
SCE_NP_CLANS_ERROR_OUT_OF_MEMORY	0x80022704	
SCE_NP_CLANS_ERROR_INVALID_ARGUMENT	0x80022705	
SCE_NP_CLANS_ERROR_EXCEEDS_MAX	0x80022706	
SCE_NP_CLANS_ERROR_BAD_RESPONSE	0x80022707	
SCE_NP_CLANS_ERROR_BAD_DATA	0x80022708	
SCE_NP_CLANS_ERROR_BAD_REQUEST	0x80022709	
SCE_NP_CLANS_ERROR_INVALID_SIGNATURE	0x8002270A	
SCE_NP_CLANS_ERROR_INSUFFICIENT	0x8002270B	
SCE_NP_CLANS_ERROR_INTERNAL_BUFFER	0x8002270C	
SCE_NP_CLANS_ERROR_SERVER_MAINTENANCE	0x8002270D	
SCE_NP_CLANS_ERROR_SERVER_END_OF_SERVICE	0x8002270E	
SCE_NP_CLANS_ERROR_SERVER_BEFORE_START_OF_SERVICE	0x8002270F	
SCE_NP_CLANS_ERROR_ABORTED	0x80022710	
SCE_NP_CLANS_ERROR_SERVICE_UNAVAILABLE	0x80022711	
NP Clans Server Error		

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_CLANS_SERVER_ERROR_BAD_REQUEST	0x80022801	
SCE_NP_CLANS_SERVER_ERROR_INVALID_TICKET	0x80022802	
SCE_NP_CLANS_SERVER_ERROR_INVALID_SIGNATURE	0x80022803	
SCE_NP_CLANS_SERVER_ERROR_TICKET_EXPIRED	0x80022804	
SCE_NP_CLANS_SERVER_ERROR_INVALID_NPID	0x80022805	
SCE_NP_CLANS_SERVER_ERROR_FORBIDDEN	0x80022806	
SCE_NP_CLANS_SERVER_ERROR_INTERNAL_SERVER_ERROR	0x80022807	
SCE_NP_CLANS_SERVER_ERROR_BANNED	0x8002280A	Clan banned
SCE_NP_CLANS_SERVER_ERROR_BLACKLISTED	0x80022811	Clan blacklisted
SCE_NP_CLANS_SERVER_ERROR_INVALID_ENVIRONMENT	0x8002281D	
SCE_NP_CLANS_SERVER_ERROR_NO SUCH CLAN SERVICE	0x8002282F	
SCE_NP_CLANS_SERVER_ERROR_NO SUCH CLAN	0x80022830	
SCE_NP_CLANS_SERVER_ERROR_NO SUCH CLAN MEMBER	0x80022831	
SCE_NP_CLANS_SERVER_ERROR_BEFORE_HOURS	0x80022832	
SCE_NP_CLANS_SERVER_ERROR_CLOSED_SERVICE	0x80022833	
SCE_NP_CLANS_SERVER_ERROR_PERMISSION_DENIED	0x80022834	
SCE_NP_CLANS_SERVER_ERROR_CLAN_LIMIT_REACHED	0x80022835	
SCE_NP_CLANS_SERVER_ERROR_CLAN_LEADER_LIMIT_REACHED	0x80022836	
SCE_NP_CLANS_SERVER_ERROR_CLAN_MEMBER_LIMIT_REACHED	0x80022837	
SCE_NP_CLANS_SERVER_ERROR_CLAN_JOINED_LIMIT_REACHED	0x80022838	
SCE_NP_CLANS_SERVER_ERROR_MEMBER_STATUS_INVALID	0x80022839	
SCE_NP_CLANS_SERVER_ERROR_DUPLICATED_CLAN_NAME	0x8002283A	
SCE_NP_CLANS_SERVER_ERROR_CLAN_LEADER_CANNOT_LEAVE	0x8002283B	
SCE_NP_CLANS_SERVER_ERROR_ANNOUNCEMENT_LIMIT_REACHED	0x8002283D	
SCE_NP_CLANS_SERVER_ERROR_CLAN_CONFIG_MASTER_NOT_FOUND	0x8002283E	
SCE_NP_CLANS_SERVER_ERROR_DUPLICATED_CLAN_TAG	0x8002283F	
SCE_NP_CLANS_SERVER_ERROR_EXCEEDS_CREATE_CLAN_FREQUENCY	0x80022840	
SCE_NP_CLANS_SERVER_ERROR_CLAN_PASSPHRASE_INCORRECT	0x80022841	
SCE_NP_CLANS_SERVER_ERROR_CANNOT_RECORD_BLACKLIST_ENTRY	0x80022842	
SCE_NP_CLANS_SERVER_ERROR_NO SUCH CLAN ANNOUNCEMENT	0x80022843	
SCE_NP_CLANS_SERVER_ERROR_VULGAR_WORDS_POSTED	0x80022844	Post contained inappropriate words
SCE_NP_CLANS_SERVER_ERROR_BLACKLIST_LIMIT_REACHED	0x80022845	Clan blacklisted, limit reached
SCE_NP_CLANS_SERVER_ERROR_NO SUCH BLACKLIST ENTRY	0x80022846	
SCE_NP_CLANS_SERVER_ERROR_INVALID_NP_MESSAGE_FORMAT	0x8002284B	
SCE_NP_CLANS_SERVER_ERROR_FAILED_TO_SEND_NP_MESSAGE	0x8002284C	
NP Commerce2 system utility error (0x80024000 - 0x800240ff)		
SCE_NP_COMMERCE2_SYSTEM_UTIL_ERROR_INVALID_VOUCHER	0x80024002	
NP Rating error		
SCE_NP_RATING_ERROR_ALREADY_INITIALIZED	0x80024801	
SCE_NP_RATING_ERROR_NOT_INITIALIZED	0x80024802	
SCE_NP_RATING_ERROR_INVALID_ARGUMENT	0x80024803	
SCE_NP_RATING_ERROR_SERVER_STATUS_CODE	0x80024804	
SCE_NP_RATING_ERROR_SNPRINTF	0x80024805	
SCE_NP_RATING_ERROR_BAD_RESPONSE	0x80024806	
SCE_NP_RATING_ERROR_TICKET_LEN	0x80024807	
SCE_NP_RATING_ERROR_SEND_BUF_LEN	0x80024808	
SCE_NP_RATING_ERROR_NPENV_LEN	0x80024809	
SCE_NP_RATING_ERROR_NO_TRANSACTION	0x8002480A	
SCE_NP_RATING_ERROR_INVALID_SIGNATURE	0x8002480B	
SCE_NP_RATING_ERROR_ABORTED	0x8002480C	
SCE_NP_RATING_SERVER_ERROR_BAD_REQUEST	0x80024901	
SCE_NP_RATING_SERVER_ERROR_INVALID_TICKET	0x80024902	
SCE_NP_RATING_SERVER_ERROR_INVALID_SIGNATURE	0x80024903	
SCE_NP_RATING_SERVER_ERROR_EXPIRED_TICKET	0x80024904	
SCE_NP_RATING_SERVER_ERROR_INVALID_JID	0x80024905	
SCE_NP_RATING_SERVER_ERROR_INTERNAL_SERVER_ERROR	0x80024907	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_RATING_SERVER_ERROR_BANNED	0x8002490A	Rating banned
SCE_NP_RATING_SERVER_ERROR_BEFORE_SERVICE	0x800249AD	
SCE_NP_RATING_SERVER_ERROR_END_OF_SERVICE	0x800249AE	
SCE_NP_RATING_SERVER_ERROR_MAINTENANCE	0x800249AF	
SCE_NP_RATING_SERVER_ERROR_BLACKLISTED_ID	0x80024911	
SCE_NP_RATING_SERVER_ERROR_INVALID_ANTICHEAT_DATA	0x80024919	
SCE_NP_RATING_SERVER_ERROR_TITLE_MASTER_NOT_FOUND	0x8002495A	
SCE_NP_RATING_SERVER_ERROR_RATING_OUT_OF_BOUNDS	0x8002495B	
SCE_NP_RATING_SERVER_ERROR_INVALID_TARGET_STRING	0x8002495C	
NP Commerce2 error (0x80023000 - 0x800230ff)		
SCE_NP_COMMERCE2_ERROR_NOT_INITIALIZED	0x80023001	
SCE_NP_COMMERCE2_ERROR_ALREADY_INITIALIZED	0x80023002	
SCE_NP_COMMERCE2_ERROR_INVALID_ARGUMENT	0x80023003	
SCE_NP_COMMERCE2_ERROR_UNSUPPORTED_VERSION	0x80023004	
SCE_NP_COMMERCE2_ERROR_CTX_MAX	0x80023005	
SCE_NP_COMMERCE2_ERROR_INVALID_INDEX	0x80023006	
SCE_NP_COMMERCE2_ERROR_INVALID_SKUID	0x80023007	
SCE_NP_COMMERCE2_ERROR_INVALID_SKU_NUM	0x80023008	
SCE_NP_COMMERCE2_ERROR_INVALID_MEMORY_CONTAINER	0x80023009	
SCE_NP_COMMERCE2_ERROR_INSUFFICIENT_MEMORY_CONTAINER	0x8002300A	
SCE_NP_COMMERCE2_ERROR_OUT_OF_MEMORY	0x8002300B	
SCE_NP_COMMERCE2_ERROR_CTX_NOT_FOUND	0x8002300C	
SCE_NP_COMMERCE2_ERROR_CTXID_NOT_AVAILABLE	0x8002300D	
SCE_NP_COMMERCE2_ERROR_REQ_NOT_FOUND	0x8002300E	
SCE_NP_COMMERCE2_ERROR_REQID_NOT_AVAILABLE	0x8002300F	
SCE_NP_COMMERCE2_ERROR_ABORTED	0x80023010	
SCE_NP_COMMERCE2_ERROR_REQUEST_BUF_TOO_SMALL	0x80023011	
SCE_NP_COMMERCE2_ERROR_RESPONSE_BUF_TOO_SMALL	0x80023012	
SCE_NP_COMMERCE2_ERROR_COULD_NOT_RECV_WHOLE_RESPONSE_DATA	0x80023013	
SCE_NP_COMMERCE2_ERROR_INVALID_RESULT_DATA	0x80023014	
SCE_NP_COMMERCE2_ERROR_UNKNOWN	0x80023015	
SCE_NP_COMMERCE2_ERROR_SERVER_MAINTENANCE	0x80023016	PSN may be down for maintenance
SCE_NP_COMMERCE2_ERROR_SERVER_UNKNOWN	0x80023017	"An error has occurred. (80023017)"
SCE_NP_COMMERCE2_ERROR_INSUFFICIENT_BUF_SIZE	0x80023018	
SCE_NP_COMMERCE2_ERROR_REQ_MAX	0x80023019	
SCE_NP_COMMERCE2_ERROR_INVALID_TARGET_TYPE	0x8002301A	
SCE_NP_COMMERCE2_ERROR_INVALID_TARGET_ID	0x8002301B	
SCE_NP_COMMERCE2_ERROR_INVALID_SIZE	0x8002301C	
SCE_NP_COMMERCE2_ERROR_INVALID_APIID	0x80023081	
SCE_NP_COMMERCE2_ERROR_INVALID_PAYMENT_TYPE	0x80023082	
SCE_NP_COMMERCE2_ERROR_INVALID_VERSION	0x80023083	
SCE_NP_COMMERCE2_ERROR_OUTPUT_BUF_TOO_SMALL	0x80023084	
SCE_NP_COMMERCE2_ERROR_RESP_HEADER_INVALID_APIID	0x80023085	
SCE_NP_COMMERCE2_ERROR_RESP_HEADER_INVALID_LEN	0x80023086	
SCE_NP_COMMERCE2_ERROR_DATA_NOT_FOUND	0x80023087	
SCE_NP_COMMERCE2_ERROR_TLV_TOO_SHORT	0x80023088	
SCE_NP_COMMERCE2_ERROR_TLV_LESS_THAN_MINLEN	0x80023089	
SCE_NP_COMMERCE2_ERROR_TLV_DATALEN_TOO_LONG	0x8002308A	
SCE_NP_COMMERCE2_ERROR_INVALID_NPENV	0x8002308B	
SCE_NP_COMMERCE2_ERROR_TOO_LONG_NPENV	0x8002308C	
SCE_NP_COMMERCE2_ERROR_INTERFACE_NOT_FOUND	0x8002308D	
SCE_NP_COMMERCE2_ERROR_PLUGIN_NOT_FOUND	0x8002308E	
SCE_NP_COMMERCE2_ERROR_DIALOG_CANCELED	0x8002308F	
SCE_NP_COMMERCE2_ERROR_INVALID_CLEN	0x80023090	
SCE_NP_COMMERCE2_ERROR_UNKNOWN_COUNTRY_CODE	0x80023091	
SCE_NP_COMMERCE2_ERROR_SEE_INPUT_ERROR	0x80023092	Unable to connect to PSN

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_COMMERCE2_CS_ERROR_ABORTED	0x800230C0	
SCE_NP_COMMERCE2_SC_ERROR_INVALID_RESPONSE	0x800230E1	
NP Commerce2 server error (0x80023100 - 0x800231ff)		
SCE_NP_COMMERCE2_SERVER_ERROR_BAD_REQUEST	0x80023101	Invalid password?
SCE_NP_COMMERCE2_SERVER_ERROR_UNKNOWN_ERROR	0x80023102	"An error has occurred" // Can't connect to PSN; F down or issue with billing info
SCE_NP_COMMERCE2_SERVER_ERROR_TIMEOUT_ERROR	0x80023103	
SCE_NP_COMMERCE2_SERVER_ERROR_NO_DATA_FOUND	0x80023104	
SCE_NP_COMMERCE2_SERVER_ERROR_SESSION_EXPIRED	0x80023105	Connection closed after console sat idle
SCE_NP_COMMERCE2_SERVER_ERROR_VERSION_NOT_SUPPORTED	0x80023106	
SCE_NP_COMMERCE2_SERVER_ERROR_ACCESS_PERMISSION_DENIED	0x80023107	
SCE_NP_COMMERCE2_SERVER_ERROR_NO SUCH CATEGORY	0x80023110	"An error has occurred" // Issue connecting to PSN
SCE_NP_COMMERCE2_SERVER_ERROR_NO SUCH PRODUCT	0x80023111	Unable to connect to server
SCE_NP_COMMERCE2_SERVER_ERROR_REQUIRES_PASSWORD	0x80023112	
SCE_NP_COMMERCE2_SERVER_ERROR_NOT_ELIGIBILITY	0x80023113	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_LOGIN	0x80023114	
SCE_NP_COMMERCE2_SERVER_ERROR_NO SUCH CURRENCY	0x80023115	
SCE_NP_COMMERCE2_SERVER_ERROR_NO PAYMENT_INFO	0x80023116	
SCE_NP_COMMERCE2_SERVER_ERROR_CART_FULL	0x80023117	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_QUANTITY	0x80023118	
SCE_NP_COMMERCE2_SERVER_ERROR_ITEM_ALREADY_IN_CART	0x80023119	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_SKU	0x8002311A	Content is region-locked
SCE_NP_COMMERCE2_SERVER_ERROR_ACCOUNT_SUSPENDED1	0x8002311B	
SCE_NP_COMMERCE2_SERVER_ERROR_INACTIVE_ACCOUNT		
SCE_NP_COMMERCE2_SERVER_ERROR_SUSPENDED_ACCOUNT	0x8002311C	
SCE_NP_COMMERCE2_SERVER_ERROR_SUSPENDED_CONSOLE	0x8002311D	
SCE_NP_COMMERCE2_SERVER_ERROR_RESERVED_1E	0x8002311E	
SCE_NP_COMMERCE2_SERVER_ERROR_EXCEEDS_MAX_WALLET_PURCHASE	0x8002311F	
SCE_NP_COMMERCE2_SERVER_ERROR_OVER_SPENDING_LIMIT	0x80023120	
SCE_NP_COMMERCE2_SERVER_ERROR_AUTO_TOPUP_FAILED	0x80023121	"An error has occurred" // PSN down or PSS wallet up issue
SCE_NP_COMMERCE2_SERVER_ERROR_INSUFFICIENT_FUNDS	0x80023122	
SCE_NP_COMMERCE2_SERVER_ERROR_CART_LOAD_FAILURE	0x80023123	PSS cart issue
SCE_NP_COMMERCE2_SERVER_ERROR_PURCHASE_FAILED	0x80023124	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_PURCHASE	0x80023125	
SCE_NP_COMMERCE2_SERVER_ERROR_CART_EMPTY	0x80023126	
SCE_NP_COMMERCE2_SERVER_ERROR_PAYMENT_ALREADY_EXIST	0x80023127	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_CREDIT_CARD_ADDRESS	0x8002312A	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_PAYMENT_ERROR	0x8002312B	
SCE_NP_COMMERCE2_SERVER_ERROR_EXPIRED_CREDIT_CARD	0x8002312C	
SCE_NP_COMMERCE2_SERVER_ERROR_ACTION_NOT_ALLOWED	0x8002312D	
SCE_NP_COMMERCE2_SERVER_ERROR_NO_WALLET_INFO	0x8002312E	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_VOUCHER	0x8002312F	
SCE_NP_COMMERCE2_SERVER_ERROR_VOUCHER_ALREADY_CONSUMED	0x80023130	
SCE_NP_COMMERCE2_SERVER_ERROR_VOUCHER_TRANSACTION_OVER_LIMIT	0x80023131	
SCE_NP_COMMERCE2_SERVER_ERROR_FAILED AGE REQUIREMENT	0x80023132	
SCE_NP_COMMERCE2_SERVER_ERROR_VOUCHER_EXPIRED	0x80023133	
SCE_NP_COMMERCE2_SERVER_ERROR_VOUCHER_SKU_REGION_MISMATCH	0x80023134	
SCE_NP_COMMERCE2_SERVER_ERROR_VOUCHER_SKU_PRICE_NOT_FOUND	0x80023135	
SCE_NP_COMMERCE2_SERVER_ERROR_DEPOSIT_IN_PROGRESS_ERROR	0x80023136	
SCE_NP_COMMERCE2_SERVER_ERROR_EDY_TRANSACTION_FAILED	0x80023137	
SCE_NP_COMMERCE2_SERVER_ERROR_DEPOSIT_FAILED	0x80023138	
SCE_NP_COMMERCE2_SERVER_ERROR_EXCEEDS AGE LIMIT IN BROWSING	0x80023139	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_EULA_VERSION	0x80023140	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_ADDRESS	0x80023141	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_PASSWORD	0x80023142	
SCE_NP_COMMERCE2_SERVER_ERROR_SAME_LOGINID	0x80023143	
SCE_NP_COMMERCE2_SERVER_ERROR_LOGINID_EXISTS	0x80023144	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_SUB_ACCOUNT	0x80023145	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_BIRTH_DATE	0x80023146	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_COUNTRY	0x80023147	
SCE_NP_COMMERCE2_SERVER_ERROR_ONLINEID_EXISTS	0x80023148	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_ONLINEID	0x80023149	
SCE_NP_COMMERCE2_SERVER_ERROR_CORRUPTED_DATA	0x8002314A	PSN server data corrupted
SCE_NP_COMMERCE2_SERVER_ERROR_TOO_MANY_SUB_ACCOUNTS	0x8002314B	
SCE_NP_COMMERCE2_SERVER_ERROR_CONSOLE_REG_EXCEEDED	0x8002314C	
SCE_NP_COMMERCE2_SERVER_ERROR_ACCOUNT_BINDING_DISABLED	0x8002314D	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_KOREAN_RRN	0x8002314E	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_LOGIN_OR_DOB	0x8002314F	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_SECURITY_ANSWER	0x80023150	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_PARENT	0x80023151	
SCE_NP_COMMERCE2_SERVER_ERROR_INCORRECT_REGION	0x80023152	
SCE_NP_COMMERCE2_SERVER_ERROR_CHILD_NOT_ALLOWED	0x80023153	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_CONSOLE_ID	0x80023154	Invalid console ID
SCE_NP_COMMERCE2_SERVER_ERROR_RATE_LIMIT_EXCEEDED	0x80023156	Incorrect redemption code entered too many times 24 hours before trying again.
SCE_NP_COMMERCE2_SERVER_ERROR_VALID_REWARD_ENT_NOT_FOUND	0x80023157	
SCE_NP_COMMERCE2_SERVER_ERROR_UPGRADE_REQUIRED	0x80023158	Issue accessing SEN account; account needs to be updated
SCE_NP_COMMERCE2_SERVER_ERROR_SUBACCOUNT_UPGRADE_REQUIRED	0x80023159	
SCE_NP_COMMERCE2_SERVER_ERROR_EXCEEDED_LIMIT_NUMBER_OF_CC	0x8002315A	Credit card has too many accounts linked to it
SCE_NP_COMMERCE2_SERVER_ERROR_CC_REVERIFICATION_REQUIRED	0x8002315B	
SCE_NP_COMMERCE2_SERVER_ERROR_INVALID_DOMAIN_PROVIDED	0x8002315C	
SCE_NP_COMMERCE2_SERVER_ERROR_NO_CONTENTFILE_ID_FOUND	0x8002315D	
SCE_NP_COMMERCE2_SERVER_ERROR_AUTO_DEPOSIT_FLAG_REQUIRED	0x8002315F	
SCE_NP_COMMERCE2_SERVER_ERROR_CREDIT_CARD_REQUIRED	0x80023162	
SCE_NP_COMMERCE2_SERVER_ERROR_ATTR_REQUIRED_FOR_TAX_CALC	0x80023163	Issue with credit card (card turned down?)
	0x80023171	Issue with credit card (invalid card on file)
NP Trophy Errors		
SCE_NP_TROPHY_ERROR_ALREADY_INITIALIZED	0x80022901	sceNpTrophyInit() has already been called, or it has been called again before the call of sceNpTrophyTerm()
SCE_NP_TROPHY_ERROR_NOT_INITIALIZED	0x80022902	Not initialized. sceNpTrophyInit() has not been called. sceNpTrophyTerm() has already been called.
SCE_NP_TROPHY_ERROR_NOT_SUPPORTED	0x80022903	An unsupported feature has been specified
SCE_NP_TROPHY_ERROR_CONTEXT_NOT_REGISTERED	0x80022904	The context has not been registered yet and cannot be used before registration
SCE_NP_TROPHY_ERROR_OUT_OF_MEMORY	0x80022905	Insufficient memory to process request
SCE_NP_TROPHY_ERROR_INVALID_ARGUMENT	0x80022906	Invalid argument
SCE_NP_TROPHY_ERROR_EXCEEDS_MAX	0x80022907	A value in the request exceeds the maximum limit allowed
SCE_NP_TROPHY_ERROR_INVALID_MEMORY_CONTAINER	0x80022908	
SCE_NP_TROPHY_ERROR_INSUFFICIENT	0x80022909	There is insufficient memory or storage to process the trophy package
SCE_NP_TROPHY_ERROR_UNKNOWN_CONTEXT	0x8002290A	Unknown context. The specified context does not exist
SCE_NP_TROPHY_ERROR_INVALID_FORMAT	0x8002290B	Format of the trophy package is invalid
SCE_NP_TROPHY_ERROR_BAD_RESPONSE	0x8002290C	Internal error. The request could not be properly processed
SCE_NP_TROPHY_ERROR_INVALID_GRADE	0x8002290D	Invalid trophy grade
SCE_NP_TROPHY_ERROR_INVALID_CONTEXT	0x8002290E	Invalid context
SCE_NP_TROPHY_ERROR_PROCESSING_ABORTED	0x8002290F	An invalid value was returned from SceNpTrophyStatusCallback and further processing has been aborted
SCE_NP_TROPHY_ERROR_ABORT	0x80022910	The handle has been aborted. The processing has been aborted by sceNpTrophyAbortHandle(). Destroy the handle.
SCE_NP_TROPHY_ERROR_UNKNOWN_HANDLE	0x80022911	Unknown handle. The specified handle does not exist
SCE_NP_TROPHY_ERROR_LOCKED	0x80022912	The trophy has not been unlocked yet
SCE_NP_TROPHY_ERROR_HIDDEN	0x80022913	The trophy is hidden
SCE_NP_TROPHY_ERROR_CANNOT_UNLOCK_PLATINUM	0x80022914	Platinum trophy cannot be unlocked. The platinum is unlocked by the system and cannot be unlocked by the application.

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_TROPHY_ERROR_ALREADY_UNLOCKED	0x80022915	The trophy has already been unlocked
SCE_NP_TROPHY_ERROR_INVALID_TYPE	0x80022916	Invalid type
SCE_NP_TROPHY_ERROR_INVALID_HANDLE	0x80022917	Invalid handle
SCE_NP_TROPHY_ERROR_INVALID_NP_COMM_ID	0x80022918	Invalid NP Communication ID. Either the NP Communication ID or the NP communication signature is invalid.
SCE_NP_TROPHY_ERROR_UNKNOWN_NP_COMM_ID	0x80022919	NP Communication IDs do not match. The specific Communication ID does not match the NP Communication ID in the trophy pack file.
SCE_NP_TROPHY_ERROR_DISC_IO	0x8002291A	Failed to read from disc. Fatal error – terminate the application.
SCE_NP_TROPHY_ERROR_CONF_DOES_NOT_EXIST	0x8002291B	Trophy pack file does not exist
SCE_NP_TROPHY_ERROR_UNSUPPORTED_FORMAT	0x8002291C	Unsupported trophy pack file format. Check that the trophy pack file has been created using the latest version of the trophy editor.
SCE_NP_TROPHY_ERROR_ALREADY_INSTALLED	0x8002291D	The trophy set has already been installed or updated. It does not require further processing.
SCE_NP_TROPHY_ERROR_BROKEN_DATA	0x8002291E	Internal error. The data is corrupted.
SCE_NP_TROPHY_ERROR_VERIFICATION_FAILURE	0x8002291F	Trophy pack file signature verification failed. The trophy pack file could not be properly verified.
SCE_NP_TROPHY_ERROR_INVALID_TROPHY_ID	0x80022920	Invalid trophy ID. The trophy ID may exceed the maximum allowable number of trophies.
SCE_NP_TROPHY_ERROR_UNKNOWN_TROPHY_ID	0x80022921	Unknown trophy ID. The trophy for the specified trophy ID does not exist.
SCE_NP_TROPHY_ERROR_UNKNOWN_TITLE	0x80022922	The game title has not been installed. Be sure that the context is properly registered.
SCE_NP_TROPHY_ERROR_UNKNOWN_FILE	0x80022923	The file to be accessed could not be found.
SCE_NP_TROPHY_ERROR_DISC_NOT_MOUNTED	0x80022924	The disc has not been mounted by the file system. Fatal error – terminate the application.
SCE_NP_TROPHY_ERROR_SHUTDOWN	0x80022925	The system is being shutdown. The processing cannot be carried on and is therefore being cancelled.
SCE_NP_TROPHY_ERROR_TITLE_ICON_NOT_FOUND	0x80022926	Trophy set still image icon does not exist. Check that the trophy pack file contains a trophy set still image icon.
SCE_NP_TROPHY_ERROR_TROPHY_ICON_NOT_FOUND	0x80022927	Trophy still image icon does not exist. Check that the trophy pack file contains all the trophy still image icons.
SCE_NP_TROPHY_ERROR_INSUFFICIENT_DISK_SPACE	0x80022928	Insufficient disk space. There is not enough disk space to register the trophy package to the system. Notify the user accordingly.
SCE_NP_TROPHY_ERROR_INVALID_SIGNATURE	0x80022929	
SCE_NP_TROPHY_ERROR_ILLEGAL_UPDATE	0x8002292A	Cannot update. An irresolvable discrepancy has been found between the registered data and the data trying to be registered. Possible causes are from a change in trophy grade or a reduction in the number of trophies from the previous install. Check the trophy configuration data, and remove the previously installed trophy sets from the console.
SCE_NP_TROPHY_ERROR_SAVEDATA_USER_DOES_NOT_MATCH	0x8002292B	This user cannot use trophies. A discrepancy has been found between the creator of the save data and the trophy user. No trophies can be unlocked during the current gaming session.
SCE_NP_TROPHY_ERROR_TROPHY_ID_DOES_NOT_EXIST	0x8002292C	The trophy ID does not exist.
SCE_NP_TROPHY_ERROR_SERVICE_UNAVAILABLE	0x8002292D	The trophy service is currently unavailable.
SCE_NP_TROPHY_ERROR_INVALID_PLATFORM	0x8002292E	
SCE_NP_TROPHY_ERROR_UNKNOWN	0x800229FF	Unknown internal error.
NP Custom Menu Error		
SCE_NP_CUSTOM_MENU_ERROR_ALREADY_INITIALIZED	0x80023B01	
SCE_NP_CUSTOM_MENU_ERROR_NOT_INITIALIZED	0x80023B02	
SCE_NP_CUSTOM_MENU_ERROR_OUT_OF_MEMORY	0x80023B03	
SCE_NP_CUSTOM_MENU_ERROR_NOT_SUPPORTED	0x80023B04	
SCE_NP_CUSTOM_MENU_ERROR_INSUFFICIENT	0x80023B05	
SCE_NP_CUSTOM_MENU_ERROR_CANCEL	0x80023B06	
SCE_NP_CUSTOM_MENU_ERROR_STATUS	0x80023B07	
SCE_NP_CUSTOM_MENU_ERROR_BUSY	0x80023B08	
SCE_NP_CUSTOM_MENU_ERROR_INVALID_ARGUMENT	0x80023B09	
SCE_NP_CUSTOM_MENU_ERROR_ABORT	0x80023B0A	
SCE_NP_CUSTOM_MENU_ERROR_NOT_REGISTERED	0x80023B0B	
SCE_NP_CUSTOM_MENU_ERROR_EXCEEDS_MAX	0x80023B0C	
SCE_NP_CUSTOM_MENU_ERROR_INVALID_CHARACTER	0x80023B0D	

Name	Errorcode	Remarks
NP Authentication Error (client runtime errors)		
SCE_NP_SNS_ERROR_UNKNOWN	0x80024501	
SCE_NP_SNS_ERROR_NOT_SIGN_IN	0x80024502	
SCE_NP_SNS_ERROR_INVALID_ARGUMENT	0x80024503	
SCE_NP_SNS_ERROR_OUT_OF_MEMORY	0x80024504	
SCE_NP_SNS_ERROR_SHUTDOWN	0x80024505	
SCE_NP_SNS_ERROR_BUSY	0x80024506	
SNS FB -> Social Networks (Facebook)		
SCE_NP_SNS_FB_ERROR_ALREADY_INITIALIZED	0x80024511	
SCE_NP_SNS_FB_ERROR_NOT_INITIALIZED	0x80024512	
SCE_NP_SNS_FB_ERROR_EXCEEDS_MAX	0x80024513	
SCE_NP_SNS_FB_ERROR_UNKNOWN_HANDLE	0x80024514	
SCE_NP_SNS_FB_ERROR_ABORTED	0x80024515	
SCE_NP_SNS_FB_ERROR_ALREADY_ABORTED	0x80024516	
SCE_NP_SNS_FB_ERROR_CONFIG_DISABLED	0x80024517	
SCE_NP_SNS_FB_ERROR_FBSERVER_ERROR_RESPONSE	0x80024518	
SCE_NP_SNS_FB_ERROR_THROTTLE_CLOSED	0x80024519	
SCE_NP_SNS_FB_ERROR_OPERATION_INTERVAL_VIOLATION	0x8002451A	
SCE_NP_SNS_FB_ERROR_UNLOADED_THROTTLE	0x8002451B	
SCE_NP_SNS_FB_ERROR_ACCESS_NOT_ALLOWED	0x8002451C	
NP OAuth Errors		
SCE_NP_OAUTH_ERROR_ALREADY_INITIALIZED	0x80025F02	
SCE_NP_OAUTH_ERROR_NOT_INITIALIZED	0x80025F03	
SCE_NP_OAUTH_ERROR_ABORTED	0x80025F08	
SCE_NP_OAUTH_ERROR_REQUEST_NOT_FOUND	0x80025F0A	
SCE_NP_OAUTH_ERROR_REQUEST_MAX	0x80025F11	
LS (Login Service)		
SCE_NP_LS_ERROR_INVALID_VERSION	0x80028C07	You need to be signed in to continue.
SCE_NP_LS_ERROR_INVALID_VERSION	0x80028C0D	A system software update is required.
other		
SCE_NP_COMMERCE2_ERROR_WINDOWS_SYSTEM	0x80860001	
SCE_NP_COMMERCE2_QS_ERROR_NO_SECURITY_QUESTION_TEXT	0x800230D0	
SCE_NP_COMMERCE2_QS_ERROR_INSUFFICIENT_BUF	0x800230D1	
SCE_NP_COMMERCE2_QS_ERROR_ABORTED	0x800230D2	
SCE_NP_COMMERCE2_QS_ERROR_INVALID_NPENV	0x800230D3	
	0x8002847C	psgm failed because the .pkg url wasn't 200 OK sl code

System Update errors with HTTP Server

Description	Errorcode	Remarks
Issue connecting online	0x80028E01	HTTP status error was returned from the server // Reboot console and try connecting again (PSN may be down for maintenance), if this fails, try connecting later; if setting up a network connection, settings may be incorrect; if issues continue then check internet connection
Connection with server timed out	0x80028E02	"An error has occurred. You have been signed out of PSN (80028E02)" // No response from the server for Content-Length // Open browser and check for a message from ISP (e.g. error from router) or a login page
	0x80028E03	Size of image list file is larger than 64KB.
	0x80028E04	Content-Length of image list file and the file size that can actually be received are invalid.
	0x80028E05	Format of image list file is invalid.
Connection with server timed out	0x80028E06	Image list file does not include the Dest parameter that indicates the destination. // Open browser and check for a message from ISP (e.g. error from router) or a login page
	0x80028E07	Frequent disconnections by the server while downloading the updater.
Issue connecting to the PSN	0x80028EA1	Try connecting later; check to see if there is a PSN service outage
	0x80028EA2	Problem with network settings or network status.
	0x80028EA3	Problem with network settings or network status.
Latest system software has already been installed	0x80028EA4	No update is needed
Issue connecting online	0x80028EA5	Reboot console and try connecting again or try connecting later (temporary congestion); if issues continue then check internet connection

Description	Errorcode	Remarks
Can't download the system software	0x80028EA6	Proxy server is set. Connect to internet and turn off the proxy server
	0x80028EA7	Problem with network settings or network status.
Unable to connect to the internet	0x80028EA8	Check if PSN is up; if it is, connection info may be incorrect; may need to log in using the browser
	0x80028EA9	Problem with network settings or network status.
	0x80028EAA	Problem with network settings or network status.
	0x80028EAB	Problem with network settings or network status.
	0x80028EAC	Problem with network settings or network status.
	0x80028EAD	Problem with network settings or network status.
Cannot update the PS3	0x80029C41	Turn off console for 10 seconds, then back on and try updating again; if issues continue, go into Safe Mode and select "Restore File System"; if that did not help, go into Safe Mode and select "Restore PS3 System"; if still having issues then send console in for repairs
Cannot update the PS3	0x80029C44	Turn off console for 10 seconds, then back on and try updating again; if issues continue, go into Safe Mode and select "Restore File System"; if that did not help, go into Safe Mode and select "Restore PS3 System"; if still having issues then send console in for repairs
	0x80029C48	Error occurred while accessing the HDD.
	0x80029C54	Error occurred while accessing the HDD.
Issues updating the PS3	0x80029C55	Error occurred while accessing storage media.
	0x80029C65	Error occurred while accessing storage media.
Cannot update the PS3	0x80029C68	Turn off console for 10 seconds, then back on and try updating again; if issues continue, go into Safe Mode and select "Restore File System"; if that did not help, go into Safe Mode and select "Restore PS3 System"; if still having issues then send console in for repairs
	0x80029C75	Error occurred while accessing storage media.
Unable to update the PS3	0x80029C77	Reboot console, then run the update again (go to [Settings] > [System Update]); if issue occurs again then send console in for repairs (Possible Bad Blocks on Nands in Bootloader area, cannot be remapped, but you can copy bootloader sector if one of the bootloaders is in tact and overwrite the bad one. Requires New NAND replacement, patching as stated, and reflashing with flasher).
System update error	0x80029C78	Reboot console, then update via Safe Mode; if issues continue then console may need repair
	0x80029C9C	"The datatype is not supported" > Update data does not support downgrades. Seen when updating to lower version from XMB with QA-extra flag / System Update Debug enabled. Solution: Use Recovery Menu for QA flagged systems, for downgrades to 2.50/2.70 < 3.55
System update file corrupted	0x8002F020	If downloading from a game disc, make sure the disc is not scratched and reboot console; if using external storage, reboot the console, then re-download the file; if downloading direct from system, reboot console; if issues continue then send console in for repairs
	0x8002F029	Invalid update data. (TargetID related) / The data type is not supported. (8002F029) when trying to install Debug/DEX firmware on a Retail/CEX console.
System update file corrupted	0x8002F02B	If downloading from a game disc, make sure the disc is not scratched and reboot console; if using external storage, reboot the console, then re-download the file; if downloading direct from system, reboot console; if issues continue then send console in for repairs
System update file corrupted	0x8002F02D	If downloading from a game disc, make sure the disc is not scratched and reboot console; if using external storage, reboot the console, then re-download the file; if downloading direct from system, reboot console; if issues continue then send console in for repairs
Unable to update	0x8002F07C	Turn off console for 10 seconds, then back on and try updating again; if issues continue, go into Safe Mode and select "Restore File System"; if that did not help, go into Safe Mode and select "Restore PS3 System"; if still having issues then send console in for repairs
Issue updating the PS3 software	0x8002F087	Reboot console, re-download and install the update; if issues continue then send console in for repairs
	0x8002F828	Error occurred while checking update data.
	0x8002F82B	Error occurred while checking update data.
Unable to update the PS3	0x8002F8DC	Issue with hard drive // Turn off console for 10 seconds, then back on and try updating again; if issues continue, go into Safe Mode and select "Restore File System"; if that did not help, go into Safe Mode and select "Restore PS3 System"; if still having issues then send console in for repairs
Issue updating the PS3 system software	0x8002F997	Error occurred while checking update data; file may be corrupted.

Subdisplay errors (PSP/Remoteplay)

Description	Errorcode	Remarks
	0x80028F23	Content does not support Remote Play
	0x80029846	Content is not compatible with Remote Play
CELL_SUBDISPLAY_ERROR_OUT_OF_MEMORY	0x80029851	Insufficient memory
CELL_SUBDISPLAY_ERROR_FATAL	0x80029852	Fatal error occurred
CELL_SUBDISPLAY_ERROR_NOT_FOUND	0x80029853	Internal error
CELL_SUBDISPLAY_ERROR_INVALID_VALUE	0x80029854	Specified parameter is invalid
CELL_SUBDISPLAY_ERROR_NOT_INITIALIZED	0x80029855	Not initialized properly
CELL_SUBDISPLAY_ERROR_SET_SAMPLE	0x80029860	Number of samples set with is not a multiple of 1024
CELL_SUBDISPLAY_ERROR_AUDIOOUT_IS_BUSY	0x80029861	Audio being output - failed to set data
CELL_SUBDISPLAY_ERROR_ZERO_REGISTERED	0x80029813	No PSP has been registered
CELL_REMOTEPLAY_ERROR_INTERNAL	0x80029830	

Network errors

Description	Errorcode	Remarks
Sys Net errors (libnet)		
SYS_NET_ERROR_EPERM	0x80010201	
SYS_NET_ERROR_ENOENT	0x80010202	
SYS_NET_ERROR_ESRCH	0x80010203	
SYS_NET_ERROR_EINTR	0x80010204	
SYS_NET_ERROR_EIO	0x80010205	
SYS_NET_ERROR_ENXIO	0x80010206	
SYS_NET_ERROR_E2BIG	0x80010207	
SYS_NET_ERROR_ENOEXEC	0x80010208	
SYS_NET_ERROR_EBADF	0x80010209	
SYS_NET_ERROR_ECHILD	0x8001020a	
SYS_NET_ERROR_EDEADLK	0x8001020b	
SYS_NET_ERROR_ENOMEM	0x8001020c	
SYS_NET_ERROR_EACCES	0x8001020d	
SYS_NET_ERROR_EFAULT	0x8001020e	
SYS_NET_ERROR_ENOTBLK	0x8001020f	
SYS_NET_ERROR_EBUSY	0x80010210	
SYS_NET_ERROR_EEXIST	0x80010211	
SYS_NET_ERROR_EXDEV	0x80010212	
SYS_NET_ERROR_ENODEV	0x80010213	
SYS_NET_ERROR_ENOTDIR	0x80010214	
SYS_NET_ERROR_EISDIR	0x80010215	
SYS_NET_ERROR_EINVAL	0x80010216	
SYS_NET_ERROR_ENFILE	0x80010217	
SYS_NET_ERROR_EMFILE	0x80010218	
SYS_NET_ERROR_ENOTTY	0x80010219	
SYS_NET_ERROR_EXTBSY	0x8001021a	
SYS_NET_ERROR_EFBIG	0x8001021b	
SYS_NET_ERROR_ENOSPC	0x8001021c	
SYS_NET_ERROR_ESPIPE	0x8001021d	
SYS_NET_ERROR_EROFS	0x8001021e	
SYS_NET_ERROR_EMLINK	0x8001021f	
SYS_NET_ERROR_EPIPE	0x80010220	
SYS_NET_ERROR_EDOM	0x80010221	
SYS_NET_ERROR_ERANGE	0x80010222	
SYS_NET_ERROR_EAGAIN	0x80010223	
SYS_NET_ERROR_EWOULDBLOCK		
SYS_NET_ERROR_EINPROGRESS	0x80010224	
SYS_NET_ERROR_EALREADY	0x80010225	
SYS_NET_ERROR_ENOTSOCK	0x80010226	
SYS_NET_ERROR_EDESTADDRREQ	0x80010227	
SYS_NET_ERROR_EMSGSIZE	0x80010228	
SYS_NET_ERROR_EPROTOTYPE	0x80010229	
SYS_NET_ERROR_ENOPROTOOPT	0x8001022a	
SYS_NET_ERROR_EPROTONOSUPPORT	0x8001022b	
SYS_NET_ERROR_ESOCKTNOSUPPORT	0x8001022c	
SYS_NET_ERROR_EOPNOTSUPP	0x8001022d	
SYS_NET_ERROR_EPFNOSUPPORT	0x8001022e	
SYS_NET_ERROR_EAFNOSUPPORT	0x8001022f	
SYS_NET_ERROR_EADDRINUSE	0x80010230	
SYS_NET_ERROR_EADDRNOTAVAIL	0x80010231	
SYS_NET_ERROR_ENETDOWN	0x80010232	
SYS_NET_ERROR_ENETUNREACH	0x80010233	
SYS_NET_ERROR_ENETRESET	0x80010234	
SYS_NET_ERROR_ECONNABORTED	0x80010235	
SYS_NET_ERROR_ECONNRESET	0x80010236	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
SYS_NET_ERROR_ENOBUFS	0x80010237	no free network buffers, usually caused by very high rate of filling/emptying the network queue
SYS_NET_ERROR_EISCONN	0x80010238	
SYS_NET_ERROR_ENOTCONN	0x80010239	
SYS_NET_ERROR_ESHUTDOWN	0x8001023a	
SYS_NET_ERRORETOOMANYREFS	0x8001023b	
SYS_NET_ERRORETIMEOUT	0x8001023c	
SYS_NET_ERROR_ECONNREFUSED	0x8001023d	
SYS_NET_ERROR_ELOOP	0x8001023e	
SYS_NET_ERROR_ENAMETOOLONG	0x8001023f	
SYS_NET_ERROR_EHOSTDOWN	0x80010240	
SYS_NET_ERROR_EHOSTUNREACH	0x80010241	
SYS_NET_ERROR_ENOTEMPTY	0x80010242	
SYS_NET_ERROR_EPROCLIM	0x80010243	
SYS_NET_ERROR_EUSERS	0x80010244	
SYS_NET_ERROR_EDQUOT	0x80010245	
SYS_NET_ERROR_ESTALE	0x80010246	
SYS_NET_ERROR_EREMOTE	0x80010247	
SYS_NET_ERROR_EBADRPC	0x80010248	
SYS_NET_ERROR_ERPCMISMATCH	0x80010249	
SYS_NET_ERROR_EPROGUNAVAIL	0x8001024a	
SYS_NET_ERROR_EPROGMISMATCH	0x8001024b	
SYS_NET_ERROR_EPROCUNAVAIL	0x8001024c	
SYS_NET_ERROR_ENOLCK	0x8001024d	
SYS_NET_ERROR_ENOSYS	0x8001024e	
SYS_NET_ERROR_EFTYPE	0x8001024f	
SYS_NET_ERROR_EAUTH	0x80010250	
SYS_NET_ERROR_ENEEDAUTH	0x80010251	
SYS_NET_ERROR_EIDRM	0x80010252	
SYS_NET_ERROR_ENOMSG	0x80010253	
SYS_NET_ERROR_EOVERFLOW	0x80010254	
SYS_NET_ERROR_EILSEQ	0x80010255	
SYS_NET_ERROR_ENOTSUP	0x80010256	
SYS_NET_ERROR_ECANCELED	0x80010257	
SYS_NET_ERROR_EBADMSG	0x80010258	
SYS_NET_ERROR_ENODATA	0x80010259	
SYS_NET_ERROR_ENOSR	0x8001025a	
SYS_NET_ERROR_ENOSTR	0x8001025b	
SYS_NET_ERRORETIME	0x8001025c	
Cell Net Ctl errors (libnetctl)		
CELL_NET_CTL_ERROR_NOT_INITIALIZED	0x80130101	Library not initialized
CELL_NET_CTL_ERROR_NOT_TERMINATED	0x80130102	Library not terminated
CELL_NET_CTL_ERROR_HANDLER_MAX	0x80130103	No more handlers can be registered
CELL_NET_CTL_ERROR_ID_NOT_FOUND	0x80130104	ID specified in argument not registered
CELL_NET_CTL_ERROR_INVALID_ID	0x80130105	ID specified in argument invalid
CELL_NET_CTL_ERROR_INVALID_CODE	0x80130106	Code specified in argument invalid
CELL_NET_CTL_ERROR_INVALID_ADDR	0x80130107	Address specified in argument invalid
CELL_NET_CTL_ERROR_NOT_CONNECTED	0x80130108	Not connected
CELL_NET_CTL_ERROR_NOT_AVAIL	0x80130109	Not in state where information can be obtained
CELL_NET_CTL_ERROR_INVALID_TYPE	0x8013010A	Type specified as argument is invalid
CELL_NET_CTL_ERROR_INVALID_SIZE	0x8013010B	Value of the size member of the structure is invalid
CELL_NET_CTL_ERROR_WLAN_DEAUTHTED	0x80130137	Disconnected from the AP
CELL_NET_CTL_ERROR_WLAN_KEYINFO_EXCHNAGE_TIMEOUT	0x8013013D	Key information exchange of WPA timed out
CELL_NET_CTL_ERROR_WLAN_ASSOC_FAILED	0x8013013E	Association failed
CELL_NET_CTL_ERROR_WLAN_AP_DISAPPEARED	0x8013013F	Beacons from the AP stopped arriving
CELL_NET_CTL_ERROR_NET_DISABLED	0x80130181	Internet connection is disabled

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_NET_CTL_ERROR_NET_NOT_CONNECTED	0x80130182	"A connection to the network could not be established. Go to [Settings] > [Network Settings] and check your settings" // Network connection could not be established; connection settings may be incorrect
CELL_NET_CTL_ERROR_NP_NO_ACCOUNT	0x80130183	NP account is not set
CELL_NET_CTL_ERROR_NP_RESERVED1	0x80130184	Unused
CELL_NET_CTL_ERROR_NP_RESERVED2	0x80130185	Unused
CELL_NET_CTL_ERROR_NET_CABLE_NOT_CONNECTED	0x80130186	Ethernet cable not connected correctly
CELL_NET_CTL_ERROR_DIALOG_CANCELED	0x80130190	Dialog was cancelled
CELL_NET_CTL_ERROR_DIALOG_ABORTED	0x80130191	Dialog was forced to terminate
CELL_NET_CTL_ERROR_PPPOE_SESSION_INIT	0x80130409	PPP INIT state error
CELL_NET_CTL_ERROR_PPPOE_SESSION_NO_PAD0	0x8013040A	PADO could not be received
CELL_NET_CTL_ERROR_PPPOE_SESSION_NO_PADS	0x8013040B	PADS could not be received
CELL_NET_CTL_ERROR_PPPOE_SESSION_GET_PADT	0x8013040D	PADT was received
CELL_NET_CTL_ERROR_PPPOE_SESSION_SERVICE_NAME	0x8013040F	Service Name error was received
CELL_NET_CTL_ERROR_PPPOE_SESSION_AC_SYSTEM	0x80130410	AC System error was received
CELL_NET_CTL_ERROR_PPPOE_SESSION_GENERIC	0x80130411	Generic error was received
CELL_NET_CTL_ERROR_PPPOE_STATUS_AUTH	0x80130412	Authorization failed (wrong user name or password)
CELL_NET_CTL_ERROR_PPPOE_STATUS_NETWORK	0x80130413	PPP NETWORK state error
CELL_NET_CTL_ERROR_PPPOE_STATUS_TERMINATE	0x80130414	PPP TERMINATE state error
CELL_NET_CTL_ERROR_DHCPLEASE_TIME	0x80130504	IP address lease time expired
Cell Ftp Service errors (libftp)		
CELL_FTP_SERVICE_ERROR_NETWORK_NOT_INITIALIZED	0x80130701	Network access has not been initialized
CELL_FTP_SERVICE_ERROR_STORAGE_NOT_INITIALIZED	0x80130702	HDD access has not been initialized
CELL_FTP_SERVICE_ERROR_RTCLOCK_NOT_INITIALIZED	0x80130703	Real-time Clock has not been initialized
CELL_FTP_SERVICE_ERROR_ALREADY_RUNNING	0x80130704	An instance of the service is already running
CELL_FTP_SERVICE_ERROR_NOT_RUNNING	0x80130705	Service is not currently running
CELL_FTP_SERVICE_ERROR_NETWORK_ERROR	0x80130706	A core network error has occurred
CELL_FTP_SERVICE_ERROR_NULL_POINTER	0x80130707	Null pointer error
CELL_FTP_SERVICE_ERROR_INTERNAL	0x801307FF	An internal error has occurred
Cell Http errors (libhttp)		
CELL_HTTP_ERROR_ALREADY_INITIALIZED	0x80710001	Library has already been initialized and cannot be initialized again.
CELL_HTTP_ERROR_NOT_INITIALIZED	0x80710002	Library has not yet been initialized. Please initialize before use.
CELL_HTTP_ERROR_NO_MEMORY	0x80710003	Call to allocate memory failed (returns NULL)
CELL_HTTP_ERROR_NO_BUFFER	0x80710004	No buffer was provided in one of the parameters
CELL_HTTP_ERROR_NO_STRING	0x80710005	No string to read has been provided (as a parameter)
CELL_HTTP_ERROR_INSUFFICIENT	0x80710006	Buffer space was insufficient to write into
CELL_HTTP_ERROR_INVALID_URI	0x80710007	Malformed URI
CELL_HTTP_ERROR_INVALID_HEADER	0x80710008	Malformed libhttp header
CELL_HTTP_ERROR_BAD_METHOD	0x80710009	The method provided is not usable
CELL_HTTP_ERROR_BAD_CLIENT	0x80710010	Not a proper client ID
CELL_HTTP_ERROR_BAD_TRANS	0x80710011	Not a proper transaction ID
CELL_HTTP_ERROR_NO_CONNECTION	0x80710012	No connection available
CELL_HTTP_ERROR_NO_REQUEST_SENT	0x80710013	Request has not been sent yet
CELL_HTTP_ERROR_ALREADY_BUILT	0x80710014	Request has already been built
CELL_HTTP_ERROR_ALREADY_SENT	0x80710015	Request has already been sent
CELL_HTTP_ERROR_NO_HEADER	0x80710016	That header does not exist
CELL_HTTP_ERROR_NO_CONTENT_LENGTH	0x80710017	No content-length was defined
CELL_HTTP_ERROR_TOO_MANY_REDIRECTS	0x80710018	Exceeded maximum number of auto-redirects (default:5)
CELL_HTTP_ERROR_TOO_MANY_AUTHS	0x80710019	Exceeded maximum number of auto-authentication tries (default:5)
CELL_HTTP_ERROR_TRANS_NO_CONNECTION	0x80710020	Transaction does not have a connection associated to it
CELL_HTTP_ERROR_CB_FAILED	0x80710021	Tried to callback to the application, but failed (e.g.: CellHttpAuthenticationCallback returns a negative value or has not been set)
CELL_HTTP_ERROR_NOT_PIPE	0x80710022	The connection has no transactions in the pipeline –internal error
CELL_HTTP_ERROR_OUT_OF_ORDER_PIPE	0x80710023	There is another request next in the pipeline
CELL_HTTP_ERROR_TRANS_ABORTED	0x80710024	This transaction has been aborted
CELL_HTTP_ERROR_BROKEN_PIPELINE	0x80710025	The pipeline that this transaction was using has been aborted, and thus broke the pipeline
CELL_HTTP_ERROR_UNAVAILABLE	0x80710026	The request made is for an unavailable service

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_INVALID_VALUE	0x80710027	An invalid value was found in processing
CELL_HTTP_ERROR_CANNOT_AUTHENTICATE	0x80710028	Cannot authenticate the transaction (not enough info)
CELL_HTTP_ERROR_COOKIE_NOT_FOUND	0x80710041	The cookie is not valid
CELL_HTTP_ERROR_COOKIE_INVALID_DOMAIN	0x80710042	The cookie contains an invalid domain
CELL_HTTP_ERROR_CACHE_ALREADY_INITIALIZED	0x80710043	cache has already been initialized
CELL_HTTP_ERROR_CACHE_NOT_INITIALIZED	0x80710044	cache has not yet been initialized
CELL_HTTP_ERROR_LINE_EXCEEDS_MAX	0x80710045	The response line or header exceeds the maximum response buffer size
CELL_HTTP_ERROR_REQUIRES_BASIC_AUTH	0x80710046	basic auth is disabled, yet basic auth is required for authorization
CELL_HTTP_ERROR_UNKNOWN	0x80710051	Undefined error (not listed below)
CELL_HTTP_ERROR_INTERNAL	0x80710052	Internal failure
CELL_HTTP_ERROR_NONREMOVABLE	0x80710053	Not a removable connection (not free or non-existent connection)
CELL_HTTP_ERROR_BAD_CONN	0x80710054	Bad connection (non-existent)
CELL_HTTP_ERROR_BAD_MAN	0x80710055	Bad connection manager (non-existent)
CELL_HTTP_ERROR_NO_POOL	0x80710056	No connection pool exists
CELL_HTTP_ERROR_NO_REQUEST	0x80710057	No request (structure) or request has not been created yet
CELL_HTTP_ERROR_LOCK_FAILED	0x80710058	Internal failure
CELL_HTTP_ERROR_INVALID_DATA	0x80710059	Encountered invalid data during processing
CELL_HTTP_ERROR_BROKEN_CHUNK	0x8071005a	Unexpectedly interrupted while processing chunk encoding
CELL_HTTP_ERROR_DECODE_SETUP	0x8071005b	error occurred in setting up for decoding
CELL_HTTP_ERROR_DECODE_STREAM	0x8071005c	error occurred in setting up for decoding
CELL_HTTP_ERROR_BROKEN_DECODE_STREAM	0x8071005d	the decode stream has been interrupted
CELL_HTTP_ERROR_INVALID_DCACHE_PATH	0x80710060	disk cache path is invalid
CELL_HTTP_ERROR_DCACHE_ALREADY_INITIALIZED	0x80710061	disk cache has already been initialized
CELL_HTTP_ERROR_DCACHE_NOT_INITIALIZED	0x80710062	disk cache has not yet been initialized
CELL_HTTP_ERROR_TOO_MANY_DCACHE_ENTRY	0x80710063	too many disk cache entries
CELL_HTTP_ERROR_DUP_DCACHE_ENTRY	0x80710064	duplicated cache entry is found
CELL_HTTP_ERROR_WRITE_DCACHE	0x80710065	unknown disk cache writing error
CELL_HTTP_ERROR_READ_DCACHE	0x80710066	unknown disk cache reading error
CELL_HTTP_ERROR_CACHE_TOO_LARGE	0x80710067	too large cache entry
CELL_HTTP_ERROR_INVALID_DCACHE_VERSION	0x80710068	invalid disk cache version
CELL_HTTP_ERROR_DCACHE_FILE_BROKEN	0x80710069	disk cache file is broken
CELL_HTTP_ERROR_DCACHE_EXCEEDS_MAX	0x8071006a	disk cache exceeds maximum allowed
CELL_HTTP_ERROR_DCACHE_BUSY	0x8071006b	disk cache is busy
CELL_HTTP_ERROR_DCACHE_INDEX_BROKEN	0x8071006c	disk cache index file is broken
CELL_HTTP_ERROR_INVALID_DCACHE_INDEX_NODE	0x8071006d	invalid index node type
CELL_HTTP_ERROR_DCACHE_FILE_INCONSISTENCY	0x8071006e	detect inconsistency in cache file
CELL_HTTP_ERROR_DCACHE_URI_TOO_LONG	0x8071006f	too long url
CELL_HTTP_ERROR_READ_DCACHE_EOF	0x80710070	eof in reading
CELL_HTTP_ERROR_END_OF_DCACHE_INDEX_NODE	0x80710071	end of node
CELL_HTTP_ERROR_NO_CACHE_MEMORY	0x80710072	no cache memory
CELL_HTTP_ERROR_DCACHE_BROKEN	0x80710073	broken cache file
CELL_HTTP_ERROR_DCACHE_TOO_MANY_WRITE	0x80710074	too many cache file for writing
CELL_HTTP_ERROR_DCACHE_TOO_MANY_READ	0x80710075	too many cache file for reading
CELL_HTTP_ERROR_DCACHE_FATAL	0x80710076	fatal error have been occured
CELL_HTTP_ERROR_DCACHE_UNSUPPORTED_FEATURE	0x80710077	unsupported feature
CELL_HTTP_ERROR_DCACHE_INDEX_IS_ALREADY_OPEN	0x80710078	cache index node is already open
CELL_HTTP_ERROR_DCACHE_INDEX_IS_OPENING	0x80710079	cache index node is now opening
CELL_HTTP_ERROR_DCACHE_UNKNOWN	0x80710080	diskcache unknown error
CELL_HTTP_ERROR_DCACHE_INDEX_IS_CLOSED	0x80710081	cache index node is already closed
CELL_HTTP_ERROR_DCACHE_ABORTED	0x80710082	opening diskcache is aborted
CELL_HTTP_ERROR_DCACHE_INDEX_IS_CLOSING	0x80710083	opening diskcache is aborted
CELL_HTTP_ERROR_DCACHE_UNKNOWN_INDEX_STATE	0x80710084	unknown index state
CELL_HTTP_ERROR_NET_FIN	0x80710091	Received EOF (FIN) from the socket
CELL_HTTP_ERROR_NET_CONNECT_TIMEOUT	0x80710092	"An error has occurred. You have been signed out of PSN (80710092)" // Timed out while connecting
CELL_HTTP_ERROR_NET_SELECT_TIMEOUT	0x80710093	Timed out while polling
CELL_HTTP_ERROR_NET_SEND_TIMEOUT	0x80710094	timed out while polling

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_RESOLVER	0x80710100	Error calling gethostbyname(). Error code is net_h_errno.
CELL_HTTP_ERROR_NET_RESOLVER_HOST_NOT_FOUND	0x80710101	Connection error
CELL_HTTP_ERROR_NET_RESOLVER_TRY AGAIN	0x80710102	DNS Error; no DNS server available. // IP conflict, PS3 Cannot connect to the router with current IP information. Try rebooting your router
CELL_HTTP_ERROR_NET_RESOLVER_NO_RECOVERY	0x80710103	Server timed out
CELL_HTTP_ERROR_NET_RESOLVER_NO_DATA CELL_HTTP_ERROR_NET_RESOLVER_NO_ADDRESS	0x80710104	DNS Error // Experienced with Cobra CFW and trying PS3ITA/Rebug Spoof for PSN.
CELL_HTTP_ERROR_NET_RESOLVER_NETDB_INTERNAL	0x807101FF	"An error occurred during communication with the server. This is a DNS error (807101FF)"
CELL_HTTP_ERROR_NET_ABORT	0x80710200	Error calling network abort. Error code is net_errno.
CELL_HTTP_ERROR_NET_ABORT_EPERM	0x80710201	
CELL_HTTP_ERROR_NET_ABORT_ENOENT	0x80710202	Disconnection error
CELL_HTTP_ERROR_NET_ABORT_ESRCH	0x80710203	
CELL_HTTP_ERROR_NET_ABORT_EINTR	0x80710204	
CELL_HTTP_ERROR_NET_ABORT_EIO	0x80710205	
CELL_HTTP_ERROR_NET_ABORT_ENXIO	0x80710206	
CELL_HTTP_ERROR_NET_ABORT_E2BIG	0x80710207	
CELL_HTTP_ERROR_NET_ABORT_ENOEXEC	0x80710208	
CELL_HTTP_ERROR_NET_ABORT_EBADF	0x80710209	
CELL_HTTP_ERROR_NET_ABORT_ECHILD	0x8071020a	
CELL_HTTP_ERROR_NET_ABORT_EDEADLK	0x8071020b	
CELL_HTTP_ERROR_NET_ABORT_ENOMEM	0x8071020c	
CELL_HTTP_ERROR_NET_ABORT_EACCES	0x8071020d	
CELL_HTTP_ERROR_NET_ABORT_EFAULT	0x8071020e	
CELL_HTTP_ERROR_NET_ABORT_ENOTBLK	0x8071020f	
CELL_HTTP_ERROR_NET_ABORT_EBUSY	0x80710210	
CELL_HTTP_ERROR_NET_ABORT_EEXIST	0x80710211	
CELL_HTTP_ERROR_NET_ABORT_EXDEV	0x80710212	
CELL_HTTP_ERROR_NET_ABORT_ENODEV	0x80710213	
CELL_HTTP_ERROR_NET_ABORT_ENOTDIR	0x80710214	
CELL_HTTP_ERROR_NET_ABORT_EISDIR	0x80710215	
CELL_HTTP_ERROR_NET_ABORT_EINVAL	0x80710216	
CELL_HTTP_ERROR_NET_ABORT_ENFILE	0x80710217	
CELL_HTTP_ERROR_NET_ABORT_EMFILE	0x80710218	
CELL_HTTP_ERROR_NET_ABORT_ENOTTY	0x80710219	
CELL_HTTP_ERROR_NET_ABORT_ETXTBSY	0x8071021a	
CELL_HTTP_ERROR_NET_ABORT_EFBIG	0x8071021b	
CELL_HTTP_ERROR_NET_ABORT_ENOSPC	0x8071021c	
CELL_HTTP_ERROR_NET_ABORT_ESPIPE	0x8071021d	
CELL_HTTP_ERROR_NET_ABORT_EROFS	0x8071021e	
CELL_HTTP_ERROR_NET_ABORT_EMLINK	0x8071021f	
CELL_HTTP_ERROR_NET_ABORT_EPIPE	0x80710220	
CELL_HTTP_ERROR_NET_ABORT_EDOM	0x80710221	
CELL_HTTP_ERROR_NET_ABORT_ERANGE	0x80710222	
CELL_HTTP_ERROR_NET_ABORT_EAGAIN	0x80710223	
CELL_HTTP_ERROR_NET_ABORT_EWOULDBLOCK	0x80710223	
CELL_HTTP_ERROR_NET_ABORT_EINPROGRESS	0x80710224	
CELL_HTTP_ERROR_NET_ABORT_EALREADY	0x80710225	
CELL_HTTP_ERROR_NET_ABORT_ENOTSOCK	0x80710226	
CELL_HTTP_ERROR_NET_ABORT_EDESTADDRREQ	0x80710227	
CELL_HTTP_ERROR_NET_ABORT_EMSGSIZE	0x80710228	
CELL_HTTP_ERROR_NET_ABORT_EPROTOTYPE	0x80710229	
CELL_HTTP_ERROR_NET_ABORT_ENOPROTOOPT	0x8071022a	
CELL_HTTP_ERROR_NET_ABORT_EPROTONOSUPPORT	0x8071022b	
CELL_HTTP_ERROR_NET_ABORT_ESOCKTNOSUPPORT	0x8071022c	
CELL_HTTP_ERROR_NET_ABORT_EOPNOTSUPP	0x8071022d	
CELL_HTTP_ERROR_NET_ABORT_EPFNOSUPPORT	0x8071022e	
CELL_HTTP_ERROR_NET_ABORT_EAFNOSUPPORT	0x8071022f	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_ABORT_EADDRINUSE	0x80710230	
CELL_HTTP_ERROR_NET_ABORT_EADDRNOTAVAIL	0x80710231	
CELL_HTTP_ERROR_NET_ABORT_ENETDOWN	0x80710232	
CELL_HTTP_ERROR_NET_ABORT_ENETUNREACH	0x80710233	
CELL_HTTP_ERROR_NET_ABORT_ENETRESET	0x80710234	
CELL_HTTP_ERROR_NET_ABORT_ECONNABORTED	0x80710235	
CELL_HTTP_ERROR_NET_ABORT_ECONNRESET	0x80710236	
CELL_HTTP_ERROR_NET_ABORT_ENOBUFS	0x80710237	
CELL_HTTP_ERROR_NET_ABORT_EISCONN	0x80710238	
CELL_HTTP_ERROR_NET_ABORT_ENOTCONN	0x80710239	
CELL_HTTP_ERROR_NET_ABORT_ESHUTDOWN	0x8071023a	
CELL_HTTP_ERROR_NET_ABORTETOOMANYREFS	0x8071023b	
CELL_HTTP_ERROR_NET_ABORTETIMEOUT	0x8071023c	
CELL_HTTP_ERROR_NET_ABORT_ECONNREFUSED	0x8071023d	
CELL_HTTP_ERROR_NET_ABORT_ELOOP	0x8071023e	
CELL_HTTP_ERROR_NET_ABORT_ENAMETOOLONG	0x8071023f	
CELL_HTTP_ERROR_NET_ABORT_EHOSTDOWN	0x80710240	
CELL_HTTP_ERROR_NET_ABORT_EHOSTUNREACH	0x80710241	
CELL_HTTP_ERROR_NET_ABORT_ENOTEMPTY	0x80710242	
CELL_HTTP_ERROR_NET_ABORT_EPROCLIM	0x80710243	
CELL_HTTP_ERROR_NET_ABORT_EUSERS	0x80710244	
CELL_HTTP_ERROR_NET_ABORT_EDQUOT	0x80710245	
CELL_HTTP_ERROR_NET_ABORT_ESTALE	0x80710246	
CELL_HTTP_ERROR_NET_ABORT_EREMOTE	0x80710247	
CELL_HTTP_ERROR_NET_ABORT_EBADRPC	0x80710248	
CELL_HTTP_ERROR_NET_ABORT_ERPCMISMATCH	0x80710249	
CELL_HTTP_ERROR_NET_ABORT_EPROGUNAVAIL	0x8071024a	
CELL_HTTP_ERROR_NET_ABORT_EPROGMISMATCH	0x8071024b	
CELL_HTTP_ERROR_NET_ABORT_EPROCUNAVAIL	0x8071024c	
CELL_HTTP_ERROR_NET_ABORT_ENOLCK	0x8071024d	
CELL_HTTP_ERROR_NET_ABORT_ENOSYS	0x8071024e	
CELL_HTTP_ERROR_NET_ABORT_EFTYPE	0x8071024f	
CELL_HTTP_ERROR_NET_ABORT_EAUTH	0x80710250	
CELL_HTTP_ERROR_NET_ABORT_ENEEDAUTH	0x80710251	
CELL_HTTP_ERROR_NET_ABORT_EIDRM	0x80710252	
CELL_HTTP_ERROR_NET_ABORT_ENOMSG	0x80710253	
CELL_HTTP_ERROR_NET_ABORT_EOVERFLOW	0x80710254	
CELL_HTTP_ERROR_NET_ABORT_EILSEQ	0x80710255	
CELL_HTTP_ERROR_NET_ABORT_ENOTSUP	0x80710256	
CELL_HTTP_ERROR_NET_ABORT_ECANCELED	0x80710257	
CELL_HTTP_ERROR_NET_ABORT_EBADMSG	0x80710258	
CELL_HTTP_ERROR_NET_ABORT_ENODATA	0x80710259	
CELL_HTTP_ERROR_NET_ABORT_ENOSR	0x8071025a	
CELL_HTTP_ERROR_NET_ABORT_ENOSTR	0x8071025b	
CELL_HTTP_ERROR_NET_ABORTETIME	0x8071025c	
CELL_HTTP_ERROR_NET_OPTION	0x80710300	Error calling setsockopt(). Error code is net_errno.
CELL_HTTP_ERROR_NET_OPTION_EPERM	0x80710301	
CELL_HTTP_ERROR_NET_OPTION_ENOENT	0x80710302	
CELL_HTTP_ERROR_NET_OPTION_ESRCH	0x80710303	
CELL_HTTP_ERROR_NET_OPTION_EINTR	0x80710304	
CELL_HTTP_ERROR_NET_OPTION_EIO	0x80710305	
CELL_HTTP_ERROR_NET_OPTION_ENXIO	0x80710306	
CELL_HTTP_ERROR_NET_OPTION_E2BIG	0x80710307	
CELL_HTTP_ERROR_NET_OPTION_ENOEXEC	0x80710308	
CELL_HTTP_ERROR_NET_OPTION_EBADF	0x80710309	
CELL_HTTP_ERROR_NET_OPTION_ECHILD	0x8071030a	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_OPTION_EDEADLK	0x8071030b	
CELL_HTTP_ERROR_NET_OPTION_ENOMEM	0x8071030c	
CELL_HTTP_ERROR_NET_OPTION_EACCES	0x8071030d	
CELL_HTTP_ERROR_NET_OPTION_EFAULT	0x8071030e	
CELL_HTTP_ERROR_NET_OPTION_ENOTBLK	0x8071030f	
CELL_HTTP_ERROR_NET_OPTION_EBUSY	0x80710310	
CELL_HTTP_ERROR_NET_OPTION_EEXIST	0x80710311	
CELL_HTTP_ERROR_NET_OPTION_EXDEV	0x80710312	
CELL_HTTP_ERROR_NET_OPTION_ENODEV	0x80710313	
CELL_HTTP_ERROR_NET_OPTION_ENOTDIR	0x80710314	
CELL_HTTP_ERROR_NET_OPTION_EISDIR	0x80710315	
CELL_HTTP_ERROR_NET_OPTION_EINVAL	0x80710316	
CELL_HTTP_ERROR_NET_OPTION_ENFILE	0x80710317	
CELL_HTTP_ERROR_NET_OPTION_EMFILE	0x80710318	
CELL_HTTP_ERROR_NET_OPTION_ENOTTY	0x80710319	
CELL_HTTP_ERROR_NET_OPTION_ETXTBSY	0x8071031a	
CELL_HTTP_ERROR_NET_OPTION_EFBIG	0x8071031b	
CELL_HTTP_ERROR_NET_OPTION_ENOSPC	0x8071031c	
CELL_HTTP_ERROR_NET_OPTION_ESPIPE	0x8071031d	
CELL_HTTP_ERROR_NET_OPTION_EROFS	0x8071031e	
CELL_HTTP_ERROR_NET_OPTION_EMLINK	0x8071031f	
CELL_HTTP_ERROR_NET_OPTION_EPIPE	0x80710320	
CELL_HTTP_ERROR_NET_OPTION_EDOM	0x80710321	
CELL_HTTP_ERROR_NET_OPTION_ERANGE	0x80710322	
CELL_HTTP_ERROR_NET_OPTION_EAGAIN	0x80710323	
CELL_HTTP_ERROR_NET_OPTION_EWOULDBLOCK	0x80710323	
CELL_HTTP_ERROR_NET_OPTION_EINPROGRESS	0x80710324	
CELL_HTTP_ERROR_NET_OPTION_EALREADY	0x80710325	
CELL_HTTP_ERROR_NET_OPTION_ENOTSOCK	0x80710326	
CELL_HTTP_ERROR_NET_OPTION_EDESTADDRREQ	0x80710327	
CELL_HTTP_ERROR_NET_OPTION_EMSGSIZE	0x80710328	
CELL_HTTP_ERROR_NET_OPTION_EPROTOTYPE	0x80710329	
CELL_HTTP_ERROR_NET_OPTION_ENOPROTOOPT	0x8071032a	
CELL_HTTP_ERROR_NET_OPTION_EPROTONOSUPPORT	0x8071032b	
CELL_HTTP_ERROR_NET_OPTION_ESOCKTNOSUPPORT	0x8071032c	
CELL_HTTP_ERROR_NET_OPTION_EOPNOTSUPP	0x8071032d	
CELL_HTTP_ERROR_NET_OPTION_EPFNOSUPPORT	0x8071032e	
CELL_HTTP_ERROR_NET_OPTION_EAFNOSUPPORT	0x8071032f	
CELL_HTTP_ERROR_NET_OPTION_EADDRINUSE	0x80710330	
CELL_HTTP_ERROR_NET_OPTION_EADDRNOTAVAIL	0x80710331	
CELL_HTTP_ERROR_NET_OPTION_ENETDOWN	0x80710332	
CELL_HTTP_ERROR_NET_OPTION_ENETUNREACH	0x80710333	
CELL_HTTP_ERROR_NET_OPTION_ENETRESET	0x80710334	
CELL_HTTP_ERROR_NET_OPTION_ECONNABORTED	0x80710335	
CELL_HTTP_ERROR_NET_OPTION_ECONNRESET	0x80710336	
CELL_HTTP_ERROR_NET_OPTION_ENOBUFS	0x80710337	
CELL_HTTP_ERROR_NET_OPTION_EISCONN	0x80710338	
CELL_HTTP_ERROR_NET_OPTION_ENOTCONN	0x80710339	
CELL_HTTP_ERROR_NET_OPTION_ESHUTDOWN	0x8071033a	
CELL_HTTP_ERROR_NET_OPTIONETOOMANYREFS	0x8071033b	
CELL_HTTP_ERROR_NET_OPTION_ETIMEDOUT	0x8071033c	
CELL_HTTP_ERROR_NET_OPTION_ECONNREFUSED	0x8071033d	
CELL_HTTP_ERROR_NET_OPTION_ELOOP	0x8071033e	
CELL_HTTP_ERROR_NET_OPTION_ENAMETOOLONG	0x8071033f	
CELL_HTTP_ERROR_NET_OPTION_EHOSTDOWN	0x80710340	
CELL_HTTP_ERROR_NET_OPTION_EHOSTUNREACH	0x80710341	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_OPTION_ENOTEMPTY	0x80710342	
CELL_HTTP_ERROR_NET_OPTION_EPROCLIM	0x80710343	
CELL_HTTP_ERROR_NET_OPTION_EUSERS	0x80710344	
CELL_HTTP_ERROR_NET_OPTION_EDQUOT	0x80710345	
CELL_HTTP_ERROR_NET_OPTION_ESTALE	0x80710346	
CELL_HTTP_ERROR_NET_OPTION_EREMOTE	0x80710347	
CELL_HTTP_ERROR_NET_OPTION_EBADRPC	0x80710348	
CELL_HTTP_ERROR_NET_OPTION_ERPCMISMATCH	0x80710349	
CELL_HTTP_ERROR_NET_OPTION_EPROGUNAVAIL	0x8071034a	
CELL_HTTP_ERROR_NET_OPTION_EPROGMISMATCH	0x8071034b	
CELL_HTTP_ERROR_NET_OPTION_EPROCUNAVAIL	0x8071034c	
CELL_HTTP_ERROR_NET_OPTION_ENOLCK	0x8071034d	
CELL_HTTP_ERROR_NET_OPTION_ENOSYS	0x8071034e	
CELL_HTTP_ERROR_NET_OPTION_EFTYPE	0x8071034f	
CELL_HTTP_ERROR_NET_OPTION_EAUTH	0x80710350	
CELL_HTTP_ERROR_NET_OPTION_ENEEDAUTH	0x80710351	
CELL_HTTP_ERROR_NET_OPTION_EIDRM	0x80710352	
CELL_HTTP_ERROR_NET_OPTION_ENOMSG	0x80710353	
CELL_HTTP_ERROR_NET_OPTION_EOVERFLOW	0x80710354	
CELL_HTTP_ERROR_NET_OPTION_EILSEQ	0x80710355	
CELL_HTTP_ERROR_NET_OPTION_ENOTSUP	0x80710356	
CELL_HTTP_ERROR_NET_OPTION_ECANCELED	0x80710357	
CELL_HTTP_ERROR_NET_OPTION_EBADMSG	0x80710358	
CELL_HTTP_ERROR_NET_OPTION_ENODATA	0x80710359	
CELL_HTTP_ERROR_NET_OPTION_ENOSR	0x8071035a	
CELL_HTTP_ERROR_NET_OPTION_ENOSTR	0x8071035b	
CELL_HTTP_ERROR_NET_OPTIONETIME	0x8071035c	
CELL_HTTP_ERROR_NET_SOCKET	0x80710400	Error calling socket(). Error code is net_errno.
CELL_HTTP_ERROR_NET_SOCKET_EPERM	0x80710401	
CELL_HTTP_ERROR_NET_SOCKET_ENOENT	0x80710402	
CELL_HTTP_ERROR_NET_SOCKET_ESRCH	0x80710403	
CELL_HTTP_ERROR_NET_SOCKET_EINTR	0x80710404	
CELL_HTTP_ERROR_NET_SOCKET_EIO	0x80710405	
CELL_HTTP_ERROR_NET_SOCKET_ENXIO	0x80710406	
CELL_HTTP_ERROR_NET_SOCKET_E2BIG	0x80710407	
CELL_HTTP_ERROR_NET_SOCKET_ENOEXC	0x80710408	
CELL_HTTP_ERROR_NET_SOCKET_EBADF	0x80710409	
CELL_HTTP_ERROR_NET_SOCKET_ECHILD	0x8071040A	
CELL_HTTP_ERROR_NET_SOCKET_EDEADLK	0x8071040B	
CELL_HTTP_ERROR_NET_SOCKET_ENOMEM	0x8071040C	Network memory running low. If playing a game, exit out and restart it or reboot console; if doing something else, reboot console and issue should resolve itself
CELL_HTTP_ERROR_NET_SOCKET_EACCES	0x8071040D	
CELL_HTTP_ERROR_NET_SOCKET_EFAULT	0x8071040E	
CELL_HTTP_ERROR_NET_SOCKET_ENOTBLK	0x8071040F	
CELL_HTTP_ERROR_NET_SOCKET_EBUSY	0x80710410	
CELL_HTTP_ERROR_NET_SOCKET_EEXIST	0x80710411	
CELL_HTTP_ERROR_NET_SOCKET_EXDEV	0x80710412	
CELL_HTTP_ERROR_NET_SOCKET_ENODEV	0x80710413	
CELL_HTTP_ERROR_NET_SOCKET_ENOTDIR	0x80710414	
CELL_HTTP_ERROR_NET_SOCKET_EISDIR	0x80710415	
CELL_HTTP_ERROR_NET_SOCKET_EINVAL	0x80710416	
CELL_HTTP_ERROR_NET_SOCKET_ENFILE	0x80710417	
CELL_HTTP_ERROR_NET_SOCKET_EMFILE	0x80710418	
CELL_HTTP_ERROR_NET_SOCKET_ENOTTY	0x80710419	
CELL_HTTP_ERROR_NET_SOCKET_EXTBSY	0x8071041a	
CELL_HTTP_ERROR_NET_SOCKET_EFBIG	0x8071041b	
CELL_HTTP_ERROR_NET_SOCKET_ENOSPC	0x8071041c	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_SOCKET_ESPIPE	0x8071041d	
CELL_HTTP_ERROR_NET_SOCKET_EROFS	0x8071041e	
CELL_HTTP_ERROR_NET_SOCKET_EMLINK	0x8071041f	
CELL_HTTP_ERROR_NET_SOCKET_EPIPE	0x80710420	
CELL_HTTP_ERROR_NET_SOCKET_EDOM	0x80710421	
CELL_HTTP_ERROR_NET_SOCKET_ERANGE	0x80710422	
CELL_HTTP_ERROR_NET_SOCKET_EAGAIN	0x80710423	
CELL_HTTP_ERROR_NET_SOCKET_EWOULDBLOCK	0x80710423	
CELL_HTTP_ERROR_NET_SOCKET_EINPROGRESS	0x80710424	
CELL_HTTP_ERROR_NET_SOCKET_EALREADY	0x80710425	
CELL_HTTP_ERROR_NET_SOCKET_ENOTSOCK	0x80710426	
CELL_HTTP_ERROR_NET_SOCKET_EDESTADDRREQ	0x80710427	
CELL_HTTP_ERROR_NET_SOCKET_EMMSGSIZE	0x80710428	
CELL_HTTP_ERROR_NET_SOCKET_EPROTOTYPE	0x80710429	
CELL_HTTP_ERROR_NET_SOCKET_ENOPROTOOPT	0x8071042a	
CELL_HTTP_ERROR_NET_SOCKET_EPROTONOSUPPORT	0x8071042b	
CELL_HTTP_ERROR_NET_SOCKET_ESOCKTNOSUPPORT	0x8071042c	
CELL_HTTP_ERROR_NET_SOCKET_EOPNOTSUPP	0x8071042d	
CELL_HTTP_ERROR_NET_SOCKET_EPFNOSUPPORT	0x8071042e	
CELL_HTTP_ERROR_NET_SOCKET_EAFNOSUPPORT	0x8071042f	
CELL_HTTP_ERROR_NET_SOCKET_EADDRINUSE	0x80710430	
CELL_HTTP_ERROR_NET_SOCKET_EADDRNOTAVAIL	0x80710431	
CELL_HTTP_ERROR_NET_SOCKET_ENETDOWN	0x80710432	
CELL_HTTP_ERROR_NET_SOCKET_ENETUNREACH	0x80710433	
CELL_HTTP_ERROR_NET_SOCKET_ENETRESET	0x80710434	
CELL_HTTP_ERROR_NET_SOCKET_ECONNABORTED	0x80710435	
CELL_HTTP_ERROR_NET_SOCKET_ECONNRESET	0x80710436	
CELL_HTTP_ERROR_NET_SOCKET_ENOBUFS	0x80710437	Network memory too low. If still playing a game, restart it; if still having issues after restarting the game, reboot console
CELL_HTTP_ERROR_NET_SOCKET_EISCONN	0x80710438	
CELL_HTTP_ERROR_NET_SOCKET_ENOTCONN	0x80710439	
CELL_HTTP_ERROR_NET_SOCKET_ESHUTDOWN	0x8071043a	
CELL_HTTP_ERROR_NET_SOCKETETOOLONG	0x8071043b	
CELL_HTTP_ERROR_NET_SOCKET_ETIMEDOUT	0x8071043c	
CELL_HTTP_ERROR_NET_SOCKET_ECONNREFUSED	0x8071043d	
CELL_HTTP_ERROR_NET_SOCKET_ELOOP	0x8071043e	
CELL_HTTP_ERROR_NET_SOCKET_ENAMETOOLONG	0x8071043f	
CELL_HTTP_ERROR_NET_SOCKET_EHOSTDOWN	0x80710440	
CELL_HTTP_ERROR_NET_SOCKET_EHOSTUNREACH	0x80710441	
CELL_HTTP_ERROR_NET_SOCKET_ENOTEMPTY	0x80710442	
CELL_HTTP_ERROR_NET_SOCKET_EPROCLIM	0x80710443	
CELL_HTTP_ERROR_NET_SOCKET_EUSERS	0x80710444	
CELL_HTTP_ERROR_NET_SOCKET_EDQUOT	0x80710445	
CELL_HTTP_ERROR_NET_SOCKET_ESTALE	0x80710446	
CELL_HTTP_ERROR_NET_SOCKET_EREMOTE	0x80710447	
CELL_HTTP_ERROR_NET_SOCKET_EBADRPC	0x80710448	
CELL_HTTP_ERROR_NET_SOCKET_ERPCMISMATCH	0x80710449	
CELL_HTTP_ERROR_NET_SOCKET_EPROGUNAVAIL	0x8071044a	
CELL_HTTP_ERROR_NET_SOCKET_EPROGMISMATCH	0x8071044b	
CELL_HTTP_ERROR_NET_SOCKET_EPROCUNAVAIL	0x8071044c	
CELL_HTTP_ERROR_NET_SOCKET_ENOLCK	0x8071044d	
CELL_HTTP_ERROR_NET_SOCKET_ENOSYS	0x8071044e	
CELL_HTTP_ERROR_NET_SOCKET_EFTYPE	0x8071044f	
CELL_HTTP_ERROR_NET_SOCKET_EAUTH	0x80710450	
CELL_HTTP_ERROR_NET_SOCKET_ENEEDAUTH	0x80710451	
CELL_HTTP_ERROR_NET_SOCKET_EIDRM	0x80710452	
CELL_HTTP_ERROR_NET_SOCKET_ENOMSG	0x80710453	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_SOCKET_EOVERFLOW	0x80710454	
CELL_HTTP_ERROR_NET_SOCKET_EILSEQ	0x80710455	
CELL_HTTP_ERROR_NET_SOCKET_ENOTSUP	0x80710456	
CELL_HTTP_ERROR_NET_SOCKET_ECANCELED	0x80710457	
CELL_HTTP_ERROR_NET_SOCKET_EBADMSG	0x80710458	
CELL_HTTP_ERROR_NET_SOCKET_ENODATA	0x80710459	
CELL_HTTP_ERROR_NET_SOCKET_ENOSR	0x8071045a	
CELL_HTTP_ERROR_NET_SOCKET_ENOSTR	0x8071045b	
CELL_HTTP_ERROR_NET_SOCKETETIME	0x8071045c	
CELL_HTTP_ERROR_NET_CONNECT	0x80710500	Error calling connect(). Error code is net_errno.
CELL_HTTP_ERROR_NET_CONNECT_EPERM	0x80710501	
CELL_HTTP_ERROR_NET_CONNECT_ENOENT	0x80710502	
CELL_HTTP_ERROR_NET_CONNECT_ESRCH	0x80710503	
CELL_HTTP_ERROR_NET_CONNECT_EINTR	0x80710504	Game server error // Run internet connection test on console; if it fails, may be a game server issue; check with publisher to see if there are any server issues
CELL_HTTP_ERROR_NET_CONNECT_EIO	0x80710505	
CELL_HTTP_ERROR_NET_CONNECT_ENXIO	0x80710506	
CELL_HTTP_ERROR_NET_CONNECT_E2BIG	0x80710507	
CELL_HTTP_ERROR_NET_CONNECT_ENOEXEC	0x80710508	
CELL_HTTP_ERROR_NET_CONNECT_EBADF	0x80710509	
CELL_HTTP_ERROR_NET_CONNECT_ECHILD	0x8071050a	
CELL_HTTP_ERROR_NET_CONNECT_EDEADLK	0x8071050b	
CELL_HTTP_ERROR_NET_CONNECT_ENOMEM	0x8071050c	
CELL_HTTP_ERROR_NET_CONNECT_EACCES	0x8071050d	
CELL_HTTP_ERROR_NET_CONNECT_EFAULT	0x8071050e	
CELL_HTTP_ERROR_NET_CONNECT_ENOTBLK	0x8071050f	
CELL_HTTP_ERROR_NET_CONNECT_EBUSY	0x80710510	
CELL_HTTP_ERROR_NET_CONNECT_EEXIST	0x80710511	
CELL_HTTP_ERROR_NET_CONNECT_EXDEV	0x80710512	
CELL_HTTP_ERROR_NET_CONNECT_ENODEV	0x80710513	
CELL_HTTP_ERROR_NET_CONNECT_ENOTDIR	0x80710514	
CELL_HTTP_ERROR_NET_CONNECT_EISDIR	0x80710515	
CELL_HTTP_ERROR_NET_CONNECT_EINVAL	0x80710516	
CELL_HTTP_ERROR_NET_CONNECT_ENFILE	0x80710517	
CELL_HTTP_ERROR_NET_CONNECT_EMFILE	0x80710518	
CELL_HTTP_ERROR_NET_CONNECT_ENOTTY	0x80710519	
CELL_HTTP_ERROR_NET_CONNECT_ETXTBSY	0x8071051a	
CELL_HTTP_ERROR_NET_CONNECT_EFBIG	0x8071051b	
CELL_HTTP_ERROR_NET_CONNECT_ENOSPC	0x8071051c	
CELL_HTTP_ERROR_NET_CONNECT_ESPIPE	0x8071051d	
CELL_HTTP_ERROR_NET_CONNECT_EROFS	0x8071051e	
CELL_HTTP_ERROR_NET_CONNECT_EMLINK	0x8071051f	
CELL_HTTP_ERROR_NET_CONNECT_EPIPE	0x80710520	
CELL_HTTP_ERROR_NET_CONNECT_EDOM	0x80710521	
CELL_HTTP_ERROR_NET_CONNECT_ERANGE	0x80710522	
CELL_HTTP_ERROR_NET_CONNECT_EAGAIN	0x80710523	
CELL_HTTP_ERROR_NET_CONNECT_EWOULDBLOCK	0x80710523	
CELL_HTTP_ERROR_NET_CONNECT_EINPROGRESS	0x80710524	
CELL_HTTP_ERROR_NET_CONNECT_EALREADY	0x80710525	
CELL_HTTP_ERROR_NET_CONNECT_ENOTSOCK	0x80710526	
CELL_HTTP_ERROR_NET_CONNECT_EDESTADDRREQ	0x80710527	
CELL_HTTP_ERROR_NET_CONNECT_EMSGSIZE	0x80710528	
CELL_HTTP_ERROR_NET_CONNECT_EPROTOTYPE	0x80710529	
CELL_HTTP_ERROR_NET_CONNECT_ENOPROTOOPT	0x8071052a	
CELL_HTTP_ERROR_NET_CONNECT_EPROTONOSUPPORT	0x8071052b	
CELL_HTTP_ERROR_NET_CONNECT_ESOCKTNOSUPPORT	0x8071052c	
CELL_HTTP_ERROR_NET_CONNECT_EOPNOTSUPP	0x8071052d	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_CONNECT_EPFNOSUPPORT	0x8071052e	
CELL_HTTP_ERROR_NET_CONNECT_EAFNOSUPPORT	0x8071052f	
CELL_HTTP_ERROR_NET_CONNECT_EADDRINUSE	0x80710530	
CELL_HTTP_ERROR_NET_CONNECT_EADDRNOTAVAIL	0x80710531	"An error occurred during the download operation" (80710531)
CELL_HTTP_ERROR_NET_CONNECT_ENETDOWN	0x80710532	
CELL_HTTP_ERROR_NET_CONNECT_ENETUNREACH	0x80710533	
CELL_HTTP_ERROR_NET_CONNECT_ENETRESET	0x80710534	Network error // Issue connecting to http: server // This error is rare, but contact Sony if receiving this error frequently
CELL_HTTP_ERROR_NET_CONNECT_ECONNABORTED	0x80710535	
CELL_HTTP_ERROR_NET_CONNECT_ECONNRESET	0x80710536	
CELL_HTTP_ERROR_NET_CONNECT_ENOBUFS	0x80710537	
CELL_HTTP_ERROR_NET_CONNECT_EISCONN	0x80710538	
CELL_HTTP_ERROR_NET_CONNECT_ENOTCONN	0x80710539	
CELL_HTTP_ERROR_NET_CONNECT_ESHUTDOWN	0x8071053a	
CELL_HTTP_ERROR_NET_CONNECTETOOMANYREFS	0x8071053b	Network error // Issue with http connection // Reboot console
CELL_HTTP_ERROR_NET_CONNECTETIMEOUT	0x8071053d	Server timed out
CELL_HTTP_ERROR_NET_CONNECT_ECONNREFUSED	0x8071053d	Issue connecting to PSN
CELL_HTTP_ERROR_NET_CONNECT_ELOOP	0x8071053e	
CELL_HTTP_ERROR_NET_CONNECT_ENAMETOOLONG	0x8071053f	
CELL_HTTP_ERROR_NET_CONNECT_EHOSTDOWN	0x80710540	
CELL_HTTP_ERROR_NET_CONNECT_EHOSTUNREACH	0x80710541	
CELL_HTTP_ERROR_NET_CONNECT_ENOTEMPTY	0x80710542	
CELL_HTTP_ERROR_NET_CONNECT_EPROCLIM	0x80710543	
CELL_HTTP_ERROR_NET_CONNECT_EUSERS	0x80710544	
CELL_HTTP_ERROR_NET_CONNECT_EDQUOT	0x80710545	
CELL_HTTP_ERROR_NET_CONNECT_ESTALE	0x80710546	
CELL_HTTP_ERROR_NET_CONNECT_EREMOTE	0x80710547	
CELL_HTTP_ERROR_NET_CONNECT_EBADRPC	0x80710548	
CELL_HTTP_ERROR_NET_CONNECT_ERPCMISMATCH	0x80710549	
CELL_HTTP_ERROR_NET_CONNECT_EPROGUNAVAIL	0x8071054a	
CELL_HTTP_ERROR_NET_CONNECT_EPROGMISMATCH	0x8071054b	
CELL_HTTP_ERROR_NET_CONNECT_EPROCUNAVAIL	0x8071054c	
CELL_HTTP_ERROR_NET_CONNECT_ENOLCK	0x8071054d	
CELL_HTTP_ERROR_NET_CONNECT_ENOSYS	0x8071054e	
CELL_HTTP_ERROR_NET_CONNECT_EFTYPE	0x8071054f	
CELL_HTTP_ERROR_NET_CONNECT_EAUTH	0x80710550	
CELL_HTTP_ERROR_NET_CONNECT_ENEEDAUTH	0x80710551	
CELL_HTTP_ERROR_NET_CONNECT_EIDRM	0x80710552	
CELL_HTTP_ERROR_NET_CONNECT_ENOMSG	0x80710553	
CELL_HTTP_ERROR_NET_CONNECT_EOVERFLOW	0x80710554	
CELL_HTTP_ERROR_NET_CONNECT_EILSEQ	0x80710555	
CELL_HTTP_ERROR_NET_CONNECT_ENOTSUP	0x80710556	
CELL_HTTP_ERROR_NET_CONNECT_ECANCELED	0x80710557	
CELL_HTTP_ERROR_NET_CONNECT_EBADMSG	0x80710558	
CELL_HTTP_ERROR_NET_CONNECT_ENODATA	0x80710559	
CELL_HTTP_ERROR_NET_CONNECT_ENOSR	0x8071055a	
CELL_HTTP_ERROR_NET_CONNECT_ENOSTR	0x8071055b	
CELL_HTTP_ERROR_NET_CONNECTETIME	0x8071055c	
CELL_HTTP_ERROR_NET_SEND	0x80710600	Error calling send(). Error code is net_errno.
CELL_HTTP_ERROR_NET_SEND_EPERM	0x80710601	
CELL_HTTP_ERROR_NET_SEND_ENOENT	0x80710602	
CELL_HTTP_ERROR_NET_SEND_ESRCH	0x80710603	
CELL_HTTP_ERROR_NET_SEND_EINTR	0x80710604	
CELL_HTTP_ERROR_NET_SEND_EIO	0x80710605	
CELL_HTTP_ERROR_NET_SEND_ENXIO	0x80710606	
CELL_HTTP_ERROR_NET_SEND_E2BIG	0x80710607	
CELL_HTTP_ERROR_NET_SEND_ENOEXC	0x80710608	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_SEND_EBADF	0x80710609	
CELL_HTTP_ERROR_NET_SEND_ECHILD	0x8071060a	
CELL_HTTP_ERROR_NET_SEND_EDEADLK	0x8071060b	
CELL_HTTP_ERROR_NET_SEND_ENOMEM	0x8071060c	
CELL_HTTP_ERROR_NET_SEND_EACCES	0x8071060d	
CELL_HTTP_ERROR_NET_SEND_EFAULT	0x8071060e	
CELL_HTTP_ERROR_NET_SEND_ENOTBLK	0x8071060f	
CELL_HTTP_ERROR_NET_SEND_EBUSY	0x80710610	
CELL_HTTP_ERROR_NET_SEND_EEXIST	0x80710611	
CELL_HTTP_ERROR_NET_SEND_EXDEV	0x80710612	
CELL_HTTP_ERROR_NET_SEND_ENODEV	0x80710613	
CELL_HTTP_ERROR_NET_SEND_ENOTDIR	0x80710614	
CELL_HTTP_ERROR_NET_SEND_EISDIR	0x80710615	
CELL_HTTP_ERROR_NET_SEND_EINVAL	0x80710616	
CELL_HTTP_ERROR_NET_SEND_ENFILE	0x80710617	
CELL_HTTP_ERROR_NET_SEND_EMFILE	0x80710618	
CELL_HTTP_ERROR_NET_SEND_ENOTTY	0x80710619	
CELL_HTTP_ERROR_NET_SEND_ETXTBSY	0x8071061a	
CELL_HTTP_ERROR_NET_SEND_EFBIG	0x8071061b	
CELL_HTTP_ERROR_NET_SEND_ENOSPC	0x8071061c	
CELL_HTTP_ERROR_NET_SEND_ESPIPE	0x8071061d	
CELL_HTTP_ERROR_NET_SEND_EROFS	0x8071061e	
CELL_HTTP_ERROR_NET_SEND_EMLINK	0x8071061f	
CELL_HTTP_ERROR_NET_SEND_EPIPE	0x80710620	
CELL_HTTP_ERROR_NET_SEND_EDOM	0x80710621	
CELL_HTTP_ERROR_NET_SEND_ERANGE	0x80710622	
CELL_HTTP_ERROR_NET_SEND_EAGAIN	0x80710623	
CELL_HTTP_ERROR_NET_SEND_EWOULDBLOCK	0x80710623	
CELL_HTTP_ERROR_NET_SEND_EINPROGRESS	0x80710624	
CELL_HTTP_ERROR_NET_SEND_EALREADY	0x80710625	
CELL_HTTP_ERROR_NET_SEND_ENOTSOCK	0x80710626	
CELL_HTTP_ERROR_NET_SEND_EDESTADDRREQ	0x80710627	
CELL_HTTP_ERROR_NET_SEND_EMSGSIZE	0x80710628	
CELL_HTTP_ERROR_NET_SEND_EPROTOTYPE	0x80710629	
CELL_HTTP_ERROR_NET_SEND_ENOPROTOOPT	0x8071062a	
CELL_HTTP_ERROR_NET_SEND_EPROTONOSUPPORT	0x8071062b	
CELL_HTTP_ERROR_NET_SEND_ESOCKTNOSUPPORT	0x8071062c	
CELL_HTTP_ERROR_NET_SEND_EOPNOTSUPP	0x8071062d	
CELL_HTTP_ERROR_NET_SEND_EPFNOSUPPORT	0x8071062e	
CELL_HTTP_ERROR_NET_SEND_EAFNOSUPPORT	0x8071062f	
CELL_HTTP_ERROR_NET_SEND_EADDRINUSE	0x80710630	
CELL_HTTP_ERROR_NET_SEND_EADDRNOTAVAIL	0x80710631	
CELL_HTTP_ERROR_NET_SEND_ENETDOWN	0x80710632	
CELL_HTTP_ERROR_NET_SEND_ENETUNREACH	0x80710633	
CELL_HTTP_ERROR_NET_SEND_ENETRESET	0x80710634	
CELL_HTTP_ERROR_NET_SEND_ECONNABORTED	0x80710635	
CELL_HTTP_ERROR_NET_SEND_ECONNRESET	0x80710636	
CELL_HTTP_ERROR_NET_SEND_ENOBUFS	0x80710637	
CELL_HTTP_ERROR_NET_SEND_EISCONN	0x80710638	
CELL_HTTP_ERROR_NET_SEND_ENOTCONN	0x80710639	
CELL_HTTP_ERROR_NET_SEND_ESHUTDOWN	0x8071063a	
CELL_HTTP_ERROR_NET_SEND_ETOOMANYREFS	0x8071063b	
CELL_HTTP_ERROR_NET_SEND_ETIMEDOUT	0x8071063c	
CELL_HTTP_ERROR_NET_SEND_ECONNREFUSED	0x8071063d	
CELL_HTTP_ERROR_NET_SEND_ELOOP	0x8071063e	
CELL_HTTP_ERROR_NET_SEND_ENAMETOOLONG	0x8071063f	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_SEND_EHOSTDOWN	0x80710640	
CELL_HTTP_ERROR_NET_SEND_EHOSTUNREACH	0x80710641	
CELL_HTTP_ERROR_NET_SEND_ENOTEMPTY	0x80710642	
CELL_HTTP_ERROR_NET_SEND_EPROCLIM	0x80710643	
CELL_HTTP_ERROR_NET_SEND_EUSERS	0x80710644	
CELL_HTTP_ERROR_NET_SEND_EDQUOT	0x80710645	
CELL_HTTP_ERROR_NET_SEND_ESTALE	0x80710646	
CELL_HTTP_ERROR_NET_SEND_EREMOTE	0x80710647	
CELL_HTTP_ERROR_NET_SEND_EBADRPC	0x80710648	
CELL_HTTP_ERROR_NET_SEND_ERPCMISMATCH	0x80710649	
CELL_HTTP_ERROR_NET_SEND_EPROGUNAVAIL	0x8071064a	
CELL_HTTP_ERROR_NET_SEND_EPROGMISMATCH	0x8071064b	
CELL_HTTP_ERROR_NET_SEND_EPROCUNAVAIL	0x8071064c	
CELL_HTTP_ERROR_NET_SEND_ENOLCK	0x8071064d	
CELL_HTTP_ERROR_NET_SEND_ENOSYS	0x8071064e	
CELL_HTTP_ERROR_NET_SEND_EFTYPE	0x8071064f	
CELL_HTTP_ERROR_NET_SEND_EAUTH	0x80710650	
CELL_HTTP_ERROR_NET_SEND_ENEEDAUTH	0x80710651	
CELL_HTTP_ERROR_NET_SEND_EIDRM	0x80710652	
CELL_HTTP_ERROR_NET_SEND_ENOMSG	0x80710653	
CELL_HTTP_ERROR_NET_SEND_EOVERFLOW	0x80710654	
CELL_HTTP_ERROR_NET_SEND_EILSEQ	0x80710655	
CELL_HTTP_ERROR_NET_SEND_ENOTSUP	0x80710656	
CELL_HTTP_ERROR_NET_SEND_ECANCELED	0x80710657	
CELL_HTTP_ERROR_NET_SEND_EBADMSG	0x80710658	
CELL_HTTP_ERROR_NET_SEND_ENODATA	0x80710659	
CELL_HTTP_ERROR_NET_SEND_ENOSR	0x8071065a	
CELL_HTTP_ERROR_NET_SEND_ENOSTR	0x8071065b	
CELL_HTTP_ERROR_NET_SENDETIME	0x8071065c	
CELL_HTTP_ERROR_NET_RECV	0x80710700	Error calling recv(). Error code is net_errno.
CELL_HTTP_ERROR_NET_RECV_EPERM	0x80710701	
CELL_HTTP_ERROR_NET_RECV_ENOENT	0x80710702	
CELL_HTTP_ERROR_NET_RECV_ESRCH	0x80710703	
CELL_HTTP_ERROR_NET_RECV_EINTR	0x80710704	
CELL_HTTP_ERROR_NET_RECV_EIO	0x80710705	
CELL_HTTP_ERROR_NET_RECV_ENXIO	0x80710706	
CELL_HTTP_ERROR_NET_RECV_E2BIG	0x80710707	
CELL_HTTP_ERROR_NET_RECV_ENOEXEC	0x80710708	
CELL_HTTP_ERROR_NET_RECV_EBADF	0x80710709	
CELL_HTTP_ERROR_NET_RECV_ECHILD	0x8071070a	
CELL_HTTP_ERROR_NET_RECV_EDEADLK	0x8071070b	
CELL_HTTP_ERROR_NET_RECV_ENOMEM	0x8071070c	
CELL_HTTP_ERROR_NET_RECV_EACCES	0x8071070d	
CELL_HTTP_ERROR_NET_RECV_EFAULT	0x8071070e	
CELL_HTTP_ERROR_NET_RECV_ENOTBLK	0x8071070f	
CELL_HTTP_ERROR_NET_RECV_EBUSY	0x80710710	
CELL_HTTP_ERROR_NET_RECV_EEXIST	0x80710711	
CELL_HTTP_ERROR_NET_RECV_EXDEV	0x80710712	
CELL_HTTP_ERROR_NET_RECV_ENODEV	0x80710713	
CELL_HTTP_ERROR_NET_RECV_ENOTDIR	0x80710714	
CELL_HTTP_ERROR_NET_RECV_EISDIR	0x80710715	
CELL_HTTP_ERROR_NET_RECV_EINVAL	0x80710716	
CELL_HTTP_ERROR_NET_RECV_ENFILE	0x80710717	
CELL_HTTP_ERROR_NET_RECV_EMFILE	0x80710718	
CELL_HTTP_ERROR_NET_RECV_ENOTTY	0x80710719	
CELL_HTTP_ERROR_NET_RECV_EXTTBSY	0x8071071a	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_RECV_EFBIG	0x8071071b	
CELL_HTTP_ERROR_NET_RECV_ENOSPC	0x8071071c	
CELL_HTTP_ERROR_NET_RECV_ESPIPE	0x8071071d	
CELL_HTTP_ERROR_NET_RECV_EROFS	0x8071071e	
CELL_HTTP_ERROR_NET_RECV_EMLINK	0x8071071f	
CELL_HTTP_ERROR_NET_RECV_EPIPE	0x80710720	
CELL_HTTP_ERROR_NET_RECV_EDOM	0x80710721	
CELL_HTTP_ERROR_NET_RECV_ERANGE	0x80710722	
CELL_HTTP_ERROR_NET_RECV_EAGAIN	0x80710723	
CELL_HTTP_ERROR_NET_RECV_EWOULDBLOCK	0x80710723	
CELL_HTTP_ERROR_NET_RECV_EINPROGRESS	0x80710724	
CELL_HTTP_ERROR_NET_RECV_EALREADY	0x80710725	
CELL_HTTP_ERROR_NET_RECV_ENOTSOCK	0x80710726	
CELL_HTTP_ERROR_NET_RECV_EDESTADDRREQ	0x80710727	
CELL_HTTP_ERROR_NET_RECV_EMSGSIZE	0x80710728	
CELL_HTTP_ERROR_NET_RECV_EPROTOTYPE	0x80710729	
CELL_HTTP_ERROR_NET_RECV_ENOPROTOOPT	0x8071072a	
CELL_HTTP_ERROR_NET_RECV_EPROTONOSUPPORT	0x8071072b	
CELL_HTTP_ERROR_NET_RECV_ESOCKTNOSUPPORT	0x8071072c	
CELL_HTTP_ERROR_NET_RECV_EOPNOTSUPP	0x8071072d	
CELL_HTTP_ERROR_NET_RECV_EPFNOSUPPORT	0x8071072e	
CELL_HTTP_ERROR_NET_RECV_EAFNOSUPPORT	0x8071072f	
CELL_HTTP_ERROR_NET_RECV_EADDRINUSE	0x80710730	
CELL_HTTP_ERROR_NET_RECV_EADDRNOTAVAIL	0x80710731	
CELL_HTTP_ERROR_NET_RECV_ENETDOWN	0x80710732	
CELL_HTTP_ERROR_NET_RECV_ENETUNREACH	0x80710733	
CELL_HTTP_ERROR_NET_RECV_ENETRESET	0x80710734	
CELL_HTTP_ERROR_NET_RECV_ECONNABORTED	0x80710735	
CELL_HTTP_ERROR_NET_RECV_ECONNRESET	0x80710736	Caused by a poor/unstable connection, usually while receiving large amounts of data from server
CELL_HTTP_ERROR_NET_RECV_ENOBUFS	0x80710737	Network memory too low. If still playing a game, restart it
CELL_HTTP_ERROR_NET_RECV_EISCONN	0x80710738	
CELL_HTTP_ERROR_NET_RECV_ENOTCONN	0x80710739	
CELL_HTTP_ERROR_NET_RECV_ESHUTDOWN	0x8071073a	
CELL_HTTP_ERROR_NET_RECVETOOLIMIT	0x8071073b	
CELL_HTTP_ERROR_NET_RECVETIMEOUT	0x8071073c	
CELL_HTTP_ERROR_NET_RECV_ECONNREFUSED	0x8071073d	
CELL_HTTP_ERROR_NET_RECV_ELOOP	0x8071073e	
CELL_HTTP_ERROR_NET_RECV_ENAMETOOLONG	0x8071073f	
CELL_HTTP_ERROR_NET_RECV_EHOSTDOWN	0x80710740	
CELL_HTTP_ERROR_NET_RECV_EHOSTUNREACH	0x80710741	
CELL_HTTP_ERROR_NET_RECV_ENOTEMPTY	0x80710742	
CELL_HTTP_ERROR_NET_RECV_EPROCLIM	0x80710743	
CELL_HTTP_ERROR_NET_RECV_EUSERS	0x80710744	
CELL_HTTP_ERROR_NET_RECV_EDQUOT	0x80710745	
CELL_HTTP_ERROR_NET_RECV_ESTALE	0x80710746	
CELL_HTTP_ERROR_NET_RECV_EREMOTE	0x80710747	
CELL_HTTP_ERROR_NET_RECV_EBADRPC	0x80710748	
CELL_HTTP_ERROR_NET_RECV_ERPCMISMATCH	0x80710749	
CELL_HTTP_ERROR_NET_RECV_EPROGUNAVAIL	0x8071074a	
CELL_HTTP_ERROR_NET_RECV_EPROGMISMATCH	0x8071074b	
CELL_HTTP_ERROR_NET_RECV_EPROCUNAVAIL	0x8071074c	
CELL_HTTP_ERROR_NET_RECV_ENOLCK	0x8071074d	
CELL_HTTP_ERROR_NET_RECV_ENOSYS	0x8071074e	
CELL_HTTP_ERROR_NET_RECV_EFTYPE	0x8071074f	
CELL_HTTP_ERROR_NET_RECV_EAUTH	0x80710750	
CELL_HTTP_ERROR_NET_RECV_ENEEDAUTH	0x80710751	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_RECV_EIDRM	0x80710752	
CELL_HTTP_ERROR_NET_RECV_ENOMSG	0x80710753	
CELL_HTTP_ERROR_NET_RECV_EOVERFLOW	0x80710754	
CELL_HTTP_ERROR_NET_RECV_EILSEQ	0x80710755	
CELL_HTTP_ERROR_NET_RECV_ENOTSUP	0x80710756	
CELL_HTTP_ERROR_NET_RECV_ECANCELED	0x80710757	
CELL_HTTP_ERROR_NET_RECV_EBADMSG	0x80710758	
CELL_HTTP_ERROR_NET_RECV_ENODATA	0x80710759	
CELL_HTTP_ERROR_NET_RECV_ENOSR	0x8071075a	
CELL_HTTP_ERROR_NET_RECV_ENOSTR	0x8071075b	
CELL_HTTP_ERROR_NET_RECVETIME	0x8071075c	
CELL_HTTP_ERROR_NET_SELECT	0x80710800	Error calling select(). Error code is net_errno.
CELL_HTTP_ERROR_NET_SELECT_EPERM	0x80710801	
CELL_HTTP_ERROR_NET_SELECT_ENOENT	0x80710802	
CELL_HTTP_ERROR_NET_SELECT_ESRCH	0x80710803	
CELL_HTTP_ERROR_NET_SELECT_EINTR	0x80710804	
CELL_HTTP_ERROR_NET_SELECT_EIO	0x80710805	
CELL_HTTP_ERROR_NET_SELECT_ENXIO	0x80710806	
CELL_HTTP_ERROR_NET_SELECT_E2BIG	0x80710807	
CELL_HTTP_ERROR_NET_SELECT_ENOEXEC	0x80710808	
CELL_HTTP_ERROR_NET_SELECT_EBADF	0x80710809	
CELL_HTTP_ERROR_NET_SELECT_ECHILD	0x8071080a	
CELL_HTTP_ERROR_NET_SELECT_EDEADLK	0x8071080b	
CELL_HTTP_ERROR_NET_SELECT_ENOMEM	0x8071080c	
CELL_HTTP_ERROR_NET_SELECT_EACCES	0x8071080d	
CELL_HTTP_ERROR_NET_SELECT_EFAULT	0x8071080e	
CELL_HTTP_ERROR_NET_SELECT_ENOTBLK	0x8071080f	
CELL_HTTP_ERROR_NET_SELECT_EBUSY	0x80710810	
CELL_HTTP_ERROR_NET_SELECT_EEXIST	0x80710811	
CELL_HTTP_ERROR_NET_SELECT_EXDEV	0x80710812	
CELL_HTTP_ERROR_NET_SELECT_ENODEV	0x80710813	
CELL_HTTP_ERROR_NET_SELECT_ENOTDIR	0x80710814	
CELL_HTTP_ERROR_NET_SELECT_EISDIR	0x80710815	
CELL_HTTP_ERROR_NET_SELECT_EINVAL	0x80710816	
CELL_HTTP_ERROR_NET_SELECT_ENFILE	0x80710817	
CELL_HTTP_ERROR_NET_SELECT_EMFILE	0x80710818	
CELL_HTTP_ERROR_NET_SELECT_ENOTTY	0x80710819	
CELL_HTTP_ERROR_NET_SELECT_ETXTBSY	0x8071081a	
CELL_HTTP_ERROR_NET_SELECT_EFBIG	0x8071081b	
CELL_HTTP_ERROR_NET_SELECT_ENOSPC	0x8071081c	
CELL_HTTP_ERROR_NET_SELECT_ESPIPE	0x8071081d	
CELL_HTTP_ERROR_NET_SELECT_EROFS	0x8071081e	
CELL_HTTP_ERROR_NET_SELECT_EMLINK	0x8071081f	
CELL_HTTP_ERROR_NET_SELECT_EPIPE	0x80710820	
CELL_HTTP_ERROR_NET_SELECT_EDOM	0x80710821	
CELL_HTTP_ERROR_NET_SELECT_ERANGE	0x80710822	
CELL_HTTP_ERROR_NET_SELECT_EAGAIN	0x80710823	
CELL_HTTP_ERROR_NET_SELECT_EWOULDBLOCK	0x80710823	
CELL_HTTP_ERROR_NET_SELECT_EINPROGRESS	0x80710824	
CELL_HTTP_ERROR_NET_SELECT_EALREADY	0x80710825	
CELL_HTTP_ERROR_NET_SELECT_ENOTSOCK	0x80710826	
CELL_HTTP_ERROR_NET_SELECT_EDESTADDRREQ	0x80710827	
CELL_HTTP_ERROR_NET_SELECT_EMGSIZE	0x80710828	
CELL_HTTP_ERROR_NET_SELECT_EPROTOTYPE	0x80710829	
CELL_HTTP_ERROR_NET_SELECT_ENOPROTOOPT	0x8071082a	
CELL_HTTP_ERROR_NET_SELECT_EPROTONOSUPPORT	0x8071082b	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTP_ERROR_NET_SELECT_ESOCKTNOSUPPORT	0x8071082c	
CELL_HTTP_ERROR_NET_SELECT_EOPNOTSUPP	0x8071082d	
CELL_HTTP_ERROR_NET_SELECT_EPFNOSUPPORT	0x8071082e	
CELL_HTTP_ERROR_NET_SELECT_EAFNOSUPPORT	0x8071082f	
CELL_HTTP_ERROR_NET_SELECT_EADDRINUSE	0x80710830	
CELL_HTTP_ERROR_NET_SELECT_EADDRNOTAVAIL	0x80710831	
CELL_HTTP_ERROR_NET_SELECT_ENETDOWN	0x80710832	
CELL_HTTP_ERROR_NET_SELECT_ENETUNREACH	0x80710833	
CELL_HTTP_ERROR_NET_SELECT_ENETRESET	0x80710834	
CELL_HTTP_ERROR_NET_SELECT_ECONNABORTED	0x80710835	
CELL_HTTP_ERROR_NET_SELECT_ECONNRESET	0x80710836	
CELL_HTTP_ERROR_NET_SELECT_ENOBUFS	0x80710837	
CELL_HTTP_ERROR_NET_SELECT_EISCONN	0x80710838	
CELL_HTTP_ERROR_NET_SELECT_ENOTCONN	0x80710839	
CELL_HTTP_ERROR_NET_SELECT_ESHUTDOWN	0x8071083a	
CELL_HTTP_ERROR_NET_SELECTETOOMANYREFS	0x8071083b	
CELL_HTTP_ERROR_NET_SELECT_ETIMEDOUT	0x8071083c	Server timed out
CELL_HTTP_ERROR_NET_SELECT_ECONNREFUSED	0x8071083d	
CELL_HTTP_ERROR_NET_SELECT_ELOOP	0x8071083e	
CELL_HTTP_ERROR_NET_SELECT_ENAMETOOLONG	0x8071083f	
CELL_HTTP_ERROR_NET_SELECT_EHOSTDOWN	0x80710840	
CELL_HTTP_ERROR_NET_SELECT_EHOSTUNREACH	0x80710841	
CELL_HTTP_ERROR_NET_SELECT_ENOTEMPTY	0x80710842	
CELL_HTTP_ERROR_NET_SELECT_EPROCLIM	0x80710843	
CELL_HTTP_ERROR_NET_SELECT_EUSERS	0x80710844	
CELL_HTTP_ERROR_NET_SELECT_EDQUOT	0x80710845	
CELL_HTTP_ERROR_NET_SELECT_ESTALE	0x80710846	
CELL_HTTP_ERROR_NET_SELECT_EREMOTE	0x80710847	
CELL_HTTP_ERROR_NET_SELECT_EBADRPC	0x80710848	
CELL_HTTP_ERROR_NET_SELECT_ERPCMISMATCH	0x80710849	
CELL_HTTP_ERROR_NET_SELECT_EPROGUNAVAIL	0x8071084a	
CELL_HTTP_ERROR_NET_SELECT_EPROGMISMATCH	0x8071084b	
CELL_HTTP_ERROR_NET_SELECT_EPROCUNAVAIL	0x8071084c	
CELL_HTTP_ERROR_NET_SELECT_ENOLCK	0x8071084d	
CELL_HTTP_ERROR_NET_SELECT_ENOSYS	0x8071084e	
CELL_HTTP_ERROR_NET_SELECT_EFTYPE	0x8071084f	
CELL_HTTP_ERROR_NET_SELECT_EAUTH	0x80710850	
CELL_HTTP_ERROR_NET_SELECT_ENEEDAUTH	0x80710851	
CELL_HTTP_ERROR_NET_SELECT_EIDRM	0x80710852	
CELL_HTTP_ERROR_NET_SELECT_ENOMSG	0x80710853	
CELL_HTTP_ERROR_NET_SELECT_EOVERFLOW	0x80710854	
CELL_HTTP_ERROR_NET_SELECT_EILSEQ	0x80710855	
CELL_HTTP_ERROR_NET_SELECT_ENOTSUP	0x80710856	
CELL_HTTP_ERROR_NET_SELECT_ECANCELED	0x80710857	
CELL_HTTP_ERROR_NET_SELECT_EBADMSG	0x80710858	
CELL_HTTP_ERROR_NET_SELECT_ENODATA	0x80710859	
CELL_HTTP_ERROR_NET_SELECT_ENOSR	0x8071085a	
CELL_HTTP_ERROR_NET_SELECT_ENOSTR	0x8071085b	
CELL_HTTP_ERROR_NET_SELECTETIME	0x8071085c	
CellHttps errors (libhttps)		
CELL_HTTPS_ERROR_CERTIFICATE_LOAD	0x80710A01	Not able to load SSL certificates
CELL_HTTPS_ERROR_BAD_MEMORY	0x80710A02	SSL memory call failed
CELL_HTTPS_ERROR_CONTEXT_CREATION	0x80710A03	"An error has occurred, you have been signed out of PSN" (80710A03) // Failed to create SSL context: ports not properly opened on router
CELL_HTTPS_ERROR_CONNECTION_CREATION	0x80710A04	Failed to create SSL connection
CELL_HTTPS_ERROR_SOCKET_ASSOCIATION	0x80710A05	Failed to associate socket with SSL connection
CELL_HTTPS_ERROR_HANDSHAKE	0x80710A06	SSL Connect Handshake error, or SSL certificate verification failed

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTPS_ERROR_LOOKUP_CERTIFICATE	0x80710A07	Failed to retrieve SSL certificate
CELL_HTTPS_ERROR_NO_SSL	0x80710A08	libssl is not available or has not been initialized
CELL_HTTPS_ERROR_KEY_LOAD	0x80710A09	Cannot load the private key
CELL_HTTPS_ERROR_CERT_KEY_MISMATCH	0x80710A0A	The private key and client certificate do not match
CELL_HTTPS_ERROR_KEY_NEEDS_CERT	0x80710A0B	The private key needs a client certificate
CELL_HTTPS_ERROR_CERT_NEEDS_KEY	0x80710A0C	The client certificate needs a private key
CELL_HTTPS_ERROR_RETRY_CONNECTION	0x80710A0D	internal error code
CELL_HTTPS_ERROR_NET_SSL_CONNECT	0x80710B00	Error calling connect(). Error code is net_errno.
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EPERM	0x80710B01	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOENT	0x80710B02	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ESRCH	0x80710B03	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EINTR	0x80710B04	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EIO	0x80710B05	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENXIO	0x80710B06	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_E2BIG	0x80710B07	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOEXC	0x80710B08	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EBADF	0x80710B09	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ECHILD	0x80710B0A	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EDEADLK	0x80710B0B	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOMEM	0x80710B0C	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EACCES	0x80710B0D	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EFAULT	0x80710B0E	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOTBLK	0x80710B0F	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EBUSY	0x80710B10	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EEXIST	0x80710B11	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EXDEV	0x80710B12	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENODEV	0x80710B13	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOTDIR	0x80710B14	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EISDIR	0x80710B15	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EINVAL	0x80710B16	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENFILE	0x80710B17	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EMFILE	0x80710B18	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOTTY	0x80710B19	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ETXTBSY	0x80710B1A	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EFBIG	0x80710B1B	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOSPC	0x80710B1C	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ESPIPE	0x80710B1D	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EROFS	0x80710B1E	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EMLINK	0x80710B1F	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EPIPE	0x80710B20	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EDOM	0x80710B21	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ERANGE	0x80710B22	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EAGAIN	0x80710B23	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EWOULDBLOCK	0x80710B23	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EINPROGRESS	0x80710B24	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EALREADY	0x80710B25	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOTSOCK	0x80710B26	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EDESTADDRREQ	0x80710B27	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EMSGSIZE	0x80710B28	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EPROTOTYPE	0x80710B29	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOPROTOOPT	0x80710B2A	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EPROTONOSUPPORT	0x80710B2B	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ESOCKTNOSUPPORT	0x80710B2C	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EOPNOTSUPP	0x80710B2D	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EPFNOSUPPORT	0x80710B2E	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EAFNOSUPPORT	0x80710B2F	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EADDRINUSE	0x80710B30	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EADDRNOTAVAIL	0x80710B31	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENETDOWN	0x80710B32	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENETUNREACH	0x80710B33	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENETRESET	0x80710B34	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ECONNABORTED	0x80710B35	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ECONNRESET	0x80710B36	"An error has occurred." (80710B36) // Game server down or website is blocked
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOBUFS	0x80710B37	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EISCONN	0x80710B38	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOTCONN	0x80710B39	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ESHUTDOWN	0x80710B3A	
CELL_HTTPS_ERROR_NET_SSL_CONNECTETOOMANYREFS	0x80710B3B	
CELL_HTTPS_ERROR_NET_SSL_CONNECTETIMEOUT	0x80710B3C	Server timeout
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ECONNREFUSED	0x80710B3D	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ELOOP	0x80710B3E	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENAMETOOLONG	0x80710B3F	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EHOSTDOWN	0x80710B40	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EHOSTUNREACH	0x80710B41	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOTEMPTY	0x80710B42	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EPROCLIM	0x80710B43	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EUSERS	0x80710B44	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EDQUOT	0x80710B45	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ESTALE	0x80710B46	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EREMOTE	0x80710B47	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EBADRPC	0x80710B48	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ERPCMISMATCH	0x80710B49	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EPROGUNAVAIL	0x80710B4A	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EPROGMISMATCH	0x80710B4B	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EPROCUNAVAIL	0x80710B4C	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOLCK	0x80710b4d	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOSYS	0x80710b4e	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EFTYPE	0x80710b4f	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EAUTH	0x80710b50	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENEEDAUTH	0x80710b51	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EIDRM	0x80710b52	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOMSG	0x80710b53	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EOVERFLOW	0x80710b54	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EILSEQ	0x80710b55	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOTSUP	0x80710b56	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ECANCELED	0x80710b57	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_EBADMSG	0x80710b58	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENODATA	0x80710b59	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOSR	0x80710B5A	
CELL_HTTPS_ERROR_NET_SSL_CONNECT_ENOSTR	0x80710B5B	
CELL_HTTPS_ERROR_NET_SSL_CONNECTETIME	0x80710B5C	
CELL_HTTPS_ERROR_NET_SSL_SEND	0x80710C00	Error calling send(). Error code is net_errno.
CELL_HTTPS_ERROR_NET_SSL_SEND_EPERM	0x80710c01	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOENT	0x80710c02	
CELL_HTTPS_ERROR_NET_SSL_SEND_ESRCH	0x80710c03	
CELL_HTTPS_ERROR_NET_SSL_SEND_EINTR	0x80710c04	
CELL_HTTPS_ERROR_NET_SSL_SEND_EIO	0x80710c05	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENXIO	0x80710c06	
CELL_HTTPS_ERROR_NET_SSL_SEND_E2BIG	0x80710c07	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOEXC	0x80710c08	
CELL_HTTPS_ERROR_NET_SSL_SEND_EBADF	0x80710c09	
CELL_HTTPS_ERROR_NET_SSL_SENDECHILD	0x80710c0a	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTPS_ERROR_NET_SSL_SEND_EDEADLK	0x80710c0b	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOMEM	0x80710c0c	
CELL_HTTPS_ERROR_NET_SSL_SEND_EACCES	0x80710c0d	
CELL_HTTPS_ERROR_NET_SSL_SEND_EFAULT	0x80710c0e	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOTBLK	0x80710c0f	
CELL_HTTPS_ERROR_NET_SSL_SEND_EBUSY	0x80710c10	
CELL_HTTPS_ERROR_NET_SSL_SEND_EEXIST	0x80710c11	
CELL_HTTPS_ERROR_NET_SSL_SEND_EXDEV	0x80710c12	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENODEV	0x80710c13	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOTDIR	0x80710c14	
CELL_HTTPS_ERROR_NET_SSL_SEND_EISDIR	0x80710c15	
CELL_HTTPS_ERROR_NET_SSL_SEND_EINVAL	0x80710c16	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENFILE	0x80710c17	
CELL_HTTPS_ERROR_NET_SSL_SEND_EMFILE	0x80710c18	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOTTY	0x80710c19	
CELL_HTTPS_ERROR_NET_SSL_SEND_ETXTBSY	0x80710c1a	
CELL_HTTPS_ERROR_NET_SSL_SEND_EFBIG	0x80710c1b	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOSPC	0x80710c1c	
CELL_HTTPS_ERROR_NET_SSL_SEND_ESPIPE	0x80710c1d	
CELL_HTTPS_ERROR_NET_SSL_SEND_EROFS	0x80710c1e	
CELL_HTTPS_ERROR_NET_SSL_SEND_EMLINK	0x80710c1f	
CELL_HTTPS_ERROR_NET_SSL_SEND_EPIPE	0x80710c20	
CELL_HTTPS_ERROR_NET_SSL_SEND_EDOM	0x80710c21	
CELL_HTTPS_ERROR_NET_SSL_SEND_ERANGE	0x80710c22	
CELL_HTTPS_ERROR_NET_SSL_SEND_EAGAIN	0x80710c23	
CELL_HTTPS_ERROR_NET_SSL_SEND_EWOULDBLOCK	0x80710c23	
CELL_HTTPS_ERROR_NET_SSL_SEND_EINPROGRESS	0x80710c24	
CELL_HTTPS_ERROR_NET_SSL_SEND_EALREADY	0x80710c25	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOTSOCK	0x80710c26	
CELL_HTTPS_ERROR_NET_SSL_SEND_EDESTADDRREQ	0x80710c27	
CELL_HTTPS_ERROR_NET_SSL_SEND_EMSGSIZE	0x80710c28	
CELL_HTTPS_ERROR_NET_SSL_SEND_EPROTOTYPE	0x80710c29	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOPROTOOPT	0x80710c2a	
CELL_HTTPS_ERROR_NET_SSL_SEND_EPROTONOSUPPORT	0x80710c2b	
CELL_HTTPS_ERROR_NET_SSL_SEND_ESOCKTNOSUPPORT	0x80710c2c	
CELL_HTTPS_ERROR_NET_SSL_SEND_EOPNOTSUPP	0x80710c2d	
CELL_HTTPS_ERROR_NET_SSL_SEND_EPFNOSUPPORT	0x80710c2e	
CELL_HTTPS_ERROR_NET_SSL_SEND_EAFNOSUPPORT	0x80710c2f	
CELL_HTTPS_ERROR_NET_SSL_SEND_EADDRINUSE	0x80710c30	
CELL_HTTPS_ERROR_NET_SSL_SEND_EADDRNOTAVAIL	0x80710c31	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENETDOWN	0x80710c32	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENETUNREACH	0x80710c33	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENETRESET	0x80710c34	
CELL_HTTPS_ERROR_NET_SSL_SEND_ECONNABORTED	0x80710c35	
CELL_HTTPS_ERROR_NET_SSL_SEND_ECONNRESET	0x80710c36	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOBUFS	0x80710c37	
CELL_HTTPS_ERROR_NET_SSL_SEND_EISCONN	0x80710c38	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOTCONN	0x80710c39	
CELL_HTTPS_ERROR_NET_SSL_SEND_ESHUTDOWN	0x80710c3a	
CELL_HTTPS_ERROR_NET_SSL_SENDETOOMANYREFS	0x80710c3b	
CELL_HTTPS_ERROR_NET_SSL_SENDETIMEOUT	0x80710C3C	Server timeout
CELL_HTTPS_ERROR_NET_SSL_SENECONNREFUSED	0x80710c3d	
CELL_HTTPS_ERROR_NET_SSL_SENELoop	0x80710c3e	
CELL_HTTPS_ERROR_NET_SSL_SENENAMETOOLONG	0x80710c3f	
CELL_HTTPS_ERROR_NET_SSL_SENEHOSTDOWN	0x80710c40	
CELL_HTTPS_ERROR_NET_SSL_SENEHOSTUNREACH	0x80710c41	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOTEMPTY	0x80710c42	
CELL_HTTPS_ERROR_NET_SSL_SEND_EPROCLIM	0x80710c43	
CELL_HTTPS_ERROR_NET_SSL_SEND_EUSERS	0x80710c44	
CELL_HTTPS_ERROR_NET_SSL_SEND_EDQUOT	0x80710c45	
CELL_HTTPS_ERROR_NET_SSL_SEND_ESTALE	0x80710c46	
CELL_HTTPS_ERROR_NET_SSL_SEND_EREMOTE	0x80710c47	
CELL_HTTPS_ERROR_NET_SSL_SEND_EBADRPC	0x80710c48	
CELL_HTTPS_ERROR_NET_SSL_SEND_ERPCMISMATCH	0x80710c49	
CELL_HTTPS_ERROR_NET_SSL_SEND_EPROGUNAVAIL	0x80710c4a	
CELL_HTTPS_ERROR_NET_SSL_SEND_EPROGMISMATCH	0x80710c4b	
CELL_HTTPS_ERROR_NET_SSL_SEND_EPROCUNAVAIL	0x80710c4c	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOLCK	0x80710c4d	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOSYS	0x80710c4e	
CELL_HTTPS_ERROR_NET_SSL_SEND_EFTYPE	0x80710c4f	
CELL_HTTPS_ERROR_NET_SSL_SEND_EAUTH	0x80710c50	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENEEDAUTH	0x80710c51	
CELL_HTTPS_ERROR_NET_SSL_SEND_EIDRM	0x80710c52	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOMSG	0x80710c53	
CELL_HTTPS_ERROR_NET_SSL_SEND_EOVERFLOW	0x80710c54	
CELL_HTTPS_ERROR_NET_SSL_SEND_EILSEQ	0x80710c55	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOTSUP	0x80710c56	
CELL_HTTPS_ERROR_NET_SSL_SEND_ECANCELED	0x80710c57	
CELL_HTTPS_ERROR_NET_SSL_SEND_EBADMSG	0x80710c58	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENODATA	0x80710c59	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOSR	0x80710c5a	
CELL_HTTPS_ERROR_NET_SSL_SEND_ENOSTR	0x80710c5b	
CELL_HTTPS_ERROR_NET_SSL_SEND_ETIME	0x80710c5c	
CELL_HTTPS_ERROR_NET_SSL_RECV	0x80710d00	Error calling recv(). Error code is net_errno.
CELL_HTTPS_ERROR_NET_SSL_RECV_EPERM	0x80710d01	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOENT	0x80710d02	
CELL_HTTPS_ERROR_NET_SSL_RECV_ESRCH	0x80710d03	
CELL_HTTPS_ERROR_NET_SSL_RECV_EINTR	0x80710d04	
CELL_HTTPS_ERROR_NET_SSL_RECV_EIO	0x80710d05	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENXIO	0x80710d06	
CELL_HTTPS_ERROR_NET_SSL_RECV_E2BIG	0x80710d07	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOEXC	0x80710d08	
CELL_HTTPS_ERROR_NET_SSL_RECV_EBADF	0x80710d09	
CELL_HTTPS_ERROR_NET_SSL_RECV_ECHILD	0x80710d0a	
CELL_HTTPS_ERROR_NET_SSL_RECV_EDEADLK	0x80710d0b	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOMEM	0x80710d0c	
CELL_HTTPS_ERROR_NET_SSL_RECV_EACCES	0x80710d0d	
CELL_HTTPS_ERROR_NET_SSL_RECV_EFAULT	0x80710d0e	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOTBLK	0x80710d0f	
CELL_HTTPS_ERROR_NET_SSL_RECV_EBUSY	0x80710d10	
CELL_HTTPS_ERROR_NET_SSL_RECV_EEXIST	0x80710d11	
CELL_HTTPS_ERROR_NET_SSL_RECV_EXDEV	0x80710d12	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENODEV	0x80710d13	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOTDIR	0x80710d14	
CELL_HTTPS_ERROR_NET_SSL_RECV_EISDIR	0x80710d15	
CELL_HTTPS_ERROR_NET_SSL_RECV_EINVAL	0x80710d16	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENFILE	0x80710d17	
CELL_HTTPS_ERROR_NET_SSL_RECV_EMFILE	0x80710d18	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOTTY	0x80710d19	
CELL_HTTPS_ERROR_NET_SSL_RECV_EXTBSY	0x80710d1a	
CELL_HTTPS_ERROR_NET_SSL_RECV_EFBIG	0x80710d1b	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOSPC	0x80710d1c	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTPS_ERROR_NET_SSL_RECV_ESPIPE	0x80710d1d	
CELL_HTTPS_ERROR_NET_SSL_RECV_EROFS	0x80710d1e	
CELL_HTTPS_ERROR_NET_SSL_RECV_EMLINK	0x80710d1f	
CELL_HTTPS_ERROR_NET_SSL_RECV_EPIPE	0x80710d20	
CELL_HTTPS_ERROR_NET_SSL_RECV_EDOM	0x80710d21	
CELL_HTTPS_ERROR_NET_SSL_RECV_ERANGE	0x80710d22	
CELL_HTTPS_ERROR_NET_SSL_RECV_EAGAIN	0x80710d23	
CELL_HTTPS_ERROR_NET_SSL_RECV_EWOULDBLOCK	0x80710d23	
CELL_HTTPS_ERROR_NET_SSL_RECV_EINPROGRESS	0x80710d24	
CELL_HTTPS_ERROR_NET_SSL_RECV_EALREADY	0x80710d25	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOTSOCK	0x80710d26	
CELL_HTTPS_ERROR_NET_SSL_RECV_EDESTADDRREQ	0x80710d27	
CELL_HTTPS_ERROR_NET_SSL_RECV_EMSGSIZE	0x80710d28	
CELL_HTTPS_ERROR_NET_SSL_RECV_EPROTOTYPE	0x80710d29	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOPROTOOPT	0x80710d2a	
CELL_HTTPS_ERROR_NET_SSL_RECV_EPROTONOSUPPORT	0x80710d2b	
CELL_HTTPS_ERROR_NET_SSL_RECV_ESOCKTNOSUPPORT	0x80710d2c	
CELL_HTTPS_ERROR_NET_SSL_RECV_EOPNOTSUPP	0x80710d2d	
CELL_HTTPS_ERROR_NET_SSL_RECV_EPFNOSUPPORT	0x80710d2e	
CELL_HTTPS_ERROR_NET_SSL_RECV_EAFNOSUPPORT	0x80710d2f	
CELL_HTTPS_ERROR_NET_SSL_RECV_EADDRINUSE	0x80710d30	
CELL_HTTPS_ERROR_NET_SSL_RECV_EADDRNOTAVAIL	0x80710d31	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENETDOWN	0x80710d32	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENETUNREACH	0x80710d33	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENETRESET	0x80710d34	
CELL_HTTPS_ERROR_NET_SSL_RECV_ECONNABORTED	0x80710d35	
CELL_HTTPS_ERROR_NET_SSL_RECV_ECONNRESET	0x80710D36	PSN down or internet connection issues
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOBUFS	0x80710d37	
CELL_HTTPS_ERROR_NET_SSL_RECV_EISCONN	0x80710d38	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOTCONN	0x80710d39	
CELL_HTTPS_ERROR_NET_SSL_RECV_ESHUTDOWN	0x80710d3a	
CELL_HTTPS_ERROR_NET_SSL_RECVETOOMANYREFS	0x80710d3b	
CELL_HTTPS_ERROR_NET_SSL_RECV_ETIMEDOUT	0x80710d3c	Server timeout
CELL_HTTPS_ERROR_NET_SSL_RECV_ECONNREFUSED	0x80710d3d	
CELL_HTTPS_ERROR_NET_SSL_RECV_ELOOP	0x80710d3e	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENAMETOOLONG	0x80710d3f	
CELL_HTTPS_ERROR_NET_SSL_RECV_EHOSTDOWN	0x80710d40	
CELL_HTTPS_ERROR_NET_SSL_RECV_EHOSTUNREACH	0x80710d41	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOTEMPTY	0x80710d42	
CELL_HTTPS_ERROR_NET_SSL_RECV_EPROCLIM	0x80710d43	
CELL_HTTPS_ERROR_NET_SSL_RECV_EUSERS	0x80710d44	
CELL_HTTPS_ERROR_NET_SSL_RECV_EDQUOT	0x80710d45	
CELL_HTTPS_ERROR_NET_SSL_RECV_ESTALE	0x80710d46	
CELL_HTTPS_ERROR_NET_SSL_RECV_EREMOTE	0x80710d47	
CELL_HTTPS_ERROR_NET_SSL_RECV_EBADRPC	0x80710d48	
CELL_HTTPS_ERROR_NET_SSL_RECV_ERPCMISMATCH	0x80710d49	
CELL_HTTPS_ERROR_NET_SSL_RECV_EPROGUNAVAIL	0x80710d4a	
CELL_HTTPS_ERROR_NET_SSL_RECV_EPROGMISMATCH	0x80710d4b	
CELL_HTTPS_ERROR_NET_SSL_RECV_EPROCUNAVAIL	0x80710d4c	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOLCK	0x80710d4d	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOSYS	0x80710d4e	
CELL_HTTPS_ERROR_NET_SSL_RECV_EFTYPE	0x80710d4f	
CELL_HTTPS_ERROR_NET_SSL_RECV_EAUTH	0x80710d50	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENEEDAUTH	0x80710d51	
CELL_HTTPS_ERROR_NET_SSL_RECV_EIDRM	0x80710d52	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOMSG	0x80710d53	

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_HTTPS_ERROR_NET_SSL_RECV_EOVERFLOW	0x80710d54	
CELL_HTTPS_ERROR_NET_SSL_RECV_EILSEQ	0x80710d55	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOTSUP	0x80710d56	
CELL_HTTPS_ERROR_NET_SSL_RECV_ECANCELED	0x80710d57	
CELL_HTTPS_ERROR_NET_SSL_RECV_EBADMSG	0x80710d58	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENODATA	0x80710d59	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOSR	0x80710d5a	
CELL_HTTPS_ERROR_NET_SSL_RECV_ENOSTR	0x80710d5b	
CELL_HTTPS_ERROR_NET_SSL_RECVETIME	0x80710d5c	
Cell Http Util errors (libhttp_util)		
CELL_HTTP_UTIL_ERROR_NO_MEMORY	0x80711001	There was not enough memory in the pool
CELL_HTTP_UTIL_ERROR_NO_BUFFER	0x80711002	No buffer has been provided (as a parameter)
CELL_HTTP_UTIL_ERROR_NO_STRING	0x80711003	No string to read has been provided (as a parameter)
CELL_HTTP_UTIL_ERROR_INSUFFICIENT	0x80711004	Buffer space was insufficient to write into
CELL_HTTP_UTIL_ERROR_INVALID_URI	0x80711005	Malformed URI // URL contains bad characters or DLNA settings are incorrect
CELL_HTTP_UTIL_ERROR_INVALID_HEADER	0x80711006	Malformed header
CELL_HTTP_UTIL_ERROR_INVALID_REQUEST	0x80711007	Malformed request line
CELL_HTTP_UTIL_ERROR_INVALID_RESPONSE	0x80711008	Malformed response (status line)
CELL_HTTP_UTIL_ERROR_INVALID_LENGTH	0x80711009	Invalid length of buffer
CELL_HTTP_UTIL_ERROR_INVALID_CHARACTER	0x8071100A	Illegal character
Cell SSL errors (libssl)		
CELL_SSL_ERROR_NOT_INITIALIZED	0x80740001	libssl has not yet been initialized. Please initialize before use.
CELL_SSL_ERROR_ALREADY_INITIALIZED	0x80740002	libssl has already been initialized and cannot be initialized again
CELL_SSL_ERROR_INITIALIZATION_FAILED	0x80740003	Initialization of the communication part of libssl failed
CELL_SSL_ERROR_NO_BUFFER	0x80740004	No buffer was provided in one of the parameters
CELL_SSL_ERROR_INVALID_CERTIFICATE	0x80740005	The pointer to the SSL Certificate provided is invalid
CELL_SSL_ERROR_UNRETRIEVABLE	0x80740006	Failed to get the requested information
CELL_SSL_ERROR_INVALID_FORMAT	0x80740007	The format of the SSL Certificate is invalid
CELL_SSL_ERROR_NOT_FOUND	0x80740008	The requested information was not found in the SSL Certificate
CELL_SSL_ERROR_READ_FAILED	0x80740009	
CELL_SSL_ERROR_INVALID_TIME	0x80740031	Invalid time element in the SSL Certificate
CELL_SSL_ERROR_INAVLID_NEGATIVE_TIME	0x80740032	Invalid time element with negative values in the SSL Certificate
CELL_SSL_ERROR_INCORRECT_TIME	0x80740033	Value in the time element for the SSL Certificate is incorrect
CELL_SSL_ERROR_UNDEFINED_TIME_TYPE	0x80740034	Type in the time element for the SSL Certificate is not defined correctly
CELL_SSL_ERROR_NO_MEMORY	0x80740035	Call to allocate memory failed (returns NULL)
CELL_SSL_ERROR_NO_STRING	0x80740036	No string to read has been provided (as a parameter)
CELL_SSL_ERROR_UNKNOWN_LOAD_CERT	0x80740037	Unknown certificate load flag
Cell Rudp errors (librudp)		
CELL_RUDP_ERROR_NOT_INITIALIZED	0x80770001	Not initialized
CELL_RUDP_ERROR_ALREADY_INITIALIZED	0x80770002	Already initialized
CELL_RUDP_ERROR_INVALID_CONTEXT_ID	0x80770003	Invalid context ID
CELL_RUDP_ERROR_INVALID_ARGUMENT	0x80770004	Invalid argument
CELL_RUDP_ERROR_INVALID_OPTION	0x80770005	Invalid option name
CELL_RUDP_ERROR_INVALID_MUXMODE	0x80770006	Invalid multiplexing mode
CELL_RUDP_ERROR_MEMORY	0x80770007	Memory allocation failed
CELL_RUDP_ERROR_INTERNAL	0x80770008	Undefined internal error
CELL_RUDP_ERROR_CONN_RESET	0x80770009	Connection was reset
CELL_RUDP_ERROR_CONN_REFUSED	0x8077000a	Connection was refused
CELL_RUDP_ERROR_CONN_TIMEOUT	0x8077000b	Connection timed out
CELL_RUDP_ERROR_CONN_VERSION_MISMATCH	0x8077000c	Version does not match
CELL_RUDP_ERROR_CONN_TRANSPORT_TYPE_MISMATCH	0x8077000d	Transport type does not match
CELL_RUDP_ERROR_QUALITY_LEVEL_MISMATCH	0x8077000e	Quality level does not match
CELL_RUDP_ERROR_THREAD	0x8077000f	Internal I/O thread error
CELL_RUDP_ERROR_THREAD_IN_USE	0x80770010	Internal I/O thread is currently in use
CELL_RUDP_ERROR_NOT_ACCEPTABLE	0x80770011	Operation is not permitted
CELL_RUDP_ERROR_MSG_TOO_LARGE	0x80770012	Message is too large

Description	Errorcode	Remarks
Sys Net errors (libnet)		
CELL_RUDP_ERROR_NOT_BOUND	0x80770013	Not bound
CELL_RUDP_ERROR_CANCELLED	0x80770014	Blocking was cancelled
CELL_RUDP_ERROR_INVALID_VPORT	0x80770015	Invalid virtual port
CELL_RUDP_ERROR_WOULD_BLOCK	0x80770016	Currently executing operation
CELL_RUDP_ERROR_VPORT_IN_USE	0x80770017	Virtual port is currently in use
CELL_RUDP_ERROR_VPORT_EXHAUSTED	0x80770018	No more available virtual port numbers
CELL_RUDP_ERROR_INVALID_SOCKET	0x80770019	Invalid socket
CELL_RUDP_ERROR_BUFFER_TOO_SMALL	0x8077001a	Buffer is too small
CELL_RUDP_ERROR_MSG_MALFORMED	0x8077001b	Invalid packet
CELL_RUDP_ERROR_ADDR_IN_USE	0x8077001c	Address is currently in use
CELL_RUDP_ERROR_ALREADY_BOUND	0x8077001d	Already bound
CELL_RUDP_ERROR_ALREADY_EXISTS	0x8077001e	Already exists
CELL_RUDP_ERROR_INVALID_POLL_ID	0x8077001f	Invalid polling ID
CELL_RUDP_ERROR_TOO_MANY_CONTEXTS	0x80770020	Too many contexts
CELL_RUDP_ERROR_IN_PROGRESS	0x80770021	Currently executing operation
CELL_RUDP_ERROR_NO_EVENT_HANDLER	0x80770022	Common event handler has not been registered
CELL_RUDP_ERROR_PAYLOAD_TOO_LARGE	0x80770023	Payload is too large
CELL_RUDP_ERROR_END_OF_DATA	0x80770024	End of receive data
CELL_RUDP_ERROR_ALREADY_ESTABLISHED	0x80770025	Connection is already established
CELL_RUDP_ERROR_KEEP_ALIVE_FAILURE	0x80770026	Connection was closed due to keep-alive timeout

SSC SPU errors

Description	Errorcode	Remarks
for cellSscQueryAttr()		
CELL_SSC_ERROR_Q_ARG_CFG_NULL	0x80780010	
CELL_SSC_ERROR_Q_ARG_CFG_INVALID	0x80780011	
CELL_SSC_ERROR_Q_ARG_ATTR_NULL	0x80780014	
for cellSscOpen()		
CELL_SSC_ERROR_O_ARG_CFG_NULL	0x80780020	
CELL_SSC_ERROR_O_ARG_CFG_INVALID	0x80780021	
CELL_SSC_ERROR_O_ARG_RSRC_NULL	0x80780022	
CELL_SSC_ERROR_O_ARG_RSRC_INVALID	0x80780023	
CELL_SSC_ERROR_O_ARG_RSRCMEM_INVALID	0x80780024	
CELL_SSC_ERROR_O_ARG_RSRCSPU_INVALID	0x80780025	
CELL_SSC_ERROR_O_ARG_HDL_NULL	0x80780026	
CELL_SSC_ERROR_O_FATAL_CMUTEX	0x80780027	
CELL_SSC_ERROR_O_FATAL_CASYNCTHR	0x80780028	
CELL_SSC_ERROR_O_FATAL_CTASKSET	0x80780029	
for cellSscClose()		
CELL_SSC_ERROR_C_ARG_HDL_NULL	0x80780030	
CELL_SSC_ERROR_C_ARG_HDL_INVALID	0x80780031	
CELL_SSC_ERROR_C_STAT_BUSY	0x80780032	
CELL_SSC_ERROR_C_FATAL_DTHR	0x80780033	
CELL_SSC_ERROR_C_FATAL_DMUTEX	0x80780034	
CELL_SSC_ERROR_C_FATAL_DTASKSET	0x80780035	
for cellSscExec/ExecAsync()		
CELL_SSC_ERROR_E_ARG_HDL_NULL	0x80780040	
CELL_SSC_ERROR_E_ARG_HDL_INVALID	0x80780041	
CELL_SSC_ERROR_E_ARG_INPICBUF_INVALID	0x80780042	
CELL_SSC_ERROR_E_ARG_INPICINFO_NULL	0x80780043	
CELL_SSC_ERROR_E_ARG_INPICINFO_INVALID	0x80780044	
CELL_SSC_ERROR_E_ARG_TASKNUM_INVALID	0x80780045	
CELL_SSC_ERROR_E_ARG_CB_NULL	0x80780046	
CELL_SSC_ERROR_E_ARG_CB_INVALID	0x80780047	
CELL_SSC_ERROR_E_ARG_CTRL_NULL	0x80780048	
CELL_SSC_ERROR_E_ARG_CTRL_INVALID	0x80780049	

Description	Errorcode	Remarks
for cellSscQueryAttr()		
CELL_SSC_ERROR_E_ARG_LEFTPICBUF_INVALID	0x8078004a	
CELL_SSC_ERROR_E_ARG_RIGHTPICBUF_INVALID	0x8078004b	
CELL_SSC_ERROR_E_ARG_SSCTPICINFO_NULL	0x8078004c	
CELL_SSC_ERROR_E_ARG_SSCTPICINFO_INVALID	0x8078004d	
CELL_SSC_ERROR_E_STAT_BUSY	0x80780050	
CELL_SSC_ERROR_E_FATAL_TASK	0x80780051	
CELL_SSC_ERROR_E_FATAL_ASYNCTHR	0x80780052	
CELL_SSC_ERROR_E_FATAL_MUTEX	0x80780053	

SSC GPU errors

Description	Errorcode	Remarks
for cellSscGpuQueryAttr()		
CELL_SSC_GPU_ERROR_Q_ARG_ATTR_NULL	0x80780110	
for cellSscGpuOpen()		
CELL_SSC_GPU_ERROR_O_ARG_RSRC_NULL	0x80780120	
CELL_SSC_GPU_ERROR_O_ARG_RSRC_INVALID	0x80780121	
CELL_SSC_GPU_ERROR_O_ARG_HDL_NULL	0x80780122	
CELL_SSC_GPU_ERROR_O_ARG_RSRCMEM_INVALID	0x80780123	
for cellSscGpuClose()		
CELL_SSC_GPU_ERROR_C_ARG_HDL_NULL	0x80780130	
CELL_SSC_GPU_ERROR_C_ARG_HDL_INVALID	0x80780131	
CELL_SSC_GPU_ERROR_C_SEQ	0x80780132	
for cellSscExec()		
CELL_SSC_GPU_ERROR_E_ARG_CONTEXT_NULL	0x80780140	
CELL_SSC_GPU_ERROR_E_ARG_HDL_NULL	0x80780141	
CELL_SSC_GPU_ERROR_E_ARG_HDL_INVALID	0x80780142	
CELL_SSC_GPU_ERROR_E_ARG_INPICINFO_NULL	0x80780143	
CELL_SSC_GPU_ERROR_E_ARG_INPICINFO_INVALID	0x80780144	
CELL_SSC_GPU_ERROR_E_ARG_CTRL_NULL	0x80780145	
CELL_SSC_GPU_ERROR_E_ARG_CTRL_INVALID	0x80780146	
CELL_SSC_GPU_ERROR_E_ARG_SURFACEINFO_NULL	0x80780147	
CELL_SSC_GPU_ERROR_E_ARG_SURFACEINFO_INVALID	0x80780148	
CELL_SSC_GPU_ERROR_E_ARG_OUTPICINFO_NULL	0x80780149	
CELL_SSC_GPU_ERROR_E_ARG_LEFTPICINFO_INVALID	0x8078014a	
CELL_SSC_GPU_ERROR_E_ARG_RIGHTPICINFO_INVALID	0x8078014b	
CELL_SSC_GPU_ERROR_E_SEQ	0x8078014c	

AV Chat 2 errors

Description	Errorcode	Remarks
CELL_AV2_ERROR_UNKNOWN	0x8002b701	Internal error
CELL_AV2_ERROR_NOT_SUPPORTED	0x8002b702	Function is not supported
CELL_AV2_ERROR_NOT_INITIALIZED	0x8002b703	Not loaded
CELL_AV2_ERROR_ALREADY_INITIALIZED	0x8002b704	Already initialized
CELL_AV2_ERROR_INVALID_ARGUMENT	0x8002b705	Invalid argument was passed
CELL_AV2_ERROR_OUT_OF_MEMORY	0x8002b706	Memory could not be allocated
CELL_AV2_ERROR_ERROR_BAD_ID	0x8002b707	Invalid ID was passed
CELL_AV2_ERROR_INVALID_STATUS	0x8002b70a	Function was called when processing could not be executed
CELL_AV2_ERROR_TIMEOUT	0x8002b70b	Processing failed due to timeout
CELL_AV2_ERROR_NO_SESSION	0x8002b70d	Function was called when the user has not joined an AV chat session
CELL_AV2_ERROR_INCOMPATIBLE_PROTOCOL	0x8002b70e	
CELL_AV2_ERROR_WINDOW_ALREADY_EXISTS	0x8002b70f	Window has already been created
CELL_AV2_ERROR_TOO_MANY_WINDOWS	0x8002b710	Number of windows has reached the maximum allowed
CELL_AV2_ERROR_TOO_MANY_PEER_WINDOWS	0x8002b711	Number of peer windows has reached the maximum allowed
CELL_AV2_ERROR_WINDOW_NOT_FOUND	0x8002b712	Window has not been created
CELL_AV2_PRIVATE_ERROR_HDD_NO_SPACE	0x8002B786	

Description	Errorcode	Remarks
CELL_AVG2_PRIVATE_ERROR_TEXT_LOGMGR_INTERNAL_FILEBROKEN	0x8002B7CC	

Gameupdate errors

Description	Errorcode	Remarks
CELL_GAMEUPDATE_ERROR_NOT_INITIALIZED	0x8002cc01	Not initialized
CELL_GAMEUPDATE_ERROR_ALREADY_INITIALIZED	0x8002cc02	Already initialized
CELL_GAMEUPDATE_ERROR_INVALID_ADDR	0x8002cc03	Address of the passed argument is invalid
CELL_GAMEUPDATE_ERROR_INVALID_SIZE	0x8002cc04	Size of the passed argument is invalid
CELL_GAMEUPDATE_ERROR_INVALID_MEMORY_CONTAINER	0x8002cc05	Memory container is invalid
CELL_GAMEUPDATE_ERROR_INSUFFICIENT_MEMORY_CONTAINER	0x8002cc06	Size of the memory container is insufficient
CELL_GAMEUPDATE_ERROR_BUSY	0x8002cc07	An API is being processed
CELL_GAMEUPDATE_ERROR_NOT_START	0x8002cc08	Game update utility has not been started up
CELL_GAMEUPDATE_ERROR_LOAD_FAILED	0x8002cc09	Failed to load the game update module

Sysutil Accesspoint errors (PSP/Remoteplay)

Description	Errorcode	Remarks
CELL_SYSUTIL_AP_ERROR_OUT_OF_MEMORY	0x8002cd00	Not enough memory
CELL_SYSUTIL_AP_ERROR_FATAL	0x8002cd01	Internal error occurred
CELL_SYSUTIL_AP_ERROR_INVALID_VALUE	0x8002cd02	Invalid argument
CELL_SYSUTIL_AP_ERROR_NOT_INITIALIZED	0x8002cd03	Not correctly initialized
CELL_SYSUTIL_AP_ERROR_ZERO_REGISTERED	0x8002cd13	No PSP is registered
CELL_SYSUTIL_AP_ERROR_NETIF_DISABLED	0x8002cd14	Usable network does not exist
CELL_SYSUTIL_AP_ERROR_NETIF_NO_CABLE	0x8002cd15	Cable is not connected
CELL_SYSUTIL_AP_ERROR_NETIF_CANNOT_CONNECT	0x8002cd16	Could not obtain IP

Background Download Utility errors

Description	Errorcode	Remarks
CELL_BGDL_UTIL_ERROR_BUSY	0x8002ce01	Requested processing could not be executed because required processing has not been completed
CELL_BGDL_UTIL_ERROR_INTERNAL	0x8002ce02	Internal error
CELL_BGDL_UTIL_ERROR_PARAM	0x8002ce03	Invalid parameter
CELL_BGDL_UTIL_ERROR_ACCESS_ERROR	0x8002ce04	HDD access error
CELL_BGDL_UTIL_ERROR_INITIALIZE	0x8002ce05	Initialization error

Video Upload Utility errors

Description	Errorcode	Remarks
CELL_VIDEO_UPLOAD_ERROR_CANCEL	0x8002d000	User cancelled the operation
CELL_VIDEO_UPLOAD_ERROR_NETWORK	0x8002d001	Network error
CELL_VIDEO_UPLOAD_ERROR_SERVICE_STOP	0x8002d002	Service is stopped
CELL_VIDEO_UPLOAD_ERROR_SERVICE_BUSY	0x8002d003	Service is busy
CELL_VIDEO_UPLOAD_ERROR_SERVICE_UNAVAILABLE	0x8002d004	Service could not be used
CELL_VIDEO_UPLOAD_ERROR_SERVICE_QUOTA	0x8002d005	Service limit on upload size was exceeded
CELL_VIDEO_UPLOAD_ERROR_ACCOUNT_STOP	0x8002d006	Account for using service was stopped
CELL_VIDEO_UPLOAD_ERROR_OUT_OF_MEMORY	0x8002d020	Memory could not be allocated
CELL_VIDEO_UPLOAD_ERROR_FATAL	0x8002d021	Fatal internal error
CELL_VIDEO_UPLOAD_ERROR_INVALID_VALUE	0x8002d022	Invalid argument
CELL_VIDEO_UPLOAD_ERROR_FILE_OPEN	0x8002d023	Specified file could not be opened
CELL_VIDEO_UPLOAD_ERROR_INVALID_STATE	0x8002d024	Function was called in an incorrect state
CELL_VIDEO_UPLOAD_ERROR_INTERNAL_INVALID_USER	0x8002d040	
CELL_VIDEO_UPLOAD_ERROR_INTERNAL_BOUNDARY	0x8002d041	

USB PSP Connection Manager errors (PSP/Remoteplay)

Description	Errorcode	Remarks
CELL_USBPSPCM_ERROR_NOT_INITIALIZED	0x80110401	Library has not been initialized
CELL_USBPSPCM_ERROR_ALREADY	0x80110402	Already being processed

Description	Errorcode	Remarks
CELL_USBSPPCM_ERROR_INVALID	0x80110403	Argument value is invalid
CELL_USBSPPCM_ERROR_NO_MEMORY	0x80110404	Memory pool size is insufficient
CELL_USBSPPCM_ERROR_BUSY	0x80110405	Processing currently cannot be performed
CELL_USBSPPCM_ERROR_INPROGRESS	0x80110406	Processing is currently in progress
CELL_USBSPPCM_ERROR_NO_SPACE	0x80110407	No free channel exists
CELL_USBSPPCM_ERROR_CANCELED	0x80110408	Canceled
CELL_USBSPPCM_ERROR_RESETTING	0x80110409	Reset processing is in progress
CELL_USBSPPCM_ERROR_RESET_END	0x8011040A	Reset processing has completed
CELL_USBSPPCM_ERROR_CLOSED	0x8011040B	Channel has been discarded
CELL_USBSPPCM_ERROR_NO_DATA	0x8011040C	No data has been received

USB errors

Description	Errorcode	Remarks
CELL_USBD_ERROR_NOT_INITIALIZED	0x80110001	
CELL_USBD_ERROR_ALREADY_INITIALIZED	0x80110002	
CELL_USBD_ERROR_NO_MEMORY	0x80110003	
CELL_USBD_ERROR_INVALID_PARAM	0x80110004	
CELL_USBD_ERROR_INVALID_TRANSFER_TYPE	0x80110005	
CELL_USBD_ERROR_LDD_ALREADY_REGISTERED	0x80110006	
CELL_USBD_ERROR_LDD_NOT_ALLOCATED	0x80110007	
CELL_USBD_ERROR_LDD_NOT_RELEASED	0x80110008	
CELL_USBD_ERROR_LDD_NOT_FOUND	0x80110009	
CELL_USBD_ERROR_DEVICE_NOT_FOUND	0x8011000a	
CELL_USBD_ERROR_PIPE_NOT_ALLOCATED	0x8011000b	
CELL_USBD_ERROR_PIPE_NOT_RELEASED	0x8011000c	
CELL_USBD_ERROR_PIPE_NOT_FOUND	0x8011000d	
CELL_USBD_ERROR_IOREQ_NOT_ALLOCATED	0x8011000e	
CELL_USBD_ERROR_IOREQ_NOT_RELEASED	0x8011000f	
CELL_USBD_ERROR_IOREQ_NOT_FOUND	0x80110010	
CELL_USBD_ERROR_CANNOT_GET_DESCRIPTOR	0x80110011	
CELL_USBD_ERROR_FATAL	0x801100ff	

LIBMIXER errors

Description	Errorcode	Remarks
CELL_LIBMIXER_ERROR_UNDEFINED	0x80310001	
CELL_LIBMIXER_ERROR_NOT_INITIALIZED	0x80310002	
CELL_LIBMIXER_ERROR_INVALID_PARAMETER	0x80310003	
CELL_LIBMIXER_ERROR_NO_MEMORY	0x80310005	
CELL_LIBMIXER_ERROR_ALREADY_EXIST	0x80310006	
CELL_LIBMIXER_ERROR_FULL	0x80310007	
CELL_LIBMIXER_ERROR_NOT_EXIST	0x80310008	
CELL_LIBMIXER_ERROR_TYPE_MISMATCH	0x80310009	
CELL_LIBMIXER_ERROR_NOT_FOUND	0x8031000A	
CELL_LIBMIXER_ERROR_NO_EFFECT	0x8031000B	

SYNTH2 errors

Description	Errorcode	Remarks
CELL_SOUND_SYNTH2_ERROR_FATAL	0x80310201	
CELL_SOUND_SYNTH2_ERROR_INVALID_PARAMETER	0x80310202	
CELL_SOUND_SYNTH2_ERROR_ALREADY_INITIALIZED	0x80310203	

SND3 errors

Description	Errorcode	Remarks
CELL SND3_ERROR_PARAM	0x80310301	bad argument

Description	Errorcode	Remarks
CELL SND3_ERROR_CREATE_MUTEX	0x80310302	cannot create mutex
CELL SND3_ERROR_SYNTH	0x80310303	error in soft synth
CELL SND3_ERROR_ALREADY	0x80310304	already initial
CELL SND3_ERROR_NOTINIT	0x80310305	not initial
CELL SND3_ERROR_SMFFULL	0x80310306	sfm bind full
CELL SND3_ERROR_HD3ID	0x80310307	bad hd3ID
CELL SND3_ERROR_SMF	0x80310308	bad SMF address
CELL SND3_ERROR_SMFCXT	0x80310309	bad CellSnd3SmfCtx address
CELL SND3_ERROR_FORMAT	0x8031030a	bad SMF format
CELL SND3_ERROR_SMFID	0x8031030b	bad smfID
CELL SND3_ERROR_SOUNDATAFULL	0x8031030c	sound data bind full
CELL SND3_ERROR_VOICENUM	0x8031030d	bad voice num
CELL SND3_ERROR_RESERVEDVOICE	0x8031030e	voice is reserved by user
CELL SND3_ERROR_REQUESTQUEFULL	0x8031030f	request queue is full
CELL SND3_ERROR_OUTPUTMODE	0x80310310	out of output mode

AUDIO errors

Description	Errorcode	Remarks
CELL_AUDIO_ERROR_ALREADY_INIT	0x80310701	already init
CELL_AUDIO_ERROR_AUDIOSYSTEM	0x80310702	error in AudioSystem.
CELL_AUDIO_ERROR_NOT_INIT	0x80310703	not init
CELL_AUDIO_ERROR_PARAM	0x80310704	param error
CELL_AUDIO_ERROR_PORT_FULL	0x80310705	audio port is full
CELL_AUDIO_ERROR_PORT_ALREADY_RUN	0x80310706	audio port is already run
CELL_AUDIO_ERROR_PORT_NOT_OPEN	0x80310707	audio port is close
CELL_AUDIO_ERROR_PORT_NOT_RUN	0x80310708	audio port is not run
CELL_AUDIO_ERROR_TRANS_EVENT	0x80310709	trans event error
CELL_AUDIO_ERROR_PORT_OPEN	0x8031070a	error in port open
CELL_AUDIO_ERROR_SHAREDMEMORY	0x8031070b	error in shared memory
CELL_AUDIO_ERROR_MUTEX	0x8031070c	error in mutex
CELL_AUDIO_ERROR_EVENT_QUEUE	0x8031070d	error in event queue
CELL_AUDIO_ERROR_AUDIOSYSTEM_NOT_FOUND	0x8031070e	
CELL_AUDIO_ERROR_TAG_NOT_FOUND	0x8031070f	

VOICE errors

Description	Errorcode	Remarks
CELL_VOICE_ERROR_LIBVOICE_NOT_INIT	0x80310801	The libvoice library has not been initialized
CELL_VOICE_ERROR_LIBVOICE_INITIALIZED	0x80310802	The libvoice library has already been initialized
CELL_VOICE_ERROR_GENERAL	0x80310803	Errors that do not belong to any other category
CELL_VOICE_ERROR_PORT_INVALID	0x80310804	Invalid port
CELL_VOICE_ERROR_ARGUMENT_INVALID	0x80310805	Invalid argument
CELL_VOICE_ERROR_CONTAINER_INVALID	0x80310806	Invalid container
CELL_VOICE_ERROR_TOPOLOGY	0x80310807	Topology error
CELL_VOICE_ERROR_RESOURCE_INSUFFICIENT	0x80310808	Insufficient resources
CELL_VOICE_ERROR_NOT_IMPLEMENTED	0x80310809	Feature not yet implemented
CELL_VOICE_ERROR_ADDRESS_INVALID	0x8031080a	Invalid address
CELL_VOICE_ERROR_SERVICE_DETACHED	0x8031080b	System Voice Service is detached
CELL_VOICE_ERROR_SERVICE_ATTACHED	0x8031080c	System Voice Service is attached
CELL_VOICE_ERROR_SERVICE_NOT_FOUND	0x8031080d	System Voice Service not found
CELL_VOICE_ERROR_SHAREDMEMORY	0x8031080e	Shared memory error
CELL_VOICE_ERROR_EVENT_QUEUE	0x8031080f	Event Queue error
CELL_VOICE_ERROR_SERVICE_HANDLE	0x80310810	Invalid System Voice Service Handler
CELL_VOICE_ERROR_EVENT_DISPATCH	0x80310811	Voice event dispatch fails
CELL_VOICE_ERROR_DEVICE_NOT_PRESENT	0x80310812	Device was not present

MicIn errors

Description	Errorcode	Remarks
CELL_MICIN_ERROR_ALREADY_INIT	0x80140101	already init
CELL_MICIN_ERROR_SYSTEM CELL_MICIN_ERROR_DEVICE	0x80140102	error in device
CELL_MICIN_ERROR_NOT_INIT	0x80140103	not init
CELL_MICIN_ERROR_PARAM	0x80140104	param error
CELL_MICIN_ERROR_PORT_FULL	0x80140105	device port is full
CELL_MICIN_ERROR_ALREADY_OPEN	0x80140106	device is already opened
CELL_MICIN_ERROR_NOT_OPEN	0x80140107	device is already closed
CELL_MICIN_ERROR_NOT_RUN	0x80140108	device is not running
CELL_MICIN_ERROR_TRANS_EVENT	0x80140109	device trans event error
CELL_MICIN_ERROR_OPEN	0x8014010a	error in open
CELL_MICIN_ERROR_SHAREDMEMORY	0x8014010b	error in shared memory
CELL_MICIN_ERROR_MUTEX	0x8014010c	error in mutex
CELL_MICIN_ERROR_EVENT_QUEUE	0x8014010d	error in event queue
CELL_MICIN_ERROR_SYSTEM_NOT_FOUND CELL_MICIN_ERROR_DEVICE_NOT_FOUND	0x8014010e	device not found
CELL_MICIN_ERROR_FATAL	0x8014010f	generic error
CELL_MICIN_ERROR_SYSTEM_NOT_SUPPORT CELL_MICIN_ERROR_DEVICE_NOT_SUPPORT	0x80140110	device is not supported

CAMERA errors

Description	Errorcode	Remarks
CELL_CAMERA_ERROR_ALREADY_INIT	0x80140801	libcamera was already init
CELL_CAMERA_ERROR_NOT_INIT	0x80140803	libcamera has not been init
CELL_CAMERA_ERROR_PARAM	0x80140804	parameter error
CELL_CAMERA_ERROR_ALREADY_OPEN	0x80140805	device is already open
CELL_CAMERA_ERROR_NOT_OPEN	0x80140806	device is closed
CELL_CAMERA_ERROR_DEVICE_NOT_FOUND	0x80140807	device not found, could be unplugged
CELL_CAMERA_ERROR_DEVICE_DEACTIVATED	0x80140808	device was deactivated
CELL_CAMERA_ERROR_NOT_STARTED	0x80140809	device is not started
CELL_CAMERA_ERROR_FORMAT_UNKNOWN	0x8014080a	unknown format passed to Open
CELL_CAMERA_ERROR_RESOLUTION_UNKNOWN	0x8014080b	unknown resolution passed to Open
CELL_CAMERA_ERROR_BAD_FRAMERATE	0x8014080c	framerate passed to Open is not supported
CELL_CAMERA_ERROR_TIMEOUT	0x8014080d	timeout occurred. function may not have completed
CELL_CAMERA_ERROR_BUSY	0x8014080e	asynchronous processing error
CELL_CAMERA_ERROR_FATAL	0x8014080f	generic internal error
CELL_CAMERA_ERROR_MUTEX	0x80140810	mutex error

MicIn DSP errors

Description	Errorcode	Remarks
CELL_MICIN_ERROR_DSP	0x80140200	generic error
CELL_MICIN_ERROR_DSP_ASSERT	0x80140201	assertion failure
CELL_MICIN_ERROR_DSP_PATH	0x80140202	Path is wrong in file system
CELL_MICIN_ERROR_DSP_FILE	0x80140203	File is with corruption
CELL_MICIN_ERROR_DSP_PARAM	0x80140204	called function arg/param is bad
CELL_MICIN_ERROR_DSP_MEMALLOC	0x80140205	insufficient memory
CELL_MICIN_ERROR_DSP_POINTER	0x80140206	Bad pointer to invalid memory addr
CELL_MICIN_ERROR_DSP_FUNC	0x80140207	unsupported function
CELL_MICIN_ERROR_DSP_MEM	0x80140208	bad memory region
CELL_MICIN_ERROR_DSP_ALIGN16	0x80140209	bad memory alignment in 16 bytes
CELL_MICIN_ERROR_DSP_ALIGN128	0x8014020a	bad memory alignment in 128 bytes
CELL_MICIN_ERROR_DSP_EAALIGN128	0x8014020b	bad effective address(EA) alignment in 128 bytes
CELL_MICIN_ERROR_DSP_LIB_HANDLER	0x80140216	invalid dsp library handler, mostly memory corruption
CELL_MICIN_ERROR_DSP_LIB_INPARAM	0x80140217	unrecognized input parameter to dsp library API
CELL_MICIN_ERROR_DSP_LIB_NOSPU	0x80140218	failure to communicate with SPU side dsp library
CELL_MICIN_ERROR_DSP_LIB_SAMPLRATE	0x80140219	this sampling rate is not supported by dsp library

Face Recognition errors

Description	Errorcode	Remarks
CELL_FACE_ERROR_IMG_WIDTH_LIMIT	0x80140901	Width or data width of the input image is outside the valid range
CELL_FACE_ERROR_IMG_WIDTH_ALIGN	0x80140902	Data width of the input image is not a multiple of 16
CELL_FACE_ERROR_INVALID_EA	0x80140903	Specified pointer is not valid (Not aligned, or NULL)
CELL_FACE_ERROR_INVALID_PARAM	0x80140904	Specified parameter is not valid
CELL_FACE_ERROR_INVALID_WORK	0x80140905	Invalid work area
CELL_FACE_ERROR_INVALID_DICT	0x80140906	Invalid dictionary data
CELL_FACE_ERROR_OUT_OF_BOUNDS	0x80140907	Face area is outside the input image area
CELL_FACE_ERROR_NON_FRONTAL	0x80140908	Angle of face area is outside the range
CELL_FACE_ERROR_TOO_SMALL	0x80140909	Face area is too small
CELL_FACE_ERROR_PARTS_MISSING	0x8014090a	One or more parts could not be detected
CELL_FACE_ERROR_NO_MEMORY	0x8014090b	Not enough memory
CELL_FACE_ERROR_DMA_TAG	0x8014090c	Problem with the specified DMA tag numbers

Head Tracker errors

Description	Errorcode	Remarks
CELL_HEAD_TRACKER_ERROR_INVAL	0x80140a01	Value of argument is invalid
CELL_HEAD_TRACKER_ERROR_ALIGN	0x80140a02	Address alignment of argument is invalid
CELL_HEAD_TRACKER_ERROR_NOMEM	0x80140a03	Not enough memory for this operation
CELL_HEAD_TRACKER_ERROR_CALIB_FAIL	0x80140a04	Calibration failed
CELL_HEAD_TRACKER_ERROR_CALIB_INCOMPLETE	0x80140a05	Calibration is incomplete

Face Tracker errors

Description	Errorcode	Remarks
CELL_FACE_TRACKER_ERROR_BASE	0x80140940	
CELL_FACE_TRACKER_ERROR_INVALID_WORKAREA	0x80140941	
CELL_FACE_TRACKER_ERROR_WORKAREA_ALIGN	0x80140942	
CELL_FACE_TRACKER_ERROR_ROWSTRIDE_ALIGN	0x80140943	
CELL_FACE_TRACKER_ERROR_SHORT_WORKSIZE	0x80140944	
CELL_FACE_TRACKER_ERROR_IMAGE_WIDTH_LIMIT	0x80140945	
CELL_FACE_TRACKER_ERROR_INVALID_PARAM	0x80140946	
CELL_FACE_TRACKER_ERROR_FACEID_FULL	0x80140947	
CELL_FACE_TRACKER_ERROR_FACEID_NOT_EXIST	0x80140948	
CELL_FACE_TRACKER_ERROR_NOT_INITIALIZED	0x80140949	
CELL_FACE_TRACKER_ERROR_INVALID_TIMING	0x8014094a	
CELL_FACE_TRACKER_ERROR_ALREADY_INITIALIZED	0x8014094b	

Debug errors

Description	Errorcode	Remarks
Debug errors (libdbg)		
CELL_DBG_EINVAL	0x80510002	Specified argument is invalid
CELL_DBG_EABORT	0x8051000C	Processing has been aborted because of an abnormal state
CELL_DBG_ENULL	0x8051000E	The pointer specified in the argument is NULL
Debug Font errors (libdbgfont)		
CELL_DBGFONT_ERROR_MALLOC	0x80510104	Allocation of main memory failed
CELL_DBGFONT_ERROR_TEMP_BUFFER	0x80510105	Internal buffer for printf functions overflowed
CELL_DBGFONT_ERROR_LABEL_BUFFER	0x80510106	Label buffer space not enough
CELL_DBGFONT_ERROR_PARAM	0x80510107	Inappropriate argument value
CELL_DBGFONT_ERROR_EXISTS	0x80510108	Library initialization attempted twice
CELL_DBGFONT_ERROR_NOT_INIT	0x80510109	Library not initialized
CELL_DBGFONT_ERROR_CG_PROFILE	0x8051010a	Cg profile not supported
CELL_DBGFONT_ERROR_CONSOLE_ID	0x80510111	Inappropriate console ID
CELL_DBGFONT_ERROR_CONSOLE_FULL	0x80510112	No free console
Debug RSX errors (libdbgrsx)		
CELL_DBG_RSX_ERROR_FAILURE		RSX function fails

Description	Errorcode	Remarks
Debug errors (libdbg)		
CELL_DBG_RSX_ERROR_INVALID_VALUE		Invalid Value (data is NULL, or not a multiple of 64)
CELL_DBG_RSX_ERROR_INVALID_ENUM		Invalid enum value
Debug LV2 errors (liblv2dbg)		
CELL_LV2DBG_ERROR_DEINVALIDPROCESSID	0x80010401	
CELL_LV2DBG_ERROR_DEINVALIDTHREADID	0x80010402	
CELL_LV2DBG_ERROR_DEILLEGALREGISTERTYPE	0x80010403	
CELL_LV2DBG_ERROR_DEILLEGALREGISTERNUMBER	0x80010404	
CELL_LV2DBG_ERROR_DEILLEGALTHREADSTATE	0x80010405	
CELL_LV2DBG_ERROR_DEINVALIDEFFECTIVEADDRESS	0x80010406	
CELL_LV2DBG_ERROR_DENOTFOUNDPROCESSID	0x80010407	
CELL_LV2DBG_ERROR_DENOMEM	0x80010408	
CELL_LV2DBG_ERROR_DEINVALIDARGUMENTS	0x80010409	
CELL_LV2DBG_ERROR_DENOTFOUNDFILE	0x8001040a	
CELL_LV2DBG_ERROR_DEINVALIDFILETYPE	0x8001040b	
CELL_LV2DBG_ERROR_DENOTFOUNDTHREADID	0x8001040c	
CELL_LV2DBG_ERROR_DEINVALIDTHREADSTATUS	0x8001040d	
CELL_LV2DBG_ERROR_DENOAVAILABLEPROCESSID	0x8001040e	
CELL_LV2DBG_ERROR_DENOTFOUNDEVENTHANDLER	0x8001040f	
CELL_LV2DBG_ERROR_DESPNOROOM	0x80010410	
CELL_LV2DBG_ERROR_DESPNOTFOUND	0x80010411	
CELL_LV2DBG_ERROR_DESPINPROCESS	0x80010412	
CELL_LV2DBG_ERROR_DEINVALIDPRIMARYSPUTHREADID	0x80010413	
CELL_LV2DBG_ERROR_DETHREADSTATEISNOTSTOPPED	0x80010414	
CELL_LV2DBG_ERROR_DEINVALIDTHREADTYPE	0x80010415	
CELL_LV2DBG_ERROR_DECONTINUEFAILED	0x80010416	
CELL_LV2DBG_ERROR_DESTOPFAILED	0x80010417	
CELL_LV2DBG_ERROR_DENOEXCEPTION	0x80010418	
CELL_LV2DBG_ERROR_DENOREEVENTQUE	0x80010419	
CELL_LV2DBG_ERROR_DEEVENTQUENOTCREATED	0x8001041a	
CELL_LV2DBG_ERROR_DEEVENTQUEOVERFLOWED	0x8001041b	
CELL_LV2DBG_ERROR_DENOTIMPLEMENTED	0x8001041c	
CELL_LV2DBG_ERROR_DEQUENOTREGISTERED	0x8001041d	
CELL_LV2DBG_ERROR_DENOREEVENTPROCESS	0x8001041e	
CELL_LV2DBG_ERROR_DEPROCESSNOTREGISTERED	0x8001041f	
CELL_LV2DBG_ERROR_DEEVENTDISCARDED	0x80010420	
CELL_LV2DBG_ERROR_DENORESYNCID	0x80010421	
CELL_LV2DBG_ERROR_DESYNCIDALREADYADDED	0x80010422	
CELL_LV2DBG_ERROR_DESYNCIDNOTFOUND	0x80010423	
CELL_LV2DBG_ERROR_DESYNCIDNOTACQUIRED	0x80010424	
CELL_LV2DBG_ERROR_DEPROCESSALREADYREGISTERED	0x80010425	
CELL_LV2DBG_ERROR_DEINVALIDLSDADDRESS	0x80010426	
CELL_LV2DBG_ERROR_DEINVALIDOPERATION	0x80010427	
CELL_LV2DBG_ERROR_DEINVALIDMODULEID	0x80010428	
CELL_LV2DBG_ERROR_DEHANDLERALREADYREGISTERED	0x80010429	
CELL_LV2DBG_ERROR_DEINVALIDHANDLER	0x8001042a	
CELL_LV2DBG_ERROR_DEHANDLENOTREGISTERED	0x8001042b	
CELL_LV2DBG_ERROR_DEOPERATIONDENIED	0x8001042c	
CELL_LV2DBG_ERROR_DEHANDLERNOTINITIALIZED	0x8001042d	
CELL_LV2DBG_ERROR_DEHANDLERALREADYINITIALIZED	0x8001042e	
CELL_LV2DBG_ERROR_DEILLEGALCOREDUMPPARAMETER	0x8001042f	

DECI3 errors

Description	Errorcode	Remarks
DECI3 Remote File Protocol / File Management Protocol / Controller Protocol errors (drfp/dfmp/ctrlp)		
DRFP_EINVAL / DFMP_EINVAL / CTRLP_EINVAL	0x80010002	Argument is invalid (Invalid packet, e.g. controller information has been sent when its playback was not being processed)

Description	Errorcode	Remarks
DECI3 Remote File Protocol / File Management Protocol / Controller Protocol errors (drfp/dfmp/ctrlp)		
DRFP_ENOMEM / DFMP_ENOMEM / CTRL_P_ENOMEM	0x80010004	Not enough memory
DRFP_ENOENT / DFMP_ENOENT	0x80010006	File could not be found, or filename is invalid
DRFP_EBUSY / DFMP_EBUSY / CTRL_P_EBUSY	0x8001000a	Already open (or already recording or playing)
DRFP_EISDIR / DFMP_EISDIR	0x80010012	Is a directory
DRFP_EEXIST / DFMP_EEXIST	0x80010014	File already exists
DRFP_EFBIG / DFMP_EFBIG	0x80010020	File is too big
DRFP_ENOSPC / DFMP_ENOSPC	0x80010023	Space cannot be allocated on disk
DRFP_EROFS / DFMP_EROFS	0x80010026	Write access was requested for read-only file system
DRFP_EACCES / DFMP_EACCES	0x80010029	Do not have access rights
DRFP_EBADF / DFMP_EBADF	0x8001002a	File descriptor is invalid
DRFP_EIO / DFMP_EIO	0x8001002b	I/O error
DRFP_EMFILE / DFMP_EMFILE	0x8001002c	Maximum number of operable files exceeded
DRFP_ENODEV / DFMP_ENODEV / CTRL_P_ENODEV	0x8001002d	Specified device does not exist (or disconnected)
DRFP_ENOTDIR / DFMP_ENOTDIR	0x8001002e	Not a directory
DRFP_EXDEV / DFMP_EXDEV	0x80010030	Multiple devices are specified
DRFP_ENAMETOOLONG / DFMP_ENAMETOOLONG	0x80010034	File pathname is too long
DRFP_ENOTEMPTY / DFMP_ENOTEMPTY	0x80010036	Directory is not empty
DRFP_ENOTSUP / DFMP_EUNSUP / CTRL_P_EUNSUP	0x80010037	Request is not supported by this device
DRFP_ESPECIFIC / DFMP_EFSSPECIFIC	0x80010038	Undefined error
DECI3 Systemcalls errors (libdeci3)		
SYS_DEC13_EINVAL CELL_DEBUG_ERROR_INVAL	0x80510201	Invalid parameter
SYS_DEC13_EBADF CELL_DEBUG_ERROR_BADF	0x80510202	Invalid session ID
SYS_DEC13_EALREADYUSE CELL_DEBUG_ERROR_ALREADYUSE	0x80510203	Session is already opened
SYS_DEC13_EMFILE CELL_DEBUG_ERROR_MFILE	0x80510204	Number of sessions that can be open simultaneously was exceeded
SYS_DEC13_EPKTSIZE CELL_DEBUG_ERROR_PKTSIZE	0x80510205	Send data is too large
SYS_DEC13_ENHOSTIF CELL_DEBUG_ERROR_NOHOSTIF	0x80510206	Not connected with host
SYS_DEC13_ENSPACE CELL_DEBUG_ERROR_NOSPACE	0x80510207	Send buffer is full
SYS_DEC13_EPERM CELL_DEBUG_ERROR_PERM	0x80510208	Not in a state in which the function can be executed
SYS_DEC13_ENOMEM CELL_DEBUG_ERROR_NOMEM	0x80510209	Not enough memory
SYS_DEC13_EBUSY CELL_DEBUG_ERROR_BUSY	0x8051020a	Timeout occurred
SYS_DEC13_ENXIO CELL_DEBUG_ERROR_NXIO	0x8051020b	Communication device does not exist
SYS_DEC13_EFAULT CELL_DEBUG_ERROR_FAULT	0x8051020c	Internal error occurred
Dtlb errors		
DTLIB_INVALID_TARGETNAME	50001	hostname is not valid
DTLIB_INVALID_SOCKET	50002	Socket is invalid
DTLIB_INVALID_PCK	50003	Unknown packet was received, or packet is unrelated to specified deciH
DTLIB_INVALID_PERM	50004	Specified argument is invalid
DTLIB_ERROR_READ	50005	Read of DECI header failed
DTLIB_INVALID_SIZE	50006	Packet size of DECI header is invalid
DTLIB_DCMP_INVALHEAD	50100	Unsupported DECI header
DTLIB_DCMP_SYSTEM_OFF	50101	System power has dropped
DTLIB_DCMP_SYSTEM_SUSPENDED	50102	System is suspended
DTLIB_DCMP_LPAR_NONE	50103	Invalid LPAR
DTLIB_DCMP_LPAR_SUSPENDED	50104	LPAR is suspended
DTLIB_DCMP_NOCONNECT	50105	DECI3 Manager is not connected
DTLIB_DCMP_NOPROTO	50106	Invalid protocol number
DTLIB_DCMP_PRIORITY	50107	Invalid priority

Description	Errorcode	Remarks
DECI3 Remote File Protocol / File Management Protocol / Controller Protocol errors (drfp/dfmp/ctrlp)		
DTLIB_DCMP_NOSPACE	50108	Insufficient memory
DTLIB_DCMP_VERSION	50110	Unsupported DECI version
DTLIB_NETMP_INVAL	50121	Invalid request (dtntm error)
DTLIB_NETMP_BUSY	50122	Another application is already connected using the same protocol, same port, and same priority (dtntm error)
DTLIB_NETMP_NOTCONNECT	50123	Not connected to dtntm (dtntm error)
DTLIB_NETMP_ALREADYCONN	50124	Already connected (dtntm error)
DTLIB_NETMP_NOMEM	50125	Insufficient memory (dtntm error)
DTLIB_NETMP_INVALLPAR	50126	Invalid LPAR (dtntm error)
DTLIB_NETMP_INVALPRIORITY	50127	Invalid priority (dtntm error)
DTLIB_NETMP_INVALPROTO	50128	Invalid protocol number (dtntm error)
DTLIB_NETMP_POWER_OFF	50129	Target power is off (dtntm error)
DTLIB_NETMP_NODECI_CONNECT	50130	DECI3 Manager is not connected (dtntm error)
DTLIB_NETMP_NOREGISTER	50131	Not registered (dtntm error)
DTLIB_NETMP_ALREADY_REGISTER	50132	Already registered (dtntm error)
DTLIB_SOCKET_CLOSE	50141	Communication is not possible due to closed socket
DTLIB_WAIT_TIMEOUT	50142	Timeout
DTLIB_DONT_CONTINUE	50143	Callback routine returned false or communication could not be performed for some other reason.
DTLIB_TOO_BIG_PACKET	50201	Size of data to be sent is larger than 64KB

FIOS errors

Description	Errorcode	Remarks
CELL_FIOS_ERROR_INPROGRESS	0x80010701	I/O is in progress.
CELL_FIOS_ERROR_UNKNOWNCALLBACKEVENT	0x80010702	Callback return code: event was not handled.
CELL_FIOS_ERROR_NOTREADY	0x80010703	Callback return code: no buffer ready yet, try again later.
CELL_FIOS_ERROR_TIMEOUT	0x80010704	The deadline has been reached while waiting on an operation, and the I/O has not completed yet.
CELL_FIOS_ERROR_BADPATH	0x80010705	Bad path argument, or file not found.
CELL_FIOS_ERROR_BADHANDLE	0x80010706	Bad filehandle argument.
CELL_FIOS_ERROR_BADPARAM	0x80010707	Bad parameter (invalid or illegal).
CELL_FIOS_ERROR_CANCELLED	0x80010708	Operation was cancelled.
CELL_FIOS_ERROR_EOF	0x80010709	End-of-file was reached during a read; some data may have been returned prior to the EOF. Check the actual bytes transferred.
CELL_FIOS_ERROR_NOMEM	0x8001070A	Out of memory.
CELL_FIOS_ERROR_BADOFFSET	0x8001070B	Bad offset during seek.
CELL_FIOS_ERROR_BADCALLBACK	0x8001070C	Callback was NULL when it shouldn't have been.
CELL_FIOS_ERROR_PLATFORM	0x8001070D	Some platform-specific error occurred that is not enumerated here (for example, too many open files).
CELL_FIOS_ERROR_ACCESS	0x8001070E	Access was denied, you don't have appropriate security permission.
CELL_FIOS_ERROR_DECOMPRESSION	0x8001070F	Decompression failed.
CELL_FIOS_ERROR_READONLY	0x80010710	Write not supported by media or file access permissions.
CELL_FIOS_ERROR_NOBLOCK	0x80010711	Block APIs not supported by media.
CELL_FIOS_ERROR_NOPATH	0x80010712	Path APIs not supported by media.
CELL_FIOS_ERROR_MEDIAGONE	0x80010713	Media is no longer mounted. When this error code is returned in a mediacallback_proc, FIOS will not retry any I/O and will cancel all I/O to the corresponding media.
CELL_FIOS_ERROR_CANTIMMED	0x80010714	An operation had kOPF_IMMED set but I/O was required.

CXML errors

Description	Errorcode	Remarks
RESULT_ERROR_CANT_OPEN	0x80550001	File could not be opened
RESULT_ERROR_CANT_READ	0x80550002	Could not read from file or buffer
RESULT_ERROR_CANT_WRITE	0x80550003	Could not write to file or buffer
RESULT_ERROR_CANT_SEEK	0x80550004	Could not set read position in file or buffer
RESULT_ERROR_CANT_ALLOC	0x80550005	Memory allocation failed
RESULT_ERROR_FORMAT	0x80550006	Incorrect file format
RESULT_ERROR_VERSION	0x80550007	Incorrect file version
RESULT_ERROR_INVALID_NODE	0x80550008	Access to invalid node (Element, Attribute, File)
RESULT_ERROR_NOT_ENOUGH_BUF	0x80550009	Buffer size is not large enough

Description	Errorcode	Remarks
RESULT_ERROR_ACCESS_MODE	0x80550010	Operation forbidden in current access mode
RESULT_ERROR_NOT_EXIST	0x80550011	Does not exist
RESULT_ERROR_TYPE	0x80550012	Incorrect attribute type
RESULT_ERROR_CANT MODIFY	0x80550013	Cannot modify
RESULT_ERROR_NO_ALLOCATOR	0x80550014	Allocator is not registered

SPASM errors/warnings

Description	Errorcode	Remarks
SPU Assembly Preprocessor errors (spasm)		
	0x1000	An identifier defined as a label is being used in a place where a variable is expected.
	0x1001	An identifier defined as a variable is being used in a place where a label is expected.
	0x1002	A label with the same name is multiply defined.
	0x1003	An invalid form operand was used where a d-form instruction operand of the form offset(baseVar) was expected.
	0x1004	A variable is used before initialization.
	0x1005	There are insufficient temporary registers to compile the program. Define extra temporary registers or alter the code to use fewer registers.
	0x1006	Code contains an unrecognized instruction pattern.
	0x1007	Code contains an unrecognized SPASM directive.
	0x1008	Code contains an unrecognized SPASM prag directive.
	0x1009	Code contains an invalid label identifier such as a zero-length label.
	0x1010	A variable identifier is expected in this instruction pattern.
	0x1011	Code contains nested --function directives.
	0x1012	Code contains an --endfunction directive without a matching --function directive.
	0x1020	Code uses an unrecognized data type.
SPU Assembly Preprocessor warnings (spasm)		
	0x4000	A variable may be used before initialization.
	0x4001	Code contains an undefined label. It is assumed to be an external symbol.
	0x4002	Code is unreachable and will be deleted from the final program.
	0x4003	Code uses an undefined target label. It is assumed to be an external symbol.
	0x4004	Code is unreachable due to a missing label.
	0x4005	Code contains a dependency on an undefined name.
	0x4006	Dead code was removed from the final program.

Game Content Utility errors

Description	Errorcode	Remarks
CELL_GAME_RET_OK		Normal termination
CELL_GAME_RET_CANCEL		Processing has been canceled
CELL_GAME_RET_NONE		The specified game content does not exist
	0x8002cb01	System software needs to be updated
CELL_GAME_ERROR_NOTFOUND	0x8002cb04	The specified game content or file cannot be found (application bug)
CELL_GAME_ERROR_BROKEN	0x8002cb05	The specified game content is corrupted
CELL_GAME_ERROR_INTERNAL	0x8002cb06	Fatal error occurred in the utility
CELL_GAME_ERROR_PARAM	0x8002cb07	There is an error in the argument (application bug)
CELL_GAME_ERROR_NOAPP	0x8002cb08	The target application does not exist
CELL_GAME_ERROR_ACCESS_ERROR	0x8002cb09	HDD access error
CELL_GAME_ERROR_NOSPACE	0x8002cb20	Insufficient space on the HDD (application bug)
CELL_GAME_ERROR_NOTSUPPORTED	0x8002cb21	Operation is not supported (debugger)
CELL_GAME_ERROR_FAILURE	0x8002cb22	Calling order is invalid (application bug)
CELL_GAME_ERROR_BUSY	0x8002cb23	The call of an access preparing function was repeated
CELL_GAME_ERROR_IN_SHUTDOWN	0x8002cb24	Processing cannot be executed because application termination is being processed
CELL_GAME_ERROR_INVALID_ID	0x8002cb25	A specified ID is invalid (application bug)
CELL_GAME_ERROR_EXIST	0x8002cb26	Content specified already exists
CELL_GAME_ERROR_NOTPATCH	0x8002cb27	Not booted from a patch
CELL_GAME_ERROR_INVALID_THEME_FILE	0x8002cb28	Invalid format for theme file(application bug)
CELL_GAME_ERROR_BOOTPATH	0x8002cb50	Pathname of booted program file is too long (>128b)

System Cache Utility errors

Description	Errorcode	Remarks
CELL_SYS CACHE _RET_OK_CLEARED		Normal termination. Cache was cleared
CELL_SYS CACHE _RET_OK_RELAYED		Normal termination. Cache became usable in the same state as the previous usage
CELL_SYS CACHE _ERROR_ACCESS_ERROR		HDD access error
CELL_SYS CACHE _ERROR_INTERNAL		Fatal internal error
CELL_SYS CACHE _ERROR_PARAM		Error in argument (problem with the application)
CELL_SYS CACHE _ERROR_NOTMOUNTED		System cache is not in the usable state

Ftp Service events

Description	Errorcode	Remarks
CELL_FTP_SERVICE_EVENT_FATAL		The service has terminated due to a fatal error
CELL_FTP_SERVICE_EVENT_STARTED		The local FTP service has started successfully
CELL_FTP_SERVICE_EVENT_STOPPED		The local FTP service has been gracefully shut down, not forcefully terminated
CELL_FTP_SERVICE_EVENT_CLIENT_CONNECTED		A new connection request has been received and processed
CELL_FTP_SERVICE_EVENT_CLIENT_DISCONNECTED		An existing connection has been closed
CELL_FTP_SERVICE_EVENT_SHUTDOWN		Service has received the remote shutdown command and has shut down

File System errors

Description	Errorcode	Remarks
CELL_FS_SUCCEEDED		Normal termination
CELL_FS_ENOTMOUNTED		File system corresponding to path is not mounted
CELL_FS_ENOENT		The file specified by path does not exist
CELL_FS_EINVAL		The specified path or extended argument is invalid
CELL_FS_EMFILE		The number of file descriptors that can be opened at the same time has reached the maximum
CELL_FS_EISDIR		The specified path is a directory
CELL_FS_EIO		I/O error has occurred
CELL_FS_ENOMEM		Memory is insufficient
CELL_FS_ENOTDIR		Components in path contain something other than a directory
CELL_FS_ENAMETOOLONG		path or components in path exceed the maximum length
CELL_FS_EFSSPECIFIC		File system specific internal error has occurred
CELL_FS_EFAULT		When size is not 0, a NULL pointer is specified in arg. path or fd is NULL
CELL_FS_EPERM		Permission is invalid
CELL_FS_EACCES		Permission is invalid (Only CFS, FAT and HOSTFS)
CELL_FS_EEXIST		When the specified file exists, CELL_FS_O_CREAT and CELL_FS_O_EXCL are specified
CELL_FS_ENOSPC		When CELL_FS_O_CREAT is specified in flags and the file does not exist, there is no area to create a new file
CELL_FS_EROFS		When CELL_FS_O_CREAT is specified in flags and the file does not exist, the directory in which it is to be created does not permit writing (Only CFS (SYS_DEV_HDD1) and FAT)
CELL_FS_ENOTMSELF		A file other than the MSELF file is specified in path, and either CELL_FS_O_MSELF or CELL_FS_O_RDONLY/CELL_FS_O_MSELF is specified in flags

Flash errors

Description	Errorcode	Remarks
CELL_FLASH_ERROR_INVAL		EINVAL
CELL_FLASH_ERROR_NOMEM		ENOMEM
CELL_FLASH_ERROR_SRCH		ESRCH
CELL_FLASH_ERROR_PERM		EPERM
CELL_FLASH_ERROR AGAIN		EAGAIN
CELL_FLASH_ERROR_NOENT		ENOENT
CELL_FLASH_ERROR_ISDIR		EISDIR
CELL_FLASH_ERROR_ACCESS		EACCESS
CELL_FLASH_ERROR_IO		EIO
CELL_FLASH_ERROR_TIMEDOUT		ETIMEDOUT
CELL_FLASH_ERROR_BUSY		EBUSY
CELL_FLASH_ERROR_NOSYS		ENOSYS

Cg Compiler errors

Description	Errorcode	Remarks
SCECGC_OK	0	Compilation successful.
SCECGC_ERROR_NO_IHANDLER	-6	includeHandler is not specified.
SCECGC_ERROR_NO_PROGRAM	-5	Program source not found.
SCECGC_ERROR_CANT_OPEN_FILE	-4	Unable to open file.
SCECGC_ERROR_BAD_ALLOC	-3	Memory allocation failure.
SCECGC_ERROR_INVALID_OPTION	-2	Invalid option.
SCECGC_ERROR_UNEXPECTED	-1	Unexpected failure.

CG API errors

Description	Errorcode	Remarks
CG_NO_ERROR	0	No error has occurred.
CG_COMPILER_ERROR	1	The compile returned an error.
CG_INVALID_PARAMETER_ERROR	2	The parameter used is invalid.
CG_INVALID_PROFILE_ERROR	3	The profile is not supported.
CG_PROGRAM_LOAD_ERROR	4	The program could not load.
CG_PROGRAM_BIND_ERROR	5	The program could not bind.
CG_PROGRAM_NOT_LOADED_ERROR	6	The program must be loaded before this operation may be used.
CG_UNSUPPORTED_GL_EXTENSION_ERROR	7	An unsupported GL extension was required to perform this operation.
CG_INVALID_VALUE_TYPE_ERROR	8	An unknown value type was assigned to a parameter.
CG_NOT_MATRIX_PARAM_ERROR	9	The parameter is not of matrix type.
CG_INVALID_ENUMERANT_ERROR	10	The enumerant parameter has an invalid value.
CG_NOT_4x4_MATRIX_ERROR	11	The parameter must be a 4x4 matrix type.
CG_FILE_READ_ERROR	12	The file could not be read.
CG_FILE_WRITE_ERROR	13	The file could not be written.
CG_NVPARSE_ERROR	14	nvparse could not successfully parse the output from the Cg compiler backend.
CG_MEMORY_ALLOC_ERROR	15	Memory allocation failed.
CG_INVALID_CONTEXT_HANDLE_ERROR	16	Invalid context handle.
CG_INVALID_PROGRAM_HANDLE_ERROR	17	Invalid program handle.
CG_INVALID_PARAM_HANDLE_ERROR	18	Invalid parameter handle.
CG_UNKNOWN_PROFILE_ERROR	19	The specified profile is unknown.
CG_VAR_ARG_ERROR	20	The variable arguments were specified incorrectly.
CG_INVALID_DIMENSION_ERROR	21	The dimension value is invalid.
CG_ARRAY_PARAM_ERROR	22	The parameter must be an array.
CG_OUT_OF_ARRAY_BOUNDS_ERROR	23	Index into the array is out of bounds.
CG_CONFLICTING_TYPES_ERROR	24	A type being added to the context conflicts with an existing type.
CG_CONFLICTING_PARAMETER_TYPES_ERROR	25	The parameters being bound have conflicting types.
CG_PARAMETER_IS_NOT_SHARED_ERROR	26	The parameter must be global.
CG_INVALID_PARAMETER_VARIABILITY_ERROR	27	The parameter could not be changed to the given variability.
CG_CANNOT_DESTROY_PARAMETER_ERROR	28	Cannot destroy the parameter. It is bound to other parameters or is not a root parameter.
CG_NOT_ROOT_PARAMETER_ERROR	29	The parameter is not a root parameter.
CG_PARAMETERS_DO_NOT_MATCH_ERROR	30	The two parameters being bound do not match.
CG_IS_NOT_PROGRAM_PARAMETER_ERROR	31	The parameter is not a program parameter.
CG_INVALID_PARAMETER_TYPE_ERROR	32	The type of the parameter is invalid.
CG_PARAMETER_IS_NOT_RESIZABLE_ARRAY_ERROR	33	The parameter must be a resizable array.
CG_INVALID_SIZE_ERROR	34	The size value is invalid.
CG_BIND_CREATES_CYCLE_ERROR	35	Cannot bind the given parameters. Binding will form a cycle.
CG_ARRAY_TYPES_DO_NOT_MATCH_ERROR	36	Cannot bind the given parameters. Array types do not match.
CG_ARRAY_DIMENSIONS_DO_NOT_MATCH_ERROR	37	Cannot bind the given parameters. Array dimensions do not match.
CG_ARRAY_HAS_WRONG_DIMENSION_ERROR	38	The array has the wrong dimension.
CG_TYPE_IS_NOT_DEFINED_IN_PROGRAM_ERROR	39	Connecting the parameters failed because The type of the source parameter is not defined within the given program or does not match the type with the same name in the program.
CG_INVALID_EFFECT_HANDLE_ERROR	40	Invalid effect handle.
CG_INVALID_STATE_HANDLE_ERROR	41	Invalid state handle.
CG_INVALID_STATE_ASSIGNMENT_HANDLE_ERROR	42	Invalid stateassignment handle.
CG_INVALID_PASS_HANDLE_ERROR	43	Invalid pass handle.
CG_INVALID_ANNOTATION_HANDLE_ERROR	44	Invalid annotation handle.
CG_INVALID_TECHNIQUE_HANDLE_ERROR	45	Invalid technique handle.

Description	Errorcode	Remarks
CG_INVALID_PARAMETER_HANDLE_ERROR	46	Invalid parameter handle. Do not use this! Use CG_INVALID_PARAM_HANDLE_ERROR instead.
CG_STATE_ASSIGNMENT_TYPE_MISMATCH_ERROR	47	Operation is not valid for this type of stateassignment.
CG_INVALID_FUNCTION_HANDLE_ERROR	48	Invalid function handle.
CG_INVALID_TECHNIQUE_ERROR	49	Technique did not pass validation.
CG_INVALID_POINTER_ERROR	50	The supplied pointer is NULL.
CG_NOT_ENOUGH_DATA_ERROR	51	Not enough data was provided.
CG_NON_NUMERIC_PARAMETER_ERROR	52	The parameter is not of a numeric type.
CG_ARRAY_SIZE_MISMATCH_ERROR	53	The specified array sizes are not compatible with the given array.
CG_CANNOT_SET_NON_UNIFORM_PARAMETER_ERROR	54	Cannot set the value of a non-uniform parameter.
CG_DUPLICATE_NAME_ERROR	55	This name is already in use.
CG_INVALID_OBJ_HANDLE_ERROR	56	Invalid object handle.
CG_INVALID_BUFFER_HANDLE_ERROR	57	Invalid buffer handle.
CG_BUFFER_INDEX_OUT_OF_RANGE_ERROR	58	Buffer index is out of bounds.
CG_BUFFER_ALREADY_MAPPED_ERROR	59	The buffer is already mapped.
CG_BUFFER_UPDATE_NOT_ALLOWED_ERROR	60	The buffer cannot be updated.

GCM errors

Description	Errorcode	Remarks
GCM errors		
CELL_GCM_ERROR_NO_IO_PAGE_TABLE	0x80210001	
CELL_GCM_ERROR_INVALID_ENUM	0x80210002	
CELL_GCM_ERROR_INVALID_VALUE	0x80210003	
CELL_GCM_ERROR_INVALID_ALIGNMENT	0x80210004	
CELL_GCM_ERROR_ADDRESS_OVERWRAP	0x80210005	
CELL_GCM_ERROR_EINVAL		
CELL_GCM_ERROR_FAILURE	0x802100ff	
GCM Method Check errors		
CELL_GCM_METHOD_CHECK_OK		Normal termination (no problem found)
CELL_GCM_METHOD_CHECK_ERROR_JUMP		jump command was included
CELL_GCM_METHOD_CHECK_ERROR_RETURN		return command was included
CELL_GCM_METHOD_CHECK_ERROR_CALL		call command was included
CELL_GCM_METHOD_CHECK_ERROR_OTHER		A command that is not of the method format was included
CELL_GCM_METHOD_CHECK_ERROR_METHOD_UNCLOSED		At the end of the check target, the method count in the method header does not match the number of data included
CELL_GCM_METHOD_CHECK_ERROR_METHOD_INVALID_ADDRESS		Method address is invalid (an unusable method address is being used)
CELL_GCM_METHOD_CHECK_ERROR_METHOD_INCORRECT_DATA		Method data is not appropriate for the method address
CELL_GCM_METHOD_CHECK_ERROR_METHOD_NOP_NOT_DELIVER		NOP is used in an un-provided format
CELL_GCM_METHOD_CHECK_ERROR_ETC		Other error (unexpected state entered)

PSGL HW Cursor errors

Description	Errorcode	Remarks
PSGL_HW_CURSOR_ERROR_INVALID_VALUE	0x80210003	
PSGL_HW_CURSOR_ERROR_FAILURE	0x802100ff	

Resizer errors

Description	Errorcode	Remarks
CELL_RESC_ERROR_NOT_INITIALIZED	0x80210301	libresc has not been initialized
CELL_RESC_ERROR_REINITIALIZED	0x80210302	libresc initialization has been attempted when libresc has already been initialized
CELL_RESC_ERROR_BAD_ALIGNMENT	0x80210303	Invalid alignment
CELL_RESC_ERROR_BAD_ARGUMENT	0x80210304	Invalid argument value
CELL_RESC_ERROR_LESS_MEMORY	0x80210305	Insufficient main memory
CELL_RESC_ERROR_GCM_FLIP_QUE_FULL	0x80210306	The queue used internally by cellGcmSetPrepareFlip() or cellGcmSetFlipImmediate() is full, or an internal libresc queue overflowed
CELL_RESC_ERROR_BAD_COMBINATION	0x80210307	Invalid value was set for combination of function and structure, or the order of function calls was incorrect

DBG_RSX errors

Description	Errorcode	Remarks
CELL_DBG_RSX_ERROR_INVALID_ENUM	0x80210501	
CELL_DBG_RSX_ERROR_INVALID_VALUE	0x80210502	
CELL_DBG_RSX_ERROR_INVALID_ALIGNMENT	0x80210503	
CELL_DBG_RSX_ERROR_FAILURE	0x802105ff	

NVShaderPerf errors

Description	Errorcode	Remarks
SCESP_OK	0	Normal termination
SCESP_ERROR_UNKNOWN	-5	Unknown error
SCESP_ERROR_PATH_NOT_FOUND	-4	Registry settings cannot be found (reinstall NVShaderPerf)
SCESP_ERROR_LIBRARY_NOT_FOUND	-2	NVIDIA dll cannot be found (reinstall NVShaderPerf)
SCESP_ERROR_NVSP_INIT	-1	Error upon NVIDIA dll initialization
SCESP_ERROR_NVSP_INTERNAL	2	Internal error of NVIDIA dll
SCESP_ERROR_BAD_ARGUMENTS	4	Content of the option array is incorrect
SCESP_ERROR_FILE_NOT_FOUND	6	Input file cannot be found
SCESP_ERROR_SHADER_TYPE_UNSUPPORTED	7	The passed shader type is not supported
SCESP_ERROR_FAILURE_OPENING_OUTPUT_FILE	10	The output file could not be properly opened
SCESP_ERROR_CGBIN_FILE_INVALID	16	Cg binary format is invalid, or the version is misaligned
SCESP_ERROR_SIMULATION_ERROR	17	Error occurred in the RSX simulator
SCESP_ERROR_ENUMERATION_ENDED_EARLY	18	Error occurred at the front-end of NVIDIA dll

Font errors

Description	Errorcode	Remarks
CELL_FONT_ERROR_FATAL	0x80540001	Fatal error
CELL_FONT_ERROR_INVALID_PARAMETER	0x80540002	Object specified as argument is invalid
CELL_FONT_ERROR_UNINITIALIZED	0x80540003	Uninitialized object was used
CELL_FONT_ERROR_INITIALIZE_FAILED	0x80540004	Initialization failed
CELL_FONT_ERROR_INVALID_CACHE_BUFFER	0x80540005	Invalid cache buffer specified
CELL_FONT_ERROR_ALREADY_INITIALIZED	0x80540006	Already initialized
CELL_FONT_ERROR_ALLOCATION_FAILED	0x80540007	Memory could not be allocated
CELL_FONT_ERROR_NO_SUPPORT_FONTSET	0x80540008	Unsupported font set
CELL_FONT_ERROR_OPEN_FAILED	0x80540009	Internal open process failed
CELL_FONT_ERROR_READ_FAILED	0x8054000a	Internal read process failed
CELL_FONT_ERROR_FONT_OPEN_FAILED	0x8054000b	Could not open font
CELL_FONT_ERROR_FONT_NOT_FOUND	0x8054000c	Font could not be found
CELL_FONT_ERROR_FONT_OPEN_MAX	0x8054000d	Maximum number of fonts already open
CELL_FONT_ERROR_FONT_CLOSE_FAILED	0x8054000e	Could not close font
CELL_FONT_ERROR_ALREADY_OPENED	0x8054000f	A font is already opened
CELL_FONT_ERROR_NO_SUPPORT_FUNCTION	0x80540010	Unsupported function
CELL_FONT_ERROR_NO_SUPPORT_CODE	0x80540011	Specified character code is not supported
CELL_FONT_ERROR_NO_SUPPORT_GLYPH	0x80540012	Glyph could not be found
CELL_FONT_ERROR_BUFFER_SIZE_NOT_ENOUGH	0x80540016	Size of the specified buffer is not enough
CELL_FONT_ERROR_RENDERER_ALREADY_BIND	0x80540020	Renderer is already bound
CELL_FONT_ERROR_RENDERER_UNBIND	0x80540021	Renderer is not bound
CELL_FONT_ERROR_RENDERER_INVALID	0x80540022	Invalid renderer was specified
CELL_FONT_ERROR_RENDERER_ALLOCATION_FAILED	0x80540023	Memory allocation by renderer failed
CELL_FONT_ERROR_ENOUGH_RENDERING_BUFFER	0x80540024	Exceeded the scale limit of the rendering buffer
CELL_FONT_ERROR_NO_SUPPORT_SURFACE	0x80540040	Unsupported surface

Gifdec errors

Description	Errorcode	Remarks
CELL_GIFDEC_ERROR_OPEN_FILE	0x80611300	Error while attempting to open a file
CELL_GIFDEC_ERROR_STREAM_FORMAT	0x80611301	Error in the GIF stream
CELL_GIFDEC_ERROR_SEQ	0x80611302	Error in the calling sequence
CELL_GIFDEC_ERROR_ARG	0x80611303	Error in the argument values
CELL_GIFDEC_ERROR_FATAL	0x80611304	Fatal error

Description	Errorcode	Remarks
CELL_GIFDEC_ERROR_SPU_UNSUPORT	0x80611305	Tried to decode on SPUs a stream unsupported by SPUs
CELL_GIFDEC_ERROR_SPU_ERROR	0x80611306	SPU decoding error
CELL_GIFDEC_ERROR_CB_PARAM	0x80611307	Error in the parameters specified for the callback function

Jpgdec errors

Description	Errorcode	Remarks
CELL_JPGDEC_ERROR_HEADER	0x80611101	Header of stream is not a JPEG header
CELL_JPGDEC_ERROR_STREAM_FORMAT	0x80611102	Error in the stream, or the stream format is not supported
CELL_JPGDEC_ERROR_ARG	0x80611103	Error in arguments of function
CELL_JPGDEC_ERROR_SEQ	0x80611104	Error in execution procedure of function
CELL_JPGDEC_ERROR_BUSY	0x80611105	Internal state of decoder is in BUSY state
CELL_JPGDEC_ERROR_FATAL	0x80611106	Fatal error
CELL_JPGDEC_ERROR_OPEN_FILE	0x80611107	Error in opening file
CELL_JPGDEC_ERROR_SPU_UNSUPORT	0x80611108	Tried to decode progressive JPEG data on SPUs
CELL_JPGDEC_ERROR_CB_PARAM	0x80611109	Error in user-defined parameters for callback function

Jpgenc errors

Description	Errorcode	Remarks
CELL_JPGENC_ERROR_ARG	0x80611191	Specified argument is invalid
CELL_JPGENC_ERROR_SEQ	0x80611192	Function calling sequence is invalid
CELL_JPGENC_ERROR_BUSY	0x80611193	Internal state of the encoder is BUSY, and the operation requested by the upper-level program cannot be executed. This error occurs when the queue inside the encoder (of instructions by the upper-level program) is full.
CELL_JPGENC_ERROR_EMPTY	0x80611194	No encoding results are available in the encoder
CELL_JPGENC_ERROR_RESET	0x80611195	Blocking wait was released with a cellJpgEncReset() call
CELL_JPGENC_ERROR_FATAL	0x80611196	Internal state of the encoder is in an unexpected state. This error cannot usually occur. For example, this error can occur when there is an inconsistency in the configuration of data managed internally by the encoder. This error can also occur when a write error occurs when the stream output is to a file.
CELL_JPGENC_ERROR_STREAM_ABORT	0x806111A1	Encoding was aborted with cellJpgEncReset(). The output stream is undefined.
CELL_JPGENC_ERROR_STREAM_SKIP	0x806111A2	Encoding was skipped with cellJpgEncReset().
CELL_JPGENC_ERROR_STREAM_OVERFLOW	0x806111A3	Size of the stream exceeded the maximum allowed (when the output is to a buffer)
CELL_JPGENC_ERROR_STREAM_FILE_OPEN	0x806111A4	File could not be opened (when the output is to a file)

Pngdec errors

Description	Errorcode	Remarks
CELL_PNGDEC_ERROR_HEADER	0x80611201	Error in PNG header
CELL_PNGDEC_ERROR_STREAM_FORMAT	0x80611202	Error in PNG stream
CELL_PNGDEC_ERROR_ARG	0x80611203	Error in argument value
CELL_PNGDEC_ERROR_SEQ	0x80611204	Error in calling sequence
CELL_PNGDEC_ERROR_BUSY	0x80611205	Decoder is BUSY
CELL_PNGDEC_ERROR_FATAL	0x80611206	Fatal error
CELL_PNGDEC_ERROR_OPEN_FILE	0x80611207	File open error
CELL_PNGDEC_ERROR_SPU_UNSUPORT	0x80611208	Tried to decode data undecodable by the SPU
CELL_PNGDEC_ERROR_SPU_ERROR	0x80611209	SPU decoding error
CELL_PNGDEC_ERROR_CB_PARAM	0x8061120a	Error in the user-defined parameters for the callback function

Pngenc errors

Description	Errorcode	Remarks
CELL_PNGENC_ERROR_ARG	0x80611291	Problem with the argument
CELL_PNGENC_ERROR_SEQ	0x80611292	Problem with the calling sequence
CELL_PNGENC_ERROR_BUSY	0x80611293	The encoder is in the busy state, and the requested operation cannot be executed. This error occurs when the queue inside the encoder storing instructions from the upper-level program becomes full
CELL_PNGENC_ERROR_EMPTY	0x80611294	No encoding results are available in the encoder
CELL_PNGENC_ERROR_RESET	0x80611295	Blocking wait was released with a cellPngEncReset() call
CELL_PNGENC_ERROR_FATAL	0x80611296	An error occurred during the writing of the stream's output file. Or, the encoder has fallen into an unexpected state because, for example, a bug has occurred in the data structure within the encoder
CELL_PNGENC_ERROR_STREAM_ABORT	0x806112A1	Encode processing is aborted by the calling of cellPngEncReset(). The output stream is undefined
CELL_PNGENC_ERROR_STREAM_SKIP	0x806112A2	Encode processing is skipped by the calling of cellPngEncReset()

Description	Errorcode	Remarks
CELL_PNGENC_ERROR_STREAM_OVERFLOW	0x806112A3	Size of the stream exceeded the maximum allowed (when the output is to a buffer)
CELL_PNGENC_ERROR_STREAM_FILE_OPEN	0x806112A4	The output destination file could not be opened

GLES errors

EGL errors

Description	Errorcode	Remarks
EGL_SUCCESS	0x3000	
EGL_NOT_INITIALIZED	0x3001	
EGL_BAD_ACCESS	0x3002	
EGL_BAD_ALLOC	0x3003	
EGL_BAD_ATTRIBUTE	0x3004	
EGL_BAD_CONFIG	0x3005	
EGL_BAD_CONTEXT	0x3006	
EGL_BAD_CURRENT_SURFACE	0x3007	
EGL_BAD_DISPLAY	0x3008	
EGL_BAD_MATCH	0x3009	
EGL_BAD_NATIVE_PIXMAP	0x300A	
EGL_BAD_NATIVE_WINDOW	0x300B	
EGL_BAD_PARAMETER	0x300C	
EGL_BAD_SURFACE	0x300D	

GL errors

Description	Errorcode	Remarks
GL_NO_ERROR	0	
GL_INVALID_ENUM	0x0500	
GL_INVALID_VALUE	0x0501	
GL_INVALID_OPERATION	0x0502	
GL_STACK_OVERFLOW	0x0503	
GL_STACK_UNDERFLOW	0x0504	
GL_OUT_OF_MEMORY	0x0505	

PSGL errors

Description	Errorcode	Remarks
PSGL_REPORT_VERSION		Reported once at the initialization of PSGL. Reports the version of PSGL compiled in.
PSGL_REPORT_DEBUG, PSGL_REPORT_ASSERT, PSGL_REPORT_UNKNOWN		Reported only when a PSGL defect was encountered. Please contact Developer Support if you see any of those.
PSGL_REPORT_GL_ERROR		Reported when PSGL needs to trigger a GL error, as per the GLES specification.
PSGL_REPORT_CG_ERROR		Reported when PSGL needs to trigger a Cg error, as per the Cg specification.
PSGL_REPORT_MISSING_STATE		Reported when PSGL needs a fixed function fragment program that was not loaded. See psglLoadShaderLibrary() for more information.
PSGL_REPORT_VERTEX_SLOW_PATH		Reported when the current vertex data setup requires software per-vertex setup. An associated PSGL_REPORT_VERTEX_DATA_WARNING report gives more information as to why the slow path was taken.
PSGL_REPORT_VERTEX_DATA_WARNING		Reported when the current vertex data setup requires software per-vertex setup. Includes a description of why the slow path was taken.
PSGL_REPORT_COPY_TEXTURE_SLOW_PATH		Reported when PSGL cannot use the hardware to copy part of the frame buffer to a texture. An associated PSGL_REPORT_COPY_TEXTURE_WARNING report gives more information as to why the slow path was taken.
PSGL_REPORT_COPY_TEXTURE_WARNING		Reported when PSGL cannot use the hardware to copy part of the frame buffer to a texture. Includes a description of the conditions which triggered the slow path.
PSGL_REPORT_TEXTURE_COPY_BACK		Reported when PSGL needs to copy a texture back from RSX memory to system memory.
PSGL_REPORT_TEXTURE_REALLOC		Reported when PSGL needs to reallocate a texture.
PSGL_REPORT_FP32_FILTERING		Reported when an FP32 texture requires an unsupported filtering mode (one that requires blending of texels). Includes information about which mode is unsupported, and which mode is used instead.
PSGL_REPORT_TEXTURE_INCOMPLETE		Reported when a texture unit is used with a texture that is not complete. The texture will be ignored.
PSGL_REPORT_FRAMEBUFFER_INCOMPLETE		Reported when a frame buffer is used that is not complete.
PSGL_REPORT_FRAMEBUFFER_UNSUPPORTED		Reported when the frame buffer used is not supported by PSGL. The report provides information about what is unsupported.

Description	Errorcode	Remarks
PSGL_REPORT_BUFFER_OBJECT_OUT_OF_BOUNDS		Reported when PSGL tries to draw using data that is out of the object bounds.
PSGL_REPORT_GPU_MEMORY_ALLOC		Reported when PSGL allocates RSX memory.
PSGL_REPORT_GPU_MEMORY_FREE		Reported when PSGL frees RSX memory.
PSGL_REPORT_GPU_MEMORY_ASYNC_FREE		Reported when PSGL asynchronously frees RSX memory.
PSGL_REPORT_HOST_MEMORY_ALLOC		Reported when PSGL allocates host memory.
PSGL_REPORT_HOST_MEMORY_FREE		Reported when PSGL frees host memory.
PSGL_REPORT_HOST_MEMORY_ASYNC_FREE		Reported when PSGL asynchronously frees host memory.
PSGL_REPORT_MALLOC_MEMORY_ALLOC		Reported when PSGL allocates malloc memory.
PSGL_REPORT_MALLOC_MEMORY_FREE		Reported when PSGL frees malloc memory.
PSGL_REPORT_MALLOC_MEMORY_REALLOC		Reported when PSGL reallocates malloc memory.
PSGL_REPORT_TEXTURE_CONVERSION		Reported when texture color format conversion occurs.
PSGL_REPORT_RESC		Reported when resolution conversion (RESC) is enabled.
PSGL_REPORT_RESC_FLIP_ERROR		Reported when an error occurs during resolution conversion (RESC) flip. The report includes the error code returned by cellRescSetConvertAndFlip().
PSGL_REPORT_COMMAND_RECORD_CALLBACK		Reported when recording with static command buffers in PSGL. There is no more space for command in the current command buffer and there is no psglStaticCommandBufferCallback to call to resolve the issue.

PSGL Utility errors

Description	Errorcode	Remarks
GLU_INVALID_ENUM	100900	
GLU_INVALID_VALUE	100901	
GLU_OUT_OF_MEMORY	100902	
GLU_INVALID_OPERATION	100904	

Content Search Utility errors

Description	Errorcode	Remarks
CELL_SEARCH_ERROR_PARAM	0x8002C801	Parameter is invalid. func or Id is NULL.
CELL_SEARCH_ERROR_BUSY	0x8002C802	Currently processing. Executing initialization or a search
CELL_SEARCH_ERROR_NO_MEMORY	0x8002C803	Not enough memory for execution
CELL_SEARCH_ERROR_UNKNOWN_MODE	0x8002C804	Mode is invalid. Value specified to mode is not CELL_SEARCH_MODE_NORMAL
CELL_SEARCH_ERROR_ALREADY_INITIALIZED	0x8002C805	Already initialized
CELL_SEARCH_ERROR_NOT_INITIALIZED	0x8002C806	Not initialized
CELL_SEARCH_ERROR_FINALIZING	0x8002C807	Executing termination processing
CELL_SEARCH_ERROR_NOT_SUPPORTED_SEARCH	0x8002C808	Specified search conditions are not supported. Combination of type and sortOrder is invalid.
CELL_SEARCH_ERROR_CONTENT_OBSOLETE	0x8002C809	contentId, listID, videoID is old (content was modified by the user and therefore cannot be found)
CELL_SEARCH_ERROR_CONTENT_NOT_FOUND	0x8002C80A	Content indicated by contentId, listID, videoID cannot be found (deleted by the user).
CELL_SEARCH_ERROR_NOT_LIST	0x8002C80B	contentId, listID, videoID cannot be found in the list.
CELL_SEARCH_ERROR_OUT_OF_RANGE	0x8002C80C	Offset is either negative or too large
CELL_SEARCH_ERROR_INVALID_SEARCHID	0x8002C80D	Search ID is invalid
CELL_SEARCH_ERROR_ALREADY_GOT_RESULT	0x8002C80E	Search results have already been obtained
CELL_SEARCH_ERROR_NOT_SUPPORTED_CONTEXT	0x8002C80F	Selection context cannot be created
CELL_SEARCH_ERROR_INVALID_CONTENTTYPE	0x8002C810	Content type is invalid
CELL_SEARCH_ERROR_DRM	0x8002C811	DRM error. Could not execute request/obtain path because file is a DRM file.
CELL_SEARCH_ERROR_TAG	0x8002C812	Tag information is invalid. tagNum is larger than CELL_SEARCH_TAG_NUM_MAX; or tagNum is at least 1 and tags or tags[n] is NULL; or length of tags[n] is larger than CELL_SEARCH_TAG_LEN_MAX
CELL_SEARCH_ERROR_GENERIC	0x8002C8FF	Other error

Music Decode errors

Description	Errorcode	Remarks
CELL_MUSIC_DECODE_DECODE_FINISHED	0x8002C101	End of music content was reached and decoding stopped
CELL_MUSIC_DECODE_ERROR_PARAM	0x8002C102	Parameters are invalid
CELL_MUSIC_DECODE_ERROR_BUSY	0x8002C103	Required processing has not completed, so request could not be executed
CELL_MUSIC_DECODE_ERROR_NO_ACTIVE_CONTENT	0x8002C104	No open content
CELL_MUSIC_DECODE_ERROR_NO_MATCH_FOUND	0x8002C105	Content corresponding to passed context could not be found
CELL_MUSIC_DECODE_ERROR_INVALID_CONTEXT	0x8002C106	Context is invalid
CELL_MUSIC_DECODE_ERROR_DECODE_FAILURE	0x8002C107	Error occurred during decoding and decoding stopped

Description	Errorcode	Remarks
CELL_MUSIC_DECODE_ERROR_NO_MORE_CONTENT	0x8002C108	Next/previous content does not exist
CELL_MUSIC_DECODE_DIALOG_OPEN	0x8002C109	Message dialog will be displayed
CELL_MUSIC_DECODE_DIALOG_CLOSE	0x8002C10A	Message dialog was closed
CELL_MUSIC_DECODE_ERROR_NO_LPCM_DATA	0x8002C10B	No decoded data was available
CELL_MUSIC_DECODE_NEXT_CONTENTS_READY	0x8002C10C	Decoding of next content can be started
CELL_MUSIC_DECODE_ERROR_GENERIC	0x8002C1FF	Unknown error occurred

Music Playback errors

Using memory container

Description	Errorcode	Remarks
CELL_MUSIC_PLAYBACK_FINISHED	0x8002C101	End of music content was reached and playback stopped
CELL_MUSIC_ERROR_PARAM	0x8002C102	Parameters are invalid
CELL_MUSIC_ERROR_BUSY	0x8002C103	Required processing has not completed, so request could not be executed
CELL_MUSIC_ERROR_NO_ACTIVE_CONTENT	0x8002C104	No open content
CELL_MUSIC_ERROR_NO_MATCH_FOUND	0x8002C105	Content corresponding to passed context could not be found
CELL_MUSIC_ERROR_INVALID_CONTEXT	0x8002C106	Context is invalid
CELL_MUSIC_ERROR_PLAYBACK_FAILURE	0x8002C107	Error occurred during playback and playback stopped
CELL_MUSIC_ERROR_NO_MORE_CONTENT	0x8002C108	Next/previous content does not exist
CELL_MUSIC_DIALOG_OPEN	0x8002C109	Message dialog will be displayed
CELL_MUSIC_DIALOG_CLOSE	0x8002C10A	Message dialog was closed
CELL_MUSIC_ERROR_GENERIC	0x8002C1FF	Unknown error occurred

Not using memory container

Description	Errorcode	Remarks
CELL_MUSIC2_PLAYBACK_FINISHED	0x8002C101	End of music content was reached and playback stopped
CELL_MUSIC2_ERROR_PARAM	0x8002C102	Parameters are invalid
CELL_MUSIC2_ERROR_BUSY	0x8002C103	Required processing has not completed, so request could not be executed
CELL_MUSIC2_ERROR_NO_ACTIVE_CONTENT	0x8002C104	No open content
CELL_MUSIC2_ERROR_NO_MATCH_FOUND	0x8002C105	Content corresponding to passed context could not be found
CELL_MUSIC2_ERROR_INVALID_CONTEXT	0x8002C106	Context is invalid
CELL_MUSIC2_ERROR_PLAYBACK_FAILURE	0x8002C107	Error occurred during playback and playback stopped
CELL_MUSIC2_ERROR_NO_MORE_CONTENT	0x8002C108	Next/previous content does not exist
CELL_MUSIC2_DIALOG_OPEN	0x8002C109	Message dialog will be displayed
CELL_MUSIC2_DIALOG_CLOSE	0x8002C10A	Message dialog was closed
CELL_MUSIC2_ERROR_GENERIC	0x8002C1FF	Unknown error occurred

Music Export Utility errors

Description	Errorcode	Remarks
CELL_MUSIC_EXPORT_UTIL_ERROR_BUSY	0x8002c601	Because the required processing has not been completed yet, the requested processing could not be executed
CELL_MUSIC_EXPORT_UTIL_ERROR_INTERNAL	0x8002c602	Internal error
CELL_MUSIC_EXPORT_UTIL_ERROR_PARAM	0x8002c603	Parameter is invalid
CELL_MUSIC_EXPORT_UTIL_ERROR_ACCESS_ERROR	0x8002c604	HDD access error
CELL_MUSIC_EXPORT_UTIL_ERROR_DB_INTERNAL	0x8002c605	Internal database error
CELL_MUSIC_EXPORT_UTIL_ERROR_DB_REGIST	0x8002c606	Registration to database failed
CELL_MUSIC_EXPORT_UTIL_ERROR_SET_META	0x8002c607	Metadata configuration failed
CELL_MUSIC_EXPORT_UTIL_ERROR_FLUSH_META	0x8002c608	Metadata flush failed
CELL_MUSIC_EXPORT_UTIL_ERROR_MOVE	0x8002c609	File move failed
CELL_MUSIC_EXPORT_UTIL_ERROR_INITIALIZE	0x8002c60a	Initialization error

Photo Utility errors

Export errors

Description	Errorcode	Remarks
CELL_PHOTO_EXPORT_UTIL_ERROR_BUSY	0x8002c201	Requested operation could not be executed because required operation has not ended
CELL_PHOTO_EXPORT_UTIL_ERROR_INTERNAL	0x8002c202	Internal error
CELL_PHOTO_EXPORT_UTIL_ERROR_PARAM	0x8002c203	Invalid parameter
CELL_PHOTO_EXPORT_UTIL_ERROR_ACCESS_ERROR	0x8002c204	HDD access error, file copy failed
CELL_PHOTO_EXPORT_UTIL_ERROR_DB_INTERNAL	0x8002c205	Internal error in database
CELL_PHOTO_EXPORT_UTIL_ERROR_DB_REGIST	0x8002c206	Registration to database failed
CELL_PHOTO_EXPORT_UTIL_ERROR_SET_META	0x8002c207	Metadata configuration failed
CELL_PHOTO_EXPORT_UTIL_ERROR_FLUSH_META	0x8002c208	Metadata writeback failed
CELL_PHOTO_EXPORT_UTIL_ERROR_MOVE	0x8002c209	File move failed
CELL_PHOTO_EXPORT_UTIL_ERROR_INITIALIZE	0x8002c20a	Initialization error

Import errors

Description	Errorcode	Remarks
CELL_PHOTO_IMPORT_ERROR_BUSY	0x8002c701	Required processing has not completed, so request could not be executed
CELL_PHOTO_IMPORT_ERROR_INTERNAL	0x8002c702	Internal error
CELL_PHOTO_IMPORT_ERROR_PARAM	0x8002c703	Parameters are invalid
CELL_PHOTO_IMPORT_ERROR_ACCESS_ERROR	0x8002c704	HDD access error
CELL_PHOTO_IMPORT_ERROR_COPY	0x8002c705	Copy failed
CELL_PHOTO_IMPORT_ERROR_INITIALIZE	0x8002c706	Initialization error

Decode errors

Description	Errorcode	Remarks
CELL_PHOTO_DECODE_ERROR_BUSY	0x8002c901	Required processing has not completed, so request could not be executed
CELL_PHOTO_DECODE_ERROR_INTERNAL	0x8002c902	Internal error
CELL_PHOTO_DECODE_ERROR_PARAM	0x8002c903	Parameters are invalid
CELL_PHOTO_DECODE_ERROR_ACCESS_ERROR	0x8002c904	HDD access error
CELL_PHOTO_DECODE_ERROR_INITIALIZE	0x8002c905	Initialization error
CELL_PHOTO_DECODE_ERROR_DECODE	0x8002c906	Decoding failed

Screenshot Utility errors

Description	Errorcode	Remarks
CELL_SCREENSHOT_ERROR_INTERNAL	0x8002d101	Internal error
CELL_SCREENSHOT_ERROR_PARAM	0x8002d102	Invalid parameter
CELL_SCREENSHOT_ERROR_DECODE	0x8002d103	Image decoding failed
CELL_SCREENSHOT_ERROR_NOSPACE	0x8002d104	Insufficient HDD space (500MB free needed)
CELL_SCREENSHOT_ERROR_UNSUPPORTED_COLOR_FORMAT	0x8002d105	The color format of the current frame buffer is not supported

Video Utility errors

Description	Errorcode	Remarks
CELL_VIDEO_EXPORT_UTIL_ERROR_BUSY	0x8002ca01	Requested processing could not be executed because the required processing has not been completed
CELL_VIDEO_EXPORT_UTIL_ERROR_INTERNAL	0x8002ca02	Internal error
CELL_VIDEO_EXPORT_UTIL_ERROR_PARAM	0x8002ca03	Parameter is invalid
CELL_VIDEO_EXPORT_UTIL_ERROR_ACCESS_ERROR	0x8002ca04	HDD access error, file copy failed
CELL_VIDEO_EXPORT_UTIL_ERROR_DB_INTERNAL	0x8002ca05	Internal database error
CELL_VIDEO_EXPORT_UTIL_ERROR_DB_REGIST	0x8002ca06	Registration to database failed
CELL_VIDEO_EXPORT_UTIL_ERROR_SET_META	0x8002ca07	Metadata set failed
CELL_VIDEO_EXPORT_UTIL_ERROR_FLUSH_META	0x8002ca08	Metadata flush failed
CELL_VIDEO_EXPORT_UTIL_ERROR_MOVE	0x8002ca09	File move failed
CELL_VIDEO_EXPORT_UTIL_ERROR_INITIALIZE	0x8002ca0a	Initialization error

Hash Function errors

Description	Errorcode	Remarks
CELL_ERROR_HASH_NULL_POINTER	0x80f00001	Null pointer was passed as an argument. workarea, taskset, md5, sha1, sha224, sha256, sha384, sha512, plain or digest is a null pointer.

Description	Errorcode	Remarks
CELL_ERROR_HASH_QUEUE_CREATE_FAILED	0x80f00002	SPURS event queue could not be created, or the event queue could not be attached to a SPURS queue.
CELL_ERROR_HASH_FLAG_CREATE_FAILED	0x80f00003	SPURS event flag could not be created, or the event flag could not be attached to a SPURS queue.
CELL_ERROR_HASH_INVALID_ALIGN	0x80f00004	Argument was not aligned to the correct boundary.
CELL_ERROR_HASH_INVALID_NOMEM	0x80f00005	Insufficient memory.
CELL_ERROR_HASH_TASK_CREATE_FAILED	0x80f00006	Failed to create SPURS task.
CELL_ERROR_HASH_INVALID_STATE	0x80f00007	Invalid state to process data.
CELL_ERROR_HASH_INVALID_BUFFER_SIZE	0x80f00008	Invalid context size to process data. spu_dma_buffer_size is not a multiple of 16 or the size is greater than 16KB.
CELL_ERROR_HASH_INVALID_STREAM_ID	0x80f00009	Invalid stream ID size.

KB errors

Description	Errorcode	Remarks
CELL_KB_ERROR_FATAL	0x80121001	
CELL_KB_ERROR_INVALID_PARAMETER	0x80121002	
CELL_KB_ERROR_ALREADY_INITIALIZED	0x80121003	
CELL_KB_ERROR_UNINITIALIZED	0x80121004	
CELL_KB_ERROR_RESOURCE_ALLOCATION_FAILED	0x80121005	
CELL_KB_ERROR_DATA_READ_FAILED	0x80121006	
CELL_KB_ERROR_NO_DEVICE	0x80121007	
CELL_KB_ERROR_SYS_SETTING_FAILED	0x80121008	

PAD errors

Description	Errorcode	Remarks
CELL_PAD_ERROR_FATAL	0x80121101	
CELL_PAD_ERROR_INVALID_PARAMETER	0x80121102	
CELL_PAD_ERROR_ALREADY_INITIALIZED	0x80121103	
CELL_PAD_ERROR_UNINITIALIZED	0x80121104	
CELL_PAD_ERROR_RESOURCE_ALLOCATION_FAILED	0x80121105	
CELL_PAD_ERROR_DATA_READ_FAILED	0x80121106	
CELL_PAD_ERROR_NO_DEVICE	0x80121107	
CELL_PAD_ERROR_UNSUPPORTED_GAMEPAD	0x80121108	
CELL_PAD_ERROR_TOO_MANY_DEVICES	0x80121109	
CELL_PAD_ERROR_EBUSY	0x8012110a	

MOUSE errors

Description	Errorcode	Remarks
CELL_MOUSE_ERROR_FATAL	0x80121201	
CELL_MOUSE_ERROR_INVALID_PARAMETER	0x80121202	
CELL_MOUSE_ERROR_ALREADY_INITIALIZED	0x80121203	
CELL_MOUSE_ERROR_UNINITIALIZED	0x80121204	
CELL_MOUSE_ERROR_RESOURCE_ALLOCATION_FAILED	0x80121205	
CELL_MOUSE_ERROR_DATA_READ_FAILED	0x80121206	
CELL_MOUSE_ERROR_NO_DEVICE	0x80121207	
CELL_MOUSE_ERROR_SYS_SETTING_FAILED	0x80121208	

K2C errors

Description	Errorcode	Remarks
CELL_K2C_ERROR_FATAL	0x80121301	
CELL_K2C_ERROR_INVALID_HANDLE	0x80121302	
CELL_K2C_ERROR_INVALID_PARAMETER	0x80121303	
CELL_K2C_ERROR_ALREADY_INITIALIZED	0x80121304	
CELL_K2C_ERROR_UNINITIALIZED	0x80121305	
CELL_K2C_ERROR_OTHER	0x80121306	

PADFILTER errors

Description	Errorcode	Remarks
CELL_PADFILTER_ERROR_INVALID_PARAMETER	0x80121401	

GEM errors

Description	Errorcode	Remarks
CELL_GEM_ERROR_RESOURCE_ALLOCATION_FAILED	0x80121801	libgem initialization failed to allocate the required resources.
CELL_GEM_ERROR_ALREADY_INITIALIZED	0x80121802	libgem initialization failed as the library is already initialized.
CELL_GEM_ERROR_UNINITIALIZED	0x80121803	Call failed because libgem is not initialized.
CELL_GEM_ERROR_INVALID_PARAMETER	0x80121804	Call failed because one or more parameters passed was not valid.
CELL_GEM_ERROR_INVALID_ALIGNMENT	0x80121805	Call failed because the video buffer could not be read.
CELL_GEM_ERROR_UPDATE_NOT_FINISHED	0x80121806	cellGemUpdateStart() call failed because it was called before cellGemUpdateFinish() completed.
CELL_GEM_ERROR_UPDATE_NOT_STARTED	0x80121807	cellGemUpdateFinish() call failed because it was called before cellGemUpdateStart().
CELL_GEM_ERROR_CONVERT_NOT_FINISHED	0x80121808	cellGemConvertVideoStart() call failed because it was called before cellGemConvertVideoFinish().
CELL_GEM_ERROR_CONVERT_NOT_STARTED	0x80121809	cellGemConvertVideoFinish() call failed because it was called before cellGemConvertVideoStart().
CELL_GEM_ERROR_WRITE_NOT_FINISHED	0x8012180A	cellGemWriteExternalPort() call failed because it was called before previous cellGemWriteExternalPort() completed.
CELL_GEM_ERROR_NOT_A_HUE	0x8012180B	Returned by cellGemGetTrackerHue() if the controller is not currently being tracked.

PERF errors

Description	Errorcode	Remarks
CELL_PERF_ERROR_NOT_OPENED	0x80520001	
CELL_PERF_ERROR_INVALID_SIGNAL	0x80520002	
CELL_PERF_ERROR_TRACE_BUS_BUSY	0x80520003	
CELL_PERF_ERROR_SIGNAL_CONTROL_FULL	0x80520004	
CELL_PERF_ERROR_INVALID_PARAMETER	0x80520005	
CELL_PERF_ERROR_LV1_NO_PRIVILEGE	0x80520006	
CELL_PERF_ERROR_LV1_DENIED_BY_POLICY	0x80520007	
CELL_PERF_ERROR_LV1_NO_ENTRY	0x80520008	
CELL_PERF_ERROR_LV1_DUPLICATE_ENTRY	0x80520009	
CELL_PERF_ERROR_LV1_BUSY	0x8052000a	
CELL_PERF_ERROR_LV1_RESOURCE_SHORTAGE	0x8052000b	
CELL_PERF_ERROR_LV1_WRONG_STATE	0x8052000c	
CELL_PERF_ERROR_LV1_ALIGNMENT_ERROR	0x8052000d	
CELL_PERF_ERROR_LV1_ILLEGAL_PARAMETER_VALUE	0x8052000e	
CELL_PERF_ERROR_LV2_BUSY	0x8052000f	
CELL_PERF_ERROR_LV2_NO_RESOURCE	0x80520010	
CELL_PERF_ERROR_LV2_NOT_OPENED	0x80520011	
CELL_PERF_ERROR_LV2_NOT_IMPLEMENTED	0x80520012	
CELL_PERF_ERROR_LV2_INVALID_PARAMETER	0x80520013	
CELL_PERF_ERROR_LV2_UNSUPPORTED_HARDWARE	0x80520014	
CELL_PERF_ERROR_LV2_NOT_ALLOWED	0x80520015	
CELL_PERF_ERROR_UNDEFINED	0x80520016	
CELL_PERF_ERROR_NO_RESOURCE	0x80520017	
CELL_PERF_ERROR_ADDED_ALREADY	0x80520018	
CELL_PERF_ERROR_NO_ENTRY	0x80520019	

Home coordination utility errors

Description	Errorcode	Remarks
CELL_HDDGAME_ERROR_INTERNAL		Fatal internal error
CELL_HDDGAME_ERROR_PARAM		Invalid argument (application bug)
CELL_HDDGAME_ERROR_NOAPP		PlayStation Home is not installed
CELL_GAME_ERROR_ACCESS_ERROR		HDD access error

IMEJP utility errors

Description	Errorcode	Remarks
CELL_IMEJP_ERROR_ERR	0x8002bf01	Function call error
CELL_IMEJP_ERROR_CONTEXT	0x8002bf11	Invalid context handle or context handle not opened
CELL_IMEJP_ERROR_ALREADY_OPEN	0x8002bf21	Attempted to open when the ImeJp utility is already opened
CELL_IMEJP_ERROR_DIC_OPEN	0x8002bf31	Dictionary open error
CELL_IMEJP_ERROR_PARAM	0x8002bf41	Invalid parameter
CELL_IMEJP_ERROR_IME_ALREADY_IN_USE	0x8002bf51	Character input engine is being used
CELL_IMEJP_ERROR_OTHER	0x8002bfff	Other error, internal error

L1On errors

Description	Errorcode	Remarks
SRCllegal		Target character string is corrupt
DSTExhausted		Buffer is too small for the conversion result
ConverterUnknown		Specified converter is invalid

Pthread errors

Description	Errorcode	Remarks
ESRCH		Non-existent thread
EINVAL		The value specified is invalid or does not refer to an initialized thread attribute object.
EINVAL		Invalid value for scheduling parameters.
ENOTSUP		An attempt was made to set the attribute to an unsupported value
ENOMEM		The process cannot allocate enough memory to initialize a mutex or a condition variable
EAGAIN		The system lacks the resources to initialize a mutex or a condition variable
EBUSY		Mutex is locked by another thread.
EDEADLK		A deadlock would occur if the thread blocked waiting for mutex
EPERM		The current thread does not hold a lock on mutex.
ETIMEDOUT		The system time has reached or exceeded the time specified in abstime.

Scream / MultiStream errors

Description	Errorcode	Remarks
Scream/MultiStream errors		
CELL_SCREAM_ERROR_NONE	0	
CELL_SCREAM_ERROR_NULL_PARAM	-1	
CELL_SCREAM_ERROR_SYSTEM_ALREADY_STARTED	-2	
CELL_SCREAM_ERROR_BAD RETURNS	-3	
CELL_SCREAM_ERROR_SYSTEM_NOT_RUNNING	-4	
CELL_SCREAM_ERROR_BAD_FLAGS	-5	
CELL_SCREAM_ERROR_BAD_MS_BUS	-6	
SCREAM specific errors		
CELL_SCREAM_LOAD_ERR_COUDNT_OPEN_FILE	0x100	
CELL_SCREAM_LOAD_ERR_READING_FILE	0x101	
CELL_SCREAM_LOAD_ERR_MEMORY	0x102	
CELL_SCREAM_LOAD_ERR_SYNTH_MEMORY	0x103	
CELL_SCREAM_LOAD_ERR_IN_PROGRESS	0x104	
CELL_SCREAM_LOAD_ERR_DMA	0x105	
CELL_SCREAM_LOAD_ERR_RPC	0x106	
CELL_SCREAM_LOAD_ERR_INVALID_FORMAT	0x107	

Realtimeclock errors

Description	Errorcode	Remarks
CELL_RTC_ERROR_NOT_INITIALIZED	0x80010601	Library has not yet been initialized. Please initialize before use.
CELL_RTC_ERROR_INVALID_POINTER	0x80010602	The pointer passed in is invalid.
CELL_RTC_ERROR_INVALID_VALUE	0x80010603	A value in the arguments is invalid and cannot be used.
CELL_RTC_ERROR_INVALID_ARG	0x80010604	An argument contains invalid data.
CELL_RTC_ERROR_NOT_SUPPORTED	0x80010605	The feature is not supported
CELL_RTC_ERROR_NO_CLOCK	0x80010606	The clock is not available

Description	Errorcode	Remarks
CELL_RTC_ERROR_BAD_PARSE	0x80010607	Error occurred in parsing, perhaps an unknown format
CELL_RTC_ERROR_INVALID_YEAR	0x80010621	The year value is invalid
CELL_RTC_ERROR_INVALID_MONTH	0x80010622	The month value is invalid
CELL_RTC_ERROR_INVALID_DAY	0x80010623	The day value is invalid
CELL_RTC_ERROR_INVALID_HOUR	0x80010624	The hour value is invalid
CELL_RTC_ERROR_INVALID_MINUTE	0x80010625	The minute value is invalid
CELL_RTC_ERROR_INVALID_SECOND	0x80010626	The second value is invalid
CELL_RTC_ERROR_INVALID_MICROSECOND	0x80010627	The microsecond value is invalid

USERINFO errors

Description	Errorcode	Remarks
CELL_USERINFO_ERROR_BUSY	0x8002c301	
CELL_USERINFO_ERROR_INTERNAL	0x8002c302	
CELL_USERINFO_ERROR_PARAM	0x8002c303	
CELL_USERINFO_ERROR_NOUSER	0x8002c304	

Print Utility errors

Print ErrorStatus

Description	Errorcode	Remarks
CELL_PRINT_ERRORSTATUS_COMM	0x80000000	Printer communication error
CELL_PRINT_ERRORSTATUS_COVEROPEN	0x80000001	Cover is opened
CELL_PRINT_ERRORSTATUS_INKCOVEROPEN	0x80000002	Ink (cartridge) cover is opened
CELL_PRINT_ERRORSTATUS_NOPAPER	0x80000003	No paper
CELL_PRINT_ERRORSTATUS_NOTRAY	0x80000004	No paper tray
CELL_PRINT_ERRORSTATUS_SIZE_TYPE_PATH	0x80000005	Paper feed method is not matching
CELL_PRINT_ERRORSTATUS_DOUBLEFEED	0x80000006	Paper feed error (double feed)
CELL_PRINT_ERRORSTATUS_FEEDERROR	0x80000007	Paper feed error (other than double feed)
CELL_PRINT_ERRORSTATUS_PAPERJAM	0x80000008	Paper jammed
CELL_PRINT_ERRORSTATUS_TRAYCLOSE	0x80000009	Eject tray is closed
CELL_PRINT_ERRORSTATUS_NOINK	0x8000000a	No ink
CELL_PRINT_ERRORSTATUS_NOCARTRIDGE	0x8000000b	No ink cartridge
CELL_PRINT_ERRORSTATUS_COVERFLOW	0x8000000c	Ink cartridge's waste ink full
CELL_PRINT_ERRORSTATUS_CFAIL	0x8000000d	Ink cartridge detection error
CELL_PRINT_ERRORSTATUS_CFACTORY	0x8000000e	Ink cartridge error (factory default settings)
CELL_PRINT_ERRORSTATUS_BATTERYVOLTAGE	0x8000000f	Abnormal battery voltage
CELL_PRINT_ERRORSTATUS_BATTERYTEMPERATURE	0x80000010	Abnormal battery temperature
CELL_PRINT_ERRORSTATUS_BATTERYEMPTY	0x80000011	No battery (cannot print)
CELL_PRINT_ERRORSTATUS_SERVICEREQ	0x80000012	Printer adjustment necessary
CELL_PRINT_ERRORSTATUS_GENERAL	0x80000013	Printer-related error
CELL_PRINT_ERRORSTATUS_FATAL	0x80000014	Fatal printer error

Print Error

Description	Errorcode	Remarks
CELL_PRINT_ERROR_INTERNAL	0x8002c401	Internal error
CELL_PRINT_ERROR_NO_MEMORY	0x8002c402	Memory allocation failed
CELL_PRINT_ERROR_PRINTER_NOT_FOUND	0x8002c403	Printer could not be found
CELL_PRINT_ERROR_INVALID_PARAM	0x8002c404	Parameter is invalid
CELL_PRINT_ERROR_INVALID_FUNCTION	0x8002c405	API call is invalid
CELL_PRINT_ERROR_NOT_SUPPORT	0x8002c406	Printer is not supported
CELL_PRINT_ERROR_OCCURRED	0x8002c407	API execution error
CELL_PRINT_ERROR_CANCELED_BY_PRINTER	0x8002c408	Print job was cancelled

Multistream errors

Description	Errorcode	Remarks
CELL_MS_ERROR	0x88000000	Base error value
CELL_MS_ERROR_SYSPAUSED	0x88000001	The system is paused.
CELL_MS_ERROR_INVAL	0x88000002	A parameter is invalid.
CELL_MS_ERROR_WRONGSTATE	0x88000003	A state is wrong.
CELL_MS_ERROR_RESOURCEUNAVAIL	0x88000004	A system resource is unavailable.
CELL_MS_ERROR_CIRCULARDEPEND	0x88000005	There is a circular dependency.
CELL_MS_ERROR_BUSMISMATCH	0x88000006	There is a bus mismatch.
CELL_MS_ERROR_INVALIDELF	0x88000007	An ELF file is invalid.
CELL_MS_ERROR_FILEACCESS	0x88000008	Access to a file failed.
CELL_MS_ERROR_INVALIDENV	0x88000009	An envelope is invalid.
CELL_MS_ERROR_OUTOFRANGE	0x8800000a	Out of range.
CELL_MS_ERROR_BADMODE	0x8800000b	There is a bad mode.
CELL_MS_ERROR_NOFREESTREAMS	0x8800000c	There are no free streams.
CELL_MS_ERROR_SURROUNDNOTINIT	0x8800000d	Surround sound is not initialised.
CELL_MS_ERROR_INVALID_CHANNEL	0x8800000e	A channel is invalid.
CELL_MS_ERROR_INVALID_TYPE	0x8800000f	A type is invalid.
CELL_MS_ERROR_AUDIO_CONFIGURE	0x88000010	cellMSSystemConfigureSysUtil failed processing cellAudioOutConfigure function
CELL_MS_ERROR_AUDIO_GETSTATE	0x88000011	cellMSSystemConfigureSysUtil failed processing cellAudioOutGetState function

Record Utility Error

Description	Errorcode	Remarks
CELL_REC_ERROR_OUT_OF_MEMORY	0x8002c501	
CELL_REC_ERROR_FATAL	0x8002c502	
CELL_REC_ERROR_INVALID_VALUE	0x8002c503	
CELL_REC_ERROR_FILE_OPEN	0x8002c504	
CELL_REC_ERROR_FILE_WRITE	0x8002c505	
CELL_REC_ERROR_INVALID_STATE	0x8002c506	
CELL_REC_ERROR_FILE_NO_DATA	0x8002c507	

PRX Error

Description	Errorcode	Remarks
CELL_PRX_ERROR_ERROR	0x80011001	
CELL_PRX_ERROR_ILLEGAL_PERM	0x800110d1	
CELL_PRX_ERROR_UNKNOWN_MODULE	0x8001112e	
CELL_PRX_ERROR_ALREADY_STARTED	0x80011133	
CELL_PRX_ERROR_NOT_STARTED	0x80011134	
CELL_PRX_ERROR_ALREADY_STOPPED	0x80011135	
CELL_PRX_ERROR_CAN_NOT_STOP	0x80011136	
CELL_PRX_ERROR_NOT_REMOVABLE	0x80011138	
CELL_PRX_ERROR_LIBRARY_NOT_YET_LINKED	0x8001113a	
CELL_PRX_ERROR_LIBRARY_FOUND	0x8001113b	
CELL_PRX_ERROR_LIBRARY_NOTFOUND	0x8001113c	
CELL_PRX_ERROR_ILLEGAL_LIBRARY	0x8001113d	
CELL_PRX_ERROR_LIBRARY_INUSE	0x8001113e	
CELL_PRX_ERROR_ALREADY_STOPPING	0x8001113f	
CELL_PRX_ERROR_UNSUPPORTED_PRX_TYPE	0x80011148	
CELL_PRX_ERROR_INVAL	0x80011324	
CELL_PRX_ERROR_ILLEGAL_PROCESS	0x80011801	
CELL_PRX_ERROR_NO_LIBLV2	0x80011881	
CELL_PRX_ERROR_UNSUPPORTED_ELF_TYPE	0x80011901	
CELL_PRX_ERROR_UNSUPPORTED_ELF_CLASS	0x80011902	
CELL_PRX_ERROR_UNDEFINED_SYMBOL	0x80011904	
CELL_PRX_ERROR_UNSUPPORTED_RELLOCATION_TYPE	0x80011905	
CELL_PRX_ERROR_ELF_IS_REGISTERED	0x80011910	
CELL_PRX_ERROR_NO_EXIT_ENTRY	0x80011911	

Sysmodule Error

Description	Errorcode	Remarks
CELL_SYSMODULE_ERROR_DUPLICATED	0x80012001	Tried to load a PRX that is already loaded
CELL_SYSMODULE_ERROR_UNKNOWN	0x80012002	Tried to load an unknown PRX
CELL_SYSMODULE_ERROR_UNLOADED	0x80012003	Tried to unload a PRX that is already unloaded, or the module is not loaded
CELL_SYSMODULE_ERROR_INVALID_MEMCONTAINER	0x80012004	An invalid memory container ID was passed
CELL_SYSMODULE_ERROR_FATAL	0x800120ff	Function call failed

System Utility Error

Description	Errorcode	Remarks
CELL_SYSUTIL_ERROR_TYPE	0x8002b101	Type is invalid
CELL_SYSUTIL_ERROR_VALUE	0x8002b102	Value is invalid
CELL_SYSUTIL_ERROR_SIZE	0x8002b103	Size is invalid
CELL_SYSUTIL_ERROR_NUM	0x8002b104	Number exceeds valid range
CELL_SYSUTIL_ERROR_BUSY	0x8002b105	Service cannot run because another service is running
CELL_SYSUTIL_ERROR_STATUS	0x8002b106	Invalid API was called for the current service status
CELL_SYSUTIL_ERROR_MEMORY	0x8002b107	Sufficient memory could not be allocated for the requested service
CELL_SYSUTIL_ERROR_3D_SUPPORT	0x8002b108	

System BGM Control Error

Description	Errorcode	Remarks
CELL_SYSUTIL_BGMPLAYBACK_ERROR_PARAM	0x8002b101	Invalid parameter
CELL_SYSUTIL_BGMPLAYBACK_ERROR_BUSY	0x8002b102	Requested processing cannot be executed because the required processing has not completed yet
CELL_SYSUTIL_BGMPLAYBACK_ERROR_GENERIC	0x8002b1ff	Unknown error occurred
CELL_SYSUTIL_BGMPLAYBACK_EX_ERROR_PARAM	0x8002d301	Invalid parameter
CELL_SYSUTIL_BGMPLAYBACK_EX_ERROR_ALREADY_SETPARAM	0x8002d302	Processing cannot be accepted because the setting has already been made
CELL_SYSUTIL_BGMPLAYBACK_EX_ERROR_DISABLE_SETPARAM	0x8002d303	Processing cannot be accepted because the feature is disabled
CELL_SYSUTIL_BGMPLAYBACK_EX_ERROR_GENERIC	0x8002d3ff	Unknown error occurred

COMBOPLAY errors

Description	Errorcode	Remarks
CELL_CROSS_CONTROLLER_ERROR_CANCEL	0x8002cd80	
CELL_CROSS_CONTROLLER_ERROR_NETWORK	0x8002cd81	
CELL_CROSS_CONTROLLER_ERROR_OUT_OF_MEMORY	0x8002cd90	
CELL_CROSS_CONTROLLER_ERROR_FATAL	0x8002cd91	
CELL_CROSS_CONTROLLER_ERROR_INVALID_PKG_FILENAME	0x8002cd92	
CELL_CROSS_CONTROLLER_ERROR_INVALID_SIG_FILENAME	0x8002cd93	
CELL_CROSS_CONTROLLER_ERROR_INVALID_ICON_FILENAME	0x8002cd94	
CELL_CROSS_CONTROLLER_ERROR_INVALID_VALUE	0x8002cd95	
CELL_CROSS_CONTROLLER_ERROR_PKG_FILE_OPEN	0x8002cd96	
CELL_CROSS_CONTROLLER_ERROR_SIG_FILE_OPEN	0x8002cd97	
CELL_CROSS_CONTROLLER_ERROR_ICON_FILE_OPEN	0x8002cd98	
CELL_CROSS_CONTROLLER_ERROR_INVALID_STATE	0x8002cd99	
CELL_CROSS_CONTROLLER_ERROR_INVALID_PKG_FILE	0x8002cd9a	
CELL_CROSS_CONTROLLER_ERROR_INTERNAL	0x8002cda0	

SYSTEMPARAM errors

Description	Errorcode	Remarks
CELL_VIDEO_OUT_ERROR_NOT_IMPLEMENTED	0x8002b220	
CELL_VIDEO_OUT_ERROR_ILLEGAL_CONFIGURATION	0x8002b221	
CELL_VIDEO_OUT_ERROR_ILLEGAL_PARAMETER	0x8002b222	
CELL_VIDEO_OUT_ERROR_PARAMETER_OUT_OF_RANGE	0x8002b223	
CELL_VIDEO_OUT_ERROR_DEVICE_NOT_FOUND	0x8002b224	
CELL_VIDEO_OUT_ERROR_UNSUPPORTED_VIDEO_OUT	0x8002b225	
CELL_VIDEO_OUT_ERROR_UNSUPPORTED_DISPLAY_MODE	0x8002b226	

Description	Errorcode	Remarks
CELL_VIDEO_OUT_ERROR_CONDITION_BUSY	0x8002b227	
CELL_VIDEO_OUT_ERROR_VALUE_IS_NOT_SET	0x8002b228	
CELL_AUDIO_OUT_ERROR_NOT_IMPLEMENTED	0x8002b240	
CELL_AUDIO_OUT_ERROR_ILLEGAL_CONFIGURATION	0x8002b241	
CELL_AUDIO_OUT_ERROR_ILLEGAL_PARAMETER	0x8002b242	
CELL_AUDIO_OUT_ERROR_PARAMETER_OUT_OF_RANGE	0x8002b243	
CELL_AUDIO_OUT_ERROR_DEVICE_NOT_FOUND	0x8002b244	
CELL_AUDIO_OUT_ERROR_UNSUPPORTED_AUDIO_OUT	0x8002b245	
CELL_AUDIO_OUT_ERROR_UNSUPPORTED_SOUND_MODE	0x8002b246	
CELL_AUDIO_OUT_ERROR_CONDITION_BUSY	0x8002b247	
CELL_AUDIO_IN_ERROR_NOT_IMPLEMENTED	0x8002b260	
CELL_AUDIO_IN_ERROR_ILLEGAL_CONFIGURATION	0x8002b261	
CELL_AUDIO_IN_ERROR_ILLEGAL_PARAMETER	0x8002b262	
CELL_AUDIO_IN_ERROR_PARAMETER_OUT_OF_RANGE	0x8002b263	
CELL_AUDIO_IN_ERROR_DEVICE_NOT_FOUND	0x8002b264	
CELL_AUDIO_IN_ERROR_UNSUPPORTED_AUDIO_IN	0x8002b265	
CELL_AUDIO_IN_ERROR_UNSUPPORTED_SOUND_MODE	0x8002b266	
CELL_AUDIO_IN_ERROR_CONDITION_BUSY	0x8002b267	

MsgDialog Error

Description	Errorcode	Remarks
CELL_MSGDIALOG_ERROR_PARAM	0x8002b301	Parameter is invalid
CELL_MSGDIALOG_ERROR_DIALOG_NOT_OPENED	0x8002b302	The dialogue is not opened

SAVEDATA errors

Description	Errorcode	Remarks
CELL_SAVEDATA_ERROR_CBRESULT	0x8002B401	
CELL_SAVEDATA_ERROR_ACCESS_ERROR	0x8002B402	
CELL_SAVEDATA_ERROR_INTERNAL	0x8002B403	Game save issue // Reboot console
CELL_SAVEDATA_ERROR_PARAM	0x8002B404	
CELL_SAVEDATA_ERROR_NOSPACE	0x8002B405	
CELL_SAVEDATA_ERROR_BROKEN	0x8002B406	
CELL_SAVEDATA_ERROR_FAILURE	0x8002B407	
CELL_SAVEDATA_ERROR_BUSY	0x8002B408	
CELL_SAVEDATA_ERROR_NOUSER	0x8002B409	
CELL_SAVEDATA_ERROR_SIZEOVER	0x8002B40A	
CELL_SAVEDATA_ERROR_NODATA	0x8002b40b	
CELL_SAVEDATA_ERROR_NOTSUPPORTED	0x8002b40c	

OSKDIALOG errors

Description	Errorcode	Remarks
CELL_OSKDIALOG_ERROR_IME_ALREADY_IN_USE	0x8002b501	
CELL_OSKDIALOG_ERROR_GET_SIZE_ERROR	0x8002b502	
CELL_OSKDIALOG_ERROR_UNKNOWN	0x8002b503	
CELL_OSKDIALOG_ERROR_PARAM	0x8002b504	

WEBBROWSER errors

Description	Errorcode	Remarks
CELL_WEBBROWSER_ERROR_NOMEM	0x8002b901	
CELL_WEBBROWSER_ERROR_INVALID	0x8002b902	
CELL_WEBBROWSER_ERROR_EXCLUSIVE	0x8002b903	

SYSCONF errors

Description	Errorcode	Remarks
CELL_SYSCONF_ERROR_PARAM	0x8002bb01	

SYSCACHE errors

Description	Errorcode	Remarks
CELL_SYSCACHE_ERROR_ACCESS_ERROR	0x8002bc01	
CELL_SYSCACHE_ERROR_INTERNAL	0x8002bc02	
CELL_SYSCACHE_ERROR_PARAM	0x8002bc03	
CELL_SYSCACHE_ERROR_NOTMOUNTED	0x8002bc04	

STORAGEDATA errors

Description	Errorcode	Remarks
CELL_STORAGEDATA_ERROR_BUSY	0x8002be01	
CELL_STORAGEDATA_ERROR_INTERNAL	0x8002be02	
CELL_STORAGEDATA_ERROR_PARAM	0x8002be03	
CELL_STORAGEDATA_ERROR_ACCESS_ERROR	0x8002be04	
CELL_STORAGEDATA_ERROR_FAILURE	0x8002be05	

CXML Error

Description	Errorcode	Remarks
CXML_RESULT_OK	0x0	
CXML_RESULT_ERROR_CANT_OPEN	0x8002E001	
CXML_RESULT_ERROR_CANT_READ	0x8002E002	
CXML_RESULT_ERROR_CANT_WRITE	0x8002E003	
CXML_RESULT_ERROR_CANT_SEEK	0x8002E004	
CXML_RESULT_ERROR_CANT_ALLOC	0x8002E005	
CXML_RESULT_ERROR_FORMAT	0x8002E006	
CXML_RESULT_ERROR_VERSION	0x8002E007	
CXML_RESULT_ERROR_INVALID_NODE	0x8002E008	
CXML_RESULT_ERROR_NOT_ENOUGH_BUF	0x8002E009	
CXML_RESULT_ERROR_ACCESS_MODE	0x8002E010	
CXML_RESULT_ERROR_NOT_EXIST	0x8002E011	
CXML_RESULT_ERROR_TYPE	0x8002E012	
CXML_RESULT_ERROR_CANT MODIFY	0x8002E013	
CXML_RESULT_ERROR_NO_ALLOCATOR	0x8002E014	

Media? Player Video Player Error

Description	Errorcode	Remarks
MP_SUCCESS	0x0	
MP_VP_ERROR	0x80028801	fake Blu-Ray discs] and video.
MP_VP_NO_MORE_ITEM_ERROR	0x80028802	
MP_VP_DATA_TOP_ERROR	0x80028803	
MP_VP_DATA_END_ERROR	0x80028804	
MP_VP_NO_DATA_ERROR	0x80028805	
MP_VP_BUFFER_FULL_ERROR	0x80028806	
MP_VP_FILE_OPEN_ERROR	0x80028807	
MP_VP_FILE_READ_ERROR	0x80028808	
MP_VP_FILE_SEEK_ERROR	0x80028809	
MP_VP_NO_SUPPORTED_ERROR	0x8002880A	
MP_VP_DECODE_ERROR	0x8002880B	
MP_VP_V_DECODE_ERROR	0x8002880C	
MP_VP_A_DECODE_ERROR	0x8002880D	
MP_VP_DATA_SET_FAILED_ERROR	0x8002880E	
MP_VP_NOTFOUND_NEXT_DATA_ERROR	0x8002880F	
MP_VP_NOTFOUND_PREV_DATA_ERROR	0x80028810	
MP_VP_ANALYZE_ERROR	0x80028811	

Description	Errorcode	Remarks
MP_VP_LACK_OF_BUFFER_ERROR	0x80028812	
MP_VP_LICENSE_ERROR	0x80028813	
MP_VP_LICENSE_NOT_YET_AVAILABLE_ERROR	0x80028814	
MP_VP_LICENSE_EXPIRED_ERROR	0x80028815	
MP_VP_LICENSE_VOID_SECURE_CLOCK_ERROR	0x80028816	
MP_VP_GET_PICTURE_ERROR	0x80028817	
MP_VP_VPOST_ERROR	0x80028818	
MP_VP_IMAGE_LOAD_FAILED_ERROR	0x80028819	
MP_VP_NO_EXECUTE_ERROR	0x80028881	
MP_VP_OUT_OF_RANGE_ERROR	0x8002888D	
MP_VP_FILE_NOT_EXIST_ERROR	0x80028882	
MP_VP_LICENSE_EXCLUDED_ERROR	0x80028883	
MP_VP_CREATE_SHORT_ICON_ERROR	0x80028884	
MP_VP_CREATE_ICON_ERROR	0x80028885	
MP_VP_VTRM_BROKEN_ERROR	0x80028886	
MP_VP_INCOMPAT_ADAPTER_ERROR	0x80028887	MagicGate device required
MP_VP_MEDIA_INCOMPAT_ERROR	0x80028888	
MP_VP_GID_NO_SET_ERROR	0x80028889	
MP_VP_PREMATURE_GID_ERROR	0x8002888A	
MP_VP_BELATED_GID_ERROR	0x8002888B	
MP_VP_PSN_NOLICENSE_ERROR	0x8002888E	Authenticate via PsStore
MP_VP_PSN_NEED_ACTIVATION_ERROR	0x8002888F	Need Certification
MP_VP_PSN_UNEXPECTED_AIV_ERROR	0x80028890	Wrong Certification Data
MP_VP_INVALID_FORMAT_ERROR	0x80028891	
MP_VP_ACCESS_DENIED_ERROR	0x80028892	
MP_VP_HTTP_SERVER_NOT_FOUND_ERROR	0x80028893	
MP_VP_HTTP_GENERIC_ERROR	0x80028894	HTTP MediaServer Error
MP_VP_NOT_ENOUGH_MEMORY_ERROR	0x80028895	
MP_VP_NO_AUDIO_STREAM_ERROR	0x80028896	No Audio
MP_VP_NO_SUBTITLE_ERROR	0x80028897	No Subtitle
MP_VP_NETWORK_ERROR	0x80028898	
MP_VP_A_ENCODE_ERROR	0x80028899	
MP_VP_V_ENCODE_ERROR	0x8002889A	
MP_VP_FILE_WRITE_ERROR	0x8002889B	
MP_VP_FILE_WRITE_RES_ERROR	0x8002889C	
MP_VP_S_DECODE_ERROR	0x8002889D	
MP_VP_FILE_IO_CANCELLED_ERROR	0x8002889E	
MP_VP_HTTP_CONTENT_NOT_FOUND_ERROR	0x8002889F	
MP_VP_EXPIRED_ERROR	0x800288A0	
MP_VP_WMA_NOT_ENABLED_ERROR	0x800288A1	WMA Playback not enabled.
MP_VP_ACCESS_NOT_DOWNLOADED_AREA_ERROR	0x800288A2	
MP_VP_DTCP_IP_AUTH_INVALID_HOSTNAME_ERROR	0x800288A3	
MP_VP_DTCP_IP_AUTH_SERVER_NOT_FOUND_ERROR	0x800288A4	
MP_VP_DTCP_IP_AUTH_CANNOT_ACCESS_ERROR	0x800288A5	
MP_VP_DTCP_IP_AUTH_FAILED_ERROR	0x800288A6	
MP_VP_DTCP_IP_AUTH_FAILED_ERROR_WLAN	0x800288A7	DTCP/IP Error set WEP/WPA
MP_VP_DTCP_IP_DEVCERT_EXPIRED_ERROR	0x800288A8	
MP_VP_DTCP_IP_INVALID_URL_ERROR	0x800288A9	
MP_VP_DTCP_IP_KM_NEED_ACTIVATE_ERROR	0x800288AA	
MP_VP_DTCP_IP_KM_NEED_UPDATE_ERROR	0x800288AB	
MP_VP_DTCP_IP_KM_FATAL_ERROR	0x800288AC	
MP_VP_DTCP_IP_KM_FATAL_ERROR_REGISTRY	0x800288AD	
MP_VP_DTCP_IP_KM_FATAL_ERROR_BUFFER	0x800288AE	
MP_VP_DTCP_IP_KM_FATAL_ERROR_SRM	0x800288AF	
MP_VP_DTCP_IP_KM_NEED_CLOCK_SETUP_ERROR	0x800288B0	
MP_VP_HTTP_SEEK_NOT_ALLOWED_ERROR	0x800288B1	
MP_VP_DTCP_IP_UNKNOWN_ERROR	0x800288B2	

Description	Errorcode	Remarks
MP_VP_DTCP_IP_INVALID_ARG_ERROR	0x800288B3	
MP_VP_DTCP_IP_INVALID_STATE_ERROR	0x800288B4	
MP_VP_DTCP_IP_NOT_IMPLEMENTED_ERROR	0x800288B5	
MP_VP_DTCP_IP_INTERNAL_ERROR	0x800288B6	
MP_VP_DTCP_IP_STREAM_GENERIC_ERROR	0x800288B7	
MP_VP_REGISTRY_ERROR	0x800288B8	
MP_VP_HDCP_OFF_ERROR	0x800288B9	
MP_VP_DTCP_IP_EMI_CCI_ERROR	0x800288BA	
MP_VP_NET_CTL_ERROR	0x800288BB	
MP_VP_NO_SUPPORTED_ERROR_PICTURE_TOO_LARGE	0x800288BC	
MP_VP_NO_SUPPORTED_ERROR_PICTURE_TOO_SMALL	0x800288BD	
MP_VP_NO_SUPPORTED_ERROR_PROFILE	0x800288BE	
MP_VP_NO_SUPPORTED_ERROR_TOOL	0x800288BF	PS3 cannot play this file type
MP_VP_NO_SUPPORTED_ERROR_VIDEO_CODEC	0x800288C0	"The data type is not supported." Related to video.
MP_VP_NO_SUPPORTED_ERROR_AUDIO_CODEC	0x800288C1	PS3 cannot play this file type
MP_VP_NO_SUPPORTED_ERROR_AU_SIZE	0x800288C2	
MP_VP_HTTP_NO_CONTENT_LENGTH_ERROR	0x800288C3	
MP_VP_DIGITAL_ONLY_ERROR	0x800288C4	Cannot output video other than HDMI
MP_VP_PSN_UNSUPPORTED_DEVICE_ERROR	0x800288C5	
MP_VP_DIVX_DRM_RENTAL_EXPIRED_ERROR	0x800288C6	divx vod rental expired
MP_VP_DIVX_DRM_AUTHORIZATION_ERROR	0x800288C7	divx vod reg visit website
MP_VP_CANNOT_PLAY_CONTENT_ERROR	0x800288C8	
MP_VP_NO_SUPPORTED_ERROR_BRAND	0x800288C9	
MP_VP_NO_SUPPORTED_ERROR_DURATION_TOO_LONG	0x800288CF	
MP_VP_NO_SUPPORTED_ERROR_TRACKS_TOO_MANY	0x800288D0	
MP_VP_NO_SUPPORTED_ERROR_LICENSE	0x800288D1	
MP_VP_NO_SUPPORTED_ERROR_MVP_SEPARATED_PVL	0x800288D2	
MP_VP_NO_SUPPORTED_ERROR_PROHIBITED.DAO	0x800288D3	
MP_VP_NO_SUPPORTED_ERROR_FORMAT_VERSION	0x800288D4	
MP_VP_NO_SUPPORTED_ERROR_MEDIA	0x800288D5	
MP_VP_NO_SUPPORTED_ERROR_64BIT_BOXSIZE	0x800288D6	
MP_VP_CONTENTS_NOT_EXIST_ERROR	0x800288CA	
MP_VP_NO_NEXT_CONTENTS_ERROR	0x800288CC	
MP_VP_NO_PREV_CONTENTS_ERROR	0x800288CD	Content not found
MP_VP_SEQUENTIAL_PLAY_NOT_ALLOWED_ERROR	0x800288D7	
MP_VP_DELETE_CONTENTS_ERROR	0x800288DA	
MP_VP_AACS_WM_TRUSTED_SOURCE_STATE_ERROR	0x800288DB	
MP_VP_AACS_WM_NO_HOME_USE_ERROR	0x800288DC	cinavia msg code 1
MP_VP_NO_SUPPORTED_ERROR_SCREEN_SAVER	0x800288DE	
MP_VP_SELFLICENSE_NONE_ERROR	0x800288DF	Content owner account signin please
MP_VP_NOT_SUPPORT_REMOTEPLAY_ERROR	0x800288E0	Content does not support remoteplay
MP_VP_READ_FIRST_BLOCK_SIZE_0_ERROR	0x800288E1	
MP_VP_DTCP_IP_CABLE_NOT_CONNECTED_ERROR	0x800288E2	
MP_VP_FILE_IO_TIMEOUT_ERROR	0x800288E3	

DMA errors

Description	Errorcode	Remarks
CELL_DMA_ERROR_INVAL	0x80410002	

SYNC errors

Description	Errorcode	Remarks
CELL_SYNC_ERROR AGAIN	0x80410101	
CELL_SYNC_ERROR_INVAL	0x80410102	
CELL_SYNC_ERROR_NOSYS	0x80410103	
CELL_SYNC_ERROR_NOMEM	0x80410104	
CELL_SYNC_ERROR_SRCH	0x80410105	

Description	Errorcode	Remarks
CELL_SYNC_ERROR_NOENT	0x80410106	
CELL_SYNC_ERROR_NOEXEC	0x80410107	
CELL_SYNC_ERROR_DEADLK	0x80410108	
CELL_SYNC_ERROR_PERM	0x80410109	
CELL_SYNC_ERROR_BUSY	0x8041010A	
CELL_SYNC_ERROR_ABORT	0x8041010C	
CELL_SYNC_ERROR_FAULT	0x8041010D	
CELL_SYNC_ERROR_CHILD	0x8041010E	
CELL_SYNC_ERROR_STAT	0x8041010F	
CELL_SYNC_ERROR_ALIGN	0x80410110	
CELL_SYNC_ERROR_NULL_POINTER	0x80410111	
CELL_SYNC_ERROR_SHOTAGE	0x80410112	
CELL_SYNC_ERROR_UNKNOWNKEY	0x80410113	

SHEAP errors

Description	Errorcode	Remarks
CELL_SHEAP_ERROR AGAIN	0x80410301	The resource is temporarily unavailable
CELL_SHEAP_ERROR_INVAL	0x80410302	An invalid argument value is specified
CELL_SHEAP_ERROR_NOSYS	0x80410303	The feature is not yet implemented
CELL_SHEAP_ERROR_NOMEM	0x80410304	Memory allocation failure
CELL_SHEAP_ERROR_SRCH	0x80410305	The resource (process, thread, sheaphronous object, etc) with the specified identifier does not exist.
CELL_SHEAP_ERROR_NOENT	0x80410306	The file does not exist
CELL_SHEAP_ERROR_NOEXEC	0x80410307	The file is not a valid ELF file. (The file is in unrecognized format.)
CELL_SHEAP_ERROR_DEADLK	0x80410308	Resource deadlock is avoided
CELL_SHEAP_ERROR_PERM	0x80410309	The operation is not permitted
CELL_SHEAP_ERROR_BUSY	0x8041030A	The device or resource is busy
CELL_SHEAP_ERROR_ABORT	0x8041030C	The operation is aborted
CELL_SHEAP_ERROR_FAULT	0x8041030D	Invalid memory access
CELL_SHEAP_ERROR_CHILD	0x8041030E	Failed in awaiting a child, or no such child exists
CELL_SHEAP_ERROR_STAT	0x8041030F	State of the target thread is invalid
CELL_SHEAP_ERROR_ALIGN	0x80410310	Alignment is invalid
CELL_SHEAP_ERROR_KRESOURCE	0x80410311	Shortage of the kernel resources
CELL_SHEAP_ERROR_SHORTAGE	0x80410312	Shortage of the kernel resources
CELL_SHEAP_ERROR_UNKNOWNKEY	0x80410313	Shortage of the kernel resources

OVIS errors

Description	Errorcode	Remarks
CELL_OVIS_ERROR_INVAL	0x80410402	An invalid argument value is specified.
CELL_OVIS_ERROR_ABORT	0x8041040C	
CELL_OVIS_ERROR_ALIGN	0x80410416	Alignment is invalid

Daisy errors (libdaisy)

Description	Errorcode	Remarks
CELL_DAISY_ERROR_NO_BEGIN	0x80410501	
CELL_DAISY_ERROR_INVALID_PORT_ATTACH	0x80410502	
CELL_DAISY_ERROR_NOT_IMPLEMENTED	0x80410503	
CELL_DAISY_ERROR_PERM	0x80410509	
CELL_DAISY_ERROR_STAT	0x8041050f	
CELL_DAISY_ERROR AGAIN	0x80410511	
CELL_DAISY_ERROR_INVAL	0x80410512	
CELL_DAISY_ERROR_BUSY	0x8041051a	

SPUDLL errors

Description	Errorcode	Remarks
CELL_SPUDLL_ERROR AGAIN	0x80410601	

Description	Errorcode	Remarks
CELL_SPUDLL_ERROR_INVAL	0x80410602	
CELL_SPUDLL_ERROR_NOSYS	0x80410603	
CELL_SPUDLL_ERROR_NOMEM	0x80410604	
CELL_SPUDLL_ERROR_SRCH	0x80410605	
CELL_SPUDLL_ERROR_NOENT	0x80410606	
CELL_SPUDLL_ERROR_NOEXEC	0x80410607	
CELL_SPUDLL_ERROR_DEADLK	0x80410608	
CELL_SPUDLL_ERROR_PERM	0x80410609	
CELL_SPUDLL_ERROR_BUSY	0x8041060a	
CELL_SPUDLL_ERROR_ABORT	0x8041060c	
CELL_SPUDLL_ERROR_FAULT	0x8041060d	
CELL_SPUDLL_ERROR_CHILD	0x8041060e	
CELL_SPUDLL_ERROR_STAT	0x8041060f	
CELL_SPUDLL_ERROR_ALIGN	0x80410610	
CELL_SPUDLL_ERROR_NULL_POINTER	0x80410611	
CELL_SPUDLL_ERROR_UNDEF	0x80410612	
CELL_SPUDLL_ERROR_FATAL	0x80410613	

SPURS errors

Description	Errorcode	Remarks
CELL_SPURS_CORE_ERROR AGAIN	0x80410701	
CELL_SPURS_CORE_ERROR_INVAL	0x80410702	
CELL_SPURS_CORE_ERROR_NOSYS	0x80410703	
CELL_SPURS_CORE_ERROR_NOMEM	0x80410704	
CELL_SPURS_CORE_ERROR_SRCH	0x80410705	
CELL_SPURS_CORE_ERROR_NOENT	0x80410706	
CELL_SPURS_CORE_ERROR_NOEXEC	0x80410707	
CELL_SPURS_CORE_ERROR_DEADLK	0x80410708	
CELL_SPURS_CORE_ERROR_PERM	0x80410709	
CELL_SPURS_CORE_ERROR_BUSY	0x8041070A	
CELL_SPURS_CORE_ERROR_ABORT	0x8041070C	
CELL_SPURS_CORE_ERROR_FAULT	0x8041070D	
CELL_SPURS_CORE_ERROR_CHILD	0x8041070E	
CELL_SPURS_CORE_ERROR_STAT	0x8041070F	
CELL_SPURS_CORE_ERROR_ALIGN	0x80410710	
CELL_SPURS_CORE_ERROR_NULL_POINTER	0x80410711	
CELL_SPURS_POLICY_MODULE_ERROR AGAIN	0x80410801	
CELL_SPURS_POLICY_MODULE_ERROR_INVAL	0x80410802	
CELL_SPURS_POLICY_MODULE_ERROR_NOSYS	0x80410803	
CELL_SPURS_POLICY_MODULE_ERROR_NOMEM	0x80410804	
CELL_SPURS_POLICY_MODULE_ERROR_SRCH	0x80410805	
CELL_SPURS_POLICY_MODULE_ERROR_NOENT	0x80410806	
CELL_SPURS_POLICY_MODULE_ERROR_NOEXEC	0x80410807	
CELL_SPURS_POLICY_MODULE_ERROR_DEADLK	0x80410808	
CELL_SPURS_POLICY_MODULE_ERROR_PERM	0x80410809	
CELL_SPURS_POLICY_MODULE_ERROR_BUSY	0x8041080A	
CELL_SPURS_POLICY_MODULE_ERROR_ABORT	0x8041080C	
CELL_SPURS_POLICY_MODULE_ERROR_FAULT	0x8041080D	
CELL_SPURS_POLICY_MODULE_ERROR_CHILD	0x8041080E	
CELL_SPURS_POLICY_MODULE_ERROR_STAT	0x8041080F	
CELL_SPURS_POLICY_MODULE_ERROR_ALIGN	0x80410810	
CELL_SPURS_POLICY_MODULE_ERROR_NULL_POINTER	0x80410811	
CELL_SPURS_TASK_ERROR AGAIN	0x80410901	
CELL_SPURS_TASK_ERROR_INVAL	0x80410902	
CELL_SPURS_TASK_ERROR_NOSYS	0x80410903	
CELL_SPURS_TASK_ERROR_NOMEM	0x80410904	
CELL_SPURS_TASK_ERROR_SRCH	0x80410905	

Description	Errorcode	Remarks
CELL_SPURS_TASK_ERROR_NOENT	0x80410906	
CELL_SPURS_TASK_ERROR_NOEXEC	0x80410907	
CELL_SPURS_TASK_ERROR_DEADLK	0x80410908	
CELL_SPURS_TASK_ERROR_PERM	0x80410909	
CELL_SPURS_TASK_ERROR_BUSY	0x8041090A	
CELL_SPURS_TASK_ERROR_ABORT	0x8041090C	
CELL_SPURS_TASK_ERROR_FAULT	0x8041090D	
CELL_SPURS_TASK_ERROR_CHILD	0x8041090E	
CELL_SPURS_TASK_ERROR_STAT	0x8041090F	
CELL_SPURS_TASK_ERROR_ALIGN	0x80410910	
CELL_SPURS_TASK_ERROR_NULL_POINTER	0x80410911	
CELL_SPURS_TASK_ERROR_FATAL	0x80410914	
CELL_SPURS_TASK_ERROR_SHUTDOWN	0x80410920	
CELL_SPURS_JOB_ERROR AGAIN	0x80410A01	
CELL_SPURS_JOB_ERROR_INVAL	0x80410A02	
CELL_SPURS_JOB_ERROR_NOSYS	0x80410A03	
CELL_SPURS_JOB_ERROR_NOMEM	0x80410A04	
CELL_SPURS_JOB_ERROR_SRCH	0x80410A05	
CELL_SPURS_JOB_ERROR_NOENT	0x80410A06	
CELL_SPURS_JOB_ERROR_NOEXEC	0x80410A07	
CELL_SPURS_JOB_ERROR_DEADLK	0x80410A08	
CELL_SPURS_JOB_ERROR_PERM	0x80410A09	
CELL_SPURS_JOB_ERROR_BUSY	0x80410A0A	
CELL_SPURS_JOB_ERROR_JOB_DESCRIPTOR	0x80410A0B	
CELL_SPURS_JOB_ERROR_JOB_DESCRIPTOR_SIZE	0x80410A0C	
CELL_SPURS_JOB_ERROR_FAULT	0x80410A0D	
CELL_SPURS_JOB_ERROR_CHILD	0x80410A0E	
CELL_SPURS_JOB_ERROR_STAT	0x80410A0F	
CELL_SPURS_JOB_ERROR_ALIGN	0x80410A10	
CELL_SPURS_JOB_ERROR_NULL_POINTER	0x80410A11	
CELL_SPURS_JOB_ERROR_MEMORY_CORRUPTED	0x80410A12	
CELL_SPURS_JOB_ERROR_MEMORY_SIZE	0x80410A17	
CELL_SPURS_JOB_ERROR_UNKNOWN_COMMAND	0x80410A18	
CELL_SPURS_JOB_ERROR_JOBLIST_ALIGNMENT	0x80410A19	
CELL_SPURS_JOB_ERROR_JOB_ALIGNMENT	0x80410A1a	
CELL_SPURS_JOB_ERROR_CALL_OVERFLOW	0x80410A1b	
CELL_SPURS_JOB_ERROR_ABORT	0x80410A1c	
CELL_SPURS_JOB_ERROR_DMALIST_ELEMENT	0x80410A1d	
CELL_SPURS_JOB_ERROR_NUM_CACHE	0x80410A1e	
CELL_SPURS_JOB_ERROR_INVALID_BINARY	0x80410A1f	

SWCACHE errors

Description	Errorcode	Remarks
CELL_SWCACHE_ERROR AGAIN	0x80410b01	
CELL_SWCACHE_ERROR_INVAL	0x80410b02	
CELL_SWCACHE_ERROR_NOSYS	0x80410b03	
CELL_SWCACHE_ERROR_NOMEM	0x80410b04	
CELL_SWCACHE_ERROR_SRCH	0x80410b05	
CELL_SWCACHE_ERROR_NOENT	0x80410b06	
CELL_SWCACHE_ERROR_NOEXEC	0x80410b07	
CELL_SWCACHE_ERROR_DEADLK	0x80410b08	
CELL_SWCACHE_ERROR_PERM	0x80410b09	
CELL_SWCACHE_ERROR_BUSY	0x80410b0A	
CELL_SWCACHE_ERROR_ABORT	0x80410b0C	
CELL_SWCACHE_ERROR_FAULT	0x80410b0D	
CELL_SWCACHE_ERROR_CHILD	0x80410b0E	
CELL_SWCACHE_ERROR_STAT	0x80410b0F	

Description	Errorcode	Remarks
CELL_SWCACHE_ERROR_ALIGN	0x80410b10	
CELL_SWCACHE_ERROR_NULL_POINTER	0x80410b11	
CELL_SWCACHE_ERROR_NON_CACHED_POINTER	0x80410b12	
CELL_SWCACHE_ERROR_NO_HTAB	0x80410b13	
CELL_SWCACHE_ERROR_MEM_LEAKED	0x80410b14	
CELL_SWCACHE_ERROR_VTAB	0x80410b15	

SYNC2 errors

Description	Errorcode	Remarks
CELL_SYNC2_ERROR AGAIN	0x80410C01	
CELL_SYNC2_ERROR_INVAL	0x80410C02	
CELL_SYNC2_ERROR_NOSYS	0x80410C03	
CELL_SYNC2_ERROR_NOMEM	0x80410C04	
CELL_SYNC2_ERROR_SRCH	0x80410C05	
CELL_SYNC2_ERROR_NOENT	0x80410C06	
CELL_SYNC2_ERROR_NOEXEC	0x80410C07	
CELL_SYNC2_ERROR_DEADLK	0x80410C08	
CELL_SYNC2_ERROR_PERM	0x80410C09	
CELL_SYNC2_ERROR_BUSY	0x80410C0A	
CELL_SYNC2_ERROR_ABORT	0x80410C0C	
CELL_SYNC2_ERROR_FAULT	0x80410C0D	
CELL_SYNC2_ERROR_INTR	0x80410C0E	
CELL_SYNC2_ERROR_STAT	0x80410C0F	
CELL_SYNC2_ERROR_ALIGN	0x80410C10	
CELL_SYNC2_ERROR_NULL_POINTER	0x80410C11	
CELL_SYNC2_ERROR_NOT_SUPPORTED_THREAD	0x80410C12	
CELL_SYNC2_ERROR_NO_NOTIFIER	0x80410C13	
CELL_SYNC2_ERROR_NO_SPU_CONTEXT_STORAGE	0x80410C14	

Fiber errors

Description	Errorcode	Remarks
CELL_FIBER_ERROR AGAIN	0x80760001	
CELL_FIBER_ERROR_INVAL	0x80760002	
CELL_FIBER_ERROR_NOSYS	0x80760003	
CELL_FIBER_ERROR_NOMEM	0x80760004	
CELL_FIBER_ERROR_SRCH	0x80760005	
CELL_FIBER_ERROR_NOENT	0x80760006	
CELL_FIBER_ERROR_NOEXEC	0x80760007	
CELL_FIBER_ERROR_DEADLK	0x80760008	
CELL_FIBER_ERROR_PERM	0x80760009	
CELL_FIBER_ERROR_BUSY	0x8076000a	
CELL_FIBER_ERROR_ABORT	0x8076000c	
CELL_FIBER_ERROR_FAULT	0x8076000d	
CELL_FIBER_ERROR_CHILD	0x8076000e	
CELL_FIBER_ERROR_STAT	0x8076000f	
CELL_FIBER_ERROR_ALIGN	0x80760010	
CELL_FIBER_ERROR_NULL_POINTER	0x80760011	
CELL_FIBER_ERROR_NOSYSINIT	0x80760020	

ADEC errors

Description	Errorcode	Remarks
CELL_ADEC_ERROR_FATAL	0x80610001	
CELL_ADEC_ERROR_SEQ	0x80610002	
CELL_ADEC_ERROR_ARG	0x80610003	
CELL_ADEC_ERROR_BUSY	0x80610004	
CELL_ADEC_ERROR_EMPTY	0x80610005	

VDEC errors

Description	Errorcode	Remarks
CELL_VDEC_ERROR_ARG	0x80610101	
CELL_VDEC_ERROR_SEQ	0x80610102	
CELL_VDEC_ERROR_BUSY	0x80610103	
CELL_VDEC_ERROR_EMPTY	0x80610104	
CELL_VDEC_ERROR_AU	0x80610105	
CELL_VDEC_ERROR_PIC	0x80610106	
CELL_VDEC_ERROR_FATAL	0x80610180	Fatal error occurred with the decoder itself CELL_VDEC_ERROR_FATAL indicates that an error having to do with the decoder itself occurred. For example, this error will occur if a data structure inside the decoder required for the decoding process becomes inconsistent due to an unknown reason and decoding cannot be continued. Statuses other than CELL_VDEC_ERROR_FATAL indicate that an unexpected error occurred with the OS or library used inside the decoder. In such cases, too, the decoding process cannot be continued. CELL_OK will never be returned for the status. [1] (http://psx-scene.com/forums/f6/article-%5Bupdate%5D-multiman-v4-65-0-1-base-cex-deanks-showtime-builds-124904/index8.html#post1150131)

DMUX errors

Description	Errorcode	Remarks
CELL_DMUX_ERROR_ARG	0x80610201	
CELL_DMUX_ERROR_SEQ	0x80610202	
CELL_DMUX_ERROR_BUSY	0x80610203	
CELL_DMUX_ERROR_EMPTY	0x80610204	
CELL_DMUX_ERROR_FATAL	0x80610205	

ATRAC errors

Description	Errorcode	Remarks
CELL_ATRAC_ERROR_FACILITY_ATRAC	0x80610300	
CELL_ATRAC_ERROR_API_FAIL	0x80610301	
CELL_ATRAC_ERROR_READSIZE_OVER_BUFFER	0x80610311	
CELL_ATRAC_ERROR_UNKNOWN_FORMAT	0x80610312	
CELL_ATRAC_ERROR_READSIZE_IS_TOO_SMALL	0x80610313	
CELL_ATRAC_ERROR_ILLEGAL_SAMPLING_RATE	0x80610314	
CELL_ATRAC_ERROR_ILLEGAL_DATA	0x80610315	
CELL_ATRAC_ERROR_NO_DECODER	0x80610321	
CELL_ATRAC_ERROR_UNSET_DATA	0x80610322	
CELL_ATRAC_ERROR_DECODER_WAS_CREATED	0x80610323	
CELL_ATRAC_ERROR_ALldata_WAS_DECODED	0x80610331	
CELL_ATRAC_ERROR_NODATA_IN_BUFFER	0x80610332	
CELL_ATRAC_ERROR_NOT_ALIGNED_OUT_BUFFER	0x80610333	
CELL_ATRAC_ERROR_NEED_SECOND_BUFFER	0x80610334	
CELL_ATRAC_ERROR_ALldata_IS_ONMEMORY	0x80610341	
CELL_ATRAC_ERROR_ADD_DATA_IS_TOO_BIG	0x80610342	
CELL_ATRAC_ERROR_NONEED_SECOND_BUFFER	0x80610351	
CELL_ATRAC_ERROR_UNSET_LOOP_NUM	0x80610361	
CELL_ATRAC_ERROR_ILLEGAL_SAMPLE	0x80610371	
CELL_ATRAC_ERROR_ILLEGAL_RESET_BYTE	0x80610372	
CELL_ATRAC_ERROR_ILLEGAL_PPU_THREAD_PRIORITY	0x80610381	
CELL_ATRAC_ERROR_ILLEGAL_SPU_THREAD_PRIORITY	0x80610382	

PAMF errors

Description	Errorcode	Remarks
CELL_PAMF_ERROR_STREAM_NOT_FOUND	0x80610501	
CELL_PAMF_ERROR_INVALID_PAMF	0x80610502	
CELL_PAMF_ERROR_INVALID_ARG	0x80610503	
CELL_PAMF_ERROR_UNKNOWN_TYPE	0x80610504	
CELL_PAMF_ERROR_UNSUPPORTED_VERSION	0x80610505	
CELL_PAMF_ERROR_UNKNOWN_STREAM	0x80610506	
CELL_PAMF_ERROR_EP_NOT_FOUND	0x80610507	

Description	Errorcode	Remarks
CELL_PAMF_ERROR_NOT_AVAILABLE	0x80610508	

VPOST errors

VPOST Library (PPM) errors

Description	Errorcode	Remarks
for cellVpostQueryAttr()		
CELL_VPOST_ERROR_Q_ARG_CFG_NULL	0x80610410	
CELL_VPOST_ERROR_Q_ARG_CFG_INVALID	0x80610411	
CELL_VPOST_ERROR_Q_ARG_ATTR_NULL	0x80610412	
for cellVpostOpen()		
CELL_VPOST_ERROR_O_ARG_CFG_NULL	0x80610440	
CELL_VPOST_ERROR_O_ARG_CFG_INVALID	0x80610441	
CELL_VPOST_ERROR_O_ARG_RSRC_NULL	0x80610442	
CELL_VPOST_ERROR_O_ARG_RSRC_INVALID	0x80610443	
CELL_VPOST_ERROR_O_ARG_HDL_NULL	0x80610444	
CELL_VPOST_ERROR_O_FATAL_QUERY_FAIL	0x80610460	
CELL_VPOST_ERROR_O_FATAL_CREATEMON_FAIL	0x80610461	
CELL_VPOST_ERROR_O_FATAL_INITSPURS_FAIL	0x80610462	
for cellVpostClose()		
CELL_VPOST_ERROR_C_ARG_HDL_NULL	0x80610470	
CELL_VPOST_ERROR_C_ARG_HDL_INVALID	0x80610471	
CELL_VPOST_ERROR_C_FATAL_LOCKMON_FAIL	0x80610490	
CELL_VPOST_ERROR_C_FATAL_UNLOCKMON_FAIL	0x80610491	
CELL_VPOST_ERROR_C_FATAL_DESTROYSMON_FAIL	0x80610492	
CELL_VPOST_ERROR_C_FATAL_FINSPURS_FAIL	0x80610463	
for cellVpostExec()		
CELL_VPOST_ERROR_E_ARG_HDL_NULL	0x806104a0	
CELL_VPOST_ERROR_E_ARG_HDL_INVALID	0x806104a1	
CELL_VPOST_ERROR_E_ARG_INPICBUF_NULL	0x806104a2	
CELL_VPOST_ERROR_E_ARG_INPICBUF_INVALID	0x806104a3	
CELL_VPOST_ERROR_E_ARG_CTRL_NULL	0x806104a4	
CELL_VPOST_ERROR_E_ARG_CTRL_INVALID	0x806104a5	
CELL_VPOST_ERROR_E_ARG_OUTPICBUF_NULL	0x806104a6	
CELL_VPOST_ERROR_E_ARG_OUTPICBUF_INVALID	0x806104a7	
CELL_VPOST_ERROR_E_ARG_PICINFO_NULL	0x806104a8	
CELL_VPOST_ERROR_E_FATAL_LOCKMON_FAIL	0x806104c0	
CELL_VPOST_ERROR_E_FATAL_UNLOCKMON_FAIL	0x806104c1	

VPOST Library (Entry Module) errors

Description	Errorcode	Remarks
for cellVpostEntQueryAttr()		
CELL_VPOST_ENT_ERROR_Q_ARG_ATTR_NULL	0x80618110	
for cellVpostEntOpen()		
CELL_VPOST_ENT_ERROR_O_ARG_RSRC_NULL	0x80618140	
CELL_VPOST_ENT_ERROR_O_ARG_RSRC_INVALID	0x80618141	
CELL_VPOST_ENT_ERROR_O_ARG_HDL_NULL	0x80618142	
CELL_VPOST_ENT_ERROR_O_FATAL_QUERY_FAIL	0x80618160	
CELL_VPOST_ENT_ERROR_O_FATAL_CSPUCORE_FAIL	0x80618161	
for cellVpostEntClose()		
CELL_VPOST_ENT_ERROR_C_ARG_HDL_NULL	0x80618170	
CELL_VPOST_ENT_ERROR_C_ARG_HDL_INVALID	0x80618171	
CELL_VPOST_ENT_ERROR_C_FATAL_SNDCMD_FAIL	0x80618190	
CELL_VPOST_ENT_ERROR_C_FATAL_RCVRES_FAIL	0x80618191	
CELL_VPOST_ENT_ERROR_C_FATAL_DSPUCORE_FAIL	0x80618192	
for cellVpostEntExec()		

Description	Errorcode	Remarks
for cellVpostEntQueryAttr()		
CELL_VPOST_ENT_ERROR_E_ARG_HDL_NULL	0x806181a0	
CELL_VPOST_ENT_ERROR_E_ARG_HDL_INVALID	0x806181a1	
CELL_VPOST_ENT_ERROR_E_ARG_INPICBUF_NULL	0x806181a2	
CELL_VPOST_ENT_ERROR_E_ARG_INPICBUF_INVALID	0x806181a3	
CELL_VPOST_ENT_ERROR_E_ARG_INPICINFO_NULL	0x806181a4	
CELL_VPOST_ENT_ERROR_E_ARG_INPICINFO_INVALID	0x806181a5	
CELL_VPOST_ENT_ERROR_E_ARG_CTRL_NULL	0x806181a6	
CELL_VPOST_ENT_ERROR_E_ARG_CTRL_INVALID	0x806181a7	
CELL_VPOST_ENT_ERROR_E_ARG_COMB_INVALID	0x806181a8	
CELL_VPOST_ENT_ERROR_E_ARG_OUTPICBUF_NULL	0x806181a9	
CELL_VPOST_ENT_ERROR_E_ARG_OUTPICBUF_INVALID	0x806181aa	
CELL_VPOST_ENT_ERROR_E_ARG_OUTPICINFO_NULL	0x806181ab	
CELL_VPOST_ENT_ERROR_E_FATAL_SNDCMD_FAIL	0x806181c0	
CELL_VPOST_ENT_ERROR_E_FATAL_RCVRES_FAIL	0x806181c1	
CELL_VPOST_ENT_ERROR_E_FATAL_SPUCORE_FAIL	0x806181c2	

VPOST Library (IPC) errors

Description	Errorcode	Remarks
for cellVpostIpcQueryAttr()		
CELL_VPOST_IPC_ERROR_Q_ARG_ATTR_NULL	0x80618210	
for cellVpostIpcOpen()		
CELL_VPOST_IPC_ERROR_O_ARG_RSRC_NULL	0x80618240	
CELL_VPOST_IPC_ERROR_O_ARG_RSRC_INVALID	0x80618241	
CELL_VPOST_IPC_ERROR_O_ARG_HDL_NULL	0x80618242	
CELL_VPOST_IPC_ERROR_O_FATAL_QUERY_FAIL	0x80618260	
CELL_VPOST_IPC_ERROR_O_FATAL_CSPUCORE_FAIL	0x80618261	
for cellVpostIpcClose()		
CELL_VPOST_IPC_ERROR_C_ARG_HDL_NULL	0x80618270	
CELL_VPOST_IPC_ERROR_C_ARG_HDL_INVALID	0x80618271	
CELL_VPOST_IPC_ERROR_C_FATAL_SNDCMD_FAIL	0x80618290	
CELL_VPOST_IPC_ERROR_C_FATAL_RCVRES_FAIL	0x80618291	
CELL_VPOST_IPC_ERROR_C_FATAL_DSPUCORE_FAIL	0x80618292	
for cellVpostIpcExec()		
CELL_VPOST_IPC_ERROR_E_ARG_HDL_NULL	0x806182a0	
CELL_VPOST_IPC_ERROR_E_ARG_HDL_INVALID	0x806182a1	
CELL_VPOST_IPC_ERROR_E_ARG_INPICBUF_NULL	0x806182a2	
CELL_VPOST_IPC_ERROR_E_ARG_INPICBUF_INVALID	0x806182a3	
CELL_VPOST_IPC_ERROR_E_ARG_INPICINFO_NULL	0x806182a4	
CELL_VPOST_IPC_ERROR_E_ARG_INPICINFO_INVALID	0x806182a5	
CELL_VPOST_IPC_ERROR_E_ARG_CTRL_NULL	0x806182a6	
CELL_VPOST_IPC_ERROR_E_ARG_CTRL_INVALID	0x806182a7	
CELL_VPOST_IPC_ERROR_E_ARG_COMB_INVALID	0x806182a8	
CELL_VPOST_IPC_ERROR_E_ARG_OUTPICBUF_NULL	0x806182a9	
CELL_VPOST_IPC_ERROR_E_ARG_OUTPICBUF_INVALID	0x806182aa	
CELL_VPOST_IPC_ERROR_E_ARG_OUTPICINFO_NULL	0x806182ab	
CELL_VPOST_IPC_ERROR_E_FATAL_SNDCMD_FAIL	0x806182c0	
CELL_VPOST_IPC_ERROR_E_FATAL_RCVRES_FAIL	0x806182c1	
CELL_VPOST_IPC_ERROR_E_FATAL_SPUCORE_FAIL	0x806182c2	

VPOST Library (Video Scaler) errors

Description	Errorcode	Remarks
for cellVpostVscQueryAttr()		
CELL_VPOST_VSC_ERROR_Q_ARG_ATTR_NULL	0x80618310	
for cellVpostVscOpen()		
CELL_VPOST_VSC_ERROR_O_ARG_RSRC_NULL	0x80618340	

Description	Errorcode	Remarks
for cellVpostVscQueryAttr()		
CELL_VPOST_VSC_ERROR_O_ARG_RSRC_INVALID	0x80618341	
CELL_VPOST_VSC_ERROR_O_ARG_HDL_NULL	0x80618342	
CELL_VPOST_VSC_ERROR_O_FATAL_QUERY_FAIL	0x80618360	
CELL_VPOST_VSC_ERROR_O_FATAL_CSPUCORE_FAIL	0x80618361	
for cellVpostVscClose()		
CELL_VPOST_VSC_ERROR_C_ARG_HDL_NULL	0x80618370	
CELL_VPOST_VSC_ERROR_C_ARG_HDL_INVALID	0x80618371	
CELL_VPOST_VSC_ERROR_C_FATAL_SNDCMD_FAIL	0x80618390	
CELL_VPOST_VSC_ERROR_C_FATAL_RCVRES_FAIL	0x80618391	
CELL_VPOST_VSC_ERROR_C_FATAL_DSPUCORE_FAIL	0x80618392	
for cellVpostVscExec()		
CELL_VPOST_VSC_ERROR_E_ARG_HDL_NULL	0x806183a0	
CELL_VPOST_VSC_ERROR_E_ARG_HDL_INVALID	0x806183a1	
CELL_VPOST_VSC_ERROR_E_ARG_INPICBUF_NULL	0x806183a2	
CELL_VPOST_VSC_ERROR_E_ARG_INPICBUF_INVALID	0x806183a3	
CELL_VPOST_VSC_ERROR_E_ARG_INPICINFO_NULL	0x806183a4	
CELL_VPOST_VSC_ERROR_E_ARG_INPICINFO_INVALID	0x806183a5	
CELL_VPOST_VSC_ERROR_E_ARG_CTRL_NULL	0x806183a6	
CELL_VPOST_VSC_ERROR_E_ARG_CTRL_INVALID	0x806183a7	
CELL_VPOST_VSC_ERROR_E_ARG_COMB_INVALID	0x806183a8	
CELL_VPOST_VSC_ERROR_E_ARG_OUTPICBUF_NULL	0x806183a9	
CELL_VPOST_VSC_ERROR_E_ARG_OUTPICBUF_INVALID	0x806183aa	
CELL_VPOST_VSC_ERROR_E_ARG_OUTPICINFO_NULL	0x806183ab	
CELL_VPOST_VSC_ERROR_E_FATAL_SNDCMD_FAIL	0x806183c0	
CELL_VPOST_VSC_ERROR_E_FATAL_RCVRES_FAIL	0x806183c1	
CELL_VPOST_VSC_ERROR_E_FATAL_SPUCORE_FAIL	0x806183c2	

VPOST Library (CSC) errors

Description	Errorcode	Remarks
for cellVpostCscQueryAttr()		
CELL_VPOST_CSC_ERROR_Q_ARG_ATTR_NULL	0x80618410	
for cellVpostCscOpen()		
CELL_VPOST_CSC_ERROR_O_ARG_RSRC_NULL	0x80618440	
CELL_VPOST_CSC_ERROR_O_ARG_RSRC_INVALID	0x80618441	
CELL_VPOST_CSC_ERROR_O_ARG_HDL_NULL	0x80618442	
CELL_VPOST_CSC_ERROR_O_FATAL_QUERY_FAIL	0x80618460	
CELL_VPOST_CSC_ERROR_O_FATAL_CSPUCORE_FAIL	0x80618461	
for cellVpostCscClose()		
CELL_VPOST_CSC_ERROR_C_ARG_HDL_NULL	0x80618470	
CELL_VPOST_CSC_ERROR_C_ARG_HDL_INVALID	0x80618471	
CELL_VPOST_CSC_ERROR_C_FATAL_SNDCMD_FAIL	0x80618490	
CELL_VPOST_CSC_ERROR_C_FATAL_RCVRES_FAIL	0x80618491	
CELL_VPOST_CSC_ERROR_C_FATAL_DSPUCORE_FAIL	0x80618492	
for cellVpostCscExec()		
CELL_VPOST_CSC_ERROR_E_ARG_HDL_NULL	0x806184a0	
CELL_VPOST_CSC_ERROR_E_ARG_HDL_INVALID	0x806184a1	
CELL_VPOST_CSC_ERROR_E_ARG_INPICBUF_NULL	0x806184a2	
CELL_VPOST_CSC_ERROR_E_ARG_INPICBUF_INVALID	0x806184a3	
CELL_VPOST_CSC_ERROR_E_ARG_INPICINFO_NULL	0x806184a4	
CELL_VPOST_CSC_ERROR_E_ARG_INPICINFO_INVALID	0x806184a5	
CELL_VPOST_CSC_ERROR_E_ARG_CTRL_NULL	0x806184a6	
CELL_VPOST_CSC_ERROR_E_ARG_CTRL_INVALID	0x806184a7	
CELL_VPOST_CSC_ERROR_E_ARG_COMB_INVALID	0x806184a8	
CELL_VPOST_CSC_ERROR_E_ARG_OUTPICBUF_NULL	0x806184a9	
CELL_VPOST_CSC_ERROR_E_ARG_OUTPICBUF_INVALID	0x806184aa	
CELL_VPOST_CSC_ERROR_E_ARG_OUTPICINFO_NULL	0x806184ab	

Description	Errorcode	Remarks
for cellVpostCscQueryAttr()		
CELL_VPOST_CSC_ERROR_E_FATAL_SNDCMD_FAIL	0x806184c0	
CELL_VPOST_CSC_ERROR_E_FATAL_RCVRES_FAIL	0x806184c1	
CELL_VPOST_CSC_ERROR_E_FATAL_SPUCORE_FAIL	0x806184c2	

SAIL errors

Description	Errorcode	Remarks
CELL_SAIL_ERROR_INVALID_ARG	0x80610701	
CELL_SAIL_ERROR_INVALID_STATE	0x80610702	
CELL_SAIL_ERROR_UNSUPPORTED_STREAM	0x80610703	
CELL_SAIL_ERROR_INDEX_OUT_OF_RANGE	0x80610704	
CELL_SAIL_ERROR_EMPTY	0x80610705	
CELL_SAIL_ERROR_FULLED	0x80610706	
CELL_SAIL_ERROR_USING	0x80610707	
CELL_SAIL_ERROR_NOT_AVAILABLE	0x80610708	
CELL_SAIL_ERROR_CANCEL	0x80610709	
CELL_SAIL_ERROR_MEMORY	(0x806107F0	
CELL_SAIL_ERROR_INVALID_FD	0x806107F1	
CELL_SAIL_ERROR_FATAL	0x806107FF	

ATRACMULTI errors

Description	Errorcode	Remarks
CELL_ATRACMULTI_ERRORFacility_ATRAC	0x80610b00	
CELL_ATRACMULTI_ERRORAPI_FAIL	0x80610b01	
CELL_ATRACMULTI_ERRORREADSIZE_OVER_BUFFER	0x80610b11	
CELL_ATRACMULTI_ERRORUNKNOWN_FORMAT	0x80610b12	
CELL_ATRACMULTI_ERRORREADSIZE_IS_TOO_SMALL	0x80610b13	
CELL_ATRACMULTI_ERRORILLEGAL_SAMPLING_RATE	0x80610b14	
CELL_ATRACMULTI_ERRORILLEGAL_DATA	0x80610b15	
CELL_ATRACMULTI_ERRORNO_DECODER	0x80610b21	
CELL_ATRACMULTI_ERRORUNSET_DATA	0x80610b22	
CELL_ATRACMULTI_ERRORDECODER_WAS_CREATED	0x80610b23	
CELL_ATRACMULTI_ERRORALLDATA_WAS_DECODED	0x80610b31	
CELL_ATRACMULTI_ERRORNODATA_IN_BUFFER	0x80610b32	
CELL_ATRACMULTI_ERRORNOT_ALIGNED_OUT_BUFFER	0x80610b33	
CELL_ATRACMULTI_ERRORNEED_SECOND_BUFFER	0x80610b34	
CELL_ATRACMULTI_ERRORALLDATA_IS_ONMEMORY	0x80610b41	
CELL_ATRACMULTI_ERRORADD_DATA_IS_TOO_BIG	0x80610b42	
CELL_ATRACMULTI_ERRORNONEED_SECOND_BUFFER	0x80610b51	
CELL_ATRACMULTI_ERRORUNSET_LOOP_NUM	0x80610b61	
CELL_ATRACMULTI_ERRORILLEGAL_SAMPLE	0x80610b71	
CELL_ATRACMULTI_ERRORILLEGAL_RESET_BYTE	0x80610b72	
CELL_ATRACMULTI_ERRORILLEGAL_PPU_THREAD_PRIORITY	0x80610b81	
CELL_ATRACMULTI_ERRORILLEGAL_SPU_THREAD_PRIORITY	0x80610b82	
CELL_ATRACMULTI_ERRORAPI_PARAMETER	0x80610b91	

LPCM errors

Description	Errorcode	Remarks
CELL_ADEC_ERROR_LPCM_FATAL	0x80612001	
CELL_ADEC_ERROR_LPCM_SEQ	0x80612002	
CELL_ADEC_ERROR_LPCM_ARG	0x80612003	
CELL_ADEC_ERROR_LPCM_BUSY	0x80612004	
CELL_ADEC_ERROR_LPCM_EMPTY	0x80612005	

AT3 errors

Description	Errorcode	Remarks
CELL_ADEC_ERROR_AT3_OFFSET	0x80612100	
CELL_ADEC_ERROR_AT3_OK	0x80612100	
CELL_ADEC_ERROR_AT3_BUSY	0x80612164	
CELL_ADEC_ERROR_AT3_EMPTY	0x80612165	
CELL_ADEC_ERROR_AT3_ERROR	0x80612180	

ATX errors

Description	Errorcode	Remarks
CELL_ADEC_ERROR_ATX_OK	0x80612200	
CELL_ADEC_ERROR_ATX_BUSY	0x80612264	
CELL_ADEC_ERROR_ATX_EMPTY	0x80612265	
CELL_ADEC_ERROR_ATX_ATSHDR	0x80612266	
CELL_ADEC_ERROR_ATX_NON_FATAL	0x80612281	undefined error
CELL_ADEC_ERROR_ATX_NOT_IMPLE	0x80612282	not implemented
CELL_ADEC_ERROR_ATX_PACK_CE_OVERFLOW	0x80612283	pack_channel_block_at5() in pack_at5.c
CELL_ADEC_ERROR_ATX_ILLEGAL_NPROCQUS	0x80612284	unpack_sheader() in pack_at5_header.c
CELL_ADEC_ERROR_ATX_FATAL	0x8061228c	undefined error
CELL_ADEC_ERROR_ATX_ENC_OVERFLOW	0x8061228d	at5enc_proc() in at5enc.c
CELL_ADEC_ERROR_ATX_PACK_CE_UNDERFLOW	0x8061228e	pack_channel_block_at5() in pack_at5.c
CELL_ADEC_ERROR_ATX_SYNTAX_IDCT	0x8061228f	unpack_idct() in pack_at5_codetbl.c
CELL_ADEC_ERROR_ATX_SYNTAX_GAINADJ	0x80612290	unpack_gainadj() in pack_at5_gainadj.c
CELL_ADEC_ERROR_ATX_SYNTAX_IDSF	0x80612291	unpack_idsf() in pack_at5_sfactor.c
CELL_ADEC_ERROR_ATX_SYNTAX_SPECTRA	0x80612292	unpack_spectra() in pack_at5_spectra.c
CELL_ADEC_ERROR_ATX_SYNTAX_IDWL	0x80612293	unpack_idwl() in pack_at5_idwl.c
CELL_ADEC_ERROR_ATX_SYNTAX_GHWAWE	0x80612294	unpack_ghwave() in pack_at5_ghwave.c
CELL_ADEC_ERROR_ATX_SYNTAX_SHEADER	0x80612295	unpack_sheader() in pack_at5_header.c
CELL_ADEC_ERROR_ATX_SYNTAX_IDWL_A	0x80612296	idwl[0][0-7] range error*/
CELL_ADEC_ERROR_ATX_SYNTAX_IDWL_B	0x80612297	idwl restriction error (wlc_encqu<=divqu<=nprocqus,ich=0)
CELL_ADEC_ERROR_ATX_SYNTAX_IDWL_C	0x80612298	idwl restriction error (0<=wlc_divqu<=wlc_encqu,ich=0)
CELL_ADEC_ERROR_ATX_SYNTAX_IDWL_D	0x80612299	idwl restriction error (wlc_encqu<divqu<=nprocqus,ich=1)
CELL_ADEC_ERROR_ATX_SYNTAX_IDWL_E	0x8061229a	idwl restriction error (wlc_encqu<=nprocqus)
CELL_ADEC_ERROR_ATX_SYNTAX_IDSF_A	0x8061229b	idsf[0][0-63] range error
CELL_ADEC_ERROR_ATX_SYNTAX_IDSF_B	0x8061229c	sfc_nbitten[0-6] range error
CELL_ADEC_ERROR_ATX_SYNTAX_IDSF_C	0x8061229d	idsf restriction error (0<=sfc_divqu<=nrealqus)
CELL_ADEC_ERROR_ATX_SYNTAX_IDSF_D	0x8061229e	idsf restriction error (0<=sfc_sg_divqu<=nrealqus)
CELL_ADEC_ERROR_ATX_SYNTAX_IDCT_A	0x8061229f	idct restriction error (0<=ctc_divqu<=nrealqus)
CELL_ADEC_ERROR_ATX_SYNTAX_GC_NGC	0x806122a0	ngc[0][0-7] range error
CELL_ADEC_ERROR_ATX_SYNTAX_GC_IDLEV_A	0x806122a1	idlev[0][0-15] range error
CELL_ADEC_ERROR_ATX_SYNTAX_GC_IDLOC_A	0x806122a2	idloc[0][0-31] range error
CELL_ADEC_ERROR_ATX_SYNTAX_GC_IDLEV_B	0x806122a3	gain_control_data restriction error (idlev[0][0])
CELL_ADEC_ERROR_ATX_SYNTAX_GC_IDLOC_B	0x806122a4	gain_control_data restriction error (idloc[0][0])
CELL_ADEC_ERROR_ATX_SYNTAX_SN_NWVS	0x806122a5	sinusoid_data restriction error
CELL_ADEC_ERROR_ATX_FATAL_HANDLE	0x806122aa	undefined error at handle level
CELL_ADEC_ERROR_ATX_ASSERT_SAMPLING_FREQ	0x806122ab	sampling frequency assertion error
CELL_ADEC_ERROR_ATX_ASSERT_CH_CONFIG_INDEX	0x806122ac	channel_config_index assertion error
CELL_ADEC_ERROR_ATX_ASSERT_NBYTES	0x806122ad	a number of bytes(nbytes) assertion error
CELL_ADEC_ERROR_ATX_ASSERT_BLOCK_NUM	0x806122ae	a number of blocks(block_num) assertion error
CELL_ADEC_ERROR_ATX_ASSERT_BLOCK_ID	0x806122af	block_id assertion error
CELL_ADEC_ERROR_ATX_ASSERT_CHANNELS	0x806122b0	a number of channels per block assertion error
CELL_ADEC_ERROR_ATX_UNINIT_BLOCK_SPECIFIED	0x806122b1	uninitialized block specified
CELL_ADEC_ERROR_ATX_POSCFG_PRESENT	0x806122b2	"position_config_data" presents(currently fatal error)
CELL_ADEC_ERROR_ATX_BUFFER_OVERFLOW	0x806122b3	buffer overflow
CELL_ADEC_ERROR_ATX_ILL_BLK_TYPE_ID	0x806122b4	illegal "block_type_id" detected
CELL_ADEC_ERROR_ATX_UNPACK_CHANNEL_BLK_FAILED	0x806122b5	unpack_channel_block() failed
CELL_ADEC_ERROR_ATX_ILL_BLK_ID_USED_1	0x806122b6	illegal "block_id" used (more audio_channel_block)
CELL_ADEC_ERROR_ATX_ILL_BLK_ID_USED_2	0x806122b7	illegal "block_id" used (less audio_channel_block)
CELL_ADEC_ERROR_ATX_ILLEGAL_ENC_SETTING	0x806122b8	illegal encoder setting(init_atrac5_encode())

Description	Errorcode	Remarks
CELL_ADEC_ERROR_ATX_ILLEGAL_DEC_SETTING	0x806122b9	illegal decoder setting(init_atrac5_decode())
CELL_ADEC_ERROR_ATX_ASSERT_NSAMPLES	0x806122ba	a number of input PCM samples assertion error
CELL_ADEC_ERROR_ATX_ILL_SYNCWORD	0x806122bb	illegal syncword used
CELL_ADEC_ERROR_ATX_ILL_SAMPLING_FREQ	0x806122bc	illegal sampling_frequency_index @ config_data()
CELL_ADEC_ERROR_ATX_ILL_CH_CONFIG_INDEX	0x806122bd	illegal channel_config_index@ config_data()
CELL_ADEC_ERROR_ATX_RAW_DATA_FRAME_SIZE_OVER	0x806122be	size of raw_data_frame > frame_length
CELL_ADEC_ERROR_ATX_SYNTAX_ENHANCE_LENGTH_OVER	0x806122bf	enhance_length {0,2046} range error
CELL_ADEC_ERROR_ATX_SPU_INTERNAL_FAIL	0x806122c8	spu-processing failed

M4AAC errors

Description	Errorcode	Remarks
CELL_ADEC_ERROR_M4AAC_FATAL	0x80612401	
CELL_ADEC_ERROR_M4AAC_SEQ	0x80612402	
CELL_ADEC_ERROR_M4AAC_ARG	0x80612403	
CELL_ADEC_ERROR_M4AAC_BUSY	0x80612404	
CELL_ADEC_ERROR_M4AAC_EMPTY	0x80612405	
CELL_ADEC_ERROR_M4AAC_BUFFER_OVERFLOW	0x80612406	
CELL_ADEC_ERROR_M4AAC_END_OF_BITSTREAM	0x80612407	
CELL_ADEC_ERROR_M4AAC_CH_CONFIG_INCONSISTENCY	0x80612410	
CELL_ADEC_ERROR_M4AAC_NO_CH_DEFAULT_POS	0x80612411	
CELL_ADEC_ERROR_M4AAC_INVALID_CH_POS	0x80612412	
CELL_ADEC_ERROR_M4AAC_UNANTICIPATED_COUPLING_CH	0x80612413	
CELL_ADEC_ERROR_M4AAC_INVALID_LAYER_ID	0x80612414	
CELL_ADEC_ERROR_M4AAC_ADTS_SYNCWORD_ERROR	0x80612415	
CELL_ADEC_ERROR_M4AAC_INVALID_ADTS_ID	0x80612416	
CELL_ADEC_ERROR_M4AAC_CH_CHANGED	0x80612417	
CELL_ADEC_ERROR_M4AAC_SAMPLING_FREQ_CHANGED	0x80612418	
CELL_ADEC_ERROR_M4AAC_WRONG_SBR_CH	0x80612419	
CELL_ADEC_ERROR_M4AAC_WRONG_SCALE_FACTOR	0x8061241a	
CELL_ADEC_ERROR_M4AAC_INVALID_BOOKS	0x8061241b	
CELL_ADEC_ERROR_M4AAC_INVALID_SECTION_DATA	0x8061241c	
CELL_ADEC_ERROR_M4AAC_PULSE_IS_NOT_LONG	0x8061241d	
CELL_ADEC_ERROR_M4AAC_GC_IS_NOT_SUPPORTED	0x8061241e	
CELL_ADEC_ERROR_M4AAC_INVALID_ELEMENT_ID	0x8061241f	
CELL_ADEC_ERROR_M4AAC_NO_CH_CONFIG	0x80612420	
CELL_ADEC_ERROR_M4AAC_UNEXPECTED_OVERLAP_CRC	0x80612421	
CELL_ADEC_ERROR_M4AAC_CRC_BUFFER_EXCEEDED	0x80612422	
CELL_ADEC_ERROR_M4AAC_INVALID_CRC	0x80612423	
CELL_ADEC_ERROR_M4AAC_BAD_WINDOW_CODE	0x80612424	
CELL_ADEC_ERROR_M4AAC_INVALID_ADIF_HEADER_ID	0x80612425	
CELL_ADEC_ERROR_M4AAC_NOT_SUPPORTED_PROFILE	0x80612426	
CELL_ADEC_ERROR_M4AAC_PROG_NUMBER_NOT_FOUND	0x80612427	
CELL_ADEC_ERROR_M4AAC_INVALID_SAMP_RATE_INDEX	0x80612428	
CELL_ADEC_ERROR_M4AAC_UNANTICIPATED_CH_CONFIG	0x80612429	
CELL_ADEC_ERROR_M4AAC_PULSE_OVERFLOWED	0x8061242a	
CELL_ADEC_ERROR_M4AAC_CAN_NOT_UNPACK_INDEX	0x8061242b	
CELL_ADEC_ERROR_M4AAC_DEINTERLEAVE_FAILED	0x8061242c	
CELL_ADEC_ERROR_M4AAC_CALC_BAND_OFFSET_FAILED	0x8061242d	
CELL_ADEC_ERROR_M4AAC_GET_SCALE_FACTOR_FAILED	0x8061242e	
CELL_ADEC_ERROR_M4AAC_GET_CC_GAIN_FAILED	0x8061242f	
CELL_ADEC_ERROR_M4AAC_MIX_COUPLING_CH_FAILED	0x80612430	
CELL_ADEC_ERROR_M4AAC_GROUP_IS_INVALID	0x80612431	
CELL_ADEC_ERROR_M4AAC_PREDICT_FAILED	0x80612432	
CELL_ADEC_ERROR_M4AAC_INVALID_PREDICT_RESET_PATTERN	0x80612433	
CELL_ADEC_ERROR_M4AAC_INVALID_TNS_FRAME_INFO	0x80612434	
CELL_ADEC_ERROR_M4AAC_GET_MASK_FAILED	0x80612435	
CELL_ADEC_ERROR_M4AAC_GET_GROUP_FAILED	0x80612436	

Description	Errorcode	Remarks
CELL_ADEC_ERROR_M4AAC_GET_LPFLAG_FAILED	0x80612437	
CELL_ADEC_ERROR_M4AAC_INVERSE_QUANTIZATION_FAILED	0x80612438	
CELL_ADEC_ERROR_M4AAC_GET_CB_MAP_FAILED	0x80612439	
CELL_ADEC_ERROR_M4AAC_GET_PULSE_FAILED	0x8061243a	
CELL_ADEC_ERROR_M4AAC_MONO_MIXDOWN_ELEMENT_IS_NOT_SUPPORTED	0x8061243b	
CELL_ADEC_ERROR_M4AAC_STEREO_MIXDOWN_ELEMENT_IS_NOT_SUPPORTED	0x8061243c	
CELL_ADEC_ERROR_M4AAC_SBR_CH_OVERFLOW	0x80612480	
CELL_ADEC_ERROR_M4AAC_SBR_NOSYNCH	0x80612481	
CELL_ADEC_ERROR_M4AAC_SBR_ILLEGAL_PROGRAM	0x80612482	
CELL_ADEC_ERROR_M4AAC_SBR_ILLEGAL_TAG	0x80612483	
CELL_ADEC_ERROR_M4AAC_SBR_ILLEGAL_CHN_CONFIG	0x80612484	
CELL_ADEC_ERROR_M4AAC_SBR_ILLEGAL_SECTION	0x80612485	
CELL_ADEC_ERROR_M4AAC_SBR_ILLEGAL_SCFACTORS	0x80612486	
CELL_ADEC_ERROR_M4AAC_SBR_ILLEGAL_PULSE_DATA	0x80612487	
CELL_ADEC_ERROR_M4AAC_SBR_MAIN_PROFILE_NOT_IMPLEMENTED	0x80612488	
CELL_ADEC_ERROR_M4AAC_SBR_GC_NOT_IMPLEMENTED	0x80612489	
CELL_ADEC_ERROR_M4AAC_SBR_ILLEGAL_PLUS_ELE_ID	0x8061248a	
CELL_ADEC_ERROR_M4AAC_SBR_CREATE_ERROR	0x8061248b	
CELL_ADEC_ERROR_M4AAC_SBR_NOT_INITIALIZED	0x8061248c	
CELL_ADEC_ERROR_M4AAC_SBR_INVALID_ENVELOPE	0x8061248d	

AC3 errors

Description	Errorcode	Remarks
CELL_ADEC_ERROR_AC3_BUSY	0x80612500	
CELL_ADEC_ERROR_AC3_EMPTY	0x80612501	
CELL_ADEC_ERROR_AC3_PARAM	0x80612502	
CELL_ADEC_ERROR_AC3_FRAME	0x80612503	

MP3 errors

Description	Errorcode	Remarks
CELL_ADEC_ERROR_MP3_OK	0x80612700	
CELL_ADEC_ERROR_MP3_BUSY	0x80612764	
CELL_ADEC_ERROR_MP3_EMPTY	0x80612765	
CELL_ADEC_ERROR_MP3_ERROR	0x80612781	
CELL_ADEC_ERROR_MP3_LOST_SYNC	0x80612782	
CELL_ADEC_ERROR_MP3_NOT_L3	0x80612783	
CELL_ADEC_ERROR_MP3_BAD_BITRATE	0x80612784	
CELL_ADEC_ERROR_MP3_BAD_SFREQ	0x80612785	
CELL_ADEC_ERROR_MP3_BAD_EMPHASIS	0x80612786	
CELL_ADEC_ERROR_MP3_BAD_BLKTYPE	0x80612787	
CELL_ADEC_ERROR_MP3_BAD_VERSION	0x8061278c	
CELL_ADEC_ERROR_MP3_BAD_MODE	0x8061278d	
CELL_ADEC_ERROR_MP3_BAD_MODE_EXT	0x8061278e	
CELL_ADEC_ERROR_MP3_HUFFMAN_NUM	0x80612796	
CELL_ADEC_ERROR_MP3_HUFFMAN_CASE_ID	0x80612797	
CELL_ADEC_ERROR_MP3_SCALEFAC_COMPRESS	0x80612798	
CELL_ADEC_ERROR_MP3_HGETBIT	0x80612799	
CELL_ADEC_ERROR_MP3_FLOATING_EXCEPTION	0x8061279a	
CELL_ADEC_ERROR_MP3_ARRAY_OVERFLOW	0x8061279b	
CELL_ADEC_ERROR_MP3_STEREO_PROCESSING	0x8061279c	
CELL_ADEC_ERROR_MP3_JS_BOUND	0x8061279d	
CELL_ADEC_ERROR_MP3_PCMOUT	0x8061279e	

M2BC errors

Description	Errorcode	Remarks
CELL_ADEC_ERROR_M2BC_FATAL	0x80612b01	

Description	Errorcode	Remarks
CELL_ADEC_ERROR_M2BC_SEQ	0x80612b02	
CELL_ADEC_ERROR_M2BC_ARG	0x80612b03	
CELL_ADEC_ERROR_M2BC_BUSY	0x80612b04	
CELL_ADEC_ERROR_M2BC_EMPTY	0x80612b05	
CELL_ADEC_ERROR_M2BC_SYNCNF	0x80612b11	
CELL_ADEC_ERROR_M2BC_LAYER	0x80612b12	
CELL_ADEC_ERROR_M2BC_BITRATE	0x80612b13	
CELL_ADEC_ERROR_M2BC_SAMPLEFREQ	0x80612b14	
CELL_ADEC_ERROR_M2BC_VERSION	0x80612b15	
CELL_ADEC_ERROR_M2BC_MODE_EXT	0x80612b16	
CELL_ADEC_ERROR_M2BC_UNSUPPORT	0x80612b17	
CELL_ADEC_ERROR_M2BC_OPENBS_EX	0x80612b21	
CELL_ADEC_ERROR_M2BC_SYNCNF_EX	0x80612b22	
CELL_ADEC_ERROR_M2BC_CRCGET_EX	0x80612b23	
CELL_ADEC_ERROR_M2BC_CRC_EX	0x80612b24	
CELL_ADEC_ERROR_M2BC_CRCGET	0x80612b31	
CELL_ADEC_ERROR_M2BC_CRC	0x80612b32	
CELL_ADEC_ERROR_M2BC_BITALLOC	0x80612b33	
CELL_ADEC_ERROR_M2BC_SCALE	0x80612b34	
CELL_ADEC_ERROR_M2BC_SAMPLE	0x80612b35	
CELL_ADEC_ERROR_M2BC_OPENBS	0x80612b36	
CELL_ADEC_ERROR_M2BC_MC_CRCGET	0x80612b41	
CELL_ADEC_ERROR_M2BC_MC_CRC	0x80612b42	
CELL_ADEC_ERROR_M2BC_MC_BITALLOC	0x80612b43	
CELL_ADEC_ERROR_M2BC_MC_SCALE	0x80612b44	
CELL_ADEC_ERROR_M2BC_MC_SAMPLE	0x80612b45	
CELL_ADEC_ERROR_M2BC_MC_HEADER	0x80612b46	
CELL_ADEC_ERROR_M2BC_MC_STATUS	0x80612b47	
CELL_ADEC_ERROR_M2BC_AG_CCRCGET	0x80612b51	
CELL_ADEC_ERROR_M2BC_AG_CRC	0x80612b52	
CELL_ADEC_ERROR_M2BC_AG_BITALLOC	0x80612b53	
CELL_ADEC_ERROR_M2BC_AG_SCALE	0x80612b54	
CELL_ADEC_ERROR_M2BC_AG_SAMPLE	0x80612b55	
CELL_ADEC_ERROR_M2BC_AG_STATUS	0x80612b57	

CELP errors

Description	Errorcode	Remarks
CELL_ADEC_ERROR_CELP_BUSY	0x80612e01	
CELL_ADEC_ERROR_CELP_EMPTY	0x80612e02	
CELL_ADEC_ERROR_CELP_ARG	0x80612e03	
CELL_ADEC_ERROR_CELP_SEQ	0x80612e04	
CELL_ADEC_ERROR_CELP_CORE_FATAL	0x80612e81	
CELL_ADEC_ERROR_CELP_CORE_ARG	0x80612e82	
CELL_ADEC_ERROR_CELP_CORE_SEQ	0x80612e83	

CELP8 errors

Description	Errorcode	Remarks
CELL_ADEC_ERROR_CELP8_BUSY	0x80612ea1	
CELL_ADEC_ERROR_CELP8_EMPTY	0x80612ea2	
CELL_ADEC_ERROR_CELP8_ARG	0x80612ea3	
CELL_ADEC_ERROR_CELP8_SEQ	0x80612ea4	
CELL_ADEC_ERROR_CELP8_CORE_FATAL	0x80612eb1	
CELL_ADEC_ERROR_CELP8_CORE_ARG	0x80612eb2	
CELL_ADEC_ERROR_CELP8_CORE_SEQ	0x80612eb3	

CELPENC errors

Description	Errorcode	Remarks
CELL_CELPENC_ERROR_FAILED	0x80614001	
CELL_CELPENC_ERROR_SEQ	0x80614002	
CELL_CELPENC_ERROR_ARG	0x80614003	
CELL_CELPENC_ERROR_CORE_FAILED	0x80614081	
CELL_CELPENC_ERROR_CORE_SEQ	0x80614082	
CELL_CELPENC_ERROR_CORE_ARG	0x80614083	

CELP8ENC errors

Description	Errorcode	Remarks
CELL_CELP8ENC_ERROR_FAILED	0x806140a1	
CELL_CELP8ENC_ERROR_SEQ	0x806140a2	
CELL_CELP8ENC_ERROR_ARG	0x806140a3	
CELL_CELP8ENC_ERROR_CORE_FAILED	0x806140b1	
CELL_CELP8ENC_ERROR_CORE_SEQ	0x806140b2	
CELL_CELP8ENC_ERROR_CORE_ARG	0x806140b3	

Console errors

Description	Errorcode	Remarks
CELL_CONSOLE_ERROR_BASE	0xFFFFFFFF0	
	0xFFFFFFFFFB	"An error occurred during the copy operation." When trying to copy or modify memory save (PS1, .PSV) with only option to create New Internal Memory Card (other path are not displayed).
CELL_CONSOLE_IO_ERROR	0xFFFFFFFFFC	
CELL_CONSOLE_ENOMEM	0xFFFFFFFFFD	
CELL_CONSOLE_EINVAL	0xFFFFFFFFFE	"An error occurred during the delete operation." In this case, attempting (error display but deleted) to delete from XMB an already deleted (from FTP) virtual memory card. other message: see 0x81010002.
CELL_CONSOLE_NOT_INITIALIZED	0xFFFFFFFFFF	

Other errors (not specified above)

Description	Errorcode	Remarks
other errors		
PS3 install error	0x80010048	Internal memory error
	0x80010098	
	0x80010500	Bad Packet ID
unspecified trophy error	0x80010505	Trophy error caused by "Allow access to all SS services (Needed for ps3dm-utils)" patch / Access Violation / Caused by attempting to read eeprom with only root flags
	0x80010506	No Entry
	0x80010509	Backup/Restore decryption and/or verification error / Invalid Parameter
	0x8001050B	Will not play demo hard drive games, (when blue-ray disc is inserted) - cause unknown
	0x8001050D	An error during the start operation; PS3 game swapped using the eject function and then play pressed quickly - PS3 game inserted again
Call Limit Exceeded	0x8001050F	Hardware failure. Cannot update firmware or connect to internet. You can get this on the date "29.02.2010" with firmwares containing the leapyear error
	0x80010510	Will not play games installed on the hard drive
Database problem	0x80010513	System database corrupted or problem with internal flash memory
Issue reading discs	0x80010514	RSOD - Reading blu-ray disc problem // msg_errorcode_solution_check_other_bd msg_errorcode_solution_check_disc_clean msg_errorcode_if_no_solution_ask_ic_with_errorcode / drm marlin - authorization / act.dat fetch fail ERROR!! VersionFile::Get() (exdata/ver.txt/index.dat failures) "release" mismatch / OnActivatePageInitSetting failure / avatar userthumbnail.png failure / vtrm retrieve + store (root hsec+root hash doesnt match with syscon's one)
	0x80010516	An error occurred during the start operation; PS1 game swapped using the eject function and then play pressed quickly - PS1 game inserted again
Clock error	0x80010519	The firmware time is incorrect, update via internet to set it. If this keeps happening try changing the CMOS cell, if that doesn't work your firmware is probably corrupted.
Saved data was corrupt	0x8001051B	
	0x8001051C	"The data is corrupted."
Time error	0x80010601	Time/Date has not been set
Connection error	0x80022A07	Cannot connect to server. Server overloaded?
Incorrect trophy data	0x80022D00	"Error in sync operation."

Description	Errorcode	Remarks
other errors		
Incorrect trophy data	0x80022D05	
Cannot sync trophies or register trophy data	0x80022D11	"Registration of the trophy information could not be completed. The game will quit (80022D11)". Delete SEN user and create a new one
Incorrect trophy data	0x80022D1A	
Trophy installation erased from hdd but indexed in "XMB database"	0x80022D1E	"Registration of the trophy information could not be completed. The game will quit (80022D1E)". After error 0x80022D74 and after erasing the trophy folder manually, in the next boot the game tries to install trophies but the error appears (at this point "XMB database" is updated and the indexed copy of the installation is deleted), after this if trying to boot the game again the trophy installation is completed and the game works normally
Unable to sync trophy data	0x80022D27	Trophy server is down
Trophy installation not updateable	0x80022D55	"Registration of the trophy information could not be completed. The game will quit (80022D55)". Erase old trophy installation, rebuild database, and install new trophy version
Not signed into the PSN	0x80022D64	
Trophy update installer missing	0x80022D74	"Registration of the trophy information could not be completed. The game will quit (80022D74)".
Unable to connect online	0x80022D7C	
Trophy Data is corrupted	0x80022D86	"Registration of the trophy information could not be completed. The game will quit (80022D86)" : Enter Safe Mode and select "Restore File system." / If you still have the issue, delete the User and re-create the User. Then sync the trophy data by logging in to your Sony Entertainment Network account, then go to [Trophy Collection] under (Games). / If error persist, replace harddrive. // can also be generated by setting wrong (old) date/time.
cVTRM error	0x80022D90	Bad cVTRM region in flash
Issue connecting to server	0x80022F0A	
DRM error	0x80022F12	
Unable to connect online	0x80022F16	Possible congestion in internet service, try connecting later
Video license issue	0x80022F2C	
Issue connecting to server	0x80022F2E	
Content not detected	0x80022F50	Disc was ejected while game was updating
Unable to download PSN game	0x80023300	Internet service issues or corrupted data
	0x80023320	"An error occurred during the download operation. (80023320)" (with external device selected as destination for storage).
DRM error	0x80023507	
Video activation failed	0x80023691	Download failed due to activation error
PSN download error	0x800236CC	If renting a video, too many videos on console; if purchasing the video, too many videos on hard drive
PSS access error	0x8002400C	PSS down or having connection issues
Data transfer issue	0x80024611	Ethernet cable damaged or connected incorrectly
Partition error	0x80028347	There is no partition for installing another system on the harddisk (when selecting Install OtherOS from XMB on 1.02 or higher). Solution: make sure there is a partition with Harddisk Format Utility from XMB.
Removable storage media may be damaged	0x800283EB	Check storage media for damage and replace it if this is the case. Try a different storage media to determine if there is damage to the USB slot. If there is damage, send console in for repairs.
Back-up data is corrupted	0x800283F0	
Cannot find content	0x80028510	Content does not exist
File data error	0x8002888C	File data may be corrupted
Message could not be sent to some players	0x80028903	Can be caused by too much data; try sending message individually to users instead.
Message could not be sent to some players	0x80028907	Can be caused by too much data; try sending message individually to users instead. Some of the Online ID's receiving the message may be incorrect.
Trying to play a game without an invite	0x80028909	
Online ID already on block list	0x8002890E	Incorrect Online ID
Cannot add yourself to block list	0x8002890F	Incorrect Online ID
Cannot send another friend request	0x80028913	Incorrect Online ID; delete current request before sending another
Not signed into PSN	0x80028917	Sign in on XMB, then try again
Not enough free space to send message	0x80028918	Free up space (back up files as needed), then try sending the message again
	0x8002892B	Comes up when opening game invite or sending message
Cannot add yourself to block list	0x80028A05	You cannot add yourself to your own block list
Online ID already on block list	0x80028A06	Incorrect Online ID
Cannot add a friend to your block list	0x80028A07	Remove that person from your friend list, then add the person to your block list
Reached maximum number of people on block list	0x80028A09	
DNS error	0x8002A0F	
Not enough space on PS3 hard drive	0x80028A11	
Block list error	0x80028A12	
Unable to connect to network	0x80028ED4	Incorrect internet settings or connecting to an incorrect DNS or proxy server
Issue connecting to patch server	0x80028ED6	Patch server may be down
Restore error	0x800283F0	"The restore operation could not be completed. The system will restart. (800283F0)" // solutions: "I have just found that this appears to have been due to my PSP being registered to my PS3. Unregistered it, completed a backup, swapped in the new formatted HDD, restore completed successfully." / "My

Description	Errorcode	Remarks
other errors		
		protected saves did not copy over from a full restore from my back-up. Before I did my back-up I copied my protected saves over to PS+ cloud as this allows for locked/protected saves to be copied."
	0x80028F08	"An error occurred during the start operation. (80028F08)", when related to PARAM.SFO (with unsupported or corrupted Data ICON), can be resolved (not every time) by pressing triangle one time and launch the game from start or back from the ICON. When related to eboot.bin, combined with error 80010006 / 80010009 / 80010017, check the path for this type of eboot.
Issue with video output setting	0x80028F10	<p>"You cannot play this game at the current video output setting (80028F10)"</p> <p>This occurs because the game you are trying to play will only work at 16:9 resolution, and your PS3 is set for 4:3 resolution. 2 solutions:</p> <ol style="list-style-type: none"> 1) Go to Display Settings then HDMI (or whatever your connection is) and choose Automatic; -or- 2) Go to Display Settings and under select Video Display Output: select Composite or S-Video, whichever type of connection you use. Then choose 16:9 Resolution.
	0x80028F14	"An error occurred during the start operation (80028F14)", mostly caused by bad laser / user trying to directboot via app_home instead of mounting first / old/ancient payload / with malformed PARAM.SFO (unsupported or corrupted data ICON).
PS2 mode error	0x80028F17	"An error occurred during the start operation (80028F17)," PlayStation 2 disc Boot Error, also happen with PS1 PSN games (either due to customized SFO or eboot.pbp).
	0x80028F18	PS2 Disc Error, unsupported disc; eg. Utility discs, BB discs, IQ Remix game etc. ode).
	0x80028F19	PS2 Disc Error, fsck; the internal PS2 disk got corrupted and I guess that you can use HDD utility disc to fix it
	0x80028F1A	PS2 Disc Error, invalbnnetcfg; network config error
msg_error_cannot_play_ps2disc_scee/scea/scej	0x80028F17	"This title is not currently compatible with the PS3 system. If you update your system software the title may become compatible with your system." / target id 0x81
msg_error_cannot_play_ps2disc_scee/scea/scej	0x80028F18	"This title is not currently compatible with the PS3 system. If you update your system software the title may become compatible with your system." / target id 0x82
msg_error_cannot_play_ps2disc_scee/scea/scej	0x80028F19	"This title is not currently compatible with the PS3 system. If you update your system software the title may become compatible with your system." / target id 0x83
msg_error_cannot_play_ps2disc_scee/scea/scej	0x80028F1A	"This title is not currently compatible with the PS3 system. If you update your system software the title may become compatible with your system." / target id 0x84
msg_error_cannot_play_ps2disc_scee/scea/scej	0x80028F1B	"This title is not currently compatible with the PS3 system. If you update your system software the title may become compatible with your system." / target id 0x85
msg_error_cannot_play_ps2disc_scee/scea/scej	0x80028F1C	"This title is not currently compatible with the PS3 system. If you update your system software the title may become compatible with your system." / target id 0x86
msg_error_cannot_play_ps2disc_scee/scea/scej	0x80028F1D	"This title is not currently compatible with the PS3 system. If you update your system software the title may become compatible with your system." / target id 0x87
msg_error_cannot_play_ps2disc_scee/scea/scej	0x80028F1E	"This title is not currently compatible with the PS3 system. If you update your system software the title may become compatible with your system." / target id 0x88
	0x80028F22	"An error occurred during the start operation" e.g.: Starting from BD emu (not from app_home) a game without PARAM.SFO, malformed /combined ATTRIBUTE flags.
	0x80029012	Network error // Temporary congestion in service
	0x80029020	Connection timed out // If using Wi-Fi, console not getting a signal from router.
	0x80029023	Exchanging Key Information exchange has timed out
	0x80029024	"The attempt to obtain an IP address has timed out". // Check internet connection.
	0x800290A1	Unable to connect to network // Power-cycle router and console; if problems continue, may be a router issue
Game data is corrupted	0x80029105	Go into Safe Mode and select "Rebuild Database".
Unable to write data to storage media	0x80029135	Try transferring data from a computer to make sure data can be written to it; if this can't be done, device may be bad.
Game data is corrupted	0x80029207	Delete corrupt data; if this can't be done then go into Safe Mode and select "Restore File System". If issues continue try reformatting the hard drive (restore PS3 system).
	0x80029208	Error loading user profile after update [2] (http://www.ps3hax.net/showthread.php?t=69457)
Game data is corrupted	0x80029209	
Game data is corrupted	0x8002920A	
Game data is corrupted	0x8002920D	
	0x80029301	"An error occurred during the delete operation" (attempting to delete some ps2 homebrew from virtual mem card)
	0x80029303	"An error occurred during the copy operation." (attempting to copy PS1 save data with header malformed(.PSV) to internal memory card)
	0x80029901	"To play this BD, you must renew the encryption key. Perform a system software update to renew the encryption key."
	0x80029902	Playback of BDs is prohibited on this system.
Issue playing disc	0x80029903	"This is an invalid disc (80029903)" // The disc may be dirty or scratched, try cleaning it
	0x80029904	"To play this BD, you must renew the encryption key. Perform a system software update to renew the encryption key."
	0x80029905	"This is an invalid disc (80029905)"
Can't read a Blu-Ray disc?	0x80029906	Can't playback burn BD movie, missing PS3_VPRM.
	0x80029907	"This video cannot be played (80029907)" // Playback of BDs is prohibited on this system.

Description	Errorcode	Remarks
other errors		
	0x8002990C	The data type is not supported.
	0x8002990D	This video cannot be played.
	0x8002990E	Playback of this disc using the connected device is prohibited.
	0x8002990F	Playback of BDs is prohibited on this system.
	0x80029910	Playback of this disc using the connected device is prohibited.
	0x80029911	Playback of this disc using the connected device is prohibited.
	0x80029912	This is an invalid disc.
	0x80029920	This video cannot be played.
	0x80029921	This video cannot be played.
	0x80029922	This disc cannot be played. The region code is not correct.
	0x80029923	"This video cannot be played."
	0x80029925	"This video cannot be played."
	0x80029930	"This video cannot be played."
	0x80029931	"An error has occurred."
	0x80029932	"This video cannot be played."
Can't read a disc	0x80029940	Disc is dirty/scratched or damaged. (Disable the Super-White settings)
Issue playing disc	0x80029941	The PS3 could not read the disc or the disc is not supported.
	0x80029942	Video in the PAL broadcast standard is not supported.
	0x80029943	Video in the NTSC broadcast standard is not supported.
	0x80029944	"This disc cannot be played." // The region code is not correct.
Unable to play Blu-ray Disc	0x80029945	Can't playback burn BD movie
Issue playing disc	0x80029946	Attempting to play burnt Dual layer NTSC disc on a PAL ps3 (workaround is to transfer files to ps3 via TVersity)
	0x80029947	"An error has occurred."
	0x80029948	"This content cannot be played." // There is not enough free space on the system storage
	0x80029949	"This video cannot be played."
	0x8002994A	"Playback stopped. The content being played is protected by Cinavia™ and is not authorized for playback on this device. For more information, see http://www.cinavia.com . Message Code 1."
	0x80029950	"This video cannot be played."
Issue writing to the hard drive	0x8002995C	Hard drive may be corrupted or it is bad.
	0x80029962	"This video cannot be played."
Issue reading Blu-Ray disc?	0x8002996E	
	0x8002997B	
	0x8002997D	
Issue reading Blu-Ray disc?	0x8002997F	
Issue reading Blu-Ray disc?	0x80029986	
Issue reading Blu-Ray disc?	0x80029988	
	0x800299A0	"This video cannot be played". (Solution: Update AACS keys/Firmware)
Unable to read the disc	0x800299A1	Disc may not be supported by PS3
	0x800299AA	"This video cannot be played (800299AA)".
Blu-Ray disc drive error	0x800299AE	"This video cannot be played (800299AE)". // Blu-Ray disc may be damaged or the Blu-Ray laser is bad
	0x800299E1	"An error has occurred".
	0x800299E2	"An error has occurred".
	0x800299E3	"This video cannot be played".
DRL error	0x800299D2	BD Player process startup failed. (BD/DVD/AVCHD MKB mismatch DRL error (or trying to watch BD/DVD/AVCH on converted CEX>DEX))
	0x80029C78	Error occurred while accessing storage media.
	0x80029C7F	"An error has occurred." while accessing Update via System Storage/Delete Update Data on System Storage (e.g. when System Storage folder contains PUP without version to check lowest applicable firmware version).
	0x80029CAA	Error occurred while checking update data. // Mostly caused by TargetID mismatch between EID and Firmware wanting to install - e.g. DEX or Rebug DEX kernel and installing a CEX firmware.
	0x80029CCA	Error occurred while checking update data.
	0x8002AE04	Error occurred due the content ID in the XML is not the same as the pkg in the download link.
Account already associated with another user	0x8002AE05	SEN account is already linked to another user, try logging in through that user instead.
PSN sign-in error	0x8002AE06	Login failed due to out-of-date software
Online connection not established	0x8002AE16	Temporary congestion in internet service or issue with internet connection
Online connection timed out	0x8002AE17	Temporary congestion in internet service or issue with internet connection
Game application update failed	0x8002AE22	Download the update again; if problems continue, possibly an issue with the file itself

Description	Errorcode	Remarks
other errors		
Issue connecting to PSN	0x8002AE1D	
DVI has no audio	0x8002B241	Hook up audio via SCART connection or digital cable
	0x8002B401	Error when creating savedata. ("source" savedata files inside the game are not valid, e.g: PS3_GAME/USRDIR/CONTENT/SAVEDATA/PIC1.PNG with wrong size).
	0X8002B603	Corrupted system file
	0x8002B71A	Possible NAT Error, Can log onto Game Server but can't join game and can't host game
#0x8002f... - PUP / Update errors		
Update success	0x8002F000	Not an error: Success installing/downgrading in service mode. "manufacturing updating SUCCESS(0x8002f000)"
Update error	0x8002F002	Update VSH Package done(0x8002f002) / Updating or Verifying failure 0x8002f002 / manufacturing updating FAILURE(0x8002f002) (http://www.pastie.org/3724383) // Possibly bad firmware PUP, bad USB stick or harddrive going bad in PS3. Check PUP, try other stick and replace harddrive.
Update error	0x8002F020	Update file corrupted
Update error	0x8002F02B	Update file corrupted
Update error	0x8002F02D	Update file corrupted
Update error	0x8002F048	Error with installing Firmware update in service mode: "start Updating Proccess. UpMng.UpdatePackage() failure. manufacturing updating FAILURE(0x8002f048)" // Check if PUP to install is in root of stick and named PS3UPDAT.PUP
Update error	0x8002F057	Error with installing Firmware update in service mode: "Bul-ray Disc Player Revoke done(0x8002f057). Updating Or Verifying failure 0x8002f057. UpMng.UpdatePackage() failure. manufacturing updating FAILURE(0x8002f057)" // caused by downgrading and using normal lv2_diag.self (http://pastebin.com/j97SpE2J) and not a noBD firmware (using the jaicrab_lv2_diag.self (http://pastebin.com/9tTfAs2J) as workaround will cause one ROS to be empty and can result in RLOD/GLOD/RSOD).
Update error	0x8002F087	Error with installing Firmware update in service mode: "Update VSH Package done(0x8002f087), Updating or Verifying failure 0x8002f087, UpMng.UpdatePackage() failure, manufacturing updating FAILURE(0x8002f087)" // can be caused by bad vsh, broken harddrive or wrong spoofing.
Update error	0x8002F0C1	"An error occurred during the update operation. (8002F0C1)" -> Download error. Manual download the update with PC, put on /PS3/UPDATE/PS3UPDAT.PUP and install in recovery instead.
Update error	0x8002F0E0	Error with installing Firmware update. Harddrive is not found or disconnected.
Update error	0x8002F107	Update VSH Package done(0x8002f107) / Updating or Verifying failure 0x8002f107 / manufacturing updating FAILURE(0x8002f107) (http://www.pastie.org/3724398) // Possibly bad firmware PUP, bad USB stick or harddrive going bad in PS3. Check PUP, try other stick and replace harddrive.
Update error	0x8002F13E	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and/or reboot the system first
Update error	0x8002F142	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and/or reboot the system first
Update error	0x8002F147	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and reboot the system first
Update error	0x8002F149	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and reboot the system first
Update error	0x8002F14A	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and/or reboot the system first
Update error	0x8002F14B	Error with installing Firmware update. Updating or Verifying failure of CoreOS on flash area (?bad flash blocks?)
Update error	0x8002F14E	Error with installing Firmware update. (BD)Drive not found or disconnected. // or CoreOS region failure when in log "Update Core OS Package done(0x8002f14e)" or Revoke region failure when in log "Update Package Revoke list done(0x8002f14e)"
?corrupt?	0x8002F153	firmware related error - can be generated by using the MinVerChk PUP in factory service mode (must NEVER do that!)
?corrupt?	0x8002F155	solution: power down with power button remove the power cord for a few minutes then reboot (sony message:if this doesn't work contact sony)
?corrupt?	0x8002F156	NAND Downgrade eror - UpMng.UpdatePackage() failure: manufacturing updating FAILURE(0x8002f156) (http://pastebin.com/sURmGqq3)
?corrupt?	0x8002F157	firmware related error / HDD Exchange error - 3.56-1st BUG. Also happens when you try to Upgrade from 999 Downgrader to another Non-999 CFW. Go to OFW 3.55, then upgrade to the other CFW
?corrupt?	0x8002F15E	CoreOS firmware related error
Update error	0x8002F165	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and reboot the system first
Firmware data is corrupt	0x8002F169	Error when checking the firmware data (after unpacking)
Update error	0x8002F174	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and/or reboot the system first
Update error	0x8002F176	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and reboot the system first
Update error	0x8002F19D	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and reboot the system first
Update error	0x8002F1B0	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and reboot the system first
Update error	0x8002F1B3	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and reboot the system first

Description	Errorcode	Remarks
other errors		
Update error	0x8002F1C1	Error with installing Firmware update. Make sure the sourcedrive with the PUP is readable and reboot the system first - DFU Start Firmware Update failed.
Update error	0x8002F1C3	DFU End Firmware Update failed.
Update error	0x8002F1F0	Bluetooth/WLAN error. Check the connection of the Wifi/BT board, reboot system and reinstall firmware.
Update error	0x8002F1F9	Error with installing Firmware update. Check the connection of the Wifi/BT board, reboot system and reinstall firmware.
Update error	0x8002F220	Issue with System Restore or installing Firmware update in Recovery Mode. Reboot system and reinstall firmware.
Update error	0x8002F225	Error with installing Firmware update. The PUP is not recognised as valid update.
Update error	0x8002F22F	Issue with the PS3 hard drive
	0x8002F235	Error with installing Firmware update. "Data Is Corrupted"
Update error	0x8002F23F	Error with installing Firmware update. The PUP is not recognised as valid update. (with 3.56 minver console)
Update error	0x8002F26A	Error with installing Firmware update. "A serious error has occurred" (http://www.ps3hax.net/showthread.php?t=36913)
Update error	0x8002F271	Error with installing Firmware update. "An error occurred during the format operation."
Update error	0x8002F281	Error with installing Firmware update. Check the connection of the Wifi/BT board.
Issue with the PS3 harddrive.	0x8002F281	<p>Issue with the PS3 harddrive. Reboot system and use Recovery Menu options. If error persist, Format the hd on a pc, reinsert it to the ps3, install update (normal/recovery mode), format hd on install. If still not fixed: exchange harddrive. Note: This error also comes up when trying to install a 1.5TB HDD as internal HDD. Plug it into the pc, then open command prompt.</p> <p>1) Type "diskpart" 2) Type "list disk" - Get the disk number for the drive you are fixing. 3) Type "select disk 1" - If the disk is not #1, change this accordingly. 4) Type "clean" 5) Type "create partition primary" 6) Type "select partition 1" 7) Type "active" 8) Type "assign" - When it asks you to format, click cancel. 9) Type "exit" 9) Type "exit" 10) Reinsert into your ps3, and boot it into safe mode, it may take awhile to boot into safe mode. 11) Choose to update, it should ask you to format, do so then update. Issue with flash. R/B control signal for NAND not connected (leg, track, or via for R/B broken when attempting to solder a flasher on it)</p>
Update error	0x8002F282	Issue with System Restore or installing Firmware update in Recovery Mode. Reboot system and reinstall firmware.
Update error	0x8002F285	Issue with System Restore or installing Firmware update in Recovery Mode. Reboot system and reinstall firmware.
Update error	0x8002F2B5	Error with installing Firmware update. The PUP is not recognised as valid update.
Update error	0x8002F2BF	Issue with System Restore or installing Firmware update in Recovery Mode. Reboot system and reinstall firmware.
Downgrade error	0x8002F2C4	Error when downgrading below applicable firmware version with QA-flag from Recovery Mode
Update error	0x8002F2C5	Error with installing Firmware update. The PUP is not recognised as valid update. (Can be generated by pulling the storage device with the PUP when it is still in checking stage. DANGEROUS!). Or when trying to install MinVerCheck.PUP immediately after an hdd replacement in PS3 models with a NOR flash
Update error	0x8002F2CF	Issue with the Mass Storage Device when installing firmware, or PS3 hard drive
	0x8002F2E0	HDD Probe/Init failed. (No HDD attached)
	0x8002F2E2	
	0x8002F2E3	HDD Search Regions failed. (encrypted HDD incompatible with the consoles) (Formatting...)
	0x8002F2E4	The data is corrupted. (e.g. bad promo_flags.txt flag set)
	0x8002F2E5	PUP filepath error.
	0x8002F2E6	No applicable Data found.
Update error	0x8002F2F0	Error with installing Firmware update. The PUP is not recognised as valid update.
Update error	0x8002F2F2	Error with installing Firmware update. The PUP is not recognised as valid update
Update error	0x8002F310	Error with installing Firmware update. See Service Mode log to what flash region is corrupt
Update error	0x8002F311	Error with installing Firmware update. See Service Mode log to what flash region is corrupt
Update error	0x8002F312	Error with installing Firmware update. See Service Mode log to what flash region is corrupt
Update error	0x8002F313	Error with installing Firmware update. Shows up in Service Mode log as 'Update Core OS Package done(0x8002f313)' possible caused by bad ROS
Update error	0x8002F314	Error with installing Firmware update. Unknown cause.
Update error	0x8002F325	Error with installing Firmware update. data corrupted
Update error	0x8002F333	Error with installing Firmware update. data corrupted // Issue with the internal harddrive.
Update error	0x8002F334	Error with installing Firmware update. data corrupted // Issue with the internal harddrive.
Update error	0x8002F87C	Update file may be corrupted // Reboot console and try updating again; if the error occurs again, try updating a different way (e.g if updating via the console, try via a PC with a USB stick); if issues continue then restore file system and try updating again
Update error	0x8002F953	Error with installing Firmware update.
Update error	0x8002F956	Error with installing Firmware update. (bad harddrive?)

Description	Errorcode	Remarks
other errors		
Update error	0x8002F957	Error with installing Firmware update. The data is corrupted (firmware in flash does not allow the MFW installation as it does not contain the needed patches)
Update error	0x8002F976	Error with installing Firmware update. data corrupted
Update error	0x8002F95E	Error with installing Firmware update (when using Rogero 3.55 DEX DG v1 on DEX 4.20 system).
	0x8002F967	Error when checking PUP version (e.g. when using manipulated PUP without version to check lowest applicable firmware version)
	0x8002F969	Error when checking PUP version (Seen on DECR-1400)
	0x8002F96F	Error when downgrading DEX console with special PUP. To solve: reset console by holding power button until it beeps
	0x8002F994	Too many people downloading the update (download it later on)
An error has occurred	0x8002FB22	Error can be generated with a malformed license.xml file in PS3UPDAT.PUP
	0x8002F21x	(Set Recovery Mode Flag On (cex/dex/decr)) / (Connecting Controller)
	0x8002F22x	(Connect Media containing FW equal or higher)
	0x8002F23x	(System Partition formating) / (Search Updater)
	0x8002F24x	(Formatting)
	0x8002F25x	hdd probing
	0x8002F26x	region searching
	0x8002F27x	preparing partitions
	0x8002F28x	Setup Updating Environment
	0x8002F29x	
	0x8002F2Ax	
	0x8002F2Bx	(Turning Off Recovery Mode Flag)
	0x8002F2Cx	Search Updater (Formating preparing Update)
	0x8002F2Dx	(Formatting - Preparing to Update)
	0x8002F2Ex	(Turning On/Off Recovery Mode Flag)
#0x8001... RSOD/BSOD errors		
	0x80010514	RSOD - VersionFile::Get() (index.dat failures)
	0x80028C03	BSOD - NPXS01003, net if ctl fail (game updates,commerce, friend stuff ...)
	0x80028C10	BSOD - xregistry
	0x80028C12	BSOD - xregistry
	0x80030506	BSOD - empty sce net ctl ptr's
	0x8003050F	BSOD - create_open_database 0x25 failure, xregistry empty file descriptor
	0x80030517	BSOD
	0x80031150	BSOD- "Setting information is corrupted. Press the X button to repair and restore default"
	0x8003116D	BSOD - xregistry font related
	0x80031175	BSOD - xregistry
	<0x80031200	BSOD + >0x80031700 = rsod - xregistry: atrac+wma activate/dtcp ip enable/hdmi failure/menu bdvd config/(list) chat config/word register(dictionary)/edit np environment+marlin+ad catalog version+ad server url+application type+adhoc ssid prefix+update server url+np title id+fake limit size+gameutil dirname debug/ failure of swreset.self execution/Device Config/back prev setting/Display (+Output) Config/First Config/music+sound config (+wizard)
	>0x80031700	RSOD
other errors		
	0x80030001	Deleting messages from inbox
	0x80030400	Issue locating files // Rebuild database
	0x8003041C	Issue locating files on the PS3
	0x8003041F	An error occurred during the copy operation (using media server)
	0x80030517	It seems to happen when you copy large media files.
	0x8003051E	Game will not save
	0x80030920	An error occurred during the copy operation, the file may be corrupt or there isn't enough memory (Try copying data from original source)
	0x80031601	Error Creating Account // seems to occur when the user number doesn't match
	0x80031602	Error Renaming Account
	0x80031603	Error No Account name given
	0x80031606	PSN login failed due to corrupted files
PAC_INVALID_CONTENTTYPE	0x80040001	
PAC_INVALID_OPERATION	0x80040002	
PAC_UNKNOWN_CONTENT_TYPE	0x80040003	
PAC_UNKNOWN_CATEGORY_TYPE	0x80040004	
PAC_UNKNOWN_PRODUCT_TYPE	0x80040005	

Description	Errorcode	Remarks
other errors		
PAC_UNKNOWN_SKU_INFO_TYPE	0x80040006	
PAC_UNKNOWN_VOUCHER_TYPE	0x80040007	
PAC_UNKNOWN_DRM_CONTENT_TYPE	0x80040008	
PAC_UNKNOWN_DRM_TYPE	0x80040009	
PAC_INVALID_CAST_EXCEPTION	0x8004000A	
PAC_SESSION_NOT_ESTABLISHED	0x8004000C	
PAC_THREADINVOKER_EXCEPTION	0x8004000D	
PAC_DOWNLOADER_IS_ALREADY_ACTIVATED	0x8004000D	
PAC_CANNOT_DOWNLOAD AGAIN	0x8004000E	
PAC_CRITICAL_OPERATION_IN_PROGRESS	0x8004000F	
PAC_URL_LOADER_WEB_EXCEPTION	0x80040010	
	0x8004D844	Remote Play Connection error (cannot connect to PS3)
PAC_ASSERT	0x8004FFFF	
Activation error	0x80109D80	Console activated/deactivated too many times
PSS server error	0x8010A12E	Deactivate console and then re-activate it, reboot console and download content
bluetooth	0x80110104	"An error occurred during the register operation. Try to register again." (when Bluetooth device is disconnected during the register operation).
bluetooth	0x80110106	"An error occurred during the register operation. Try to register again." (when trying register Bluetooth device without pass key).
bluetooth	0x80110108	"An error occurred during the register operation. Try to register again." (with wrong pass key)
bluetooth	0x80110113	"An error occurred during the register operation. Try to register again." (with wrong pass key)
bluetooth	0x80110118	"An error occurred during the register operation. Try to register again." (time expired probably)
	0x80130121	on PS3 Slim network error during Wireless connection - Caused by bad GbLAN IC Other symptoms are: Ethernet cable not detected; System does not shut down/restart during fw update; not responding Blue Screen of Death Boot_modes#BSOD
Network error	0x80130128	Console could not be activated because it was activated/deactivated too many times; wait seven days before trying to activate/deactivate the console again
Issue with AOSS setting	0x80130143	Follow instructions for setting up AOSS equipment correctly; if on Wi-Fi, signal may be too weak
	0x80130203	PS3 connects to internet but not to network - Typically means that the required ports are not open to connect to store but PS3 can connect to internet.
	0x8013030?	System Error due to failed update download
Unable to detect access point	0x8013030F	
Unable to detect access point	0x80130310	
Problem connecting to wireless router	0x8013031A	Try connecting to the router again; if problems continue, power cycle the router and reboot the console, then try connecting again
Unable to connect to wireless router	0x8013031B	Router and console settings don't match
DHCP communication error	0x80130501	Reboot console and connect again; make sure modem/router supports DHCP
No response from DHCP server	0x80130502	Reboot console and connect again; make sure modem/router supports DHCP
DHCP communication error	0x80130503	Reboot console and connect again; make sure modem/router supports DHCP
DHCP communication error	0x80130505	Reboot console and connect again; make sure modem/router supports DHCP
Unable to connect to wireless router	0x80130804	Reboot router and console and try connecting again; if issues continue, may be a connection issue
	0x8041040F	Communication with the server failed. A DNS error has occurred.
	0x80410418	DNS Error
	0x80410A0B	Internal PSP error, hardware fault. Send back to be replaced/fixed.
Network error	0x80431021	Software is out of date and needs to be updated; contact Sony if issues continue
Unable to connect to the PSN	0x80550F17	PSN down for maintenance or congestion in internet connection
PSS content error	0x80551011	Content on PSS is incorrect and will be replaced and corrected as soon as possible; try again later
PSN wallet top-up issue or issue connecting to PSN	0x80551021	
Issue adding a credit card	0x8055105A	Credit card has too many accounts linked to it
	0x80610180	Fatal error occurred with the decoder itself. CELL_VDEC_ERROR_FATAL indicates that an error having to do with the decoder itself occurred. For example, this error will occur if a data structure inside the decoder required for the decoding process becomes inconsistent due to an unknown reason and decoding cannot be continued. Statuses other than CELL_VDEC_ERROR_FATAL indicate that an unexpected error occurred with the OS or library used inside the decoder. In such cases, too, the decoding process cannot be continued. CELL_OK will never be returned for the status. [3] (http://psx-scene.com/forums/f6/article-%5Bupdate%5D-multiman-v4-65-01-base-cex-deanks-showtime-builds-124904/index8.html#post1150131)
	0x8071053D	Hard boot the PS3, turn off the PS3 to stand-by, flip off the back switch and completely remove the power cord. Shut off your modem/router, for approx. 5 minutes, then turn the modem back up first and let it sync. Then turn the router back on (if you're using one) and let it sync. Reconnect your power cable and flip the back switch up again. Then make a new network connection
	0x80710541	The connection to the server timed out.
	0x80710723	Possible Port Error. Try opening ports, TCP port: 80, 443, 5223 and UDP port: 3478, 3479, 3658.
	0x80710B23	PS3 Network is Down or PS3 Network is too busy to respond

Description	Errorcode	Remarks
other errors		
	0x80710B36	"An error has occurred." PS3 Network ("What's news) is too busy to respond.
	0x80710D23	Turn the PS3 off for approx. 30 minutes with the power toggle, not standby mode
	0x80710D36	HTTP header "content-length" is bigger than the actual content returned by the server
	0x81010002	"An error occurred during the copy operation." From internal corrupted/modified (overwrite previously the modified .VM1) save data (PS1, .VM1) to others internals memory card (them, error 0xFFFFFFF with this message) or USB.
	0x81010006	"An error occurred during the copy operation." From internal corrupted/modified (overwrite previously the modified .VM1) save data (PS1, .VM1) to others internals memory card or USB.
	0x8101002F	"An error occurred during the copy operation." From internal corrupted/modified (overwrite previously the modified .VM1) save data (PS1, .VM1) to others internals memory card or USB.
	0x81019002	Error copying saves from location A to location B not open to connect to store but PS3 can connect to Internet.

v·e (https://www.psdevwiki.com/ps3/edit/Template:Firmware)		System Firmware
Updates and Patches	Retail / CEX	1.00 · 1.02 · 1.10 · 1.11 · 1.30 · 1.31 · 1.32 · 1.50 · 1.51 · 1.54 · 1.55 · 1.60 · 1.70 · 1.80 · 1.81 · 1.82 · 1.90 · 1.92 · 1.93 · 1.94 · 1.97 · 2.00 · 2.01 · 2.10 · 2.16 · 2.17 · 2.20 · 2.30 · 2.35 · 2.36 · 2.40 · 2.41 · 2.42 · 2.43 · 2.45 · 2.50 · 2.52 · 2.53 · 2.60 · 2.70 · 2.76 · 2.80 · 3.00 · 3.01 · 3.10 · 3.15 · 3.16 · 3.20 · 3.21 · 3.30 · 3.40 · 3.41-1 · 3.41-patch · 3.41-2 · 3.42 · 3.42-patch · 3.50 · 3.55 · 3.55-patch · 3.56-1 · 3.56-2 · 3.60 · 3.61 · 3.65 · 3.66 · 3.70 · 3.71 · 3.72 · 3.72-patch · 3.73 · 3.73-patch · 3.74 · 4.00 · 4.01 · 4.10 · 4.11 · 4.15 · 4.20 · 4.21 · 4.21-patch · 4.22 · 4.25 · 4.25-patch · 4.30 · 4.30-patch · 4.31 · 4.31-patch · 4.40 · 4.40-patch · 4.41 · 4.41-patch · 4.45 · 4.45-patch · 4.46 · 4.50 · 4.50-patch · 4.53 · 4.53-patch · 4.55 · 4.55-patch · 4.60 · 4.60-patch · 4.65 · 4.65-patch · 4.66 · 4.66-patch · 4.70 · 4.70-patch · 4.75 · 4.75-patch · 4.76 · 4.76-patch · 4.78 · 4.78-patch · 4.80 · 4.80-patch · 4.81 · 4.81-patch · 4.82 · 4.82-patch · 4.83 · 4.83-patch · 4.84 · 4.84-patch · 4.85 · 4.85-patch · 4.86 · 4.86-patch · 4.87 · 4.88 · 4.89 · 2.42 · 2.51 · 3.41 · 3.50 · 3.55 · 3.56-1 · 3.56-2 · 3.60 · 3.61 · 3.66 · 3.70 · 4.00 · 4.10 · 4.11 · 4.20 · 4.21 · 4.23 · 4.25 · 4.26 · 4.30 · 4.31 · 4.40 · 4.41 · 4.45 · 4.46 · 4.50 · 4.53 · 4.55 · 4.60 · 4.65 · 4.66 · 4.67 · 4.70 · 4.75 · 4.76 · 4.78 · 4.80 · 4.81 · 4.82 · 4.83 · 4.84 · 4.85 · 4.86
	Shop / SEX	095.001 - DEX · 096.002 - DEX · 1.00 · 1.01 · 1.02 · 1.50 · 1.54 · 1.60 · 1.70 · 1.80 · 1.81 · 1.92 · 2.00 · 2.01 · 2.10 · 2.15 · 2.17 · 2.20 · 2.30 · 2.35 · 2.36 · 2.40 · 2.41 · 2.42 · 2.50 · 2.52 · 2.53 · 2.60 · 2.70 · 2.76 · 2.80 · 2.85 · 3.00 · 3.01 · 3.10 · 3.15 ·
	Debug / DEX	3.20 · 3.21 · 3.30 · 3.31 · 3.40 · 3.41 · 3.42 · 3.50 · 3.55 · 3.55-downgrader · 3.55-001d · 3.56 · 3.60 · 3.65 · 3.66 · 3.70 · 3.71 · 3.72 · 3.73 · 3.74 · 4.00 · 4.01 · 4.10 · 4.11 · 4.20 · 4.21 · 4.25 · 4.30 · 4.31 · 4.40 · 4.41 · 4.46 · 4.50 · 4.53 · 4.55 · 4.60 · 4.65 · 4.66 · 4.70 · 4.75 · 4.76 · 4.78 · 4.80 · 4.81 · 4.82 · 4.83 · 4.84 · 4.85 · 4.86
	Tool / DECR	2.80 · 2.85 · 3.00 · 3.01 · 3.10 · 3.15 · 3.20 · 3.21 · 3.30 · 3.31 · 3.40 · 3.41 · 3.42 · 3.50 · 3.55 · 3.60 · 3.61 · 3.65 · 3.66 · 3.70 · 3.71 · 3.72 · 3.73 · 3.74 · 4.00 · 4.11 · 4.20 · 4.21 · 4.25 · 4.30 · 4.31 · 4.40 · 4.41 · 4.46 · 4.50 · 4.55 · 4.60 · 4.65 · 4.70 · 4.75 · 4.76 · 4.78 · 4.80 · 4.81 · 4.82 · 4.83
	AVTool	1.00 · 1.30
	Arcade / GEX	197.000 · 245.000 · 251.040 · 3.10 · 3.60 · 4.20 · 4.40 · 4.50 · 4.70 · 020.010 · 030.001 · 030.014 · 030.019.r003 · 030.020 · 030.020.r003 · 030.022 · 030.022.r004 · 040.001.r007 · 040.004.r009 · 040.005 · 040.005.r009 · 040.006 · 040.006.r009 · 040.012 · 040.012.r009 · 040.013 · 050.002 · 050.002.r010 · 050.003 · 050.003.r010 · 050.004 · 050.004.r010 · 050.008 · 050.008.r010 · 050.011 · 050.011.r010 · 050.012 · 050.012.r010 · 050.013 · EBOOTROM_E · 1250.bin · EBOOTROM_E.r009 · EBOOTROM_I.r009
	Eboot.rom	060.004 · 0.6.0.004.r010 · 0.6.0.012.r010 · 0.6.0.013.r010 · 0.8.0.004.r010 · 0.8.1.003.r010 · 0.8.2.006.r010 · 0.8.2.011.r010 · Proto DEH · 0.8.3.002.r010 · 083.006.r010 · 083.007.r010 · 0.8.4.9460 · 0.8.4.001.r010 · 0.8.4.006.r010 · 0.8.5.007.r010 · Ebootrom mini I · EBOOTROM_2_I · EBOOTROM_2_E
	Proto DECR	0.85.009 · 0.85.010 · 0.85.015 · 091.006 · 093.002 · 100.002 - DECR
	Misc.	Internal Ebootroms
Firmware Info	Boot modes · Button Combos · Error Codes · Factory Service Mode · More System Information · Recovery Menu · Retail, Shop, Debug, Tool firmware differences · DEX Options · Features · XMB · Licensing · Update Types	

Retrieved from 'http://www.psdevwiki.com/ps3/index.php?title=Error_Codes&oldid=69476'

This page was last modified on 21 February 2023, at 04:27.

Content is available under [GNU Free Documentation License 1.2](#) unless otherwise noted.