SIMATS ENGINEERING (SAVEETHA SCHOOL OF ENGINEERING)

Department of Computer Science and Engineering

ASSESSMENT TOOL 2 – Short Answers

Course Code:	ITA03	**Course Title:**	Mobile computing
CO Assessed:	CO1	**Assessment:**	Assessment Tool 2 – Short Answers
Weightage:	30 % of CIA	**Total Marks:**	100 Marks
CO1 Statement:	*Analyze the mobile network components, mobile base station, mobile infrastructures and protocols in cellular systems.*		
Student Name:	D.C.Boopathi	**Reg. No.:**	192511320
Section / Batch:	B.E - CSE	**Date:**	09/10/2026

Code of Conduct

I D.C.Boopathi (192511320) *(Name / Reg No) certify that this submission is my original work and that I have adhered to the guidelines specified for this assessment. I understand that any violation of academic integrity rules will result in disciplinary action.*

Signature of the Student: _____

Instructions

- This test contains 50 questions, Total: 100 Marks.
- Duration: 1 hour.

Faculty In-charge	Course Coordinator	Head of Department
Dr. T Srinivasulu		
Signature: _____	Signature: _____	Signature: _____
Date: 09/10/26	Date: _____	Date: _____

96/100

Questions

Q1. A telecom operator wins a spectrum auction for 45 MHz. Company policy sets aside 25 kHz for every simplex channel. The planning team wants to know how many full-duplex voice channels this spectrum can support.

Q2. A regional carrier runs its network on 560 total voice channels, shared across a 7-cell frequency reuse cluster. During capacity planning, an engineer needs to know how many channels a single cell will typically be allocated.

Q3. A GSM operator sets carrier spacing at 200 kHz and rolls out 100 carriers, each carrying 8 time slots for voice traffic. Determine the total number of simultaneous voice channels this deployment can offer.

Q4. During a site audit, engineers note the base station radiates 80 W while a nearby handset transmits just 4 W. They want to express this power gap as a decibel-based power control ratio (10·log10 of the ratio).

Q5. A drive test captures a serving signal at -60 dBm alongside co-channel interference at -92 dBm. The RF team needs the Carrier-to-Interference ratio (C/I) in dB to assess link quality.

Q6. An operator holds 42 MHz of spectrum, assigning 300 kHz per channel, and reuses frequencies across a 7-cell pattern. How many channels does a single cell end up with?

Q7. A transmitter delivers 64 W of power to a receiver. Engineers then move the receiver twice as far away, in an environment with a path-loss exponent of 4. What received power should they now expect?

Q8. Planners want to double a cell's radius while keeping the same SNR at the new edge, in an environment obeying an inverse-square power law. By what factor should transmit power be scaled up?

Q9. A network is built with a cluster size of 4, and every cell in the cluster is provisioned with 15 voice channels. What is the total channel count across the entire cluster?

Q10. A drive test records a vehicle traveling at 100 km/h while camped on a 900 MHz carrier. Estimate the Doppler shift the receiver experiences.

Q11. A TDMA frame lasting 5 ms is divided into 8 equal time slots. What is the duration of a single slot?

Q12. Spectrum planners have 24 MHz of allocated bandwidth and fix carrier spacing at 200 kHz for a GSM rollout. How many carrier frequencies can be created from this allocation?

Q13. A handset transmits at 8 W, but the signal experiences 33 dB of path loss on its way to the base station. Estimate the power the base station receiver actually sees, in dBm.

Q14. A network engineer uses 1 m as the reference distance while assessing a 1900 MHz deployment, where cell sites are spaced 2.5 km apart. Estimate the free-space path loss over that distance.

Q15. A cluster consists of 6 cells, each able to carry up to 250 simultaneous calls at peak. What is the cluster's total call-handling capacity?

Q16. A switching subsystem is rated to process 4000 new call requests every second, and calls last 3 minutes on average. How many calls could be active in the system at any one time?

Q17. Engineers assign 150 channels to a base station subsystem, each channel occupying 25 kHz. What total bandwidth does this base station consume?

Q18. Spectrum planners insert a 40 kHz guard band between each of 30 adjacent frequency bands to prevent interference. How much total bandwidth ends up wasted because of these guard bands?

Q19. A vehicle cruises at 90 km/h through a region of 1.5 km-radius cells. Using the cell diameter as the crossing distance, roughly how many handoffs would occur over an hour of travel?

Q20. A carrier's network hierarchy has 8 regional centers, each overseeing 40 base stations, with each base station serving 250 users. What is the network's total user-handling capacity?

Q21. Coverage planners want to blanket a 400 sq km region using hexagonal cells of 400 m radius (approximate cell area as R^2). Roughly how many cells will the rollout require?

Q22. An FDMA system allots 30 kHz to each channel, drawing from a total spectrum pool of 6 MHz. How many channels can be carved out of this allocation?

Q23. A market study notes that 1200 subscribers each place 4 calls per hour, averaging 2.5 minutes per call. What total offered traffic, in Erlangs, does this represent?

Q24. A 2.5 GHz deployment has 40 MHz of bandwidth, and each connected user consumes 400 kHz. What is the maximum number of users the band can serve at once?

Q25. A carrier's base stations each cap out at 600 simultaneous users, and the network comprises 1200 such stations. What total user capacity does the network offer?

Q26. A paging scheme sweeps through 4 cells at a time across a 200-cell network. In the worst case, how many paging rounds are needed to locate a subscriber?

Q27. A core network is engineered for 100,000 simultaneous connections. During a busy period it receives 40,000 call attempts per minute, each lasting 3 minutes on average. What fraction of the offered traffic ends up blocked?

Q28. A network policy lets 15% of its 600,000 subscribers roam onto partner networks each hour. At any given moment, how many subscribers are likely roaming?

Q29. A switching center is capable of processing 12,000 calls per second, but is currently handling a peak load of 9,000 calls per second. What percentage of its capacity is being utilized?

Q30. An operator reuses frequencies with a factor of 4 across a network holding 48 MHz of spectrum, with 200 kHz per channel. How many channels land in each cell?

Q31. A 900 MHz GSM deployment uses 200 kHz channel spacing across a 30 MHz allocation. How many channels can this spectrum support?

Q32. Over the course of an hour, a network logs 2500 handoff attempts, 99% of which succeed. How many calls were successfully handed off?

Q33. A mobile handset radiates 12 W, and the link experiences 45 dB of path loss before reaching the base station. What power level does the base station receiver detect?

Q34. A 7-cell cluster is deployed where each cell can serve up to 900 simultaneous users. What is the cluster's overall user capacity?

Q35. A TDMA carrier's frame spans 4.8 ms and is split into 8 equal slots. How long is each individual slot?

Q36. A mobile device moves at 150 km/h while connected to a 1.8 GHz carrier. What Doppler shift should the receiver expect?

Q37. A core switch is dimensioned for 250,000 simultaneous calls. It is fielding calls at a rate of 70,000 per minute, each averaging 4 minutes in duration. What share of the offered load gets blocked?

Q38. A hexagonal layout groups 9 cells into a cluster, and each cell can host 600 users. What is the cluster's combined user capacity?

Q39. A switching center processes 60,000 calls per second, with 0.4% of them dropped due to network issues. How many calls are being dropped every second?

Q40. A base station in an 1800 MHz network transmits at 43 dBm. At the edge of its 2 km-radius cell, the received signal measures -87 dBm. What path loss has the signal undergone?

Q41. A single base station covers 2.5 km² of territory, and the operator plans to deploy 150 identical stations. What total geographic area will the rollout cover?

Q42. An operator applies a frequency reuse factor of 6 over a 48 MHz spectrum allocation, with each channel taking up 200 kHz. How many channels does each cell get?

Q43. A paging system processes 6000 users per cycle, and the subscriber base totals 150,000 users. How many paging cycles are needed to sweep the entire base?

Q44. A phone call runs for 9 minutes, and during that time the network hands the call off roughly every 3 minutes. How many handoffs took place over the call?

Q45. A receiver picks up a wanted signal at -85 dBm against a noise floor of -115 dBm. What signal-to-noise ratio, in dB, does this represent?

Q46. A 4G cell is serving 250 users simultaneously, each needing a guaranteed 150 kbps. What is the minimum bandwidth the cell must provide to support them all?

Q47. A base station handles 1500 subscribers, each averaging 4 calls per hour with a 2.5-minute call length. What total traffic, in Erlangs, does this generate?

Q48. A network reserves 250 separate control channels, each 12 kHz wide, for signaling. What total bandwidth is tied up in control channels?

Q49. A network is carrying 1500 simultaneous connections, each streaming at 600 kbps on average. What total throughput must the network support?

Q50. A telecom operator wants each tower to cover a 4 km radius (treating coverage as a circle, area = πR^2) and needs to blanket a 350 km² service region. Roughly how many towers will the rollout require?

---

n :

Spectrum = 45 MHz

ex channel = 25 K

= 45 ÷ 2

= 1800

l duplex voi

hannel for cell

The channel

Total voice ch

The total num

Power ratio =

5. C/I = -60

6. channel P

7. Receiver

8. Received

Name : D.C. Boopathi

Reg.no : 192511320

Course Code : ITA03

Course Name: Mobile Computing.

1. Given :

Spectrum = 45 MHz

simplex channel = 25 KHz

$= 45 \div 25$

$= 1800$

Full duplex voice channel = 900

2. channel Per cell = $560 \div 7$

∴ The channel in a single cell is 80 channels.

3. Total voice channels = $100 \times 8 = 80$

The total number of simultaneous voice channel is 80.

4. Power ratio = $10 \log (80/4) = 13.01$ dB.

5. $C/I = -60 - (-92) = 32$ dB

6. channel Per cell = 42 MHz ÷ 300 KHz ÷ 7 = 20 channels.

7. Receiver Power = $64 \div 2^4 = 4$ W

8. Received Power factor = $2^2 = 4$ times

9. Total channels = 4 × 15 = 60
The total channel count across the entire cluster is 6

10. Doppler shift = vs/c = 83.3 Hz

11. Slot duration = 5ms ÷ 8 = 0.625 ms.

12. Carriers = 24 MHz ÷ 200 KHz = 120 carriers.

13. Receiver Power = $10 \log_{10}(8000) - 33 = 6.03$ dBm.

14. Free space Path loss = $32.44 + 20 \log_{10}(2.5) + 20 \log_{10}$ (1900) = 106 dB.

15. Capacity = 250 × 6 = 1500 cells.

16. Active cells = 4000 × 80 = 720,000 cells.

17. Bandwidth = 150 × 25 KHz = 3.75 MHz

18. Guard bands = 29 × 40 KHz = 1.16MHz.

19. Handoffs = 90 km ÷ 3 km = 30

20. Users = 40 × 8 × 250 = 80,000 users.

21. Cells = 400 ÷ 0.16 = 2500 cells.

22. Channels = 6MHz ÷ 30 KHz = 200 channels.

23. Traffic = 1200 × 4 × 2.5 × 60 = 200 channels.

24. Users = 40 MHz ÷ 400 KHz = 100 users.

25. Capacity = 1200 × 600 = 720,000 users.

Paging rounds = 200 ÷ 4 = 50 rounds.

27. Blocking = (120,000 - 100,000) ÷ 120 000 x 100 = 16.67 %

28. Roaming users = 600,000 x 15 % = 90,000 Subscribers

29. utilization = 9000 ÷ 12,000 x 100 = 75 %

30. channels Per cell = 48 MHz ÷ 200 KHz ÷ 4 = 60 channels

31. channels = 30 MHz ÷ 200 KHz = 150 channels.

32. Successful handoffs = 2500 x 99 % = 2475

33. Received Power = 10 $\log_{10}$ (12,000) - 45 = -4.21 dBm

34. Capacity = 900 x 7 = 6300 users

35. Slot duration = 4.8 ms ÷ 8 = 0.6 ms

36 Doppler shift = Vf/c = 150 km/h / 1.8 GHz = 250 Hz.

37. Blocking = (280,000 - 250,000) ÷ 280,000 x 100 = 10.71 %

38. Capacity = 600 x 9 = 5400 users.

39. dropped calls = 60,000 x 0.4 % = 240 calls /second

40. Path load = 43 - (-87) = 130 dB.

41. Coverage = 2.5 x 150 = 375 km^2

42. channels Per cell = 48 MHz ÷ 200 KHz ÷ 6 = 40 channels

43. Paging cycles = 150 00 ÷ 6000 = 25 cycles.

44. Handoffs = 9 ÷ 3 = 3 handoffs

45. SNR = -85 - (-115) = 30 dB.

46. Required data rate = 250 × 150 = 37.5 mbps.

47. Traffic = 1500 × 4 × 2.5 ÷ 60 = 250 Earlangs

48. Bandwidth = 250 × 12 kHz = 3 MHz

49. Through Put = 1500 × 600 kps = 900 mbps.

50. Towers = 350 ÷ ($\pi \times 4^2$) ≃ 6.96 = 7 towers.