

Temperature and Humidity Sensor SHTC3 Breakout

SKU 333032



What it is

The SHTC3 breakout board precisely measures temperature and humidity, featuring easy I2C connectivity and low power consumption.

Key specifications

Measurement

Measurement Types	Temperature, Humidity
Measurement Range	Temperature -40 to 125°C; Humidity 0 to 100 %RH
Measurement Accuracy	Temperature $\pm 0.2^{\circ}\text{C}$; Humidity $\pm 2\%$ RH

Interface

Interface	I2C
qwiic Compatible	Yes
I2C Address Default	0x70
I2C Address Changeable	No
Breadboard Compatible	Yes

Power

Supply Voltage	3.3–5 V
Logic Level	3.3 V or 5 V
Operating Current	0.478 mA
Sleep Current	0.3 μA

Other

IC Part Number	SHTC3
----------------	-------

Typical applications

The SHTC3 Breakout gives you a compact temperature and humidity sensor with a qwiic-compatible I2C connector. It fits into environmental sensing, HVAC monitoring and smart home prototypes where accurate air measurements matter and you want to avoid soldering a sensor directly to the board.

What's in the box

- 1 × Temperature and Humidity Sensor SHTC3 Breakout (main product)
- 1 × Header pins (unsoldered) — Header pins included for all breadboard-compatible pins

Resources

Technical Resources

Hardware Details [WEB](#)

Documentation

Full Documentation [DOCS](#)

Software Resources

Arduino Library [GITHUB](#) · Arduino: Get Started [DOCS](#) · MicroPython Module [GITHUB](#)