

Pre-Event Checklist

For the organizer, the week before. Both network profiles.

Both profiles

- & Kit packed: 2 StickIt boxes (one spare), power supplies, Ethernet cable, USB backup stick (ExFAT, named STICKITSNAP — see below), printed run sheets 1–5 + judges' stand card.
- & StickIt box software updated at home: plug in, open stickit.local:3001, click Update StickIt (only shows when no meet is loaded).
- & Meet fully built on stickitski.com: events, registrations, judges, run orders, course specs.
- & Plan for the release code: who releases the meet, and how the code reaches the venue (phone / written down).

Backup stick (one-time, on a Mac)

- & Any USB stick. Open Disk Utility, select the stick itself (not the volume under it), click Erase.
- & Name: STICKITSNAP (exactly that — 11 characters, capitals, no hyphen; the Mac refuses a longer name).
- & Format: ExFAT. Scheme: Master Boot Record. Click Erase. ExFAT is the only supported format — do not use Mac OS Extended, APFS or ext4.
- & Plug it into the StickIt box before the event. The home screen stops warning about the stick within a minute; snapshots land on it every 5 minutes.

UniFi venue (primary)

- & DHCP reservation for the Pi confirmed in the UniFi console (permanent IP, e.g. 192.168.1.50).
- & YoloBox already has the overlay URL stored in fixed-IP form — no changes expected.

Starlink Gen 3 built-in router venue (RQS / Devo)

- & Pi plugs into one of the router's two built-in Ethernet LAN ports.
- & The numeric IP can occasionally change: verify the YoloBox overlay URL against Connection Info each event morning (it is on Run Sheet 4).
- & iPads use http://stickit.local:3001 (name, not number) — unaffected by IP changes.

