Cloud Outage Runbook: RAG Platform

1. Service levels

The customer-facing RAG API has a recovery time objective (RTO) of 30 minutes and a recovery point objective (RPO) of 15 minutes. The monthly availability objective is 99.5 percent.

An outage is declared when more than 5 percent of requests fail for three consecutive minutes.

2. Provider failover

Generation uses Groq as the primary provider and Google Gemini as the secondary provider. Error code ERR-LLM-504 means the primary LLM provider timed out after 30 seconds.

After three consecutive provider failures the circuit breaker opens for 60 seconds and all traffic moves to the secondary provider. If both providers fail, the service returns an extractive answer built from the retrieved passages instead of an error.

3. Communication

During an incident the status page is updated every 20 minutes by the incident commander.

A written postmortem must be published within 5 business days of resolution and must include a timeline, root cause, and at least one preventive action.