Google Blockly積木撰寫

WBBIT教育版&BLOCKLYDUINO

講師：鳳山科技中心 傅仲儀主任

2020/8/20

自訂積木撰寫課程表

08:30-10:00 自訂積木安裝與架構說明
10:00-11:30 Blockly Developer Tools
11:30-12:00 多國語系製作
13:00-13:30 javascript.js常用技巧
13:30-15:30 自訂積木實作

研習講義與檔案下載

PDF簡報檔
https://github.com/fustyles/Workshop/blob/master/Webbit教育版&Blockduino自訂積木撰寫.pdf

PPT簡報檔
https://drive.google.com/drive/folders/1Q6I_saFnBYjrw_sCDfQ59W6mjEUI_zd2

上課檔案
https://github.com/fustyles/Workshop/blob/master/2020.8.19_blockly.zip

Google Blockly 學習資源

Blockly |Google Developers
https://developers.google.com/blockly

Blockly討論區
https://groups.google.com/g/blockly

Blockly函式庫
https://developers.google.com/blockly/reference/overview

Blockly原始碼離線包
https://github.com/google/blockly/zipball/master

Webduino官方撰寫積木教學文件
https://www.facebook.com/groups/webduino/permalink/1536223946446669/

Javascript 學習資源

免費編輯軟體 Notepad++
https://notepad-plus-plus.org/downloads/

Javascript 編輯器介紹
https://kknews.cc/zh-tw/code/nanm2ng.html
https://www.temok.com/blog/top-20-javascript-ide-source-code-editors/

JavaScript 教學文件
https://www.w3schools.com/js/

JavaScript Online Editor
https://www.w3schools.com/js/tryit.asp?filename=tryjs_myfirst

*C:\Users\fsm\Desktop\109.8.19自訂積木研習\LinkIt_customBlocks\package.nw\myBlocks\blocks.js - Notepad++

檔案(F) 編輯(E) 搜尋(S) 檢視(V) 編碼(N) 語言(L) 設定(T) 工具(O) 巨集(M) 執行(R) 外掛(P) 視窗(W) ?

資料夾工作區

- 109.8.19自訂積木研習
  - LinkIt_customBlocks
    - package.nw
      - js
      - myBlocks
        - blocks.js
        - en.js
        - en_category.xml
        - javascript.js
        - toolbox.xml
        - zh-hant.js
        - zh-hant_category.xml
    - LinkIt7697新增自訂積木說明.txt
  - Webbit_customBlocks
    - package.nw
      - blockly
      - myBlocks
    - Webbit教育版自訂積木批次檔安裝
    - Webbit教育版新增自訂積木說明.txt
    - 下拉圖檔選單範例.txt
    - 官方自訂積木模組開發說明.pdf
  - ~$傅仲儀教師-Webbit教育版&Blockduino自訂積木撰寫.pptx
  - blocklyjson.png
  - blocksjs.png
  - javascript1js.png
  - javascriptjs.png
  - library.xml
  - toolbox1xml.png
  - toolboxxml.png
  - 傅仲儀教師-Webbit教育版&Blockduino自訂積木撰寫.pptx

blocks.js

```
1  Blockly.Blocks['digitalwrite'] = {
2    init: function() {
3      this.appendDummyInput()
4          .appendField(Blockly.Msg.digitalWrite);
5      this.appendValueInput("pin")
6          .setCheck("Number")
7          .appendField("(");
8      this.appendDummyInput()
9          .appendField(",")
10         .appendField(new Blockly.FieldDropdown([["HIGH","1"], ["LOW","0"]]), "mode")
11         .appendField(")");
12     this.setInputsInline(true);
13     this.setPreviousStatement(true, null);
14     this.setNextStatement(true, null);
15     this.setColour(255);
16     this.setTooltip("digitalWrite(pin, value)");
17     this.setHelpUrl("https://www.arduino.cc/reference/en/language/functions/digital-io/digitalwrite/");
18   }
19 };
20
21 Blockly.Blocks['digitalread'] = {
22   init: function() {
23     this.appendDummyInput()
24         .appendField(Blockly.Msg.digitalRead);
25     this.appendValueInput("pin")
26         .setCheck("Number")
27         .appendField("(");
28     this.appendDummyInput()
29         .appendField(")");
30     this.setInputsInline(true);
31     this.setOutput(true, "Number");
32     this.setColour(60);
33     this.setTooltip("digitalRead(pin)");
34     this.setHelpUrl("https://www.arduino.cc/reference/en/language/functions/digital-io/digitalread/");
35   }
36 };
```

JavaScript file | length : 1,201 lines : 36 | Ln : 20 Col : 1 Sel : 0 | 0 | Unix (LF) | UTF-8 | INS

Webduino自訂積木撰寫

Webbit教育版安裝

- 下載網址：Google搜尋“WebBitSetup.exe”

  離線版：https://ota.webduino.io/WebBitInstaller/WebBitSetup.exe

  網頁版：https://webbit.webduino.io/blockly/ (無法使用USB連線)
- 驅動程式：http://www.wch.cn/download/CH341SER_ZIP.html

  (離線版安裝已內建驅動程式)
- 更新韌體：離線版接上Webbit後可自動偵測線上更新

Webbit教育版新增自訂積木(法一)

將資料夾Webbit_customBlocks\package.nw覆蓋至
C:\Webduino\WebBit\ package.nw



開啟目錄 C:\Webduino\WebBit\package.nw\blockly\toolbox\index.xml 編輯新增「進階 catPlus」程式碼，可將自訂積木設定掛載在此目錄下。

<category id="catPlus" COLOUR="190" index="99"></category>

```
    <category id="catPin" COLOUR="50">
      <block type="pin_read_digital"></block>
      <block type="pin_read_analog"></block>
      <block type="pin_write_analog">
        <value name="value_">
          <block type="math_number">
            <field name="NUM">0</field>
          </block>
        </value>
      </block>
      <block type="pin_write_digital">
        <value name="value_">
          <block type="math_number">
            <field name="NUM">0</field>
          </block>
        </value>
      </block>
    </category>
  </category>
  <sep></sep>
  <category id="catPlus" COLOUR="190" index="99"></category>
  <category id="catEduExtension" COLOUR="290" index="99"></category>
</xml>
```

新增catPlus目錄

「以瀏覽器開啟」利於自訂積木撰寫與除錯，且AI影像辨識積木才可正常執行。

Web:Bit 教育版

積木 程式碼

檔案 範例 擴充 教學 清空 更多 執行

- 顏色
- 函式
- 怪獸控制
- 偵測
- 語音&音效
- Web:Bit –
- 開發板
- 矩陣 LED
- 按鈕開關
- 偵測光線&溫度
- 音樂&聲音
- 九軸體感偵測
- I/O 引腳
- 擴充功能 –
- Google 試算表
- 氣象資訊
- 網路廣播
- LINE
- 基礎套件包
- MoonCar 自走車

自訂積木 “ ”

當紅外線 (腳位 1) 接收到訊號
執行

紅外線接收的代碼

紅外線發射 (腳位 2) , 發射代碼 (十六進位) “ ”

超音波傳感器 , Trig 3 Echo 9 所擷取的距離 (公分)

伺服馬達 , 腳位 1 旋轉角度 (0-180) 90



下午 11:04
2019/11/12

填入自訂積木連結下拉選單點選add，或點選addAll新增所有自訂積木。
https://github.com/fustyles/webduino/blob/master/CustomBlock.txt



Webbit教育版新增自訂積木(法二)



指令參考： https://github.com/fustyles/webduino/blob/master/EDU_addCustomBlocks/blockly/blocks.js

Webbit教育版新增自訂積木(法三)



Webduino檔案架構(雲端平台、教育版、Kebbi)



Webduino自訂積木架構

myBlocks自訂積木連結

http://localhost:20975/myBlocks/blockly.json

Blockly.json (Webbit) 自訂積木佈署檔

```
{
  "types": ["digitalwrite", "digitalread"],
  "category": "catPlus",
  "scripts": [
    "blockly/blocks.js",
    "blockly/javascript.js"
  ],
  "dependencies": [
    "myBlocks.js"
  ],
  "msg": "blockly/msg",
  "blocksMsg": "blockly/msg/blocks",
  "toolbox": "blockly/toolbox.xml"
}
```

自訂積木id列表。執行程式前會檢查是否使用到列表中的積木則載入"dependencies"下的檔案。

自訂積木掛載主目錄id

自訂積木定義檔 (Blockly Developer Tools產出)

自訂積木產出原始碼變數檔 (Blockly Developer Tools產出)

執行程式時載入對應javascript.js產出的函式的自訂js函式庫

自訂積木目錄名稱語系檔en.js(英文), zh-hans.js(簡中), zh-hant.js(繁中)

自訂積木文字語系檔en.js(英文), zh-hans.js(簡中), zh-hant.js(繁中)

自訂積木目錄配置檔 (Blockly Developer Tools產出)

Blockly Developer Tools (Block Factory)

Blockly Developer Tools (匯出blocks.js, javascript.js, toolbox.xml)
https://blockly-demo.appspot.com/static/demos/blockfactory/index.html

使用教學
https://developers.google.com/blockly/guides/create-custom-blocks/blockly-developer-tools

教學影片
https://www.youtube.com/watch?time_continue=705&v=s2_xaEvcVI0&feature=emb_logo

Blockly > Demos > Blockly Developer Tools

Help

Block Factory | Block Exporter | Workspace Factory

Block Library

Update "digitalwrite" | Delete "digitalwrite"

Clear Library | Import Block Library | Download Block Library

Input
Field
Type
Colour

name digitalWrite
inputs
dummy input
fields left text digitalWrite
value input pin
fields left text (
type Number
dummy input
fields left text ,
dropdown mode
• HIGH , 1
• LOW , 0
text)
inline inputs
top+bottom connections
tooltip " digitalWrite(pin, value) "
help url " https://www.arduino.cc/reference/en/language/fun..
top type

Preview: LTR

digitalWrite (, HIGH)

Block Definition: JavaScript

```
Blockly.Blocks['digitalwrite'] = {
  init: function() {
    this.appendDummyInput()
        .appendField("digitalWrite");
    this.appendValueInput("pin")
        .setCheck("Number")
        .appendField("(");
    this.appendDummyInput()
```

Generator stub: JavaScript

```
Blockly.JavaScript['digitalwrite'] = function(block) {
  var value_pin = Blockly.JavaScript.valueToCode(block, 'pin', Blockly.JavaScript.ORDER_ATOMIC
  var dropdown_mode = block.getFieldValue('mode');
  // TODO: Assemble JavaScript into code variable.
  var code = '...;\n';
  return code;
};
```

Blockly > Demos > Blockly Developer Tools

Help

Block Factory | Block Exporter | Workspace Factory

First, select blocks from your block library by clicking on them. Then, use the Export Settings form to download starter code for selected blocks.

Block Selector

Select | Clear Selected



☑ digitalwrite

☑ digitalread

Export Settings

Currently Selected:

digitalwrite, digitalread

☑ Block Definition(s)
Format: JavaScript
File Name: blocks

☑ Generator Stub(s)
Language: JavaScript
File Name: javascript

Export

Export Preview

Block Definitions:

```
Blockly.Blocks['digitalwrite'] = {
  init: function() {
    this.appendDummyInput()
        .appendField("digitalWrite");
    this.appendValueInput("pin")
        .setCheck("Number")
        .appendField("(");
    this.appendDummyInput()
        .appendField(",")
        .appendField(new Blockly.FieldDropdown([["HIGH","1"], ["LOW","0"]]), "moc
```

Generator Stubs: 若是BlocklyDuino頻將程式碼中"Javascript"全部取代為"Arduino"

```
Blockly.JavaScript['digitalwrite'] = function(block) {
  var value_pin = Blockly.JavaScript.valueToCode(block, 'pin', Blockly.JavaScript
  var dropdown_mode = block.getFieldValue('mode');
  // TODO: Assemble JavaScript into code variable.
  var code = '...;\n';
  return code;
};

Blockly.JavaScript['digitalread'] = function(block) {
  var value_pin = Blockly.JavaScript.valueToCode(block, 'pin', Blockly.JavaScript
```

Blockly > Demos > Blockly Developer Tools

Help

Block Factory | Block Exporter | Workspace Factory

Import Custom Blocks | Load to Edit | Export | Clear

Starter Code
Toolbox
Workspace Blocks
All

匯出 toolbox.xml

Edit

Drag blocks into the workspace to c…our custom workspace.

Toolbox | Workspace

- Logic
- Loops
- Math
- Text
- Lists
- Colour
- Variables
- Functions
- Block Library

拉出

digitalWrite (2 , HIGH)

digitalRead (2)

You currently have no categories.

+ - ↑ ↓

Edit Category...

Make Shadow

Preview

This is what your custom workspace will look like.

digitalWrite (2 , HIGH)

digitalRead (2)

積木定義檔 blocks.js (WebBit)

```
Blockly.Blocks['digitalwrite'] = {
  init: function() {
    this.appendDummyInput()
        .appendField(Blockly.Msg.digitalWrite);
    this.appendValueInput("pin")
        .setCheck("Number")
        .appendField("(");
    this.appendDummyInput()
        .appendField(",")
        .appendField(new Blockly.FieldDropdown([["HIGH","1"], ["LOW","0"]]), "mode")
        .appendField(")");
    this.setInputsInline(true);
    this.setPreviousStatement(true, null);
    this.setNextStatement(true, null);
    this.setColour(255);
    this.setTooltip("digitalWrite(pin, value)");
    this.setHelpUrl("https://www.arduino.cc/reference/en/language/functions/digital-io/digitalwrite/");
  }
};
```

動態語系文字

自訂名稱

固定文字

數值輸入

固定文字

選單文字 值 選單文字 值

下拉選單

固定文字

輸出指令

不換行顯示

積木顏色

myBlocks\blockly\msg\blocks\en.js
Blockly.Msg.digitalWrite = "Digital Write";
myBlocks\blockly\msg\blocks\zh-hant.js
Blockly.Msg.digitalWrite = "數位輸出";

digitalWrite(pin, value)



輸出值

```
this.setOutput(true, "Number");
```

程式碼產出檔 javascript.js (WebBit)

```
Blockly.JavaScript['digitalwrite'] = function(block) {
  var value_pin = Blockly.JavaScript.valueToCode(block, 'pin', Blockly.JavaScript.ORDER_ATOMIC);
  var dropdown_mode = block.getFieldValue('mode');

  var code = 'digitalWrite('+value_pin+', '+dropdown_mode+');\n';
  return code;
};
```

值輸入

下拉選單

換行

程式碼變數 (尾端加 ;\n)

輸出指令

一般要加上雙引號

"'+dropdown_mode+'"


```
digitalWrite(2, 1);
```

```
myBlocks.js 自訂JS函式庫
function digitalWrite(pin, val) {
    var url = "http://192.168.1.100/?digitalwrite="+pin+";"+val;
    console.log(url);
    fetch(url);
}
```

```
Blockly.JavaScript['digitalread'] = function(block) {
  var value_pin = Blockly.JavaScript.valueToCode(block, 'pin', Blockly.JavaScript.ORDER_ATOMIC);

  var code = 'digitalRead('+value_pin+')';
  return [code, Blockly.JavaScript.ORDER_NONE];
};
```

值輸入

程式碼變數 (尾端不加 ;\n)

輸出值


```
digitalRead(2);
```

```
myBlocks.js 自訂JS函式庫
function digitalRead(pin) {
    var url = "http://192.168.1.100/?digitalread="+pin;
    console.log(url);
    return url;
}
```

目錄結構檔 toolbox.xml (Webbit) 對應id

```
<category id="myBlocks" name="myBlocks">
```
主目錄

子目錄1

```
  <category id="myCategory1" name="myCategory1">
    <block type="digitalwrite">
      <field name="mode">1</field>
      <value name="pin">
        <block type="math_number">
          <field name="NUM">2</field>
        </block>
      </value>
    </block>
    <block type="digitalread">
      <value name="pin">
        <block type="math_number">
          <field name="NUM">2</field>
        </block>
      </value>
    </block>
  </category>
```

myBolck\blockly\msg\en.js

```
MSG.myBlocks = "My Blocks";
MSG.myCategory1 = "Category 1";
MSG.myCategory2 = "Category 2";
```

子目錄2

```
  <category id="myCategory2" name="myCategory2">
    <block type="digitalread">
      <value name="pin">
        <block type="math_number">
          <field name="NUM">2</field>
        </block>
      </value>
    </block>
    <block type="digitalwrite">
      <field name="mode">1</field>
      <value name="pin">
        <block type="math_number">
          <field name="NUM">2</field>
        </block>
      </value>
    </block>
  </category>
```

myBolck\blockly\msg\zh-hant.js

```
MSG.myBlocks = "我的積木";
MSG.myCategory1 = "目錄 1";
MSG.myCategory2 = "目錄 2";
```

```
</category>
```

自訂JS函式庫 myBlocks.js (Webbit)

```
+(function (window, document) {

   'use strict';

  function digitalWrite(ip, pin, val) {
          var url = "http://"+ip+"/?digitalwrite="+pin+";"+val;
          console.log(url);
          fetch(url);
  }

  function digitalRead(pin) {
          var url = "http://192.168.1.100/?digitalread="+pin;
          console.log(url);
          return url;
  }

   window.digitalWrite = digitalWrite;
   window.digitalRead = digitalRead;
   新增函式要對應新增此行程式碼
}(window, window.document));
```

Javascript.js常用技巧 (Webbit)

xmlHttp取得XML資料與AJAX取得跨網域資料
https://github.com/fustyles/webduino/blob/master/AirQuality_Taiwan_20180121/AirQualityTaiwan.js
遊戲元素自訂積木原始碼解說
https://github.com/fustyles/webduino/blob/master/GameElements_20190131/blockly/javascript.js
新增遊戲元素積木指令
https://github.com/fustyles/webduino/blob/master/EDU_addCustomBlocks/blockly/blocks.js



下拉圖檔選單 (Webbit)

```
//圖檔位置 C:\Webduino\WebBit\package.nw\blockly\media
var monsterList = [
  ['{"src":"media/demo-edu-a1-s.png", "width":"30", "height":"42", "title":"HIGH", "showTitle":"true"}', '1'],
  ['{"src":"media/demo-edu-a4-s.png", "width":"30", "height":"42", "title":"LOW", "showTitle":"true"} ', '0']
];
```

神奇的空格

```
Blockly.Blocks['digitalwrite'] = {
  init: function() {
    this.appendDummyInput()
        .appendField(Blockly.Msg.digitalWrite);
    this.appendValueInput("pin")
        .setCheck("Number")
        .appendField("(");
    this.appendDummyInput()
        .appendField(",")
        .appendField(new Blockly.FieldDropdown(monsterList), "mode")
        .appendField(")");
    this.setInputsInline(true);
    this.setPreviousStatement(true, null);
    this.setNextStatement(true, null);
    this.setColour(255);
    this.setTooltip("digitalWrite(pin, value)");
    this.setHelpUrl("https://www.arduino.cc/reference/en/language/functions/digital-io/digitalwrite/");
  }
};
```

BlocklyDuino自訂積木撰寫

BlocklyDuino v3 Beta 5

下載網址：https://github.com/MediaTek-Labs/BlocklyDuino-for-LinkIt/releases/tag/3.0.312b

64位元 blocklyduino-3.0.312b-win64-ide.zip

32位元 blocklyduino-3.0.312b-win32-ide.zip

使用指南：https://docs.labs.mediatek.com/linkit-7697-blocklyduino/linkit-7697-blocklyduino-12879411.html

吉哥積木：https://sites.google.com/jes.mlc.edu.tw/ljj/linkit7697/如何安裝吉哥自製積木

ICSHOP：https://github.com/iCShopMgr/LinkIt7697_Bit_for_BlocklyDuino

法蘭斯積木：https://github.com/fustyles/webduino/tree/master/LinkIt7697/FranceFu

BlocklyDuino自訂積木架構



自訂積木本機連結

./myBlocks/blockly.json

BlocklyDuino自訂積木安裝



BlocklyDuino手動插入新增自訂積木程式碼避免覆蓋其他自訂積木設定

將程式碼區塊複製插入在BlocklyDuino3\package.nw\js\init.js檔此行程式碼之前

Blockly.inject(document.getElementById('content_blocks'),{



積木定義檔 blocks.js (Blocklyduino)

```
Blockly.Blocks['digitalwrite'] = {
  init: function() {
    this.appendDummyInput()
        .appendField(Blockly.Msg.digitalWrite);
    this.appendValueInput("pin")
        .setCheck("Number")
        .appendField("(");
    this.appendDummyInput()
        .appendField(",")
        .appendField(new Blockly.FieldDropdown([["HIGH","1"], ["LOW","0"]]), "mode")
        .appendField(")");
    this.setInputsInline(true);
    this.setPreviousStatement(true, null);
    this.setNextStatement(true, null);
    this.setColour(255);
    this.setTooltip("digitalWrite(pin, value)");
    this.setHelpUrl("https://www.arduino.cc/reference/en/language/functions/digital-io/digitalwrite/");
  }
};
```

動態語系文字

自訂名稱

固定文字

數值輸入

固定文字

選單文字 值　選單文字 值

下拉選單

輸出指令

不換行顯示

積木顏色

en.js

Blockly.Msg.digitalWrite = "Digital Write";

zh-hant.is

Blockly.Msg.digitalWrite = "數位輸出";

digitalWrite(pin, value)

輸出值

```
this.setOutput(true, "Number");
```

程式碼產出檔 javascript.js (Blocklyduino)

```
Blockly.JavaScript['digitalwrite'] = function(block) {
  var value_pin = Blockly.JavaScript.valueToCode(block, 'pin', Blockly.JavaScript.ORDER_ATOMIC);
  var dropdown_mode = block.getFieldValue('mode');

  var code = 'digitalWrite('+value_pin+', '+dropdown_mode+');\n';
  return code;
};
```


```
digitalWrite(2, 1);
```

Arduino函式庫

將Blockly Developer Tools 產生的程式碼所有"Javascript"取代為"Arduino"

```
Blockly.Arduino['digitalwrite'] = function(block) {
  var value_pin = Blockly.Arduino.valueToCode(block, 'pin', Blockly.Arduino.ORDER_ATOMIC);
  var dropdown_mode = block.getFieldValue('mode');

  var code = 'digitalWrite('+value_pin+', '+dropdown_mode+');\n';
  return code;
};
```


```
digitalRead(2);
```

Arduino函式庫

目錄結構檔 toolbox.xml (BlocklyDuino) 對應name

檔案en_category.xml、zh-hant_category.xml 內容暫時不可換行排列，請參照範例檔內容。

主目錄

```
<category id="myBlocks" name="myBlocks">
```

子目錄1

```
<category id="myCategory1" name="myCategory1">
  <block type="digitalwrite">
    <field name="mode">1</field>
    <value name="pin">
      <block type="math_number">
        <field name="NUM">2</field>
      </block>
    </value>
  </block>
  <block type="digitalread">
    <value name="pin">
      <block type="math_number">
        <field name="NUM">2</field>
      </block>
    </value>
  </block>
</category>
```

子目錄2

```
<category id="myCategory2" name="myCategory2">
  <block type="digitalread">
    <value name="pin">
      <block type="math_number">
        <field name="NUM">2</field>
      </block>
    </value>
  </block>
  <block type="digitalwrite">
    <field name="mode">1</field>
    <value name="pin">
      <block type="math_number">
        <field name="NUM">2</field>
      </block>
    </value>
  </block>
</category>
```

```
</category>
```

en_category.xml

```
<xml>

  <category>
    <name>myBlocks</name>
    <replace>My Blocks</replace>
  </category>

  <category>
    <name>myCategory1</name>
    <replace>Category 1</replace>
  </category>

  <category>
    <name>myCategory2</name>
    <replace>Category 2</replace>
  </category>

</xml>
```

en_category.xml

```
<xml>

  <category>
    <name>myBlocks</name>
    <replace>我的積木</replace>
  </category>

  <category>
    <name>myCategory1</name>
    <replace>目錄 1</replace>
  </category>

  <category>
    <name>myCategory2</name>
    <replace>目錄 2</replace>
  </category>

</xml>
```

自訂積木所需新增函式庫置放目錄(BlocklyDuino)



package.nw\js\Init.js檔編輯新增數個自訂積木 (BlocklyDuino)

法蘭斯自訂積木

```
var blocks_path = "https://fustyles.github.io/webduino/LinkIt7697/FranceFu/blocks.js";
var javascript_path = "https://fustyles.github.io/webduino/LinkIt7697/FranceFu/javascript.js";
var toolbox_path = "https://fustyles.github.io/webduino/LinkIt7697/FranceFu/toolbox.xml";
var en_path = "https://fustyles.github.io/webduino/LinkIt7697/FranceFu/en.js";
var en_category_path = "https://fustyles.github.io/webduino/LinkIt7697/FranceFu/en_category.xml";
var zhhant_path = "https://fustyles.github.io/webduino/LinkIt7697/FranceFu/zh-hant.js";
var zhhant_category_path = "https://fustyles.github.io/webduino/LinkIt7697/FranceFu/zh-hant_category.xml";

initial(blocks_path, javascript_path, toolbox_path);
```

可重複新增此區塊程式碼設定自訂積木路徑載入多個自訂積木

我的自訂積木

```
var blocks_path = "./myBlocks/blocks.js";
var javascript_path = "./myBlocks/javascript.js";
var toolbox_path = "./myBlocks/toolbox.xml";
var en_path = "./myBlocks/en.js";
var en_category_path = "./myBlocks/en_category.xml";
var zhhant_path = "./myBlocks/zh-hant.js";
var zhhant_category_path = "./myBlocks/zh-hant_category.xml";

initial(blocks_path, javascript_path, toolbox_path);
```



自訂積木路徑設定 (BlocklyDuino)

開啟package.nw\js\init.js編輯將本機路徑修改成遠端路徑

本機路徑

```
var blocks_path = "./myBlocks/blocks.js";
var javascript_path = "./myBlocks/javascript.js";
var toolbox_path = "./myBlocks/toolbox.xml";
var en_path = "./myBlocks/en.js";
var en_category_path = "./myBlocks/en_category.xml";
var zhhant_path = "./myBlocks/zh-hant.js";
var zhhant_category_path = "./myBlocks/zh-hant_category.xml";
```

遠端路徑

```
var blocks_path = "https://xxx.xxx.xxx.xxx/myBlocks/blocks.js";
var javascript_path = "https://xxx.xxx.xxx.xxx/myBlocks/javascript.js";
var toolbox_path = "https://xxx.xxx.xxx.xxx/myBlocks/toolbox.xml";
var en_path = "https://xxx.xxx.xxx.xxx/myBlocks/en.js";
var en_category_path = "https://xxx.xxx.xxx.xxx/myBlocks/en_category.xml";
var zhhant_path = "https://xxx.xxx.xxx.xxx/myBlocks/zh-hant.js";
var zhhant_category_path = "https://xxx.xxx.xxx.xxx/myBlocks/zh-hant_category.xml";
```

javascript.js實用技巧 (BlocklyDuino)

置於程式碼最上方

```
Blockly.Arduino.definitions_['自訂名稱'] = '#include <函式庫名稱.h>';
```

取得目前Setup(){} 區塊內程式碼

```
var statements_setup = Blockly.Arduino.statementToCode(block, 'setup');
```

取得目前loop(){} 區塊內程式碼

```
var statements_loop = Blockly.Arduino.statementToCode(block, 'loop');
```

取得某statements_input區塊內程式碼

```
var statements_custom = Blockly.Arduino.statementToCode(block, 'NAME值');
```

插入程式碼置於Setup(){}區塊內最前方

```
Blockly.Arduino.setups_.manual_add = "pinMode(2, OUTPUT);\n" + statements_setup;
```

插入程式碼置於Setup(){}區塊內最後方

```
Blockly.Arduino.setups_.manual_add = statements_setup + "pinMode(2, OUTPUT);\n" ;
```

進階控制技巧

https://blockly-demo.appspot.com/static/tests/playground.html?dir=ltr&toolbox=test-blocks

法蘭斯自訂積木 (Webduino)

法蘭斯點矩陣
https://fustyles.github.io/webduino/EDU_bit_MatrixLed_20190827/blockly.json

遊戲元素

https://fustyles.github.io/webduino/GameElements_20190131/blockly.json

Javascript 指令擴充
https://fustyles.github.io/webduino/Instruction_20181213/blockly.json

朗讀語言擴充

https://fustyles.github.io/webduino/EDU_speak_setting/blockly.json

監看程式碼 (首頁開啟開發人員工具 http://localhost:20975/blockly/)

https://fustyles.github.io/webduino/ShowCode_20181216/blockly.json

姿態辨識 (tfjs posenet)
https://fustyles.github.io/webduino/posenet_20190822/blockly.json

物件辨識(tfjs mobilenet)
https://fustyles.github.io/webduino/mobilenet_20190821/blockly.json

物件辨識(tfjs coco-ssd)
https://fustyles.github.io/webduino/coco-ssd_20190821/blockly.json

臉部偵測 (tfjs face-api.js)
https://fustyles.github.io/webduino/faceapi_20200124/blockly.json

臉部辨識 (tfjs face-api.js)
https://fustyles.github.io/webduino/faceapi_20200402/blockly.json

深度學習 (tfjs KNN-Classifier)
https://fustyles.github.io/webduino/knn-classifier_20190608/blockly.json

語音辨識
https://fustyles.github.io/webduino/SpeechRecognition_20191225/blockly.json

圖像分割 (tfjs deeplab)
https://fustyles.github.io/webduino/deeplab_20200125/blockly.json

身體偵測 (tfjs bodypix2)
https://fustyles.github.io/webduino/bodypix2_20200125/blockly.json

身體偵測 (tfjs bodypix1)
https://fustyles.github.io/webduino/bodypix1_20200125/blockly.json

人臉偵測 (Tracking.js)
https://fustyles.github.io/webduino/Tracking_20190917/blockly.json

顏色偵測 (Tracking.js)
https://fustyles.github.io/webduino/Tracking_20200625/blockly.json

手勢偵測 (tfjs handpose)
https://fustyles.github.io/webduino/handpose_20200614/blockly.json

臉部網格偵測 (tfjs facemesh)
https://fustyles.github.io/webduino/Facemesh_20200626/blockly.json

臉部偵測 (tfjs brazeface)
https://fustyles.github.io/webduino/Blazeface_20200627/blockly.json

機械學習 (tfjs Machine Learning)
https://fustyles.github.io/webduino/teachablemachine_20200729/blockly.json

文字偵測 (tesseract.js)
https://fustyles.github.io/webduino/tesseract.js_20200615/blockly.json

Line Bot
https://fustyles.github.io/webduino/LineBot_20181027/blockly.json

Telegram Bot
https://fustyles.github.io/webduino/Telegram_20200809/blockly.json

物件辨識(Microsoft Azure Custom Vision)
https://fustyles.github.io/webduino/Azure_ClassifyImage_20190901/blockly.json

物件辨識(Microsoft Azure Custom Vision + TFJS)
https://fustyles.github.io/webduino/Azure_customvision-tfjs_20200128/blockly.json

臉部辨識(Microsoft Azure Face API – Face Detect)
https://fustyles.github.io/webduino/Azure_FaceDetection_20190901/blockly.json

尋找相似臉(Microsoft Azure Face API - Find Similar Face)
https://fustyles.github.io/webduino/Azure_FaceFindSimilar_20191117/blockly.json

驗證同一人(Microsoft Azure Face API API – Verify Face To Face)
https://fustyles.github.io/webduino/ Azure_FaceToFaceVerify_20191118/blockly.json

ESP32-CAM (雲端平台網址須由https改成http)

https://fustyles.github.io/webduino/ESP32-CAM_20191201/blockly.json

[韌體]

https://github.com/fustyles/Arduino/tree/master/ESP32-CAM_MyBlockly_JSON

WebBit (雲端平台網址須由https改成http)

https://fustyles.github.io/webduino/WebBit_20190225/blockly.json

[韌體]

https://github.com/fustyles/Arduino/blob/master/WebBit_ESP32_MyBlockly_JSON.ino

WiFiBoard (ESP32、LinkIt7697)

https://fustyles.github.io/webduino/ESP8266_20190128/blockly.json

[ESP32韌體]

https://github.com/fustyles/Arduino/blob/master/ESP32_MyBlockly_JSON.ino

[LinkIt7697韌體]

https://github.com/fustyles/Arduino/blob/master/LinkIt7697_MyBlockly_JSON.ino

自訂積木範例 https://github.com/fustyles/webduino

雲端平台搜尋「自訂積木」