altairsim — examples

2026-08-02 · 0c071e7

Machines that boot. Each directory here is self-contained: a `.toml` that describes the machine, the media it needs lying beside it, and a note saying what you will see. Copy any one of them anywhere and it still runs — a path inside a machine file resolves against **that file**, not against the directory you launched from.

```
altairsim examples/cpm/cpm22-buffered.toml     # CP/M 2.2b on an 8" floppy
altairsim examples/basic/basic4k.toml          # Altair 4K BASIC, off a 1975 cassette
altairsim examples/uio/uio.toml                # Altair 8K BASIC over ONE 88-UIO (serial + cassette)
altairsim examples/sol/trek80.toml             # a Sol-20 at SOLOS, with TREK80 in the deck
altairsim examples/debugger/debugger.toml      # a bench for learning the symbolic debugger
altairsim examples/dazzler/kscope.toml         # a Cromemco Dazzler, drawing a kaleidoscope
altairsim examples/printing/printer.toml       # an 88-C700 printer, wired to a real host printer
```

	What it is
`cpm/`	Mike Douglas's track-buffered **CP/M 2.2b v2.3**, 56K, booted by the DBL PROM from an 8" floppy. `A>` in one command.
`basic/`	**Altair 4K BASIC 3.1** (`basic4k.toml`) read off a period `.tap` by the bootstrap MITS shipped, unmodified: `MEMORY SIZE?`. Beside it, **8080 BASIC VER 1.0** (`basic1.toml`) — the first Altair BASIC, 1975 — booted the raw two-step way its primitive bootstrap forced: `RUN 1800`, `^E`, `RUN 0` → `MEMSIZ?`.
`uio/`	**Altair 8K BASIC 3.2** over a single **88-UIO** — the board that is a 6850 serial port (at 0x10) *and* an 88-ACR cassette (at 0x06) in one. The period bootstrap runs unmodified. `MEMORY SIZE?`
`sol/`	A **Processor Technology Sol-20** running SOLOS 1.3, with the 1977 game **TREK80** on cassette. Type `XE TRK80`.
`debugger/`	A 46-byte program with its **symbols** and a guided walk through the monitor's debugger: `SYMBOLS LOAD`, symbolic `DISASM`, single-step, break on a label, run.
`dazzler/`	A **Cromemco Dazzler**, the S-100's first color graphics card, running Li-Chen Wang's **Kaleidoscope**. Comes up drawing a four-way-mirrored pattern in a window; ATTN (Ctrl-E) breaks back to the monitor.
`pmmi/`	A **PMMI MM-103 modem** and a small 8080 **terminal** program that bridges the console to the phone line. Four control keys work the modem — `^D` DTR, `^S` the 6860 Self Test loopback, `^I` modem status, `^C` quit. `^D` then `^S` makes the card echo your keystrokes with no phone line attached; set `dial` / `answer` to place a real call over TCP.
`printing/`	An **88-C700 line printer**, and a banner program that prints through it. The README sets up a real printer on your host — a network printer over `socket:`, or a CUPS queue over `printer:` — and a page comes out. Per-OS host setup (macOS, Linux; Windows pending).

This tree is the product, which is the reason it exists as one directory rather than as media scattered through `disks/` and `tapes/`. It is what `tools/build-package.sh` assembles, it is what `docs/manual/quick-start.md` promises, and `acceptance-examples` boots every one of these out of a scratch directory with no repository in sight — because "does it work here" and "does it work where we hand it to people" turned out to be different questions.

Nothing is duplicated. `disks/` and `tapes/` keep only what does **not** ship: the period `.ASM` listings the boards were built from, download stubs for optional images, and vendor documentation.