

RC2014 Z8 CTC & DS1302 RTC V2
BOARD ADDRESSING
J2=ADDRESS
J3=ADDRESS INVERTED
J4=COMMON

	J2	J4	J3		
A5	0---	0	0		
A6	0---	0	0		
A7	0---	0	0	=	0xE0-0xFF

	J2	J4	J3		
A5	0	0---	0		
A6	0---	0	0		
A7	0---	0	0	=	0xC0-0xDF

	J2	J4	J3		
A5	0---	0	0		
A6	0	0---	0		
A7	0---	0	0	=	0xA0-0xBF

	J2	J4	J3		
A5	0	0---	0		
A6	0	0---	0		
A7	0---	0	0	=	0x80-0x9F

	J2	J4	J3		
A5	0---	0	0		
A6	0---	0	0		
A7	0	0---	0	=	0x60-0x7F

	J2	J4	J3		
A5	0	0---	0		
A6	0---	0	0		
A7	0	0---	0	=	0x40-0x5F

	J2	J4	J3		
A5	0---	0	0		
A6	0	0---	0		
A7	0	0---	0	=	0x20-0x3F

	J2	J4	J3		
A5	0	0---	0		
A6	0	0---	0		
A7	0	0---	0	=	0x00-0x1F