Set #AL 01

Doors: EXT.A1

1	Continuous Hinge(s)	780-112HD x LAR EPT/Prep	CLR	HA
1	Power Transfer(s)	2-679-0623	ALM	HA
~~1~~	~~Exit Device~~	~~QEL-RX-99NL-OP x 110MD-NL~~	~~US26D~~	~~VO~~
1	Exit Device(s)	4501 RIM MLRX FEX	US32D	HA
1	Exit Trim	45NL WTN	US26D	HA
1	Rim Cylinder	3901 SFIC x LAR	US26D	HA
~~1~~	~~Mortise Cylinder(s)~~	~~3902 SFIC x LAR~~	~~US26D~~	~~HA~~
1	Construction Core	3981-BLU	BLU	HA
1	Small Format IC	3981-C	US26D	HA
1	Overhead Stop(s)	7016 SRF	US32D	HA
1	Single Operator	8318 PUSH	ALM	HA
1	Saddle Threshold	404S x LAR	MIL	HA
1	Weatherstrip	By Frame Mfr./Supplier		
1	Sweep(s)	750S N x LAR	CLR	HA
1	Door Position Switch(es)	2-679-0626		HA
~~1~~	~~Actuator~~	~~8228-02H/06~~	~~US32D~~	~~HA~~
1	Vertical Bar Actuator	8288 04H/00	US32D	HA
~~1~~	~~Reader/Keypad~~	~~By Security Provider~~		
1	HS4 Wall Reader	WRDB0A4W0		HO
~~1~~	~~Power Supply~~	~~2908/2909/2910/2911 As Required~~	~~No Finish~~	~~HA~~
1	Power Supply	See MISC Set		
1	Intercom	By Others		
1	Wiring Diagrams	Wiring Diagrams		

Operational Description:

Door is normally closed and locked.
Valid credential or signal from the intercom system allows entry ~~- valid card~~ and engages the auto operator to open the door.
Free egress at all times by manual means or pushing the actuator to engage the operator.
Door is to remain closed and locked and the operator is disabled upon loss of power.
Door is monitored by the access control system.

Set #01

Doors: 110.B7, STR2.B7, STR3.B7

3	Hinge(s)	BB1199 4 1/2" x 4 1/2" NRP	US32D	HA
1	Power Transfer	2-679-0623	ALM	HA
~~1~~	~~Exit Device~~	~~99L-NL-F x 996L-NL-R&V~~	~~US26D~~	~~VO~~
1	Exit Device	4501 RIM RX FEC	US32D	HA
1	Electrified Trim	45ET WTN	US26D	HA
1	Mortise Cylinder(s)	3902 SFIC x LAR	US26D	HA
1	Construction Core	3981-BLU	BLU	HA
1	Small Format IC	3981-C	US26D	HA
1	Overhead Stop(s)	7016 SRF	US32D	HA
1	Drop Plate	5110 Top Jamb Mount	ALM	HA
1	Closer	5100	ALM	HA
~~1~~	~~Adapter Plate~~	~~4040XP-18G~~	~~AL~~	~~LC~~
~~1~~	~~Closer~~ ~~Top Jamb Mount~~	~~4040XP-RWPA~~	~~AL~~	~~LC~~
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Threshold	413S x LAR	MIL	HA
1	Weatherstrip	881S N x LAR	MIL	HA
1	Sweep(s)	750S N x LAR	CLR	HA
1	Rain Drip	810S x LAR	MIL	HA

Set #01

1	Door Position Switch	2-679-0626	HA
1	HS4 Wall Reader	WRDB0A4W0	HO
1	Power Supply	See MISC Set	
1	Wiring Diagrams	Wiring Diagrams	

Operational Description:

Door is normally closed and locked.
Authorized credential allows entry.
Free egress at all times.
Door is to remain locked upon loss of power.
Door is monitored by the access control system.

Set #02

Doors: 105.B1

3	Hinge(s)	BB1168 4 1/2" x 4 1/2"	US26D	HA
~~1~~	~~Exit Device~~	~~99L-BE-F x 996L-BE-R&V~~	~~US26D~~	~~VO~~
1	Exit Device	4501 RIM F FEC	US32D	HA
1	Passage Trims	45BE WTN	US26D	HA
~~1~~	~~Closer~~	~~1461T BUMP~~	~~AL~~	~~LC~~
1	Closer	5200 TRK NHOTA	ALM	HA
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Mag Holder(s)	380F	LS	HA
1	Smoke Seal	726 x LAR	S	HA

Set #03

Doors: 115.B1, 221.B1, 222.B1, 326.B1, 325.B1, 425.B1, 426.B1

3	Hinge(s)	BB1168 4 1/2" x 4 1/2"	US26D	HA
~~1~~	~~Exit Device~~	~~99L-BE-F x 996L-BE-R&V~~	~~US26D~~	~~VO~~
1	Exit Device	4501 RIM F FEC	US32D	HA
1	Passage Trim	45BE WTN	US26D	HA
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
1	Closer	5200	ALM	HA
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
~~1~~	~~Convex Wall Stop(s)~~	~~232W~~	~~US32D~~	~~HA~~
1	Mag Holder(s)	380F	LS	HA
1	Smoke Seal	726 x LAR	S	HA

Set #04

Doors: 110.B2.1, 110.B2.2

3	Hinge(s)	BB1168 4 1/2" x 4 1/2" NRP	US26D	HA
1	Power Transfer	2-6790-623	ALM	HA
~~1~~	~~Exit Device~~	~~99L-BE-F x 996L-BE-R&V~~	~~US26D~~	~~VO~~
1	Exit Device(s)	4501 RIM F RX FEC	US32D	HA
1	Exit Trim	45NL WTN	US26D	HA
1	Rim Cylinder	3901 SFIC	US26D	HA
1	Construction Core	3981-BLU	BLU	HA
1	Small Format IC	3981-C	US26D	HA
~~1~~	~~Closer~~	~~1461T BUMP~~	~~AL~~	~~LC~~
1	Closer	5200 Top Jamb Mount	ALM	HA
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Convex Wall Stop	232W	US32D	HA
1	Threshold	413S x LAR	MIL	HA
1	Smoke Seal	726 x LAR	S	HA
1	Door Bottom(s)	906S x LAR	MIL	HA
1	Door Position Switch	2-679-0626		HA
1	HS4 Wall Reader	WRDB0A4W0		HO
1	Power Supply	See MISC Set		
1	Wiring Diagrams	Wiring Diagrams		

Operational Description:

Door is normally closed and locked.
Authorized credential allows entry.
Free egress at all times.
Door is to remain locked upon loss of power.
Door is monitored by the access control system.

~~Set #05~~

~~Doors: 110.B2.2~~

~~3~~	~~Hinge(s)~~	~~BB1168 4 1/2" x 4 1/2" NRP~~	~~US26D~~	~~HA~~
~~1~~	~~Exit Device~~	~~99L-BE-F x 996L-BE-R&V~~	~~US26D~~	~~VO~~
~~1~~	~~Mag Holder(s)~~	~~380F~~	~~LS~~	~~HA~~
~~1~~	~~Mortise Cylinder(s)~~	~~3902 SFIC x LAR~~	~~US26D~~	~~HA~~
~~1~~	~~Construction Core~~	~~3981-BLU~~	~~BLU~~	~~HA~~
~~1~~	~~Small Format IC~~	~~3981-C~~	~~US26D~~	~~HA~~
~~1~~	~~Closer~~ ~~Mount pull side.~~	~~1461-RWPA~~	~~AL~~	~~LC~~
~~1~~	~~Kick Plate(s)~~	~~190S-10" x 2" LDW~~	~~US32D~~	~~HA~~
~~1~~	~~Convex Wall Stop(s)~~	~~232W~~	~~US32D~~	~~HA~~
~~1~~	~~Magnetic Lock~~	~~2951-ATS-DPS-MBS~~	~~ALM~~	~~HA~~
~~1~~	~~Threshold~~	~~413S x LAR~~	~~MIL~~	~~HA~~
~~1~~	~~Door Bottom(s)~~	~~906S x LAR~~	~~MIL~~	~~HA~~
~~1~~	~~PIR Egress Sensor~~	~~2-679-0612~~	~~BLACK~~	~~HA~~
~~1~~	~~Door Position Switch(es)~~	~~2-679-0626~~		~~HA~~
~~1~~	~~Exit Switch~~	~~2973~~	~~US32D~~	~~HA~~
~~1~~	~~Key Switch~~	~~29KS-ADD-RED/GREEN-LED'S~~	~~US32D~~	~~HA~~
~~1~~	~~Reader/Keypad~~	~~By Security Provider~~		
~~1~~	~~Power Supply~~	~~2908/2909/2910/2911-As Required~~	~~No Finish~~	~~HA~~
~~1~~	~~Power Supply~~	~~See MISC Set~~		
~~1~~	~~Wiring Diagrams~~	~~Wiring Diagrams~~		

~~Set #05~~

~~Operational Description:~~

~~During Business Hours:~~
~~Door is held open with a wall mounted magnetic hold open.~~
~~Free entry and egress.~~
~~Door to close and latch upon loss of power, signal from the fire alarm system, activation of the fire alarm system, or operation of a manual fire alarm station.~~
~~Wall mounted magnetic hold open status set by key switch.~~
~~Door is monitored by the access control system.~~

~~After Business Hours:~~
~~Door is closed and locked.~~
~~Valid credential allows entry.~~
~~Free egress - magnetic lock to unlock upon activation of the motion sensor or by pushing the request to exit button.~~
~~Door remain closed and latched and be unlocked upon loss of power, signal from the fire alarm system, activation of the fire alarm system, or operation of a manual fire alarm station.~~
~~Magnetic lock is manually rest by key switch.~~
~~Door is monitored by the access control system.~~

~~Key switch has alternate action switch - green light indicates door is unlocked and wall mounted magnetic holds are active.~~
~~Red LED indicates the door is locked and the magnetic lock is active.~~

Set #~~06~~ 05

Doors: ~~325.B1, 425.B1, 426.B1,~~ 415.B3

~~3~~	~~Hinge(s)~~	~~BB1168 4 1/2" x 4 1/2"~~	~~US26D~~	~~HA~~
3	Hinge(s)	BB1279 4 1/2" x 4 1/2" NRP	US26D	HA
~~1~~	~~Exit Device~~	~~99L-BE-F x 996L-BE-R&V~~	~~US26D~~	~~VO~~
1	HS4 Mini Cyl. Lockset	HM34JBBW23A	US26D	HO
1	Closer	5200	ALM	HA
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Convex Wall Stop(s)	232W	US32D	HA
1	Smoke Seal	726 x LAR	S	HA
~~1~~	~~Mag Holder(s)~~	~~380F~~	~~LS~~	~~HA~~

Set #~~07~~ 06

Doors: 101.B5, 104.B4

3	Hinge(s)	BB1279 4 1/2" x 4 1/2" NRP	US26D	HA
1	HS4 Mini Cyl. Lockset	HM34JBBW23A	US26D	HO
~~1~~	~~Passage Leverset~~	~~ND10 RHO~~	~~626~~	~~SC~~
~~1~~	~~Mortise Cylinder(s)~~	~~3902 SFIC x LAR~~	~~US26D~~	~~HA~~
~~1~~	~~Construction Core~~	~~3981-BLU~~	~~BLU~~	~~HA~~
~~1~~	~~Small Format IC~~	~~3981-C~~	~~US26D~~	~~HA~~
1	Closer Mount push side, top jamb.	5200 DLY	ALM	HA
~~1~~	~~Closer~~	~~1461 RWPA CYLDEL~~	~~AL~~	~~LC~~

Set #~~07~~ 06

~~Mount push side, top jamb.~~

1	Armor Plate(s)	190S 34" x 2" LDW UL	US32D	HA
~~1~~	~~Mag Holder(s)~~	~~380F~~	~~LS~~	~~HA~~
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Convex Wall Stop(s)	232W	US32D	HA
~~1~~	~~Magnetic Lock~~	~~2951 ATS DPS MBS~~	~~ALM~~	~~HA~~
1	Threshold	413S x LAR	MIL	HA
1	Smoke Seal	726 x LAR	S	HA
1	Door Bottom(s)	909S x LAR	MIL	HA
~~1~~	~~PIR Egress Sensor~~	~~2-679-0612~~	~~BLACK~~	~~HA~~
~~1~~	~~Door Position Switch(es)~~	~~2-679-0626~~		~~HA~~
~~1~~	~~Key Switch~~	~~29KS ADD Red/Green LED's~~	~~US32D~~	~~HA~~
~~1~~	~~Exit Switch~~	~~2973~~	~~US32D~~	~~HA~~
~~1~~	~~Power Supply~~	~~2908/2909/2910/2911 As Required~~	~~No Finish~~	~~HA~~
~~1~~	~~Reader/Keypad~~	~~By Security Provider~~		
~~1~~	~~Wiring Diagrams~~	~~Wiring Diagrams~~		

~~Operational Description:~~

~~During Business Hours:~~
~~Door is held open with a wall mounted magnetic hold open.~~
~~Free entry and egress.~~
~~Door to close and latch upon loss of power, signal from the fire alarm system, activation of the fire alarm system, or operation of a manual fire alarm station.~~
~~Wall mounted magnetic hold open status set by key switch.~~
~~Door is monitored by the access control system.~~

~~After Business Hours:~~
~~Door is closed and locked.~~
~~Valid credential allows entry.~~
~~Free egress - magnetic lock to unlock upon activation of the motion sensor or by pushing the request to exit button.~~
~~Door remain closed and latched and be unlocked upon loss of power, signal from the fire alarm system, activation of the fire alarm system, or operation of a manual fire alarm station.~~
~~Magnetic lock is manually rest by key switch.~~
~~Door is monitored by the access control system.~~

~~Key switch has alternate action switch - green light indicates door is unlocked and wall mounted magnetic holds are active.~~
~~Red LED indicates the door is locked and the magnetic lock is active.~~

Set #~~08~~ 07

Doors: ~~415.B3~~, 106.B10, 317.B8, 419.B8, 213.B8, 100.B10

3	Hinge(s)	BB1279 4 1/2" x 4 1/2" NRP	US26D	HA
~~1~~	~~Passage Leverset~~	~~ND10 RHO~~	~~626~~	~~SC~~
1	HS4 Mini Cyl. Lockset	HM34JBBW23A	US26D	HO
1	Closer	5200	ALM	HA

Set #~~08~~ 07

Top Jamb Mount

~~1~~	~~Magnetic Lock~~	~~2951 ATS DPS MBS~~	~~ALM~~	~~HA~~
~~1~~	~~Mortise Cylinder(s)~~	~~3902 SFIC x LAR~~	~~US26D~~	~~HA~~
~~1~~	~~Construction Core~~	~~3981 BLU~~	~~BLU~~	~~HA~~
~~1~~	~~Small Format IC~~	~~3981 C~~	~~US26D~~	~~HA~~
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Convex Wall Stop(s)	232W	US32D	HA
1	Smoke Seal	726 x LAR	S	HA
~~1~~	~~PIR Egress Sensor~~	~~2-679-0612~~	~~BLACK~~	~~HA~~
~~1~~	~~Door Position Switch(es)~~	~~2-679-0626~~		~~HA~~
~~1~~	~~Exit Switch~~	~~2973~~	~~US32D~~	~~HA~~
~~1~~	~~Key Switch~~	~~29KS MSD~~	~~US32D~~	~~HA~~
~~1~~	~~Power Supply~~	~~2908/2909/2910/2911 As Required~~	~~No Finish~~	~~HA~~
~~1~~	~~Reader/Keypad~~	~~By Security Provider~~		
~~1~~	~~Wiring Diagrams~~	~~Wiring Diagrams~~		

~~Operational Description:~~

~~Door is closed and locked.~~
~~Valid credential allows entry.~~
~~Free egress - magnetic lock to unlock upon activation of the motion sensor or by pushing the request to exit button.~~
~~Door remain closed and latched and be unlocked upon loss of power, signal from the fire alarm system, activation of the fire alarm system, or operation of a manual fire alarm station.~~
~~Magnetic lock is manually rest by key switch.~~
~~Door is monitored by the access control system.~~

~~Set #09~~

~~Doors: 106.B10, 102.B10~~

~~3~~	~~Hinge(s)~~	~~BB1279 4 1/2" x 4 1/2" NRP~~	~~US26D~~	~~HA~~
~~1~~	~~Passage Leverset~~	~~ND10 RHO~~	~~626~~	~~SC~~
~~1~~	~~Magnetic Lock~~	~~2951 ATS DPS MBS~~	~~ALM~~	~~HA~~
	~~Mount Pull Side.~~			
~~1~~	~~Mortise Cylinder(s)~~	~~3902 SFIC x LAR~~	~~US26D~~	~~HA~~
~~1~~	~~Construction Core~~	~~3981-BLU~~	~~BLU~~	~~HA~~
~~1~~	~~Small Format IC~~	~~3981 C~~	~~US26D~~	~~HA~~
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
	~~Mount pull side.~~			
~~1~~	~~Kick Plate(s)~~	~~190S 10" x 2" LDW~~	~~US32D~~	~~HA~~
~~1~~	~~Convex Wall Stop(s)~~	~~232W~~	~~US32D~~	~~HA~~
~~1~~	~~Threshold~~	~~413S x LAR~~	~~MIL~~	~~HA~~
~~1~~	~~Smoke Seal~~	~~726 x LAR~~	~~S~~	~~HA~~
~~1~~	~~Door Bottom(s)~~	~~909S x LAR~~	~~MIL~~	~~HA~~
~~1~~	~~PIR Egress Sensor~~	~~2-679-0612~~	~~BLACK~~	~~HA~~
~~1~~	~~Door Position Switch(es)~~	~~2-679-0626~~		~~HA~~
~~1~~	~~Exit Switch~~	~~2973~~	~~US32D~~	~~HA~~
~~1~~	~~Key Switch~~	~~29KS MSD~~	~~US32D~~	~~HA~~
~~1~~	~~Power Supply~~	~~2908/2909/2910/2911 As Required~~	~~No Finish~~	~~HA~~
~~1~~	~~Power Supply~~	~~See MISC Set~~		
~~1~~	~~Reader/Keypad~~	~~By Security Provider~~		
~~1~~	~~Wiring Diagrams~~	~~Wiring Diagrams~~		

~~Set #09~~

~~Operational Description:~~

~~Door is closed and locked.~~
~~Valid credential allows entry.~~
~~Free egress – magnetic lock to unlock upon activation of the motion sensor or by pushing the request to exit button.~~
~~Door remain closed and latched and be unlocked upon loss of power, signal from the fire alarm system, activation of the fire alarm system, or operation of a manual fire alarm station.~~
~~Magnetic lock is manually rest by key switch.~~
~~Door is monitored by the access control system.~~

Set #~~10~~ 08

Doors: 216.B6

3	Hinge(s)	BB1168 5" x 4 1/2" NRP	US26D	HA
1	Power Transfer(s)	2-679-0623	ALM	HA
1	Electric Strike	2930 CYL	US26D	HA
1	Storeroom Lockset with RX	3480RX WTN	US26D	HA
~~1~~	~~Passage Leverset~~	~~ND10 RHO~~	~~626~~	~~SC~~
~~1~~	~~Magnetic Lock~~	~~2951 ATS DPS MBS~~	~~ALM~~	~~HA~~
	~~Mount on pull side.~~			
1	Mortise Cylinder(s)	3902 SFIC x LAR	US26D	HA
1	Construction Core	3981-BLU	BLU	HA
1	Small Format IC	3981-C	US26D	HA
1	Overhead Stop(s)	7016 SRF	US32D	HA
1	Single Operator	8318 PULL	ALM	HA
~~1~~	~~Life Safety Closer~~	~~4314ME~~	~~689~~	~~LC~~
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Threshold	413S x LAR	MIL	HA
1	Smoke Seal	726 x LAR	S	HA
1	Door Bottom(s)	909S x LAR	MIL	HA
1	Door Position Switch(es)	2-679-0626		HA
~~1~~	~~PIR Egress Sensor~~	~~2-679-0612~~	~~BLACK~~	~~HA~~
~~1~~	~~Exit Switch~~	~~2973~~	~~US32D~~	~~HA~~
2	Vertical Bar Actuator	8228-04H/00	US32D	HA
1	Key Switch	29KS ADD Red/Green LED's	US32D	HA
~~1~~	~~Reader/Keypad~~	~~By Security Provider~~		
1	HS4 Wall Reader	WRDB0A4W0		HO
~~1~~	~~Power Supply~~	~~2908/2909/2910/2911 As Required~~	~~No Finish~~	~~HA~~
1	Power Supply	See MISC Set		
1	Wiring Diagrams	Wiring Diagrams		

Set #~~10~~ 08

Operational Description:

During Business Hours:
Door is unlocked.
Free entry and egress by manual means or pushing actuator to engage the operator.
Door to close and lock upon loss of power, signal from the fire alarm system, activation of the fire alarm system, or operation of a manual fire alarm station.
Door is monitored by the access control system.

After Business Hours:
Door is closed and locked.
Valid credential allows entry.
Free egress.
Door is to remain closed and latched and be unlocked upon loss of power, signal from the fire alarm system, activation of the fire alarm system, or operation of a manual fire alarm station.
Door is monitored by the access control system.

Key switch has alternate action switch - green light indicates the automatic operator is active and the door is unlocked; red light indicates the door is locked and the automatic operator is inactive.

~~During Business Hours:~~
~~Door is held open.~~
~~Free entry and egress.~~
~~Door to close and latch upon loss of power, signal from the fire alarm system, activation of the fire alarm system, or operation of a manual fire alarm station.~~
~~Life safety closer status set by key switch.~~
~~Door is monitored by the access control system.~~

~~After Business Hours:~~
~~Door is closed and locked.~~
~~Valid credential allows entry.~~
~~Free egress – magnetic lock to unlock upon activation of the motion sensor or by pushing the request to exit button.~~
~~Door is to remain closed and latched and be unlocked upon loss of power, signal from the fire alarm system, activation of the fire alarm system, or operation of a manual fire alarm station.~~
~~Magnetic lock is manually rest by key switch.~~
~~Door is monitored by the access control system.~~

~~Key switch has alternate action switch - green light indicates door is unlocked and the life safety closer is active. Red LED indicates the door is locked and the magnetic lock is active.~~

~~Set #11~~

~~Doors: 100.B10~~

~~3~~	~~Hinge(s)~~	~~BB1279 4 1/2" x 4 1/2" NRP~~	~~US26D~~	~~HA~~
~~1~~	~~Passage Leverset~~	~~ND10 RHO~~	~~626~~	~~SC~~
~~1~~	~~Magnetic Lock~~	~~2951 ATS DPS MBS~~	~~ALM~~	~~HA~~
~~1~~	~~Mortise Cylinder(s)~~	~~3902 SFIC x LAR~~	~~US26D~~	~~HA~~
~~1~~	~~Construction Core~~	~~3981 BLU~~	~~BLU~~	~~HA~~
~~1~~	~~Small Format IC~~	~~3981-C~~	~~US26D~~	~~HA~~
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~

~~Set #11~~

	~~Top Jamb Mount.~~			
~~1~~	~~Kick Plate(s)~~	~~190S 10" x 2" LDW~~	~~US32D~~	~~HA~~
~~1~~	~~Convex Wall Stop(s)~~	~~232W~~	~~US32D~~	~~HA~~
~~1~~	~~Threshold~~	~~413S x LAR~~	~~MIL~~	~~HA~~
~~1~~	~~Smoke Seal~~	~~726 x LAR~~	~~S~~	~~HA~~
~~1~~	~~Door Bottom(s)~~	~~909S x LAR~~	~~MIL~~	~~HA~~
~~1~~	~~PIR Egress Sensor~~	~~2-679-0612~~	~~BLACK~~	~~HA~~
~~1~~	~~Door Position Switch(es)~~	~~2-679-0626~~		~~HA~~
~~1~~	~~Exit Switch~~	~~2973~~	~~US32D~~	~~HA~~
~~1~~	~~Key Switch~~	~~29KS MSD~~	~~US32D~~	~~HA~~
~~1~~	~~Power Supply~~	~~2908/2909/2910/2911 As Required~~	~~No Finish~~	~~HA~~
~~1~~	~~Reader/Keypad~~	~~By Security Provider~~		
~~1~~	~~Wiring Diagrams~~	~~Wiring Diagrams~~		

~~Operational Description:~~

~~Door is normally closed and locked.~~
~~Valid credential allows entry.~~
~~Free egress - magnetic lock to unlock upon activation of the motion sensor or by pushing the request to exit button.~~
~~Door remain closed and latched and be unlocked upon loss of power, signal from the fire alarm system, activation of the fire alarm system, or operation of a manual fire alarm station.~~
~~Magnetic lock is manually rest by key switch.~~
~~Door is monitored by the access control system.~~

Set #~~12~~ 09

Doors: 108.B9

3	Hinge(s)	BB1279 4 1/2" x 4 1/2"	US26D	HA
~~1~~	~~Storeroom Lockset~~	~~ND80BDC RHO~~	~~626~~	~~SC~~
1	HS4 Mini Cyl. Lockset	HM34JBBW23A	US26D	HO
1	Construction Core	3981-BLU	BLU	HA
1	Small Format IC	3981-C	US26D	HA
~~1~~	~~Closer~~	~~1461T BUMP~~	~~AL~~	~~LC~~
1	Closer	5200 TRK NHOTA	ALM	HA
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Threshold	413S x LAR	MIL	HA
1	Smoke Seal	726 x LAR	S	HA
1	Door Bottom(s)	909S x LAR	MIL	HA

Set #10

Doors: 102.B10

3	Hinge(s)	BB1279 4 1/2" x 4"	US26D	HA
1	HS4 Mini Cyl. Lockset	HM34JBBW23A	US26D	HO
1	Overhead Stop(s)	7016 SRF	US32D	HA
1	Drop Plate	5922	ALM	HA
1	Closer	5200	ALM	HA
	Top Jamb Mount			
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Threshold	413S x LAR	MIL	HA
1	Smoke Seal	726 x LAR	S	HA
1	Door Bottom(s)	909S x LAR	MIL	HA

Set #~~13~~ 11

Doors: 110.B10

Set #~~13~~ 11

3	Hinge(s)	BB1279 4 1/2" x 4 1/2" NRP	US26D	HA
~~1~~	~~Storeroom Lockset~~	~~ND80BDC RHO~~	~~626~~	~~SC~~
1	Storeroom Lockset	3480 WTN SFIC	US26D	HA
1	Construction Core	3981-BLU	BLU	HA
1	Small Format IC	3981-C	US26D	HA
~~1~~	~~Overhead Stop(s)~~	~~7016 SRF~~	~~US32D~~	~~HA~~
~~1~~	~~Mounting Plate~~	~~1460-18~~	~~AL~~	~~LC~~
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
	~~Top jamb mount.~~			
1	Closer	5200 TRK NHOTA	ALM	HA
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Threshold	413S x LAR	MIL	HA
1	Smoke Seal	726 x LAR	S	HA
1	Door Bottom(s)	909S x LAR	MIL	HA

~~Set #14~~

~~Doors: 317.B8, 419.B8~~

~~3~~	~~Hinge(s)~~	~~BB1279 4 1/2" x 4 1/2" NRP~~	~~US26D~~	~~HA~~
~~1~~	~~Storeroom Lockset~~	~~ND80BDC RHO~~	~~626~~	~~SC~~
~~1~~	~~Construction Core~~	~~3981-BLU~~	~~BLU~~	~~HA~~
~~1~~	~~Small Format IC~~	~~3981-C~~	~~US26D~~	~~HA~~
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
~~1~~	~~Kick Plate(s)~~	~~190S 10" x 2" LDW~~	~~US32D~~	~~HA~~
~~1~~	~~Convex Wall Stop(s)~~	~~232W~~	~~US32D~~	~~HA~~
~~1~~	~~Threshold~~	~~413S x LAR~~	~~MIL~~	~~HA~~
~~1~~	~~Smoke Seal~~	~~726 x LAR~~	~~S~~	~~HA~~
~~1~~	~~Door Bottom(s)~~	~~909S x LAR~~	~~MIL~~	~~HA~~

~~Set #15~~

~~Doors: 213.B8~~

~~3~~	~~Hinge(s)~~	~~BB1279 4 1/2" x 4 1/2" NRP~~	~~US26D~~	~~HA~~
~~1~~	~~Storeroom Lockset~~	~~ND80BDC RHO~~	~~626~~	~~SC~~
~~1~~	~~Construction Core~~	~~3981-BLU~~	~~BLU~~	~~HA~~
~~1~~	~~Small Format IC~~	~~3981-C~~	~~US26D~~	~~HA~~
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
~~1~~	~~Kick Plate(s)~~	~~190S 10" x 2" LDW~~	~~US32D~~	~~HA~~
~~1~~	~~Convex Wall Stop(s)~~	~~232W~~	~~US32D~~	~~HA~~
~~1~~	~~Threshold~~	~~413S x LAR~~	~~MIL~~	~~HA~~
~~1~~	~~Door Bottom(s)~~	~~909S x LAR~~	~~MIL~~	~~HA~~
~~3~~	~~Silencers~~	~~307D~~	~~GREY~~	~~HA~~

Set #~~16~~ 12

Doors: 218.C4

3	Hinge(s)	BB1279 4 1/2" x 4 1/2"	US26D	HA
~~1~~	~~Storeroom Lockset~~	~~ND80BDC RHO~~	~~626~~	~~SC~~
1	Storeroom Lockset	3480 WTN SFIC	US26D	HA
1	Electric Strike	2930 CYL	US26D	HA
1	Construction Core	3981-BLU	BLU	HA
1	Small Format IC	3981-C	US26D	HA
1	Overhead Stop(s)	7016 SRF	US32D	HA
1	Single Operator	8318 PUSH	ALM	HA
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Convex Wall Stop(s)	232W	US32D	HA
1	Door Position Switch(es)	2-679-0626		HA
1	Smoke Seal	726 x LAR	S	HA
~~2~~	~~Actuator~~	~~8228 02H/06~~	~~US32D~~	~~HA~~
2	Vertical Bar Actuator	8288 04H/00	US32D	HA
1	Push to Lock Button	2-659-0370		HA
1	Occupancy Indicator(s)	2-659-0371		HA
1	Sequencer	82RL		HA
~~1~~	~~Power Supply~~	~~2908/2909/2910/2911 As Required~~	~~No Finish~~	~~HA~~
1	Power Supply	See MISC Set		
1	Wiring Diagrams	Wiring Diagrams		

Operational Description:

Door is normally closed and unlocked.
Free entry when room is not in use by manual means or outside actuator.
Free egress at all times by manual means or inside actuator.
Upon loss of power operator is disabled and the door is latched.
Battery backup provides power upon loss of power to ensure door remains locked if in use.
If the interior "Push to Lock" button has been pushed, exterior actuator is disabled and door is locked.
If the interior "Push to Lock" button has been pushed, it lights up and also lights up exterior occupancy indicator.
Door is unlocked and system is reset by pushing "Push to Lock" button a second time.

Set #~~17~~ 13

Doors: 207.C3, 312.C3, 412.C3

3	Hinge(s)	BB1279 4 1/2" x 4 1/2" NRP	US26D	HA
~~1~~	~~Privacy Lockset with Indicator~~	~~L9040 06A 09 509 X L583 363 OS OCC~~	~~626~~	~~SC~~
1	HS4 Mini Cyl. Lockset	HM34JBBW23A	US26D	HO
1	Closer	5200 TRK NHOTA	ALM	HA
~~1~~	~~Closer~~	~~1461T BUMP~~	~~AL~~	~~LC~~
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Mop Plate(s)	190S 6" x 1" LDW	US32D	HA
1	Smoke Seal	726 x LAR	S	HA
1	Push to Lock Button	2-659-0370		HA
1	Occupancy Indicator(s)	2-659-0371		HA

Operational Description:

Door is normally closed and locked.
Authorized credential allows entry when room is not in use.
Free egress at all times.
Upon loss of power the door is locked.
If the interior "Push to Lock" button has been pushed, exterior card reader is disabled and door is locked.
If the interior "Push to Lock" button has been pushed, it lights up and also lights up exterior occupancy indicator.
Opening the door will reset the card reader and LEDs.

Set #~~18~~ 14

Doors: 113.C3, 116.C3

3	Hinge(s)	BB1279 4 1/2" x 4 1/2" NRP	US26D	HA
~~1~~	~~Privacy Lockset with Indicator~~	~~L9040 06A 09-509 X L583-363 OS-OCC~~	~~626~~	~~SC~~
1	HS4 Mini Cyl. Lockset	HM34JBBW23A	US26D	HO
1	Overhead Stop(s)	7016 SRF	US32D	HA
~~1~~	~~Mounting Plate~~	~~1460-18~~	~~AL~~	~~LC~~
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
	~~Top Jamb Mount.~~			
1	Drop Plate	5922	ALM	HA
1	Closer	5200	ALM	HA
	Top Jamb Mount.			
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Mop Plate(s)	190S 6" x 1" LDW	US32D	HA
1	Smoke Seal	726 x LAR	S	HA
1	Push to Lock Button	2-659-0370		HA
1	Occupancy Indicator(s)	2-659-0371		HA

Operational Description:

Door is normally closed and locked.
Authorized credential allows entry when room is not in use.
Free egress at all times.
Upon loss of power the door is locked.
If the interior "Push to Lock" button has been pushed, exterior card reader is disabled and door is locked.
If the interior "Push to Lock" button has been pushed, it lights up and also lights up exterior occupancy indicator.
Opening the door will reset the card reader and LEDs.

Set #~~19~~ 15

Doors: 215.C3, 310.C3, 311.C3, 410.C3, 411.C3

3	Hinge(s)	BB1279 4 1/2" x 4 1/2"	US26D	HA
~~1~~	~~Privacy Lockset with Indicator~~	~~L9040 06A 09-509 X L583-363 OS-OCC~~	~~626~~	~~SC~~
1	HS4 Mini Cyl. Lockset	HM34JBBW23A	US26D	HO
1	Closer	5200	ALM	HA
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
	~~Top jamb mount.~~			
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Mop Plate(s)	190S 6" x 1" LDW	US32D	HA
1	Convex Wall Stop(s)	232W	US32D	HA
1	Smoke Seal	726 x LAR	S	HA
1	Push to Lock Button	2-659-0370		HA
1	Occupancy Indicator(s)	2-659-0371		HA

Operational Description:

Door is normally closed and locked.
Authorized credential allows entry when room is not in use.
Free egress at all times.
Upon loss of power the door is locked.
If the interior "Push to Lock" button has been pushed, exterior card reader is disabled and door is locked.
If the interior "Push to Lock" button has been pushed, it lights up and also lights up exterior occupancy indicator.
Opening the door will reset the card reader and LEDs.

Set #~~20~~ 16

Doors: 103.B10

3	Hinge(s)	BB1279 4 1/2" x 4 1/2"	US26D	HA
~~1~~	~~Passage Leverset~~	~~ND10 RHO~~	~~626~~	~~SC~~
1	Passage Leverset	3410 WTN	US26D	HA
1	Closer	5200	ALM	HA
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Convex Wall Stop(s)	232W	US32D	HA
1	Threshold	413S x LAR	MIL	HA
1	Smoke Seal	726 x LAR	S	HA
1	Door Bottom(s)	909S x LAR	MIL	HA

Set #~~21~~ 17

Doors: 200.D1

6	Hinge(s)	BB1168 4 1/2" x 4 1/2" NRP	US26D	HA
1	Power Transfer(s)	2-679-0623	ALM	HA
1	Automatic Flush Bolt Top bolt only	296D	US32D	HA
1	Electric Strike	6223	US32D	VO
1	Classroom Lockset	3470 WTN	US26D	HA
1	Mortise Cylinder(s)	3902 SFIC x LAR	US26D	HA
2	Construction Core	3981-BLU	BLU	HA
2	Small Format IC	3981-C	US26D	HA
~~2~~	~~Push Plate(s)~~	~~30S 4 X 16~~	~~US32D~~	~~HA~~
~~2~~	~~Pull Plate(s)~~	~~33L 4" x 16"~~	~~US32D~~	~~HA~~
2	Overhead Stop/Holder(s)	7017 SRF	US32D	HA
1	Coordinator	297D x LAR	BLACK	HA
2	Mounting Bracket(s)	297M/297N (as required)	BLACK	HA
2	Overhead Stop(s)	7016 SRF	US32D	HA
~~2~~	~~Mounting Plate~~	~~1460-18~~	~~AL~~	~~LC~~
~~2~~	~~Closer~~ ~~Top jamb mount.~~	~~1461 RWPA~~	~~AL~~	~~LC~~
1	Drop Plate	5922	ALM	HA
1	Closer Top jamb mount.	5200	ALM	HA
1	Single Operator	8318 PUSH	ALM	HA
2	Kick Plate(s)	190S 10" x 1" LDW	US32D	HA
1	Wood Threshold	By Others		
2	Silencers	308D	GREY	HA
2	Door Bottom	907S x LAR	MIL	HA
2	Vertical Bar Actuator	8228-04H/00	US32D	HA
1	Key Switch	29KS ADD Red/Green LED's	US32D	HA
1	Power Supply(s)	CENTRAL POWER SUPPLY (SEE MISC. SET)		HA
1	Wiring Diagrams	Wiring Diagrams		

Set #~~21~~ 17

Operational Description:

During Business Hours:
Doors are closed and unlocked.
Free entry and egress by manual means or pushing actuator to engage the operator.
Upon loss of power, operator is disabled and door is closed.

After Business Hours:
Doors are closed and locked.
Operator is disabled.
Valid key allows entry.
Free egress at all times.

Key switch has alternate action switch - green light indicates the automatic operator is active and the door is unlocked; red light indicates the door is locked and the automatic operator is inactive.

Set #~~22~~ 18

Doors: 219.C8

3	Hinge(s)	BB1279 4 1/2" x 4 1/2"	US26D	HA
~~1~~	~~Office Lockset~~	~~ND50BDC RHO~~	~~626~~	~~SC~~
1	HS4 Mini Cyl. Lockset	HM34JBBW23A	US26D	HO
1	Concave Wall Stop(s)	236W	US32D	HA
3	Silencers	308D	GREY	HA

Set #~~23~~ 19

Doors: 219.C9

4	Hinge(s)	BB1279 4 1/2" x 4 1/2"	US26D	HA
1	Automatic Flush Bolt	~~296W~~ 296D Top Bolt Only	US32D	HA
1	HS4 Mini Cyl. Lockset	HM34JBBW23A	US26D	HO
	Coordinate mounting location with accessibility requirements and shelf location.			
~~1~~	~~Office Lockset~~	~~ND50BDC RHO~~	~~626~~	~~SC~~
~~1~~	~~Construction Core~~	~~3981-BLU~~	~~BLU~~	~~HA~~
~~1~~	~~Small Format IC~~	~~3981-C~~	~~US26D~~	~~HA~~
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
2	Concave Wall Stop(s)	236W	US32D	HA
1	Smoke Seal	726 x LAR	S	HA
1	Dutch Door Astragal	835S x LAR	MIL	HA
1	Door Bottom(s)	909S x LAR	MIL	HA
1	Astragal Seal	726 x LAR	S	HA

Hardware set is intended as a guide – coordination with door manufacturer is required.

Set #EXG

Doors: EXT.A4-E, EXT.A6-E

1	Hardware	Existing to Remain

Set #LIFT.1

Doors: LIFT.INT

1	Hardware	by Door Mfr./Supplier

Set #LIFT.2

Doors: LIFT.EXT

1	HS4 Wall Reader	WRDB0A4W0		HO
1	Wiring Diagrams	Wiring Diagrams		
1	Power Supply(s)	CENTRAL POWER SUPPLY (SEE MISC. SET)		HA
1	Balance of Hardware	By Door/Frame Mfr.		

Set #U1

Doors: 107.C2, 111.C2, 114.C2, 115.C2, 211.C2, 300.C2, 301.C2, 302.C2, 303.C2, 309.C2, 313.C2, 314.C2, 315.C2, 316.C2, 318.C2, 319.C2, 320.C2, 324.C2, 400.C2, 403.C2, 409.C2, 412.C2, 413.C2, 416.C2, 417.C2, 418.C2, 419.C2, 420.C2, 421.C2, 422.C2, 423.C2, 424.C2, 201.C2, 202.C2, 203.C2, 304.C2, 305.C2, 306.C2, 307.C2, 308.C2, 321.C2, 322.C2, 401.C2, 404.C2, 405.C2, 406.C2, 407.C2, 408.C2, 425.C2, 209.C1, 210.C1, 212.C1, 214.C1, 208.C1, 204.C1, 217.C1

3	Hinge(s)	BB1279 4 1/2" x 4 1/2" NRP	US26D	HA
~~1~~	~~Wireless Access Control Lock~~	~~By Security Provider~~		
1	HS4 Wide Body Mortise - Entry	HT38MBBW23M	US32D	HO
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
1	Closer	5200	ALM	HA
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Door Stop(s)	211	US26D	HA
1	Door Viewer(s)	1759	US26D	HA
1	Threshold	413S x LAR	MIL	HA
1	Smoke Seal	726 x LAR	S	HA
1	Door Bottom(s)	909S x LAR	MIL	HA

Set #U1.1

Doors: 109.C2, 112.C2, 323.C2

3	Hinge(s)	BB1279 4 1/2" x 4 1/2" NRP	US26D	HA
~~1~~	~~Wireless Access Control Lock~~	~~By Security Provider~~		
1	HS4 Wide Body Mortise - Entry	HT38MBBW23M	US32D	HO
~~1~~	~~Closer~~	~~1461T BUMP~~	~~AL~~	~~LC~~
1	Closer	5200 TRK NHOTA	ALM	HA
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
1	Door Viewer(s)	1759	US26D	HA
1	Threshold	413S x LAR	MIL	HA
1	Smoke Seal	726 x LAR	S	HA
1	Door Bottom(s)	909S x LAR	MIL	HA

Set #U1A

Doors: 205.C1, ~~208.C1, 209.C1, 210.C1, 212.C1, 214.C1~~, 220.C1, ~~204.C1,~~ 206.C1, ~~217.C1~~

3	Hinge(s)	BB1279 4 1/2" x 4 1/2" NRP	US26D	HA
1	Electric Strike	2930 MOR	US32D	HA
~~1~~	~~Wireless Access Control Lock~~	~~By Security Provider~~		
1	Corridor Lockset	3896 SECT WTN ADA Turn	US26D	HA
1	Construction Core	3981-BLU	BLU	HA
1	Small Format IC	3981-C	US26D	HA
~~1~~	~~Closer~~	~~1461 RWPA~~	~~AL~~	~~LC~~
1	Single Operator	8318 PULL	ALM	HA
1	Kick Plate(s)	190S 10" x 2" LDW	US32D	HA
~~1~~	~~Door Stop(s)~~	~~211~~	~~US26D~~	~~HA~~
1	Convex Wall Stop(s)	232W	US32D	HA
1	Threshold	413S x LAR	MIL	HA
1	Smoke Seal	726 x LAR	S	HA
1	Door Bottom(s)	909S x LAR	MIL	HA
2	Door Viewer(s)	1759	US26D	HA
1	Vertical Bar Actuator	8228-04H/00	US32D	HA
1	HS4 Wall Reader	WRDB0A4W0		HO
1	Power Supply(s)	CENTRAL POWER SUPPLY (SEE MISC. SET)		HA
1	Wiring Diagrams	Wiring Diagrams		

Operational Description:

Door is normally closed and locked.
Authorized credential allows entry and engages the automatic operator to open the door.
Free egress at all times or pushing on interior actuator will engage the automatic operator.
Door is to remain closed and latched upon loss of power, signal from the fire command center, or activation of the fire alarm system.

Set #U2

Doors: 109.C7, 112.C7, 114.C7, 115.C7, 201.C7, 202.C7, 203.C7, 208.C7, 210.C7, 211.C7, 212.C7, 214.C7, 303.C7, 304.C7, 400.C7, 403.C7, 404.C7, 405.C7, 406.C7, 407.C7, 408.C7, 409.C7, 413.C7, 414.C7, 416.C7, 418.C7, 420.C7, 421.C7, 422.C7, 423.C7, 424.C7, 305.C7, 306.C7, 307.C7, 308.C7, 309.C7, 313.C7, 314.C7, 315.C7, 318.C7, 319.C7, 320.C7, 321.C7, 322.C7, 323.C7

3	Hinge(s)	1541 3-1/2" x 3-1/2"	US32D	HA
1	Passage Lockset	F10S ELAN	626	SCHL
1	Door Stop(s)	211	US26D	HA
3	Silencers	308D	GREY	HA

Set #U3

Doors: 111.C7, 204.C7, 205.C10, 206.C10, 217.C7, 300.C7, 301.C7, 302.C7, 316.C7, 324.C7, 401.C7, 402.C7, 417.C7, 425.C7

3	Hinge(s)	1541 3-1/2" x 3-1/2"	US32D	HA
1	Passage Lockset	F10S ELAN	626	SCHL
2	Hinge Pin Stop(s)	1507	619	DJ
3	Silencers	308D	GREY	HA

Set #U4

Doors: 201.C6, 202.C6, 203.C6, 300.C6, 303.C6, 304.C6, 305.C6, 307.C6, 308.C6, 309.C6, 313.C6, 323.C6, 400.C6, 403.C6, 409.C6, 414.C6

3	Hinge(s)	1541 3-1/2" x 3-1/2"	US32D	HA
1	Privacy Lockset	F40S ELAN	626	SCHL
1	Door Stop(s)	211	US26D	HA
3	Silencers	308D	GREY	HA

Set #U5

Doors: 112.C6, 111.C6, 302.C6, 402.C6, 404.C6, 405.C6, 406.C6, 407.C6, 408.C6, 424.C6, 425.C6, 205.C5, 206.C5, 220.C5

3	Hinge(s)	1541 3-1/2" x 3-1/2"	US32D	HA
1	Privacy Lockset	F40S ELAN	626	SCHL
2	Hinge Pin Stop(s)	1507	619	DJ
3	Silencers	308D	GREY	HA

Set #~~U6~~ 20

Doors: 221.D2

6	Hinge(s)	BB1279 4 1/2" x 4" NRP	US26D	HA
1	Power Transfer(s)	2-679-0623	ALM	HA
1	Automatic Flush Bolt Top bolt only.	292D	US26D	HA
1	Electric Strike	2930 CYL	US26D	HA
1	Storeroom Lockset	3480 WTN SFIC	US26D	HA
1	Construction Core	3981-BLU	BLU	HA
1	Small Format IC	3981-C	US26D	HA
1	Coordinator	297D	BLK	HA
2	Mounting Block(s)	297M/N as req'd	BLK	HA
1	Simultaneous Operator	8319 PUSH	ALM	HA
2	Kick Plate(s)	190S 10" x 1" LDW	US32D	HA
2	Silencers	307D	GREY	HA
2	Door Position Switch(es)	2-679-0626		HA
1	Vertical Bar Actuator	8228-04H/00	US32D	HA
1	BodyGuard Sensor	2-659-0332		
1	HS4 Wall Reader	WRDB0A4W0		HO
1	Power Supply(s)	CENTRAL POWER SUPPLY (SEE MISC. SET)		HA
~~6~~	~~Hinge(s)~~	~~1541 3-1/2" x 3-1/2"~~	~~US32D~~	~~HA~~
~~2~~	~~Dummy Trim~~	~~F170 ELAN~~	~~626~~	~~SCHL~~
~~4~~	~~Hinge Pin Stop(s)~~	~~1507~~	~~619~~	~~DJ~~
~~2~~	~~Roller Latch(es)~~	~~320R~~	~~US26D~~	~~HA~~
~~2~~	~~Silencers~~	~~308D~~	~~GREY~~	~~HA~~
1	Wiring Diagrams	Wiring Diagrams		

Operational Description:

Doors are normally closed and locked.
Authorized credential will unlock the active leaf and engage the automatic operator to open both leafs. Doors will remain held open until persons clear the area.
Room is non-occupiable and egress is not included.
Upon loss of power, the operator will be disabled and doors will be closed and locked.
Doors are monitored by the access control system.