DEPARTMENT OF COMPUTER SCIENCE AND ENGINEERING

SRM INSTITUTE OF SCIENCE AND TECHNOLOGY

TIRUCHIRAPPALLI

Lab Report

Computer Networks Lab

Cisco Packet Tracer: LAN connectivity and router configuration

Name	**Devaganesh S**
Register No.	**RA2411030050015**
Department	**CSE – Cyber Security – A**
Date	**23-10-2026**

Contents

1 Introduction to Packet Tracer, Peer-to-Peer Communication, Study of Cables and its Color Codes p. 3

2 Router Configuration (Creating Passwords, Configuring Interfaces) p. 6

Experiment

1 Introduction to Packet Tracer, Peer-to-Peer Communication, Study of Cables and its Color Codes

Date
23-10-2026

AIM

To study Cisco Packet Tracer, connect two PCs through a switch and check the communication between them using ping, and to study the straight-through and crossover cables and their color codes.

SOFTWARE USED

Cisco Packet Tracer

THEORY

Cisco Packet Tracer is a network simulation software made by Cisco. We can create networks, configure devices and test them without using real hardware. In peer-to-peer communication the computers talk to each other directly without any server. A switch is used to connect devices of the same network and it forwards data using MAC address.

Ethernet cables have 8 wires (4 twisted pairs) and RJ-45 connectors are used at the ends. There are two wiring standards, T568A and T568B.

Pin	1	2	3	4	5	6	7	8
T568A	White-Green	Green	White-Orange	Blue	White-Blue	Orange	White-Brown	Brown
T568B	White-Orange	Orange	White-Green	Blue	White-Blue	Green	White-Brown	Brown

Table 1.1 – T568A and T568B wire color order by pin

Cable	Wiring	Used to connect
Straight-through	Same standard on both ends (T568B – T568B)	Different devices, like PC to switch or switch to router
Crossover	T568A on one end and T568B on the other end	Similar devices, like PC to PC, switch to switch or router to router

IP ADDRESSES USED

Device	IP address	Subnet mask
PC0	192.168.1.1	255.255.255.0
PC1	192.168.1.2	255.255.255.0

PROCEDURE

1. Open Cisco Packet Tracer.
2. Take two PCs (PC0 and PC1) from End Devices and one 2960 switch from Switches and place them in the workspace.
3. Select Copper Straight-Through cable and connect PC0 to Fa0/1 of the switch and PC1 to Fa0/2 of the switch.
4. Click on PC0 → Desktop → IP Configuration and give IP address 192.168.1.1 and subnet mask 255.255.255.0.
5. Click on PC1 → Desktop → IP Configuration and give IP address 192.168.1.2 and subnet mask 255.255.255.0.
6. Wait till all the link lights become green.
7. Open PC0 → Desktop → Command Prompt and type `ping 192.168.1.2`
8. Check the replies.

OUTPUT




Figure 1.1 *– Topology: PC0 and PC1 connected to Switch0 with straight-through cables*




Figure 1.2 *– Ping from PC0 to PC1 (4 sent, 4 received, 0% loss)*

Result. Thus the two PCs were connected using a switch in Cisco Packet Tracer and the ping from PC0 to PC1 was successful (4 sent, 4 received, 0% loss). The straight-through and crossover cables and their color codes were studied.

2 Router Configuration (Creating Passwords, Configuring Interfaces)

Experiment

Date
23-10-2026

AIM

To configure a router by setting passwords and IP addresses on its interfaces, and to check the communication between two PCs in different networks through the router.

SOFTWARE USED

Cisco Packet Tracer

THEORY

A router is used to connect two or more different networks. It forwards packets based on IP address. Each interface of the router is in a different network and it works as the default gateway for the PCs in that network. Passwords are given to the router for security – console password for console access, enable password for privileged mode and VTY password for remote (Telnet) access. By default router interfaces are shut down, so we have to use the `no shutdown` command to turn them on.

IP ADDRESSES USED

Device	Interface	IP address / mask	Default gateway
Router (R1)	Gig0/0	192.168.1.1 / 255.255.255.0	–
Router (R1)	Gig0/1	192.168.2.1 / 255.255.255.0	–
PC2	NIC	192.168.1.2 / 255.255.255.0	192.168.1.1
PC3	NIC	192.168.2.2 / 255.255.255.0	192.168.2.1

PROCEDURE

1. Open Cisco Packet Tracer and place one 2911 router and two PCs (PC2 and PC3).
2. Connect PC2 to Gig0/0 and PC3 to Gig0/1 of the router using copper cables.
3. Click on the router and go to CLI tab. Type `no` for the initial configuration dialog and press Enter.

4. Type the following commands to set the passwords:

```
Router>enable
Router#configure terminal
Router(config)#hostname R1
R1(config)#enable password cisco
R1(config)#line console 0
R1(config-line)#password cisco
R1(config-line)#login
R1(config-line)#exit
R1(config)#line vty 0 4
R1(config-line)#password cisco
R1(config-line)#login
R1(config-line)#exit
```

5. Type the following commands to configure the interfaces:

```
R1(config)#interface gig0/0
R1(config-if)#ip address 192.168.1.1 255.255.255.0
R1(config-if)#no shutdown
R1(config-if)#exit
R1(config)#interface gig0/1
R1(config-if)#ip address 192.168.2.1 255.255.255.0
R1(config-if)#no shutdown
R1(config-if)#end
R1#show ip interface brief
```

6. In PC2 give IP 192.168.1.2, subnet mask 255.255.255.0 and default gateway 192.168.1.1.
7. In PC3 give IP 192.168.2.2, subnet mask 255.255.255.0 and default gateway 192.168.2.1.
8. Open Command Prompt in PC2 and type `ping 192.168.2.2`

OUTPUT




Figure 2.1 *– Topology: PC2 and PC3 connected to the 2911 router (R1)*




Figure 2.2 *– Ping from PC2 to PC3 through the router*

The first request timed out because of ARP, after that all replies came.

Result. Thus the router was configured with passwords and IP addresses on its interfaces, and the two PCs in different networks were able to communicate through the router.