Title: Laptop Docking and External Display Guide
Category: hardware_peripherals

[SAMPLE DOCUMENT - synthetic content for the HelpDeskAI project, not an official company policy]

Symptoms and scope
A laptop charges through its dock but one or more external monitors remain blank, flicker, or appear at the wrong resolution.

Troubleshooting procedure

1. Check the monitor power indicator and select the input that matches the connected cable. Inspect the cable ends for visible damage and make sure each connector is fully seated. Do not force a connector or use a cable with exposed conductors.

2. Disconnect the dock from the laptop and its power adapter. Wait 20 seconds, reconnect dock power first, then connect the laptop. Wait 45 seconds for the display system to enumerate the attached monitors.

3. Open display settings and choose Detect. Confirm that the external screen is enabled and set to a supported resolution. If only one screen works, test one monitor at a time so the failing cable, monitor, or dock port can be isolated.

4. Try a known-good approved cable if one is available. Do not borrow an unidentified power adapter or daisy-chain unapproved adapters. Record which monitor, cable type, and dock port were tested.

Ownership and handoff
The Service Desk owns basic connection checks and asset details. End User Computing owns dock firmware, approved replacement docks, and persistent display-driver faults. Facilities owns wall outlets and fixed building power infrastructure, not monitor settings.

Escalation and priority
Raise low priority for a single display issue with a usable laptop screen. Raise medium priority if the dock prevents normal work and the checks fail. Raise high priority if a shared workstation used for a time-critical operational function is unavailable. Stop using the equipment and report immediately if a connector is hot, sparking, or smells burnt.

Diagnostic details and records
DISP-207 means an external display was not detected after the dock power reset and detection wait. Include the asset label, dock model, monitor count, cable type, and result of the one-monitor test. Keep the laptop open and usable while waiting if it is safe to do so.

Questions and answers

Q: The laptop is charging; does that prove the dock is healthy?
A: No. Power delivery and display output are separate functions.

Q: Should I open the dock enclosure?
A: No. Do not disassemble docks or monitors. Request inspection or replacement through the Service Desk.

Ticket quality checklist
Before submitting, confirm that the report states the observed symptom rather than only a guessed cause. Separate facts from assumptions, include the time and location, and describe the troubleshooting already completed. If a step could expose a person to electrical, battery, water, or moving-equipment hazards, stop and use the safety escalation

route instead of continuing. Do not bypass access controls, disable security protections, open sealed equipment, or use another person's account. A support team may ask for additional evidence, but provide it only through the approved company channel and only when it is needed to diagnose the issue.

Expected outcome
A successful first-line check should either restore the affected function or narrow the fault to a specific service, device, destination, or building component. If the result is unchanged, preserve the original error text and report which numbered steps were completed. Do not repeat a failed action indefinitely; use the stated escalation condition and let the owning team continue diagnosis.