Orion X200 Router - Quick Start

Package contents: router, power adapter (12V, 2A), 1 Ethernet cable, quick start guide.

Connect the WAN port to your modem and power on the router. Open a browser and visit 192.168.50.1 to reach the admin page. The default username is admin. You must change the default password at first login. The Wi-Fi network name is printed on the bottom label.

Troubleshooting

If the power LED blinks red, the router has lost its internet connection. Restart the modem and wait 2 minutes.

To perform a factory reset, hold the reset button for 10 seconds until the LED flashes white.

If Wi-Fi is slow, change the 2.4 GHz channel from Auto to 1, 6 or 11.

Firmware updates are under Admin > System > Firmware. Do not power off during an update, which takes about 5 minutes.

Specifications and Warranty

Wi-Fi 6 dual-band AX1800: up to 574 Mbps on 2.4 GHz and 1201 Mbps on 5 GHz. The router has 4 Gigabit LAN ports and 1 Gigabit WAN port.

Warranty: 2 years from the purchase date. It covers manufacturing defects only and does not cover water damage. Support email: support@orion-example.com. Operating temperature is 0 to 40 degrees Celsius.