Aragon System MCP: Letting an AI Assistant Check Your Maestro

The Aragon System MCP lets an AI assistant such as Claude look inside your Aragon Maestro and find out why something does not work: a satellite that does not react, voice commands that do nothing, a slow system after an update. You describe the problem in your own words; the assistant checks the Maestro itself and explains what it finds.

It only reads. It never changes a setting, restarts anything or switches a device. It is off until you switch it on, and it switches itself off after 48 hours.

What it can check

Area	What the assistant can see
Health	The Maestro's full health check: packages, services, ports, voice models, the AI assistant, Cloud AI, disk and memory
Errors	Warnings and errors in the logs of each Aragon service, with each time they happened
Changes	Language switches, voice training, Cloud AI settings saved, reboots (and what started them), sign-ins, the last update and what it changed
Performance	CPU, memory, swap and temperature over the last hours, and which program caused a peak
Speech	How many voice commands went to Cloud AI, how fast the answers came, retries (counts only)
KNX gateway	Gateway type and address, whether the connection works, the devices and rooms Aragon loaded from it
Satellites	Each satellite's room, wake word, firmware and network connection; satellites the Maestro cannot find
Guides	Aragon's own guides and videos, so the answer can point you to the right page

What is shared, and what never is

The assistant sees system information: states, versions, settings without their secret values, and log lines. Through Claude this information goes to Anthropic; through another assistant, to that assistant's company.

Never shared:

- **Passwords and keys.** They are removed from everything the connector returns, including the user name and password of your KNX gateway.
- **What was said at home.** Speech is reported as counts and times only, never as text.
- **Recordings.** The connector has no access to audio.

What you need before you start

- **Remote Connect set up** on your Maestro, with an owner password. This is the same password you use for Aragon Control MCP. If you have not set it up yet, see Connecting Your AI Assistant to Aragon Control MCP.
- **An AI assistant that supports custom connectors**, for example Claude (claude.ai or Claude Desktop) or ChatGPT with Developer mode on.

Step 1: Switch it on

1. Open the Maestro page and choose **System → Support access** in the menu (the section sits under Remote Connection).
2. Click **Turn on for 48 hours** and enter your owner password.
3. The card shows until when it is on, and your connector address with a copy button.

You can click **Turn off now** at any time. The assistant then loses access at once. Turning it on again starts a new 48-hour window and signs out any assistant that was connected before: it has to sign in again. Changing the owner password in the Aragon Control MCP section does the same.

Step 2: Connect your assistant

Your connector address ends in `/aragon-system/mcp`:

```
https://your-device-name.your-tailnet.ts.net/aragon-system/mcp
```

Copy it from the Support access card. Leaving off `/mcp` is the most common setup mistake.

Claude (claude.ai and Claude Desktop)

1. Open **Settings → Connectors → Add custom connector** and give it a name, for example “Aragon System”.
2. **Server URL:** your address, ending in `/mcp`.
3. **OAuth client:** choose **“No client ID — register one automatically”**. Do not choose “Use Anthropic’s hosted client metadata”.
4. Leave **Additional request headers** empty and submit.
5. On the **Aragon Maestro** sign-in page, enter your **owner password** (not your Claude password). You are sent back to Claude, connected.

ChatGPT: turn on **Developer mode** in **Settings → Security and login**, then add a connector with the same address and automatic OAuth registration.

Aragon Control MCP and the System MCP are two separate connectors with two addresses. You can have both: one controls your home, the other checks it.

Step 3: Ask your question

Start a new chat, make sure the connector is turned on in that chat, and describe the problem as you would to a person. For example:

- “My Maestro no longer reacts to voice commands. Find out why and tell me what you checked.”
- “The satellite in the living room doesn’t react. What is wrong?”
- “Voice commands don’t switch any lights. Is my KNX gateway connected?”
- “Since the last update something is broken. What changed?”
- “Was anything unusual on my Maestro yesterday between 18:00 and 22:00?”
- “How do I change the wake word of a satellite?”

The assistant chooses which checks to run. Good answers say what was checked, what is normal and what is not, and link to the right Aragon guide.

Seeing each check before it runs: because the checks only read, Claude may run them without asking. To approve each one, open the connector’s settings in Claude and set the tools you want to see, for example **Recent errors** and **Support report**, to **Needs approval**.

Sending a report to Aragon support

Ask the assistant: *“Make a support report and give it to me as text to send to Aragon support.”* The report holds the same facts the assistant saw, with the date and time, so support sees exactly what was checked. Make a second report after a fix to show what changed.

If it does not connect

- **“Couldn’t connect” or “service unavailable”:** Support access is off, or its 48 hours have ended. Turn it on again on the Maestro page and reconnect.
- **The connection worked before and now asks you to sign in again:** Support access was turned on again, which signs out earlier connections. Sign in with your owner password.
- **Reconnect does not help:** remove the connector in Claude and add it again.
- **The card says “Remote Connect is not connected”:** the Maestro is not connected to Tailscale right now. Support access works again by itself as soon as Remote Connect is connected; there is no need to turn it off and on.
- **The address does not answer at all:** Remote Connect must be set up and reachable. Check the Remote Connection status on the Maestro page.

Limits

- The assistant explains; it does not repair. You or Aragon support make the change.
- It cannot check a Maestro that is switched off or has no internet connection.
- It sees the KNX gateway, the satellites and the Node-RED flow from the Maestro’s side: whether they answer and what they report, not their own internal settings.