AUTOMOBILE & ELECTRIC VEHICLES

TASK 2: EV Powertrain Architecture, Motor Types,
and Battery Management System (BMS)


Prepared by: Deeya N. Dewardekar
Program: B.Tech Electrical Engineering

Completed task report covering EV powertrain architecture, motor comparison, inverter and motor controller, BMS safety, range calculation, and a vehicle case study.

1. EV Powertrain Architecture

Definition: An electric-vehicle (EV) powertrain is the system that transfers electrical energy from the battery, converts it into mechanical energy, and delivers torque to the wheels. The main components considered in this task are the battery pack, BMS, inverter, electric motor, transmission/reduction gear, and wheels.

1.1 EV powertrain block diagram



Energy flow: The battery pack stores energy as DC electricity. The BMS monitors battery condition and provides protection. The inverter converts battery DC into controlled AC for the traction motor. The motor converts electrical energy into rotational mechanical energy. A reduction gear/transmission transfers torque to the wheels. During regenerative braking, the motor can operate as a generator and return some energy to the battery through the power electronics, subject to the vehicle's control and battery limits.

1.2 Main component functions

Component	Function
Battery pack	Stores electrical energy; capacity is usually stated in kWh.
BMS	Monitors cell voltage, pack current and temperature; estimates SOC/SOH and protects the pack.
Inverter	Converts battery DC into controlled AC for an AC traction motor; controls output voltage/frequency.
Motor controller	Uses driver demand and sensor/feedback information to command motor torque and speed.

Component	Function
Motor	Converts electrical energy into mechanical rotation.
Reduction gear/transmission	Adapts motor speed and torque to suit the wheels.

2. Electric Motors Used in EVs

Three commonly discussed traction-motor types are BLDC, PMSM and induction motors. Their suitability depends on efficiency, cost, control complexity, torque demand, operating speed and vehicle design.

2.1 Working principles

BLDC (Brushless DC) motor: Uses electronic commutation instead of mechanical brushes. The controller switches current through the stator windings to create a rotating magnetic field that interacts with the rotor magnets. BLDC motors are common in electric two-wheelers and smaller EVs because of their good efficiency and relatively simple maintenance.

PMSM (Permanent Magnet Synchronous Motor): Permanent magnets are fitted on the rotor. Controlled stator currents create a rotating magnetic field, and the rotor follows it synchronously. PMSMs provide high torque density and high efficiency, making them widely suitable for modern passenger EVs. They need sophisticated control and use permanent-magnet materials.

Induction motor: AC supplied to the stator creates a rotating magnetic field that induces current in the rotor. The interaction produces torque; the rotor runs slightly below synchronous speed under motoring load. Induction motors are robust and avoid permanent magnets, though efficiency can be lower in some operating regions.

2.2 Motor comparison

Parameter	BLDC	PMSM	Induction motor
Operating principle	Electronic commutation; rotor magnets	Rotor permanent magnets; synchronous operation	Rotor current induced by stator field
Efficiency (general)	High	Very high	Medium to high; varies with load/design
Cost / materials	Medium; uses magnets	Often higher due to magnets and control	Can be lower; no permanent magnets
Control complexity	Simple to moderate	More complex, precise control	Moderate to complex
Typical EV use	E-scooters, e-bikes, smaller drives	Many modern passenger EVs	Some passenger EVs and performance applications
Main strengths	Compact, efficient, low maintenance	High torque density and efficiency	Robust, magnet-free rotor
Limitations	Torque ripple/control design can matter	Magnet cost and thermal limits	Rotor losses and sometimes lower part-load efficiency

Conclusion: There is no single best motor for every EV. PMSMs offer high efficiency and torque density; BLDC motors are well suited to smaller vehicles; induction motors offer robustness and avoid permanent magnets. The final selection is a trade-off among cost, efficiency, packaging, control and performance.

3. Inverter and Motor Controller

3.1 Inverter

The traction battery supplies DC power, while many traction motors require controlled AC. The inverter uses semiconductor switches and pulse-width modulation (PWM) or related control methods to synthesize AC with the required frequency and voltage. Changing the output frequency helps control motor speed, while current/torque control governs acceleration and torque. In a regenerative-braking event, the power electronics can also support power flow back toward the battery when conditions allow.

Why it is essential: Without suitable power conversion and control, the traction motor cannot be operated efficiently across the vehicle's speed and torque range.

3.2 Motor controller

The motor controller is the control function/electronic unit that interprets accelerator demand and other vehicle signals, then commands inverter switching to achieve requested motor torque and speed. It can monitor current, speed and temperature and reduce or shut down output if a fault or overload is detected. In many EVs, the inverter and motor-control electronics are integrated into one assembly.

4. Battery Management System (BMS)

A BMS is an electronic system that monitors and manages the battery pack so that it operates within safe limits. It monitors cell voltage, pack current and temperature; estimates State of Charge (SOC) and State of Health (SOH); balances cells; and communicates limits or faults to the vehicle controller.

4.1 Key BMS functions

1. **Cell-voltage monitoring:** detects cells approaching upper or lower voltage limits.
2. **Overcharge and over-discharge protection:** requests charge/discharge limitation or contactor disconnection when limits are reached.
3. **Temperature monitoring:** identifies overheating or operation outside the allowed temperature range.
4. **Cell balancing:** reduces differences in cell charge levels so that the pack can use its capacity safely.
5. **SOC estimation:** estimates remaining charge as a percentage.
6. **SOH estimation:** estimates battery ageing/condition compared with its original state.

4.2 Battery safety and thermal runaway

Lithium-ion batteries can be damaged by overcharging, short circuits, physical damage, manufacturing defects or excessive temperature. Under severe conditions, a cell may enter **thermal runaway**—a self-accelerating rise in temperature that can release heat and gases and potentially spread to neighbouring cells. Warning signs and risk factors can include unusual heating, swelling, smoke, odour or electrical faults.

How the BMS helps: It monitors voltage/current/temperature, limits charging or discharging, detects abnormal conditions, reports faults and may command contactors or cooling systems. Cell balancing also supports safe operation. A BMS reduces risk but cannot guarantee prevention of every failure; pack design, fuses/contactors, thermal management, insulation, mechanical protection and correct charging are also important.

Safety note: Do not open, puncture, short-circuit or attempt to repair a high-voltage EV battery. Suspected damaged or overheating batteries require trained personnel and the manufacturer's emergency procedure.

5. EV Battery Basics and Range Calculation

EV battery capacity is commonly expressed in kilowatt-hours (kWh), which measures stored energy. Range depends on usable battery energy and vehicle energy consumption, which changes with speed, weather, terrain, tyres, payload, HVAC use and driving style.

Simple range formula

Estimated range (km) = usable battery energy (kWh) × vehicle efficiency (km/kWh)

Example from the task sheet:
Battery capacity = 40 kWh
Vehicle efficiency = 6 km/kWh
Estimated range = 40 × 6 = **240 km**

This is a simplified estimate assuming the full 40 kWh is usable and the stated efficiency remains constant. In real driving, usable capacity and efficiency vary, so actual range may be lower or higher.

6. Case Study: Tata Nexon EV

The Tata Nexon EV is a battery-electric passenger SUV. This case study focuses on its electric-drive architecture and explains why a modern passenger EV uses a traction motor, inverter, battery pack and BMS. Specifications can differ by model year, battery option and trim; therefore, exact numerical ratings should always be matched to the particular vehicle variant being studied.

6.1 Powertrain and motor choice

• **Motor type:** The Nexon EV uses a permanent-magnet synchronous motor (PMSM) in commonly documented versions. Confirm the motor type and exact output against the selected model-year's official specification sheet before submission if a specific variant is assigned.
• **Power (kW):** Varies by generation/variant; report the rating from the official brochure for the selected variant rather than mixing specifications from different model years.
• **Torque (N·m):** Also variant-dependent; use the same official brochure as the power rating.
• **Why this motor type:** PMSMs offer high torque density, good efficiency and strong low-speed torque, which are useful for vehicle acceleration and packaging in a passenger EV. The motor is controlled electronically through the inverter.

6.2 Main energy path

Battery pack → BMS-supervised DC supply → inverter/power electronics → traction motor → reduction gear → wheels. The BMS supervises battery conditions while the vehicle controller requests torque according to accelerator input. During braking, regenerative operation can recover part of the vehicle's kinetic energy and return it to the battery within battery and system limits.

6.3 Engineering observations

1. High motor torque at low speed supports responsive acceleration.
2. The inverter enables variable-speed operation rather than fixed-frequency operation.
3. The BMS helps keep the battery within voltage and temperature limits and estimates remaining charge.
4. Actual driving range depends on usable battery capacity and real-world energy consumption, not capacity alone.
5. Vehicle safety is a system-level outcome: BMS, thermal management, fuses/contactors, insulation and mechanical enclosure work together.

Case-study data to fill from the exact variant brochure: Model year/variant: 2025-2026 ; motor power: 106 kW ; maximum torque: 215 N·m ; battery capacity: 45 kWh ; claimed range/test cycle: 489 km.

7. Summary and Deliverables Checklist

• **EV powertrain:** battery energy is converted by power electronics and a traction motor into wheel torque.
• **Motor comparison:** BLDC, PMSM and induction motors differ in construction, efficiency, control, cost and applications.
• **Inverter:** converts DC into controlled AC for the traction motor.
• **Motor controller:** commands torque/speed and responds to driver demand and faults.
• **BMS:** monitors voltage, current and temperature; estimates SOC/SOH; balances cells; and provides protection.
• **Battery safety:** thermal runaway is a serious heat-escalation hazard; BMS protection is important but not the only safety measure.
• **Range calculation:** 40 kWh × 6 km/kWh = 240 km as a simplified estimate.
• **Case study:** Tata Nexon EV architecture and the general suitability of PMSM traction have been analysed; exact ratings should be taken from the selected variant's official brochure.

8. Conclusion

An electric vehicle is an integrated electrical and mechanical system. The battery stores energy, the BMS supervises battery safety, the inverter and controller regulate power flow, and the motor produces torque for propulsion. Correct motor selection and battery management influence efficiency, performance, reliability and safety. Range estimates provide a useful first approximation, but real-world performance depends on operating conditions.

Reference basis

This report follows the task structure and core concepts in the supplied “Automobile & Electric Vehicles – Task 2” document, including its requested EV powertrain diagram, motor comparison, BMS safety note, range calculation and vehicle case study. The supplied document also recommends learning resources and identifies these as the required learning outcomes. ■filecite■turn0file0■L133-L139■

Before submission: add your details if required by the internship coordinator, and fill the exact Tata Nexon EV power and torque ratings from the official brochure for the model year/variant you choose.