Lab Report

Lab Report
Time Spent: 00:41
Score: 0/8 (0%)
Not Passed
Passing Score: 8/8 (100%)

TASK SUMMARY

Required Actions & Questions

Run hciconfig to enable the Bluetooth adapter

Run hcitool to scan for the Bluetooth devices

Q1As a result of the scan, how many devices were found?
Your answer:
Correct answer: 6

Use l2ping to determine if a Bluetooth device is up

Q2How many of the devices scanned were alive and in range?
Your answer:
Correct answer: 6

Run sdptool to query Francisco's Precission Laptop

Q3Which service searches were successful on Francisco's Precision Laptop?
Your answer:
Correct answer: Ad Hoc User Service, Device ID Service Record

Q4Using the MAC address, what is the class ID number for the Brian;s Braven speaker?
Your answer:
Correct answer: 0x248080

EXPLANATION

Complete this lab as follows:

1. Initialize the Bluetooth adapter.
   a. From the Favorites bar, select **Terminal**.
   b. At the prompt, type **hciconfig** and press **Enter** to view the onboard Bluetooth adapter.
   c. Type **hciconfig hci0 up** and press **Enter** to initialize the adapter.
   d. Type **hciconfig** and press **Enter** to verify that the adapter is up and running.
2. Find all Bluetooth devices within range.
   a. Type **hcitool scan** and press **Enter** to view the detected Bluetooth devices and their MAC addresses.
   b. In the top left, select **Answer Questions**.
   c. Answer Question 1.
3. Determine if the Bluetooth devices found are in range.
   a. Type **l2ping *MAC_address*** and press **Enter** to determine if the Bluetooth device is in range.
   b. Press **Ctrl** + **c** to stop the ping process.

      To copy the MAC addresses from the scan, highlight the MAC address and then right-click.

   c. Repeat steps 3a–3b for all the devices.
   d. Answer Question 2.
4. Find details for Francisco's laptop using sdptool.
   a. Type **sdptool browse AF:52:23:92:EF:AF** and press **Enter** to view the details for Francisco's laptop.
   b. Answer Question 3.
5. Find details for Brian's Echo Show using hcitool.
   a. Type **hcitool inq** and press **Enter** to determine the clock offset and class for each device.
   b. Answer Question 4.
   c. Select **Score Lab**.