

Lab Report

Lab Report

Time Spent: 00:17

Score: 0/4 (0%)

Not Passed

Passing Score: 4/4 (100%)

TASK SUMMARY

Required Actions & Questions

Set the the wlp1s0 wireless adapter to monitor mode

Find the hidden access point

Q1 What is the BSSID of the rogue access point?

Your answer:

Correct answer: 00:00:1b:45:21:11

Connect to the rogue AP using the BookStore SSID

EXPLANATION

Complete this lab as follows:

1. From the IT-Laptop, configure the wlp1s0 card to run in monitor mode.
 - a. From the Favorites bar, select **Terminal**.
 - b. At the prompt, type **airmon-ng** and press **Enter** to find the name of the wireless adapter.
 - c. Type **airmon-ng start wlp1s0** and press **Enter** to put the adapter in monitor mode.
 - d. Type **airmon-ng** and press **Enter** to view the new name of the wireless adapter.
2. Use airodump-ng to discover and isolate the hidden access point.
 - a. Type **airodump-ng wlp1s0mon** and press **Enter** to discover all of the access points.
 - b. Press **Ctrl + c** to stop airodump-ng.
 - c. Find the hidden access point ESSID.
 - d. In the top right, select **Answer Questions**.
 - e. Answer the question.
 - f. In Terminal, type **airodump-ng wlp1s0mon --bssid 00:00:1B:45:21:11** and press **Enter** to isolate the hidden access point.
3. Switch to the Gst-Lap and connect to the Wi-Fi network.
 - a. From the top navigation tabs, select **Floor 1 Overview**.
 - b. Under Executive Office, select **Gst-Lap**.
 - c. From the notification area, select the **Wi-Fi network** icon.
 - d. Select **Hidden Network**.
 - e. Select **Connect**.
 - f. In the *Enter the name (SSID) for the network* field, type **BookStore**.

In a real environment, you'll only need to wait until the employee connects to the rogue access point again.

- g. Select **Next**.
- h. Select **Yes**.

Wait for the connection to be made.
- i. Under Lab Questions, select **Score Lab**.